



(12) **EUROPEAN PATENT SPECIFICATION**

(45) Date of publication of patent specification :
22.07.92 Bulletin 92/30

(51) Int. Cl.⁵ : **G01N 17/00**

(21) Application number : **87902657.3**

(22) Date of filing : **11.05.87**

(86) International application number :
PCT/GB87/00310

(87) International publication number :
WO 87/07022 19.11.87 Gazette 87/25

(54) **CORROSION MONITORING.**

(30) Priority : **12.05.86 GB 8611518**

(43) Date of publication of application :
08.02.89 Bulletin 89/06

(45) Publication of the grant of the patent :
22.07.92 Bulletin 92/30

(84) Designated Contracting States :
AT BE CH DE FR GB IT LI LU NL SE

(56) References cited :
EP-A- 0 084 404
DE-A- 1 804 234
GB-A- 2 118 309
US-A- 3 660 249
US-A- 3 878 064

(73) Proprietor : **CAPCIS LIMITED**
Bainbridge House, Granby Row
Manchester M1 2PW (GB)

(72) Inventor : **EDEN, David, Anthony The**
University of Manchester
Bainbridge House Laboratories Granby Row
Manchester M1 2PW (GB)
Inventor : **JOHN, David, Gareth The University**
of Manchester
Bainbridge House Laboratories Granby Row
Manchester M1 2PW (GB)
Inventor : **DAWSON, John, L. The University of**
Manchester
Bainbridge House Laboratories Granby Row
Manchester M1 2PW (GB)

(74) Representative : **Allman, Peter John et al**
MARKS & CLERK Suite 301 Sunlight House
Quay Street
Manchester M3 3JY (GB)

EP 0 302 073 B1

Note : Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid (Art. 99(1) European patent convention).

Description

The present invention relates to corrosion monitoring.

It is known that corrosion is an electrochemical phenomena and as such measurements of electrochemical parameters associated with corrosion processes may be used to estimate the rate of corrosion attack. Methods which have been used in the past and are known and well documented include the linear polarisation resistance method in which a dc signal is applied to a corroding cell consisting of two or three electrodes and the resulting dc polarisation is monitored. Provided the applied current is small so that the potential shift is less than 20 mV the response is linear in most cases and the measured resistance (termed the polarisation resistance) may be related inversely to the rate of the uniform corrosion attack. Other techniques include the application of electrochemical impedance in which a sine wave current is applied, in a similar manner to the linear polarisation technique, and the sine wave potential resulting from the applied current is monitored. Alternatively, a pseudo-random noise signal can be applied and the electrochemical impedance obtained by time domain transformations. Again, provided the current is small enough such that the resulting cell potential is not more than ± 20 mV, the response is linear. Corrosion includes capacitive components, and therefore if the frequency of the applied signal is varied the resulting output signal is also varied: hence by inputting a range of frequencies a range of outputs may be obtained and these may be suitably analysed to provide information corresponding to the solution resistance, the corrosion kinetics and other aspects including electrochemical double layer capacity, diffusion effects and absorption of intermediates on the surface. The corrosion rate is then estimated by use of the calculated charge transfer resistance from the electrochemical impedance data in a manner essentially the same as for linear polarisation resistance.

Both the above electrochemical techniques, whilst widely used, suffer severe limitations in that they can only provide information on uniform corrosion conditions, that is by their very nature they provide an average signal for the surface of the electrodes being monitored. However, depending upon the type of environment, the metallic material and type of corrosion occurring, it is often found that the assumption that the corrosion rate is proportional to the measured charge transfer or polarisation resistance is invalid since the corrosion is of a localised nature. A further complication arises from the interference effect of solution resistance which may be variable during the measurement period or of a high value thereby altering the observed measurements.

In order to overcome the above limitations the use of electrochemical noise analysis has been applied and shown to be successful particularly for localised corrosion involving breakdown of a passive film. Essentially electrochemical noise analysis consists of the measurement and analysis of small frequency, small amplitude random fluctuations in the corrosion potential of a corroding electrode. Suitable analysis is by means of frequency response analysis using Fast Fourier Transforms or Maximum Entropy Spectral Analysis, or by suitable filtering of the signal through a band pass system centred at 50 mHz ± 10 mHz and the subsequent calculation of the root mean square of the filtered signal. US Patent 4,575,678 describes such techniques. Previous experience has shown that this analysis may yield information as to both corrosion type and corrosion rate.

Another electrochemical measurement system which has been successfully applied in corrosion studies is the monitoring of coupling currents between dissimilar electrodes, for example, copper and steel electrodes, for measurement of corrosion phenomena. However, useful information can be obtained using similar electrodes of identical material, particularly when the system is moving from a general to a localised corrosion form of attack. In this instance two similar electrodes immersed in a conductive media are coupled via a zero resistance ammeter (null impedance ammeter). Such a system enables the current flowing in the network to be determined whilst imparting substantially zero resistance to the current path. Experience has shown that in cases where pitting corrosion occurs, one electrode will preferentially become anodic (that is it will pit) whilst the other electrode will become preferentially cathodic (that is provide an increased current to maintain the pitting of the other electrode). The degree or otherwise of discontinuity between the two electrodes may be related to the extent of corrosion. The method is therefore useful in identifying when corrosion changes from uniform to localised corrosion. With uniform corrosion conditions, the corrosion current may be related to the mean coupling current I_{mean} by the following:-

$$I_{\text{corr}} = k_1 I_{\text{mean}}$$

where k_1 is a system related constant.

Also by combining the coupling current analysis with electrochemical noise analysis further information may be obtained. For example, two similar electrodes are coupled together via a zero resistance ammeter and the output of the zero resistance ammeter is then passed to the input of the electrochemical noise analysis system. In this way the fluctuation of the coupling current may be analyzed in essentially a similar manner as for electrochemical potential noise analysis described previously. By suitable configuration of electrodes and analysis equipment it is possible to obtain simultaneously both electrochemical potential noise data and coupling current data and electrochemical current noise data. Experience has shown that the rms or standard devi-

ation values of both the electrochemical potential noise (termed V_n) and the electrochemical current noise (termed I_n) can be related using Ohm's law to produce a resistance noise value (termed R_n) as the frequency approaches zero Hz. Alternatively the impedance (termed Z_n) may be described as a function of frequency by means of correlation of I_n and V_n using frequency response analysis. This value appears to be related to the corrosion rate and has been considered as analogous to both the charge transfer resistance and polarisation resistance as noted previously.

German Patent Specification No. DE-A-1804234 discloses a method for measuring the type of corrosion, i.e. localized corrosion, wherein the coupling current between two electrodes of the same material is measured.

It is an object of the present invention to provide a method and apparatus for improving the accuracy with which the type of corrosion attacking a particular metallic material can be assessed.

According to the present invention there is provided an apparatus for detecting localised corrosion of a metallic surface, comprising an array of two or more electrodes fabricated from the same material as the metallic surface and exposed to the same corrosion conditions as the metallic surface, means for measuring the coupling current between two or more electrodes of the array, means for measuring electrochemical current noise originating in the electrode array, and means for comparing the coupling current with the electrochemical current noise to provide an output indicative of the degree to which corrosion is localised.

The greater the electrochemical current noise as compared to the coupling current, the greater is the degree to which corrosion is localised.

Preferably, the apparatus also comprises means for measuring the electrochemical potential noise originating in the electrode array, means for correlating the electrochemical potential noise and the electrochemical current noise to provide a resistive/impedance noise related output, and means for comparing the said output indicative of the degree to which corrosion is localised with the resistive/impedance noise output to provide an output indicative of the rate of localised corrosion.

The present invention also provides a method for detecting localised corrosion of a metallic surface, wherein an array of electrodes fabricated from the same material as the metallic surface is exposed to the same corrosion conditions as the metallic surface, the coupling current between two electrodes of the array is measured, electrochemical current noise originating in the electrode array is measured, and the coupling current is compared with the electrochemical current noise.

The present invention is particularly useful for detecting corrosion resulting in the formation of pits, but can also be used to detect other forms of localised corrosion, for example stress corrosion cracking, or crevice attack. Furthermore, variations in the ratio between coupling current and electrochemical current noise is also indicative of changes occurring in corrosion processes. Such changes can occur for example when the chemical composition of a fluid to which the electrodes are exposed varies, and detection of such changes makes it possible to assess the affects on corrosion processes of adjustments to the operation of the system being monitored.

An apparatus providing outputs suitable for use in accordance with the present invention is illustrated in the attached drawing.

Referring to that drawing, three electrodes 1, 2 and 3 are positioned so as to be exposed to the same corrosion conditions as a metallic surface (not shown) the corrosion of which is to be monitored. In the drawing these conditions are indicated by a tank 4 filled with a corrosive liquid 5.

Electrodes 1 and 2 are connected to an electrochemical potential noise monitoring apparatus 6 which provides on output 7 an output signal representative of V_n , that is the rms or standard deviation of the potential noise. The electrochemical potential noise may be monitored as shown by a circuit connected between the coupled electrodes 2 and 3 and a third electrode 1 of the array. A reference electrode or relatively inert electrode could be used rather than the third electrode of the array. A zero resistance ammeter 8 is connected across electrodes 2 and 3 and produces on output 9 an output signal corresponding to I_{mean} , that is the ddcoupling current.

The output 9 is connected to an electrochemical current noise measuring apparatus 10 which provides on output 11 an output signal corresponding to I_n , that is the rms or standard deviation of the current noise. The outputs 7 and 11 are applied to a circuit 12 for comparing the electrochemical potential noise and the electrochemical current noise. The circuit 12 provides on output 13 an output signal R_n or $|Z_n|$ which is the resistive or impedance noise and is equal to V_n/I_n . The output 13 is effectively indicative of the overall rate of corrosion.

The illustrated structure provides effectively four outputs each of which varies in a manner that is indicative of the rate and/or nature of the corrosion attack to which the electrodes 1, 2 and 3 are exposed. It has now been realized that in accordance with the present invention if a comparison is made between the signals appearing on outputs 9 and 11 that comparison yields important information as to the nature of the corrosion attack. Accordingly in accordance with the present invention a comparator circuit 14 is connected to outputs 9 and 11

and provides on output 15 an output signal which is representative of I_n/I_{mean} .

Output 15 results from the comparison of the mean (or dc) coupling current (I_{mean}) to the rms or standard deviation values of the electrochemical current noise (I_n), and is indicative of the degree or otherwise of the localised behaviour during corrosion attack. That is, a low value of the ratio I_n/I_{mean} is indicative of general corrosion, whilst high values of the ratio are indicative of localised corrosion. More specifically a ratio of greater than 1 is indicative of complete localised corrosion during pitting. The following relationships have been found to apply:

0.001 < I_n/I_{mean} < 0.01	General Corrosion
0.01 < I_n/I_{mean} < 0.1	Mixed Corrosion
0.1 < I_n/I_{mean} < 1.0	Localised Corrosion
1.0 < I_n/I_{mean}	Initiation of pits

It should be stressed that in accordance with the present invention no dc or ac potentials are applied between the electrodes and accordingly measurements are conducted under the natural conditions. This is a fundamental distinction between the present invention and prior art systems in which it has been known to apply a dc current at constant potential via a potentiostat to an electrode array and then to look at variations in the applied current resulting from electrochemical corrosion effects.

A further circuit 16 is provided which compares the output 13 (overall corrosion rate) with the output 15 (degree to which corrosion is localised) and produces an output 17 which is indicative of the rate of localised corrosion. Thus, the information yielded from application of the present invention in combination with information available from the various outputs provided in the arrangement illustrated in the accompanying drawing makes it possible to accurately determine both the rate and nature of a particular corrosion process.

Further equations relevant to an understanding of the present invention are set out below. In these equations the following terms are used:

V_n :	Electrochemical Potential Noise (volts)
I_n :	Electrochemical Current Noise (amps)
I_{mean} :	Coupling Current - Mean (ZRA) (amps)
R_n :	Resistance Noise = V_n/I_n (ohm)
I_{corr} :	Corrosion Current (amps)
$ Z_n $:	Complex impedance (ohm) derived from V_n/I_n
$k, k_1, k_2,$	Constants

(a) Corrosion Rate

The corrosion rate may be described by each of the two following equations:

$$I_{corr} = k_2/R_n = k_2 I_n/V_n = k_2/|Z_n|$$

$$I_{corr} = k_1 I_{mean}$$

Thus an improved estimate of I_{corr} is given by

$$I_{corr} = \sqrt{\frac{k I_n I_{mean}}{V_n}} \quad \text{(Geometric mean of two systems)}$$

where $k = k_1 k_2$

(b) Corrosion Type

$$\theta = \frac{\log(I_{mean}/I_n)}{k_3}$$

$\theta = 1$ General corrosion
 $\theta = 0$ Pure localised corrosion
 k_3 System dependent constant

(c) Penetration Rate

I_{corr} as calculated in (a) gives average corrosion across electrode surface in order to calculate Penetration Rate (X).

$$X = \frac{I_{corr}}{A \theta}$$

where A is electrode area and θ is 'active surface ratio' as calculated in (b).

In all cases constants are determined experimentally.

(d) An alternative approach is as follows

Monitor $I_x(I_{\text{mean}})$, I_n , $V_{\text{DC}}(V_{\text{mean}})$, V_n

5 For general attack ratio $\frac{I_n}{I_{\text{DC}}}$ is small, estimate lower limit to be approx 10^{-3} .

For pitting corrosion, single pits $\frac{I_n}{I_{\text{DC}}} \approx 1$, (can be greater than 1). particularly if the fluctuations occur around zero - this is uncommon but is related to initiation and propagation of fresh pits.

10 Normally calculate polarisation resistance from correlated potential and current signals, for noise say

$$\frac{V_n}{I_n} = R_p \quad (\text{ohm})$$

Standard practice to correct for area of specimen and to normalise to A.cm^{-2} .

$$A_{(\text{total})} \times \frac{V_n}{I_n} = R_p \Omega.\text{cm}^2$$

15 To correct for area being attacked, modify A

$$A_{(\text{real})} = A_{(\text{total})} \times \frac{I_{\text{DC}}}{I_n} \times 10^{-3}$$

20 (i.e. if $\frac{I_n}{I_{\text{DC}}} = 10^{-3}$; $A_{(\text{real})} = A_{(\text{total})}$, etc.)

$$R_{p(\text{real})} = A_{(\text{total})} \times \frac{I_{\text{DC}}}{I_n^2} \times 10^{-3} \times V_n \Omega.\text{cm}^2$$

and

$$25 \quad i_{\text{corr}} = B \left(\frac{I_n^2}{A_{(\text{total})} \times I_{\text{DC}} \times 10^{-3} \times V_n} \right) \quad \text{amps cm}^{-2}$$

But $V_n \propto B \left(\frac{B}{V_n} = K \right)$

$$i_{\text{corr}} = k \left(\frac{I_n^2}{A_{(\text{total})} \times I_{\text{DC}} \times 10^{-3}} \right) \quad \text{amps cm}^{-2}$$

30 K depends on frequency at which measurements taken, but for "standard" pitting can approximate to 3×10^3 (by assuming $V_n = 10 \mu\text{V}$ when $B = 30\text{mV}$).

$$i_{\text{corr}} = 3 \times 10^6 \left(\frac{I_n^2}{A_{(\text{total})} \times I_{\text{DC}}} \right) \quad \text{amps cm}^{-2}$$

35 now $\frac{I_n}{I_{\text{DC}}} = \text{coefficient of variation} \quad C$

$$i_{\text{corr}} = 3 \times 10^6 \left(\frac{I_n \times C}{A_{(\text{total})}} \right)$$

Measuring I_n and I_{DC} and knowing A calculate penetration rates

e.g.

$$40 \quad I_n = 10^{-9} \text{ Amps}$$

$$A = 10 \text{ cm}^2$$

$$C = 1$$

$$i_{\text{corr}} = \frac{3 \times 10^6 \times 10^{-9} \times 1}{10}$$

45 Pitting

$$= 3 \times 10^{-4} \text{ Amps cm}^2 \text{ (at pit)}$$

$$= 300 \mu\text{A cm}^{-2} \text{ (+ } i_{\text{DC}} \sim 10^{-9} \text{ Amps)}$$

$$\cong 150 \text{ mpy (for steel) (1 mpy} = \frac{1}{1000} \text{ inch per year} = 0.0254 \text{ mm per year)}$$

$$50 \quad I_n = 10^{-9}$$

$$A = 10$$

$$C = 10^{-3}$$

Uniform

$$55 \quad i_{\text{corr}} = \frac{3 \times 10^6 \times 10^{-9} \times 10^{-3}}{10}$$

$$= 3 \times 10^{-7}$$

$$= 0.3 \mu\text{A cm}^{-2}$$

≅ 0.15 mpy for steel (1 mpy = 0.0254 mm per year)

e.g.
 $I_n = 10^{-7}$ Amps
 $A = 10$ cm²
 5 $C = 0.1$
 $i_{corr} = \frac{3 \times 10^6 \times 10^{-7} \times 0.1}{10}$
 $= 3 \times 10^{-3}$ amps cm⁻²
 $\cong 1500$ mpy (for steel) (1 mpy = 0.0254 mm per year)
 10 $I_{DC} \cong 10^{-6}$ amps
 Uniform
 $C = 10^{-3}$, $i_n = 10^{-7}$, $A = 10$
 $i_{corr} = 3 \times 10^{-5}$ amps cm⁻²
 15 $I_{DC} = 10^{-4}$ amps
 $I_{DC} > \frac{1}{3} i_{corr}$

Claims

- 20
1. An apparatus for detecting localised corrosion of a metallic surface, comprising an array of two or more electrodes (1,2,3) fabricated from the same material as the metallic surface and exposed to the same corrosion conditions as the metallic surface, and means (8) for measuring the coupling current between two or more electrodes of the array, characterized in that means (10) are provided for measuring electrochemical current noise originating in the electrode array, and means (14) are provided for comparing the coupling current with the electrochemical current noise to provide an output indicative of the degree to which corrosion is localised.
- 25
2. An apparatus according to claim 1, comprising two electrodes (2,3), a zero resistance ammeter (8) connected between the two electrodes and providing an output corresponding to the dc coupling current between the electrodes, an electrochemical current noise measuring apparatus (10) connected to the output of the zero resistance ammeter and providing an output corresponding to the current noise, and a comparator (14) connected to the outputs of the zero resistance ammeter and the electrochemical current noise measuring apparatus and providing an output corresponding to the relative magnitudes of the dc coupling current and the current noise.
- 30
3. An apparatus according to claim 1, comprising means (6) for measuring the electrochemical potential noise originating in the electrode array, means (12) for correlating the electrochemical potential noise and the electrochemical current noise to provide a resistive/impedance noise related output, and means (16) for comparing the said output indicative of the degree to which corrosion is localised with the resistive/impedance noise output to provide an output indicative of the rate of localised corrosion.
- 35
4. An apparatus according to claim 2, comprising an electrochemical potential noise measuring apparatus (6) connected between the said two or more electrodes (1,2) and a further electrode, a correlator (12) connected to the outputs of the electrochemical current measuring apparatus and the means for measuring the electrochemical current noise, and a comparator 16 connected to the output of the correlator and the said output indicative of the degree to which corrosion is localised.
- 40
5. A method for detecting localised corrosion of a metallic surface, wherein an array of electrodes (1,2,3) fabricated from the same material as the metallic surface is exposed to the same corrosion conditions as the metallic surface, and the coupling current between two electrodes of the array is measured, characterized in that electrochemical current noise originating in the electrode array is measured, and the coupling current is compared with the electrochemical current noise to provide an output indicative of the degree to which corrosion is localised.
- 45
6. A method according to claim 5, wherein the electrochemical potential noise originating in the electrode array is measured, the resistive/impedance noise is measured by comparison of the electrochemical current noise with the electrochemical potential noise, and the resistance/impedance noise is compared with the said output indicative of localised corrosion to provide an output indicative of the rate of localised corrosion.
- 50

55

Patentansprüche

1. Gerät zum Nachweis örtlicher Korrosion einer Metalloberfläche, bestehend aus einer Anordnung von zwei oder mehr Elektroden (1,2,3), die aus dem gleichen Material wie die Metalloberfläche gefertigt sowie den gleichen Korrosionsbedingungen wie die Metalloberfläche ausgesetzt sind, sowie Vorrichtungen (8) zur Messung des Kopplungsstroms zwischen zwei oder mehr Elektroden der Anordnung, dadurch gekennzeichnet, daß Vorrichtungen (10) zur Messung des von der Elektrodenanordnung ausgehenden elektrochemischen Stromrauschens vorgesehen sind, und daß Vorrichtungen (14) zum Vergleich des Kopplungsstroms mit dem elektrochemischen Stromrauschen vorgesehen sind, um einen auf das Ausmaß der örtlichen Begrenzung der Korrosion hindeutenden Ausgang zu liefern.

2. Gerät nach Anspruch 1, bestehend aus zwei Elektroden (2,3), einem zwischen die beiden Elektroden geschalteten widerstandsfreien Amperemeter (8), das einen dem zwischen den Elektroden bestehenden galvanischen Kopplungsstrom entsprechenden Ausgang liefert, einem mit dem Ausgang des widerstandsfreien Amperemeters verbundenen Meßgerät (10) für elektrochemisches Stromrauschen, wobei das Meßgerät einen dem Stromrauschen entsprechenden Ausgang liefert, und einem mit den Ausgängen des widerstandsfreien Amperemeters und des Meßgeräts für elektrochemisches Stromrauschen verbundenen Komparator (14), der einen den relativen Beträgen des galvanischen Kopplungsstroms und des Stromrauschens entsprechenden Ausgang liefert.

3. Gerät nach Anspruch 1, bestehend aus Vorrichtungen (6) zur Messung des von der Elektrodenanordnung ausgehenden elektrochemischen Potentialrauschens, Vorrichtungen (12) zur Korrelation des elektrochemischen Potentialrauschens mit dem elektrochemischen Stromrauschen, um einen auf den Wirk- bzw. Scheinwiderstand bezogenen Rauschgang zu liefern, sowie Vorrichtungen (16) zum Vergleich des besagten auf das Ausmaß der örtlichen Begrenzung der Korrosion hindeutenden Ausgangs mit dem Rauschgang von Wirk- bzw. Scheinwiderstand, um einen Ausgang zu liefern, der auf die Geschwindigkeit örtlicher Korrosion hindeutet.

4. Gerät nach Anspruch 2, bestehend aus einem zwischen die besagten zwei oder mehr Elektroden (1,2) und eine weitere Elektrode geschalteten Meßgerät (6) für elektrochemisches Potentialrauschen, einem mit den Ausgängen des Meßgeräts für elektrochemisches Stromrauschen und den Vorrichtungen zur Messung des elektrochemischen Stromrauschens verbundenen Korrelator (12), sowie einem mit dem Ausgang des Korrelators und dem besagten auf das Ausmaß der örtlichen Begrenzung der Korrosion hindeutenden Ausgang verbundenen Komparator 16.

5. Verfahren zum Nachweis örtlicher Korrosion einer Metalloberfläche, wobei eine Anordnung von aus dem gleichen Material wie die Metalloberfläche gefertigten Elektroden (1,2,3) den gleichen Korrosionsbedingungen wie die Metalloberfläche ausgesetzt und wobei der Kopplungsstrom zwischen zwei Elektroden der Anordnung gemessen werden, dadurch gekennzeichnet, daß das von der Elektrodenanordnung ausgehende elektrochemische Stromrauschen gemessen und der Kopplungsstrom mit dem elektrochemischen Stromrauschen verglichen werden, um einen auf das Ausmaß der örtlichen Begrenzung der Korrosion hindeutenden Ausgang zu liefern.

6. Verfahren nach Anspruch 5, wobei das von der Elektrodenanordnung ausgehende elektrochemische Potentialrauschen gemessen, das Rauschen von Wirk- bzw. Scheinwiderstand durch den Vergleich des elektrochemischen Stromrauschens mit dem elektrochemischen Potentialrauschen gemessen und das Rauschen von Wirk- bzw. Scheinwiderstand mit besagtem auf örtliche Korrosion hindeutenden Ausgang verglichen werden, um einen Ausgang zu liefern, der auf die Geschwindigkeit örtlicher Korrosion hindeutet.

Revendications

1. Appareil pour la détection de corrosion localisée d'une surface métallique, comprenant un arrangement de deux électrodes (1,2,3) ou plus fabriquées en la même matière que la surface métallique et exposées aux mêmes conditions de corrosion que la surface métallique, et un moyen (8) pour la mesure du courant de couplage entre deux électrodes ou plus de l'arrangement, caractérisé en ce que des moyens (10) sont prévus pour la mesure du bruit de courant électrochimique provenant de l'arrangement d'électrodes, et des moyens (14) sont prévus pour la comparaison du courant de couplage et du bruit de courant électrochimique pour fournir une sortie indicative du degré auquel la corrosion est localisée.

2. Appareil selon la revendication 1, comprenant deux électrodes (2,3), un ampèremètre (8) à résistance zéro relié entre les deux électrodes et fournissant une sortie correspondant au courant de couplage direct entre les électrodes, un appareil (10) de mesure de bruit de courant électrochimique relié à la sortie de l'ampèremètre à résistance zéro et fournissant une sortie correspondant au bruit de courant, et un comparateur (14) relié aux

sorties de l'ampèremètre à résistance zéro et à l'appareil de mesure de bruit de courant électrochimique et fournissant une sortie correspondant aux grandeurs relatives du courant de couplage direct et du bruit de courant.

5 3. Appareil selon la revendication 1, comprenant un moyen (6) pour la mesure de bruit de potentiel électrochimique provenant de l'arrangement d'électrodes, un moyen (12) pour corrélérer le bruit de potentiel électrochimique et le bruit de courant électrochimique pour fournir une sortie se rapportant au bruit de résistance/d'impédance, et un moyen (16) pour la comparaison de ladite sortie indicative du degré auquel la corrosion est localisée et la sortie de bruit de résistance/d'impédance pour fournir une sortie indicative de la vitesse de la corrosion localisée.

10 4. Appareil selon la revendication 2, comprenant un appareil (6) de mesure de bruit de potentiel électrochimique relié entre lesdites deux électrodes (1,2) ou plus et une électrode supplémentaire, un corrélateur (12) relié aux sorties de l'appareil de mesure de courant électrochimique et du moyen pour la mesure du bruit de courant électrochimique, et un comparateur 16 relié à la sortie du corrélateur et à ladite sortie indicative du degré auquel la corrosion est localisée.

15 5. Méthode de détection de corrosion localisée d'une surface métallique, dans laquelle un arrangement d'électrodes (1,2,3) fabriquées en la même matière que la surface métallique est exposé aux mêmes conditions de corrosion que la surface métallique, et le courant de couplage entre deux électrodes de l'arrangement est mesuré, caractérisée en ce que le bruit de courant électrochimique provenant de l'arrangement d'électrodes est mesuré, et le courant de couplage est comparé au bruit de courant électrochimique pour fournir une sortie indicative du degré auquel la corrosion est localisée.

20 6. Méthode selon la revendication 5, dans laquelle le bruit de potentiel électrochimique provenant de l'arrangement d'électrodes est mesuré, le bruit de résistance/d'impédance est mesuré par la comparaison du bruit de courant électrochimique et du bruit de potentiel électrochimique, et le bruit de résistance/d'impédance est comparé à ladite sortie indicative de corrosion localisée pour fournir une sortie indicative de la vitesse de la corrosion localisée.

30

35

40

45

50

55

