



(12) **CORRECTED EUROPEAN PATENT SPECIFICATION**

(15) Correction information:
Corrected version no 1 (W1 B1)
Corrections, see
Description Paragraph(s) 6-11, 38, 41, 52
Claims EN 1, 4

(51) Int Cl.:
H03M 13/11 (2006.01)

(48) Corrigendum issued on:
02.09.2015 Bulletin 2015/36

(45) Date of publication and mention
of the grant of the patent:
20.02.2008 Bulletin 2008/08

(21) Application number: **04255344.6**

(22) Date of filing: **03.09.2004**

(54) **Method and system for encoding short block length low density parity check (LDPC) codes**

Verfahren und Vorrichtung für die Encodierung von Low Density Parity Check (LDPC) Codes kurzer Blocklänge

Méthod et système pour le codage de codes LDPC à courte longueur de bloc

(84) Designated Contracting States:
**AT BE BG CH CY CZ DE DK EE ES FI FR GB GR
HU IE IT LI LU MC NL PL PT RO SE SI SK TR**

(30) Priority: **04.09.2003 US 500109 P**
27.10.2003 US 514683 P
07.11.2003 US 518199 P

(43) Date of publication of application:
09.03.2005 Bulletin 2005/10

(73) Proprietor: **The Directv Group, Inc.**
El Segundo, CA 90245 (US)

(72) Inventors:
• **Eroz, Mustafa**
Germantown
Maryland 20874 (US)
• **Sun, Feng-Wen**
Germantown
Maryland 20874 (US)
• **Lee, Lin-Nan**
Potomac
Maryland 20854 (US)

(74) Representative: **Jackson, Richard Eric et al**
Carpmaels & Ransford LLP
One Southampton Row
London WC1B 5HA (GB)

(56) References cited:
US-A1- 2004 086 059

- **MANSOUR M.M. ET AL.:** "Architecture-aware low-density parity-check codes" PROC., IEEE INTERNATIONAL SYMPOSIUM ON CIRCUITS AND SYSTEMS, BANGKOK, THAILAND, vol. 2, 25 May 2003 (2003-05-25), pages II-57-II-60, XP002302868
- **HOCEVAR D. E.:** "LDPC code construction with flexible hardware implementation" PROC., IEEE INTERNATIONAL CONFERENCE ON COMMUNICATIONS, ICC'2003, ANCHORAGE, AK, vol. 1 OF 5, 11 May 2003 (2003-05-11), pages 2708-2712, XP010642938 ISBN: 0-7803-7802-4
- **SELVARATHINAM A ET AL:** "A massively scaleable decoder architecture for low-density parity-check codes" PROC., IEEE INTERNATIONAL SYMPOSIUM ON CIRCUITS AND SYSTEMS, ISCAS 2003, BANGKOK, THAILAND, vol. 2 OF 5, 25 May 2003 (2003-05-25), pages 61-64, XP002260921 ISBN: 0-7803-7761-3
- **ELEFThERIOU E ET AL.:** "Low-density parity-check codes for digital subscriber lines" PROC., IEEE INTERNATIONAL CONFERENCE ON COMMUNICATIONS, ICC 2002, NEW YORK, NY, vol. 1 OF 5, 28 April 2002 (2002-04-28), pages 1752-1757, XP010589787 ISBN: 0-7803-7400-2

- LE GOFF S Y: "Channel capacity of bit-interleaved coded modulation schemes using 8-ary signal constellations" ELECTRONICS LETTERS, IEE STEVENAGE, GB, vol. 38, no. 4, 14 February 2002 (2002-02-14), pages 187-189, XP006017828 ISSN: 0013-5194
- LE GOFF S.: "Signal constellations for bit-interleaved coded modulation" IEEE TRANSACTIONS ON INFORMATION THEORY, vol. 49, no. 1, January 2003 (2003-01), pages 307-313, XP002322414
- LE GOFF S Y: "Signalling constellations for power-efficient bit-interleaved coded modulation schemes" IEE PROCEEDINGS : COMMUNICATIONS, INSTITUTION OF ELECTRICAL ENGINEERS, GB, vol. 150, no. 3, 13 June 2003 (2003-06-13), pages 141-148, XP006020428 ISSN: 1350-2425
- HOU J., SIEGEL P.H. MILSTEIN L.B. AND PFISTER H.D.: "Capacity-approaching bandwidth-efficient coded modulation schemes based on low-density parity-check codes" IEEE TRANSACTIONS ON INFORMATION THEORY, vol. 49, no. 9, 1 September 2003 (2003-09-01), pages 2141-2155, XP002322415
- CALZOLARI G P: "Report on DVB-S2 channel coding standardization effort" SUB-PANEL CHANNEL CODING MEETING REPORT, MATERA, ITALY, 7 April 2003 (2003-04-07), pages 1-11, XP002311762
- RICHARDSON T. ET AL: "The renaissance of Gallager's low-density parity-check codes" IEEE COMMUNICATIONS MAGAZINE, IEEE SERVICE CENTER. PISCATAWAY, N.J, US, vol. 41, no. 8, August 2003 (2003-08), pages 126-131, XP001177711 ISSN: 0163-6804
- ETSI: "Digital Video Broadcasting (DVB); Second generation framing structure, channel coding and modulation systems for Broadcasting, Interactive Services, News Gathering and other broadband satellite applications" DRAFT ETSI EN 302 307 V1.1.1, June 2004 (2004-06), pages 1-74, XP002312174 Retrieved from the Internet: URL:<http://www.dvb.org/documents/en302307.v1.1.1.draft.pdf> [retrieved on 2004-12-23]
- RAVI NARAYANASWAMI: "Coded Modulation with low density parity check codes" THESIS SUBMITTED TO THE OFFICE OF GRADUATE STUDIES OF TEXAS A&M UNIVERSITY IN PARTIAL FULFILLMENT OF THE REQUIREMENTS FOR THE DEGREE OF MASTER OF SCIENCE, June 2001 (2001-06), pages 1-88, XP002271230
- YANG M ET AL: "Lowering the error-rate floors of moderate-length high-rate irregular LDPC codes" PROC., IEEE INTERNATIONAL SYMPOSIUM ON INFORMATION THEORY, 29 June 2003 (2003-06-29), page 237, XP010657265
- YANG M. ET AL.: "Design of efficiently encodable moderate-length high-rate irregular LDPC codes" PROC., 40 THE ANNUAL ALLERTON CONF. COMMUNICATION, CONTROL AND COMPUTING, 2002, 2 October 2002 (2002-10-02), pages 1415-1424, XP009042018
- RICHARDSON T J ET AL: "Efficient encoding of low-density parity-check codes" IEEE TRANSACTIONS ON INFORMATION THEORY, vol. 47, no. 2, February 2001 (2001-02), pages 638-656, XP002965294 ISSN: 0018-9448
- GALLAGER R G: "Low-density parity-check codes" IRE TRANSACTIONS ON INFORMATION THEORY, IEEE INC. NEW YORK, US, January 1962 (1962-01), pages 21-28, XP000992693
- TONG ZHANG ET AL: "Joint code and decoder design for implementation-oriented (3, k)-regular LDPC codes" PROC., THE 35TH. IEEE ASIOMAR CONFERENCE ON SIGNALS, SYSTEMS, & COMPUTERS. PACIFIC GROOVE, CA, vol. VOL. 1 OF 2. CONF. 35, 4 November 2001 (2001-11-04), pages 1232-1236, XP010582236 ISBN: 0-7803-7147-X
- "Digital Video Broadcasting (DVB); Interaction channel for satellite distribution systems; ETSI EN 301 790" ETSI STANDARDS, EUROPEAN TELECOMMUNICATIONS STANDARDS INSTITUTE, SOPHIA-ANTIPO, FR, vol. BC, no. V131, March 2003 (2003-03), pages 1-110, XP014003845 ISSN: 0000-0001

Description

FIELD OF THE INVENTION

[0001] The present invention relates to communication systems, and more particularly to coded systems.

BACKGROUND OF THE INVENTION

[0002] Communication systems employ coding to ensure reliable communication across noisy communication channels. For example, in a wireless (or radio) system, such as a satellite network, noise sources abound, from geographic and environmental factors. These communication channels exhibit a fixed capacity that can be expressed in terms of bits per symbol at certain signal to noise ratio (SNR), defining a theoretical upper limit (known as the Shannon limit). As a result, coding design has aimed to achieve rates approaching this Shannon limit. This objective is particularly germane to bandwidth constrained satellite systems. One such class of codes that approach the Shannon limit is Low Density Parity Check (LDPC) codes.

[0003] Traditionally, LDPC codes have not been widely deployed because of a number of drawbacks. One drawback is that the LDPC encoding technique is highly complex. Encoding an LDPC code using its generator matrix would require storing a very large, non-sparse matrix. Additionally, LDPC codes require large blocks to be effective; consequently, even though parity check matrices of LDPC codes are sparse, storing these matrices is problematic.

[0004] From an implementation perspective, a number of challenges are confronted. For example, storage is an important reason why LDPC codes have not become widespread in practice. Length LDPC codes, thus, require greater storage space. Also, a key challenge in LDPC code implementation has been how to achieve the connection network between several processing engines (nodes) in the decoder. Further, the computational load in the decoding process, specifically the check node operations, poses a problem.

[0005] Le Goff S.Y.: "Channel capacity of bit-interleaved coded modulation scheme using 8-ary signal constellations", IEE Electronic Letters, vol. 38, no. 4, 14th Feb. 2002 (XP006017828) describes bit-interleaved coded modulation using 8-ary signal constellations.

[0006] Le Goff S.Y.: "Signal constellations for bit-interleaved coded modulation", IEEE Trans. on Inf. Theory, vol. 49, no. 1, Jan. 2003, pp. 307-313 describes bit-interleaved coded modulation used in conjunction with turbo codes.

[0007] Le Goff S.Y.: "Signalling constellations for power-efficient bit-interleaved coded modulation schemes", IEE PROCEEDINGS : COMMUNICATIONS, INSTITUTION OF ELECTRICAL ENGINEERS, GB, 13 June 2003, pp. 141-148 (XP006020428) describes different signal constellations for bit-interleaved coded modulation schemes.

[0008] Hou J. et al.: "Capacity-approaching bandwidth-efficient coded modulation schemes based on low-density parity-check codes", IEEE Trans. on Inform. Theory, vol. 49, no. 9, pp. 2141-2155 describes bandwidth efficient-coded modulation schemes based on Low-Density Parity-Check (LDPC) codes.

[0009] Richardson T.: "The renaissance of Gallager's low-density parity-check codes", IEEE Communications Magazine, Aug. 2003, pp. 126-131 (XP001177711) discloses some background information on Low-Density Parity-Check (LDPC) codes.

[0010] Calzolari G.P.: "Report on DVB-S2 channel coding standardization effort", CCSDS Sub-Panel 1B Channel Coding, 7th April 2003, Matera, Italy (XP002311762) discusses the possibility of using various modulation schemes in conjunction with Low-Density Parity-Check (LDPC) codes.

[0011] There is still a need for an LDPC communication system that employs simple encoding and decoding processes. There is also a need for using LDPC codes efficiently to support high data rates, without introducing greater complexity. There is also a need to improve performance of LDPC encoders and decoders. There is also a need to minimize storage requirements for implementing LDPC coding.

SUMMARY OF THE INVENTION

[0012] These and other needs are addressed by the present invention, wherein an approach for encoding Low Density Parity Check (LDPC) codes is provided. An encoder generates a LDPC code having an outer Bose Chaudhuri Hocquenghem (BCH) code according to one of Tables 2-8 for transmission as the LDPC coded signal. Each of the Tables 2-8 specifies the address of parity bit accumulators. Short LDPC codes are output by utilizing LDPC mother codes that are based on Tables 2-8. k_{ldpc} of the BCH encoded bits are preceded by $k_m - k_{ldpc}$ dummy zeros. The resulting k_m bits are systematically encoded to generate n_m bits. The first $k_m - k_{ldpc}$ dummy zeros are then deleted to yield the shortened code. For an LDPC code with code rate of 3/5 utilizing 8-PSK (Phase Shift Keying) modulation, an interleaver provides for interleaving bits of the output LDPC code by serially writing data associated with the LDPC code column-wise into a table and reading the data row-wise from right to left. The approach advantageously provides expedient encoding as well as decoding of LDPC codes, while minimizing storage and processing resources.

[0013] One aspect of an embodiment of the present invention is a method for supporting transmission of a Low Density Parity Check (LDPC) coded signal as specified in the appended claims.

[0014] According to another aspect of an embodiment of the present invention, the modulated LDPC coded signal is transmitted over a satellite link in support of a broadband satellite application.

[0015] Still other aspects, features, and advantages of the present invention are readily apparent from the following detailed description, simply by illustrating a number of particular embodiments and implementations, including the best mode contemplated for carrying out the present invention. The present invention is also capable of other and different embodiments, and its several details can be modified in various obvious respects, all without departing from scope of the present invention. Accordingly, the drawing and description are to be regarded as illustrative in nature, and not as restrictive.

BRIEF DESCRIPTION OF THE DRAWINGS

[0016] The present invention is illustrated by way of example, and not by way of limitation, in the figures of the accompanying drawings and in which like reference numerals refer to similar elements and in which:

FIG. 1 is a diagram of a communications system configured to utilize Low Density Parity Check (LDPC) codes, according to an embodiment of the present invention;

FIGs. 2A and 2B are diagrams of exemplary LDPC encoders deployed in the transmitter of FIG. 1;

FIGs. 2C and 2D are flowcharts of the encoding process of the LDPC encoder of FIG. 2B for generating short frame length LDPC codes, according to an embodiment of the present invention;

FIG. 3 is a diagram of an exemplary receiver in the system of FIG. 1;

FIG. 4 is a diagram of a sparse parity check matrix, in accordance with an embodiment of the present invention;

FIG. 5 is a diagram of a bipartite graph of an LDPC code of the matrix of FIG. 4;

FIG. 6 is a diagram of a sub-matrix of a sparse parity check matrix, wherein the sub-matrix contains parity check values restricted to the lower triangular region, according to an embodiment of the present invention;

FIG. 7 is a graph of performance of the LDPC codes at the various code rates and modulation schemes supported by the transmitter of FIG. 2B;

FIG. 8 is a graph of performance of the short LDPC codes at the various code rates supported by the transmitter of FIG. 2B; and

FIG. 9 is a diagram of a computer system that can perform the LDPC encoding process, in accordance with embodiments of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENT

[0017] A system, method, and software for efficiently encoding short frame length Low Density Parity Check (LDPC) codes are described. In the following description, for the purposes of explanation, numerous specific details are set forth in order to provide a thorough understanding of the present invention. It is apparent, however, to one skilled in the art that the present invention may be practiced without these specific details or with an equivalent arrangement. In other instances, well-known structures and devices are shown in block diagram form in order to avoid unnecessarily obscuring the present invention.

[0018] FIG. 1 is a diagram of a communications system configured to utilize Low Density Parity Check (LDPC) codes, according to an embodiment of the present invention. A digital communications system 100 includes a transmitter 101 that generates signal waveforms across a communication channel 103 to a receiver 105. In this discrete communications system 100, the transmitter 101 has a message source that produces a discrete set of possible messages; each of the possible messages has a corresponding signal waveform. These signal waveforms are attenuated, or otherwise altered, by communications channel 103. To combat the noise channel 103, LDPC codes are utilized.

[0019] By way of example, the channel 103 is a satellite link serving satellite terminals (e.g., Very Small Aperture Terminals (VSATs)) in support of broadband satellite applications. Such applications include satellite broadcasting and interactive services (and compliant with the Digital Video Broadcast (DVB) - S2 standard). The Digital Video Broadcasting via Satellite (DVB-S) standard has been widely adopted worldwide to provide, for instance, digital satellite television programming.

[0020] The LDPC codes that are generated by the transmitter 101 enable high speed implementation without incurring any performance loss. These structured LDPC codes output from the transmitter 101 avoid assignment of a small number of check nodes to the bit nodes already vulnerable to channel errors by virtue of the modulation scheme (e.g., 8-PSK).

[0021] Such LDPC codes have a parallelizable decoding algorithm (unlike turbo codes), which advantageously involves simple operations such as addition, comparison and table look-up. Moreover, carefully designed LDPC codes do not

exhibit any sign of error floor.

[0022] According to one embodiment of the present invention, the transmitter 101 generates, using a relatively simple encoding technique, LDPC codes based on parity check matrices (which facilitate efficient memory access during decoding) to communicate with the receiver 105. The transmitter 101 employs LDPC codes that can outperform concatenated turbo+RS (Reed-Solomon) codes, provided the block length is sufficiently large.

[0023] FIGs. 2A and 2B are diagrams of exemplary LDPC encoders deployed in the transmitter of FIG. 1. As seen in FIG. 2A, a transmitter 200 is equipped with an LDPC encoder 203 that accepts input from an information source 201 and outputs coded stream of higher redundancy suitable for error correction processing at the receiver 105. The information source 201 generates k signals from a discrete alphabet, X . LDPC codes are specified with parity check matrices. On the other hand, encoding LDPC codes require, in general, specifying the generator matrices. Even though it is possible to obtain generator matrices from parity check matrices using Gaussian elimination, the resulting matrix is no longer sparse and storing a large generator matrix can be complex.

[0024] The encoder 203 generates signals from alphabet Y to a modulator 205 using a simple encoding technique that makes use of only the parity check matrix by imposing structure onto the parity check matrix. Specifically, a restriction is placed on the parity check matrix by constraining certain portion of the matrix to be triangular. The construction of such a parity check matrix is described more fully below in FIG. 6. Such a restriction results in negligible performance loss, and therefore, constitutes an attractive trade-off.

[0025] The modulator 205 maps the encoded messages from encoder 203 to signal waveforms that are transmitted to a transmit antenna 207, which emits these waveforms over the communication channel 103. Accordingly, the encoded messages are modulated and distributed to a transmit antenna 207. The transmissions from the transmit antenna 207 propagate to a receiver (shown in FIG. 3), as discussed below.

[0026] FIG. 2B shows an LDPC encoder utilized with a Bose Chaudhuri Hocquenghem (BCH) encoder and a cyclic redundancy check (CRC) encoder, according to one embodiment of the present invention. Under this scenario, the codes generated by the LDPC encoder 203, along with the CRC encoder 209 and the BCH encoder 211, have a concatenated outer BCH code and inner low density parity check (LDPC) code. Furthermore, error detection is achieved using cyclic redundancy check (CRC) codes. The CRC encoder 209, in an exemplary embodiment, encodes using an 8-bit CRC code with generator polynomial $(x^5+x^4+x^3+x^2+1)(x^2+x+1)(x+1)$. The CRC code is output to the BCH encoder 211.

[0027] The LDPC encoder 203 systematically encodes an information block of size k_{ldpc} , $i = (i_0, i_1, \dots, i_{k_{ldpc}-1})$ onto a codeword of size n_{ldpc} , $c = (i_0, i_1, \dots, i_{k_{ldpc}-1}, p_0, p_1, \dots, p_{n_{ldpc}-k_{ldpc}-1})$. The transmission of the codeword starts in the given order from i_0 and ends with $p_{n_{ldpc}-k_{ldpc}-1}$. LDPC code parameters (n_{ldpc}, k_{ldpc}) are given in Table 1 below.

Table 1

LDPC Code Parameters (n_{ldpc}, k_{ldpc})		
Code Rate	LDPC Uncoded Block Length k_{ldpc}	LDPC Coded Block Length n_{ldpc}
1/2	32400	64800
2/3	43200	64800
3/4	48600	64800
4/5	51840	64800
5/6	54000	64800
3/5	38880	64800
8/9	57600	64800

[0028] The task of the LDPC encoder 203 is to determine $n_{ldpc} - k_{ldpc}$ parity bits $(p_0, p_1, \dots, p_{n_{ldpc}-k_{ldpc}-1})$ for every block of k_{ldpc} information bits, $(i_0, i_1, \dots, i_{k_{ldpc}-1})$. The procedure is as follows. First, the parity bits are initialized; $p_0 = p_1 = p_2 = \dots = p_{n_{ldpc}-k_{ldpc}-1} = 0$. The first information bit, i_0 , are accumulated at parity bit addresses specified in the first row of Tables 2 - 8. For example, for rate 2/3 (Table 4), the following results:

$$p_0 = p_0 \oplus i_0$$

$$p_{10491} = p_{10491} \oplus i_0$$

$$p_{16043} = p_{16043} \oplus i_0$$

$$p_{506} = p_{506} \oplus i_0$$

$$p_{12826} = p_{12826} \oplus i_0$$

$$\begin{aligned}
 p_{8065} &= p_{8065} \oplus i_0 \\
 p_{8226} &= p_{8226} \oplus i_0 \\
 p_{2767} &= p_{2767} \oplus i_0 \\
 p_{240} &= p_{240} \oplus i_0 \\
 p_{18673} &= p_{18673} \oplus i_0 \\
 p_{9279} &= p_{9279} \oplus i_0 \\
 p_{10579} &= p_{10579} \oplus i_0 \\
 p_{20928} &= p_{20928} \oplus i_0
 \end{aligned}$$

(All additions are in GF(2)).

[0029] Then, for the next 359 information bits, $i_m, m = 1, 2, \dots, 359$, these bits are accumulated at parity bit addresses $\{x + m \bmod 360 \times q\} \bmod (n_{ldpc} - k_{ldpc})$, where x denotes the address of the parity bit accumulator corresponding to the first bit i_0 , and q is a code rate dependent constant specified in Table 9. Continuing with the example, $q = 60$ for rate 2/3. By way of example, for information bit i_1 the following operations are performed:

$$\begin{aligned}
 p_{60} &= p_{60} \oplus i_1 \\
 p_{10551} &= p_{10551} \oplus i_1 \\
 p_{16103} &= p_{16103} \oplus i_1 \\
 p_{566} &= p_{566} \oplus i_1 \\
 p_{12886} &= p_{12886} \oplus i_1 \\
 p_{8125} &= p_{8125} \oplus i_1 \\
 p_{8286} &= p_{8286} \oplus i_1 \\
 p_{2827} &= p_{2827} \oplus i_1 \\
 p_{300} &= p_{300} \oplus i_1 \\
 p_{18733} &= p_{18733} \oplus i_1 \\
 p_{9339} &= p_{9339} \oplus i_1 \\
 p_{10639} &= p_{10639} \oplus i_1 \\
 p_{20988} &= p_{20988} \oplus i_1
 \end{aligned}$$

[0030] For the 361st information bit i_{360} , the addresses of the parity bit accumulators are given in the second row of the Tables 2 - 8. In a similar manner the addresses of the parity bit accumulators for the following 359 information bits $i_m, m = 361, 362, \dots, 719$ are obtained using the formula $\{x + m \bmod 360 \times q\} \bmod (n_{ldpc} - k_{ldpc})$, where x denotes the address of the parity bit accumulator corresponding to the information bit i_{360} , i.e., the entries in the second row of the Tables 2 - 8. In a similar manner, for every group of 360 new information bits, a new row from Tables 2 - 8 are used to find the addresses of the parity bit accumulators.

[0031] Addresses of parity bit accumulators are given in Tables 2 - 8.

Table 2

Address of Parity Bit Accumulators (Rate 1/2)									
15	5604	5754	7705	4356	6844	8186	4014		
16	5341	2456	6053	4571	5034	8521	1858		
17	5207	8819	4926	8482	7518	8225	2585		
18	4948	1285	6825	8840	3454	8255	3137		
19	672	263	6959	5970	2556	1273	6091		
20	712	2386	6354	4061	1062	5045	5158		
21	2543	5748	4822	2348	3089	6328	5876		
22	926	5701	269	3693	2438	3190	3507		
23	2802	4520	3577	5324	1091	4667	4449		
24	5140	2003	1263	4742	6497	1185	6202		
0	4046	6934							
1	2855	66							
2	6694	212							
3	3439	1158							
4	3850	4422							

EP 1 513 258 B9

(continued)

Address of Parity Bit Accumulators (Rate 1/2)	
5	5 5924 290
	6 1467 4049
	7 7820 2242
	8 4606 3080
	9 4633 7877
10	10 3884 6868
	11 8935 4996
	12 3028 764
	13 5988 1057
15	14 7411 3450

Table 3

Address of Parity Bit Accumulators (Rate 3/5)	
20	2765 5713 6426 3596 1374 4811 2182 544 3394 2840 4310 771
	4951 211 2208 723 1246 2928 398 5739 265 5601 5993 2615
	210 4730 5777 3096 4282 6238 4939 1119 6463 5298 6320 4016
	4167 2063 4757 3157 5664 3956 6045 563 4284 2441 3412 6334
25	4201 2428 4474 59 1721 736 2997 428 3807 1513 4732 6195
	2670 3081 5139 3736 1999 5889 4362 3806 4534 5409 6384 5809
	5516 1622 2906 3285 1257 5797 3816 817 875 2311 3543 1205
	4244 2184 5415 1705 5642 4886 2333 287 1848 1121 3595 6022
	2142 2830 4069 5654 1295 2951 3919 1356 884 1786 396 4738
30	0 2161 2653
	1 1380 1461
	2 2502 3707
	3 3971 1057
35	4 5985 6062
	5 1733 6028
	6 3786 1936
	7 4292 956
	8 5692 3417
40	9 266 4878
	10 4913 3247
	11 4763 3937
	12 3590 2903
45	13 2566 4215
	14 5208 4707
	15 3940 3388
	16 5109 4556
50	17 4908 4177

Table 4

Address of Parity Bit Accumulators (Rate 2/3)	
55	0 2084 1613 1548 1286 1460 3196 4297 2481 3369 3451 4620 2622
	1 122 1516 3448 2880 1407 1847 3799 3529 373 971 4358 3108
	2 259 3399 929 2650 864 3996 3833 107 5287 164 3125 2350

EP 1 513 258 B9

(continued)

Address of Parity Bit Accumulators (Rate 2/3)	
5	3 342 3529
	4 4198 2147
	5 1880 4836
	6 3864 4910
	7 243 1542
10	8 3011 1436
	9 2167 2512
	10 4606 1003
	11 2835 705
	12 3426 2365
15	13 3848 2474
	14 1360 1743
	0 163 2536
	1 2583 1180
20	2 1542 509
	3 4418 1005
	4 5212 5117
	5 2155 2922
	6 347 2696
25	7 226 4296
	8 1560 487
	9 3926 1640
	10 149 2928
30	11 2364 563
	12 635 688
	13 231 1684
	14 1129 3894
35	

Table 5

Address of Parity Bit Accumulators (Rate 3/4)	
40	0 3576 1576 3860 1290 4199 815 2978 3428 3639 2181 1750
	1 1960 2307 2697 4240 3238 3555 265 379 128 2911 3653
	2 99 1389 3627 830 2448 1185 3034 2946 2598 1960 1032
	3 3198 478 4207 1481 1009 2616 1924 3437 554 683 1801
	4 2681 2135
45	5 3107 4027
	6 2637 3373
	7 3830 3449
	8 4129 2060
	9 4184 2742
50	10 3946 1070
	11 2239 984
	0 1458 3031
	1 3003 1328
55	2 1137 1716
	3 132 3725
	4 1817 638
	5 1774 3447

EP 1 513 258 B9

(continued)

5

10

15

20

25

Address of Parity Bit Accumulators (Rate 3/4)	
6 3632 1257	
7 542 3694	
8 1015 1945	
9 1948 412	
10 995 2238	
11 4141 1907	
0 2480 3079	
1 3021 1088	
2 713 1379	
3 997 3903	
4 2323 3361	
5 1110 986	
6 2532 142	
7 1690 2405	
8 1298 1881	
9 615 174	
10 1648 3112	
11 1415 2808	

Table 6

30

35

40

45

50

55

Address of Parity Bit Accumulators (Rate 4/5)	
0 2319 198 789 902 1314 2806 143 2088 3525 1972	
1 1285 1816 2194 1037 3293 509 3417 2294 2438 3111	
2 704 1967 1228 1486 842 3400 1075 2776 3473 3327	
3 1501 63 3235 2253 661 2968 1819 252 360 2174	
4 3040 2231 2531 2690 1527 2605 2130 791 1786 1699	
5 896 1565	
6 2493 184	
7 212 3210	
8 727 1339	
9 3428 612	
0 2663 1947	
1 230 2695	
2 2025 2794	
3 3039 283	
4 862 2889	
5 376 2110	
6 2034 2286	
7 951 2068	
8 3108 3542	
9 307 1421	
0 2272 1197	
1 1800 3280	
2 331 2308	
3 465 2552	
4 1038 2479	
5 1383 343	
6 94 236	

EP 1 513 258 B9

(continued)

5

10

15

20

Address of Parity Bit Accumulators (Rate 4/5)		
7	2619	121
8	1497	2774
9	2116	1855
0	722	1584
1	2767	1881
2	2701	1610
3	3283	1732
4	168	1099
5	3074	243
6	3460	945
7	2049	1746
8	566	1427
9	3545	1168

Table 7

25

30

35

40

45

50

55

Address of Parity Bit Accumulators (Rate 5/6)		
0	1752 825 2637 402 2730 1838 1945 2490 1627 2137 1202 2188	
1	1501 1900 2147 1967 1757 2803 555 2020 333 2266 2577 1399	
2	1675 799 422 488 945 1536 2288 999 1727 2214 1923 2152	
3	2409 499 1481 908 559 716 1270 333 2508 2264 1702 2805	
4	2447 1926	
5	414 1224	
6	2114 842	
7	212 573	
0	2383 2112	
1	2286 2348	
2	545 819	
3	1264 143	
4	1701 2258	
5	964 166	
6	114 2413	
7	2243 81	
0	1245 1581	
1	775 169	
2	1696 1104	
3	1914 2831	
4	532 1450	
5	91 974	
6	497 2228	
7	2326 1579	
0	2482 256	
1	1117 1261	
2	1257 1658	
3	1478 1225	
4	2511 980	
5	2320 2675	
6	435 1278	
7	228 503	

EP 1 513 258 B9

(continued)

Address of Parity Bit Accumulators (Rate 5/6)

0 1885 2369
 1 57 483
 2 838 1050
 3 1231 1990
 4 1738 68
 5 2392 951
 6 163 645
 7 2644 1704

Table 8

Address of Parity Bit Accumulators (Rate 8/9)

0 1558 712 805
 1 1450 873 1337
 2 1741 1129 1184
 3 294 806 1566
 4 482 605 923
 0 926 1578
 1 777 1374
 2 608 151
 3 1195 210
 4 1484 692
 0 427 488
 1 828 1124
 2 874 1366
 3 1500 835
 4 1496 502
 0 1006 1701
 1 1155 97
 2 657 1403
 3 1453 624
 4 429 1495
 0 809 385
 1 367 151
 2 1323 202
 3 960 318
 4 1451 1039
 0 1098 1722
 1 1015 1428
 2 1261 1564
 3 544 1190
 4 1472 1246
 0 508 630
 1 421 1704
 2 284 898
 3 392 577
 4 1155 556
 0 631 1000
 1 732 1368

(continued)

Address of Parity Bit Accumulators (Rate 8/9)

2 1328 329
3 1515 506
4 1104 1172

[0032] After all of the information bits are exhausted, the final parity bits are obtained as follows. First, the following operations are performed, starting with $i = 1$

$$p_i = p_i \oplus p_{i-1}, \quad i = 1, 2, \dots, n_{ldpc} - k_{ldpc} - 1.$$

Final content of p_i , $i = 0, 1, \dots, n_{ldpc} - k_{ldpc} - 1$ is equal to the parity bit p_i .

Table 9

Code Rate	q
2/3	60
5/6	30
1/2	90
3/4	45
4/5	36
3/5	72
8/9	20

[0033] The generator polynomial of the t error correcting BCH encoder 211 is obtained by multiplying the first t polynomials in the following list of Table 10:

Table 10

$g_1(x)$	$1+x^2+x^3+x^5+x^{16}$
$g_2(x)$	$1+x+x^4+x^5+x^6+x^8+x^{16}$
$g_3(x)$	$1+x^2+x^3+x^4+x^5+x^7+x^8+x^9+x^{10}+x^{11}+x^{16}$
$g_4(x)$	$1+x^2+x^4+x^6+x^9+x^{11}+x^{12}+x^{14}+x^{16}$
$g_5(x)$	$1+x+x^2+x^3+x^5+x^8+x^9+x^{10}+x^{11}+x^{12}+x^{16}$
$g_6(x)$	$1+x^2+x^4+x^5+x^7+x^8+x^9+x^{10}+x^{12}+x^{13}+x^{14}+x^{15}+x^{16}$
$g_7(x)$	$1+x^2+x^5+x^6+x^8+x^9+x^{10}+x^{11}+x^{13}+x^{15}+x^{16}$
$g_8(x)$	$1+x+x^2+x^5+x^6+x^8+x^9+x^{12}+x^{13}+x^{14}+x^{16}$
$g_9(x)$	$1+x^5+x^7+x^9+x^{10}+x^{11}+x^{16}$
$g_{10}(x)$	$1+x+x^2+x^5+x^7+x^8+x^{10}+x^{12}+x^{13}+x^{14}+x^{16}$
$g_{11}(x)$	$1+x^2+x^3+x^5+x^9+x^{11}+x^{12}+x^{13}+x^{16}$
$g_{12}(x)$	$1+x+x^5+x^6+x^7+x^9+x^{11}+x^{12}+x^{16}$

[0034] BCH encoding of information bits $m = (m_{k_{bch}-1}, m_{k_{bch}-2}, \dots, m_1, m_0)$ onto a codeword $c = (m_{k_{bch}-1}, m_{k_{bch}-2}, \dots, m_1, m_0, d_{n_{bch}-k_{bch}-1}, d_{n_{bch}-k_{bch}-2}, \dots, d_1, d_0)$ is achieved as follows. The message polynomial $m(x) = m_{k_{bch}-1}x^{k_{bch}-1} + m_{k_{bch}-2}x^{k_{bch}-2} + \dots + m_1x + m_0$ is multiplied by $x^{n_{bch}-k_{bch}}$. Next, $x^{n_{bch}-k_{bch}}m(x)$ divided by $g(x)$. With $d(x) = d_{n_{bch}-k_{bch}-1}x^{n_{bch}-k_{bch}-1} + \dots + d_1x + d_0$ as the remainder, the codeword polynomial is set as follows: $c(x) = x^{n_{bch}-k_{bch}}m(x) + d(x)$.

[0035] As seen in FIG. 2B, the LDPC encoder 203 outputs to a bit interleaver 213. By way of example, 8-PSK, 16-APSK, and 32-APSK modulation formats are utilized. Data is serially written into the interleaver column-wise (from the top to the bottom), and serially read out row-wise (from the left to the right). However, in the case of code rate 3/5 with 8-PSK, it has been determined that reading the data out from the right to the left, instead of left to right, yields better performance (as illustrated in FIG. 7).

[0036] The configuration of the block interleaver for each modulation format is specified in Table 11.

Table 11

Bit Interleaver Structure			
Modulation	Rows (for $n_{ldpc}=64800$)	Rows (for $n_{ldpc}=16200$)	Columns
8-PSK	21600	5400	3
16-APSK	16200	4050	4
32-APSK	12960	3240	5

[0037] FIGs. 2C and 2D are flowcharts of the encoding process of the LDPC encoder of FIG. 2B for generating short frame length LDPC codes, according to an embodiment of the present invention. In step 211, information bits are received and processed to the chain of encoders 209, 211, and 203. Consequently, the LDPC encoder 203 generates LDPC codes with outer BCH codes based on the received information bits, as in step 223. The codes also contain the CRC code. In step 225, the coded bits are altered by the bit interleaver 213, as described above. Next, the LDPC codes are represented by signals that are modulated, per step 227, for transmission over the channel 103, which in an exemplary embodiment, is a satellite link to one or more satellite terminals (step 229).

[0038] As discussed, k_{ldpc} bits are systematically encoded to generate n_{ldpc} bits. According to one embodiment of the present invention, n_{ldpc} is 16200 bits, which is a short block length. Given the relatively short length of such codes, LDPC codes having approximate lengths of 16200 bits or less are deemed "short" block length codes.

[0039] In accordance with an embodiment of the present invention, short blocks codes are generated by shortening versions of slightly longer (k_m , n_m) "mother" codes of block size $n_m > 16200$. As shown in FIG. 2D, k_{ldpc} of the BCH encoded bits are preceded by $k_m - k_{ldpc}$ dummy zeros (per step 251). The resulting k_m bits are systematically encoded to generate n_m bits, as in step 253. The first $k_m - k_{ldpc}$ dummy zeros are then deleted, as in step 255, and the resulting $n_{ldpc} = 16200$ bits will be transmitted (step 257). It is noted that $k_m - k_{ldpc} = n_m n_{ldpc}$.

[0040] The parameters of short frame length codes are provided in Table 12 as follows.

Table 12

Mother Code Rate k_m/n_m	k_{ldpc}	k_m	n_m	k_{bch}	BCH Correction (bits)	Effective Rate $k_{bch}/16200$
1/2	7200	9000	18000	7032	12	0.434
3/5	9720	9720	16200	9552	12	0.589
2/3	10800	10800	16200	10632	12	0.656
3/4	11880	12960	17280	11712	12	0.722
4/5	12600	14400	18000	12432	12	0.767
5/6	13320	14400	17280	13152	12	0.811
8/9	14400	14400	16200	14232	12	0.878

[0041] Simulations of the performance of these codes were conducted, as shown in FIG. 8.

[0042] Tables 13-15 provide other exemplary code rates, 1/3, 1/5 and 2/5 for n_{ldpc} of 16200 bits:

Table 13

Address of Parity Bit Accumulators (Rate 1/3)
416 8909 4156 3216 3112 2560 2912 6405 8593 4969 6723 6912 8978 3011 4339 9312 6396 2957 7288 5485 6031 10218 2226 3575

EP 1 513 258 B9

(continued)

5

10

15

20

Address of Parity Bit Accumulators (Rate 1/3)

3383 10059 1114 10008 10147 9384 4290 434 5139 3536 1965 2291
 2797 3693 7615 7077 743 1941 8716 6215 3840 5140 4582 5420
 6110 855 1515 7404 4879 4946 5383 1831 3441 9569 10472 4306
 1505 5682 7778
 7172 6830 6623
 7281 3941 3505
 10270 8669 914
 3622 7563 9388
 9930 5058 4554
 4844 9609 2707
 6883 3237 1714
 4768 3878 10017
 10127 3334 8267

Table 14

25

30

Address of Parity Bit Accumulators (Shortened from Rate 1/5)

6295 9626 304 7695 4839 4936 1660 144 11203 5567 6347 12557
 10691 4988 3859 3734 3071 3494 7687 10313 5964 8069 8296 11090
 10774 3613 5208 11177 7676 3549 8746 6583 7239 12265 2674 4292
 11869 3708 5981 8718 4908 10650 6805 3334 2627 10461 9285 11120
 7844 3079 10773
 3385 10854 5747
 1360 12010 12202
 6189 4241 2343
 9840 12726 4977

35

Table 15

40

45

50

55

Address of Parity Bit Accumulators (Rate 2/5)

5650 4143 8750 583 6720 8071 635 1767 1344 6922 738 6658
 5696 1685 3207 415 7019 5023 5608 2605 857 6915 1770 8016
 3992 771 2190 7258 8970 7792 1802 1866 6137 8841 886 1931
 4108 3781 7577 6810 9322 8226 5396 5867 4428 8827 7766 2254
 4247 888 4367 8821 9660 324 5864 4774 227 7889 6405 8963
 9693 500 2520 2227 1811 9330 1928 5140 4030 4824 806 3134
 1652 8171 1435
 3366 6543 3745
 9286 8509 4645
 7397 5790 8972
 6597 4422 1799
 9276 4041 3847
 8683 7378 4946
 5348 1993 9186
 6724 9015 5646
 4502 4439 8474
 5107 7342 9442
 1387 8910 2660

[0043] The above approach to designing LDPC codes, as provided in Tables 2-8 and 13-15, advantageously permits storage and retrieval of relevant information regarding partitioned groups of bit nodes and check nodes to be always placed in contiguously memory locations within memory (e.g., Random Access Memory (RAM)). Further, this enables use of a single RAM bank, thereby minimizing size of the integrated circuit. As mentioned, the above LDPC codes, can

[0044] FIG. 3 is a diagram of an exemplary receiver in the system of FIG. 1. At the receiving side, a receiver 300 includes a demodulator 301 that performs demodulation of received signals from transmitter 200. These signals are received at a receive antenna 303 for demodulation. After demodulation, the received signals are forwarded to a decoder 305, which attempts to reconstruct the original source messages by generating messages, X' , in conjunction with a bit metric generator 307. The bit metric generator 307 may exchange information with the decoder 305 back and forth (iteratively) during the decoding process. These decoding approaches are more fully described in co-pending application, entitled "Method and System for Routing in Low Density Parity Check (LDPC) Decoders," filed July 3, 2003 (Serial No. 10/613,824; Attorney Docket PD-203009). To appreciate the advantages offered by the present invention, it is instructive to examine how LDPC codes are generated, as discussed in FIG. 4.

[0045] FIG. 4 is a diagram of a sparse parity check matrix, in accordance with an embodiment of the present invention. LDPC codes are long, linear block codes with sparse parity check matrix $H_{(n-k) \times n}$. Typically the block length, n , ranges from thousands to tens of thousands of bits. For example, a parity check matrix for an LDPC code of length $n=8$ and rate $\frac{1}{2}$ is shown in FIG. 4. The same code can be equivalently represented by the bipartite graph, per FIG. 5.

[0046] FIG. 5 is a diagram of a bipartite graph of an LDPC code of the matrix of FIG. 4. Parity check equations imply that for each check node, the sum (over GF (Galois Field)(2)) of all adjacent bit nodes is equal to zero. As seen in the figure, bit nodes occupy the left side of the graph and are associated with one or more check nodes, according to a predetermined relationship. For example, corresponding to check node m_1 , the following expression exists $n_1 + n_4 + n_5 + n_8 = 0$ with respect to the bit nodes.

[0047] Returning the receiver 303, the LDPC decoder 305 is considered a message passing decoder, whereby the decoder 305 aims to find the values of bit nodes. To accomplish this task, bit nodes and check nodes iteratively communicate with each other. The nature of this communication is described below.

[0048] From check nodes to bit nodes, each check node provides to an adjacent bit node an estimate ("opinion") regarding the value of that bit node based on the information coming from other adjacent bit nodes. For instance, in the above example if the sum of n_4 , n_5 and n_8 "looks like" 0 to m_1 , then m_1 , would indicate to n_1 that the value of n_1 is believed to be 0 (since $n_1 + n_4 + n_5 + n_8 = 0$); otherwise m_1 indicate to n_1 that the value of n_1 is believed to be 1. Additionally, for soft decision decoding, a reliability measure is added.

[0049] From bit nodes to check nodes, each bit node relays to an adjacent check node an estimate about its own value based on the feedback coming from its other adjacent check nodes. In the above example n_1 has only two adjacent check nodes m_1 and m_3 . If the feedback coming from m_3 to n_1 indicates that the value of n_1 is probably 0, then n_1 would notify m_1 that an estimate of n_1 's own value is 0. For the case in which the bit node has more than two adjacent check nodes, the bit node performs a majority vote (soft decision) on the feedback coming from its other adjacent check nodes before reporting that decision to the check node it communicates. The above process is repeated until all bit nodes are considered to be correct (i.e., all parity check equations are satisfied) or until a predetermined maximum number of iterations is reached, whereby a decoding failure is declared.

[0050] FIG. 6 is a diagram of a sub-matrix of a sparse parity check matrix, wherein the sub-matrix contains parity check values restricted to the lower triangular region, according to an embodiment of the present invention. As described previously, the encoder 203 (of FIGs. 2A and 2B) can employ a simple encoding technique by restricting the values of the lower triangular area of the parity check matrix. According to an embodiment of the present invention, the restriction imposed on the parity check matrix is of the form:

$$H_{(n-k) \times n} = [A_{(n-k) \times k} B_{(n-k) \times (n-k)}]$$

, where B is lower triangular.

[0051] Any information block $i = (i_0, i_1, \dots, i_{k-1})$ is encoded to a codeword $c = (i_0, i_1, \dots, i_{k-1}, p_0, p_1, \dots, p_{n-k-1})$ using $Hc^T = 0$, and recursively solving for parity bits; for example,

$$a_{00}i_0 + a_{01}i_1 + \dots + a_{0,k-1}i_{k-1} + p_0 = 0 \Rightarrow \text{Solve } p_0$$

$$a_{10}i_0 + a_{11}i_1 + \dots + a_{1,k-1}i_{k-1} + b_{10}p_0 + p_1 = 0 \Rightarrow \text{Solve } p_1$$

and similarly for $p_2, p_3, \dots, p_{n-k-1}$.

[0052] FIG. 7 is a graph of performance of the LDPC codes at the various code rates and modulation schemes supported by the transmitter of FIG. 2B. As seen, the 3/5 rate, 8-PSK scenario rivals the performance of the LDPC codes employing QPSK.

[0053] FIG. 8 shows the simulation results for short block size LDPC codes, in accordance with an embodiment of the present invention. Table 16 provides the estimated performance at Packet Error Rate (PER) of 10^{-7} for the short codes ($n_{ldpc} = 16200$).

Table 16

Mode	Estimated Es/No (dB)
QPSK 0.444	0.65
QPSK 3/5	2.45
QPSK 2/3	3.35
QPSK 0.733	4.35
QPSK 0.777	4.90
QPSK 0.822	5.40
QPSK 8/9	6.50

[0054] FIG. 9 illustrates a computer system upon which an embodiment according to the present invention can be implemented. The computer system 900 includes a bus 901 or other communication mechanism for communicating information, and a processor 903 coupled to the bus 901 for processing information. The computer system 900 also includes main memory 905, such as a random access memory (RAM) or other dynamic storage device, coupled to the bus 901 for storing information and instructions to be executed by the processor 903. Main memory 905 can also be used for storing temporary variables or other intermediate information during execution of instructions to be executed by the processor 903. The computer system 900 further includes a read only memory (ROM) 907 or other static storage device coupled to the bus 901 for storing static information and instructions for the processor 903. A storage device 909, such as a magnetic disk or optical disk, is additionally coupled to the bus 901 for storing information and instructions.

[0055] The computer system 900 may be coupled via the bus 901 to a display 911, such as a cathode ray tube (CRT), liquid crystal display, active matrix display, or plasma display, for displaying information to a computer user. An input device 913, such as a keyboard including alphanumeric and other keys, is coupled to the bus 901 for communicating information and command selections to the processor 903. Another type of user input device is cursor control 915, such as a mouse, a trackball, or cursor direction keys for communicating direction information and command selections to the processor 903 and for controlling cursor movement on the display 911.

[0056] According to one embodiment of the invention, generation of LDPC codes is provided by the computer system 900 in response to the processor 903 executing an arrangement of instructions contained in main memory 905. Such instructions can be read into main memory 905 from another computer-readable medium, such as the storage device 909. Execution of the arrangement of instructions contained in main memory 905 causes the processor 903 to perform the process steps described herein. One or more processors in a multi-processing arrangement may also be employed to execute the instructions contained in main memory 905. In alternative embodiments, hard-wired circuitry may be used in place of or in combination with software instructions to implement the embodiment of the present invention. Thus, embodiments of the present invention are not limited to any specific combination of hardware circuitry and software.

[0057] The computer system 900 also includes a communication interface 917 coupled to bus 901. The communication interface 917 provides a two-way data communication coupling to a network link 919 connected to a local network 921. For example, the communication interface 917 may be a digital subscriber line (DSL) card or modem, an integrated services digital network (ISDN) card, a cable modem, or a telephone modem to provide a data communication connection to a corresponding type of telephone line. As another example, communication interface 917 may be a local area network (LAN) card (e.g. for Ethernet™ or an Asynchronous Transfer Model (ATM) network) to provide a data communication connection to a compatible LAN. Wireless links can also be implemented. In any such implementation, communication interface 917 sends and receives electrical, electromagnetic, or optical signals that carry digital data streams representing various types of information. Further, the communication interface 917 can include peripheral interface devices, such

as a Universal Serial Bus (USB) interface, a PCMCIA (Personal Computer Memory Card International Association) interface, etc.

[0058] The network link 919 typically provides data communication through one or more networks to other data devices. For example, the network link 919 may provide a connection through local network 921 to a host computer 923, which has connectivity to a network 925 (e.g. a wide area network (WAN) or the global packet data communication network now commonly referred to as the "Internet") or to data equipment operated by service provider. The local network 921 and network 925 both use electrical, electromagnetic, or optical signals to convey information and instructions. The signals through the various networks and the signals on network link 919 and through communication interface 917, which communicate digital data with computer system 900, are exemplary forms of carrier waves bearing the information and instructions.

[0059] The computer system 900 can send messages and receive data, including program code, through the network(s), network link 919, and communication interface 917. In the Internet example, a server (not shown) might transmit requested code belonging to an application program for implementing an embodiment of the present invention through the network 925, local network 921 and communication interface 917. The processor 903 may execute the transmitted code while being received and/or store the code in storage device 99, or other non-volatile storage for later execution. In this manner, computer system 900 may obtain application code in the form of a carrier wave.

[0060] The term "computer-readable medium" as used herein refers to any medium that participates in providing instructions to the processor 903 for execution. Such a medium may take many forms, including but not limited to non-volatile media, volatile media, and transmission media. Non-volatile media include, for example, optical or magnetic disks, such as storage device 909. Volatile media include dynamic memory, such as main memory 905. Transmission media include coaxial cables, copper wire and fiber optics, including the wires that comprise bus 901. Transmission media can also take the form of acoustic, optical, or electromagnetic waves, such as those generated during radio frequency (RF) and infrared (IR) data communications. Common forms of computer-readable media include, for example, a floppy disk, a flexible disk, hard disk, magnetic tape, any other magnetic medium, a CD-ROM, CDRW, DVD, any other optical medium, punch cards, paper tape, optical mark sheets, any other physical medium with patterns of holes or other optically recognizable indicia, a RAM, a PROM, and EPROM, a FLASH-EPROM, any other memory chip or cartridge, a carrier wave, or any other medium from which a computer can read.

[0061] Various forms of computer-readable media may be involved in providing instructions to a processor for execution. For example, the instructions for carrying out at least part of the present invention may initially be borne on a magnetic disk of a remote computer. In such a scenario, the remote computer loads the instructions into main memory and sends the instructions over a telephone line using a modem. A modem of a local computer system receives the data on the telephone line and uses an infrared transmitter to convert the data to an infrared signal and transmit the infrared signal to a portable computing device, such as a personal digital assistance (PDA) and a laptop. An infrared detector on the portable computing device receives the information and instructions borne by the infrared signal and places the data on a bus. The bus conveys the data to main memory, from which a processor retrieves and executes the instructions. The instructions received by main memory may optionally be stored on storage device either before or after execution by processor.

[0062] Accordingly, the various examples of the present invention provide an LDPC encoder generates a LDPC code having an outer Bose Chaudhuri Hocquenghem (BCH) code according to one of Tables 2-8 for transmission as a LDPC coded signal. Each of the Tables 2-8 specifies the address of parity bit accumulators. Short LDPC codes are output by utilizing LDPC mother codes that are based on Tables 2-8. k_{ldpc} of the BCH encoded bits are preceded by $k_m - k_{ldpc}$ dummy zeros. The resulting k_m bits are systematically encoded to generate n_m bits. The first $k_m - k_{ldpc}$ dummy zeros are then deleted to yield the shortened code. For an LDPC code with code rate of 3/5 utilizing 8-PSK (Phase Shift Keying) modulation, an interleaver provides for interleaving bits of the output LDPC code by serially writing data associated with the LDPC code column-wise into a table and reading the data row-wise from right to left. The above approach advantageously yields reduced complexity without sacrificing performance.

[0063] while the present invention has been described in connection with a number of embodiments and implementations, the present invention is not so limited but covers various obvious modifications and equivalent arrangements, which fall within the purview of the appended claims.

Claims

1. A transmitter (200) for supporting transmission of a Low Density Parity Check LDPC coded signal, comprising:

a Low Density Parity Check LDPC encoder (203) configured to output, based on received information bits, an LDPC code;
a bit interleaver (213); and

a modulator (205) configured to modulate the LDPC coded signal according to a signal constellation that includes 8-Phase Shift Keying, 8-PSK,

characterised in that the bit interleaver (213) is configured to interleave bits of the output LDPC code by serially writing data associated with the LDPC code column-wise into a table and reading the data row-wise from right to left, wherein the LDPC coded signal represents the interleaved LDPC code, and the LDPC encoder (203) is configured to output the LDPC code with a code rate 3/5 and to generate the LDPC code by accumulating the received information bits at parity bit addresses, the parity bit addresses being determined based on the following table specifying addresses of parity bit accumulators:

Address of Parity Bit Accumulators (Rate 3/5)																
2765	5713	6426	3596	1374	4811	2182	544	3394	2840	4310	771					
4951	211	2208	723	1246	2928	398	5739	265	5601	5993	2615					
210	4730	5777	3096	4282	6238	4939	1119	6463	5298	6320	4016					
4167	2063	4757	3157	5664	3956	6045	563	4284	2441	3412	6334					
4201	2428	4474	59	1721	736	2997	428	3807	1513	4732	6195					
2670	3081	5139	3736	1999	5889	4362	3806	4534	5409	6384	5809					
5516	1622	2906	3285	1257	5797	3816	817	875	2311	3543	1205					
4244	2184	5415	1705	5642	4886	2333	287	1848	1121	3595	6022					
2142	2830	4069	5654	1295	2951	3919	1356	884	1786	396	4738					
0	2161	2653														
1	1380	1461														
2	2502	3707														
3	3971	1057														
4	5985	6062														
5	1733	6028														
6	3786	1936														
7	4292	956														
8	5692	3417														
9	266	4878														
10	4913	3247														
11	4763	3937														
12	3590	2903														
13	2566	4215														
14	5208	4707														
15	3940	3388														
16	5109	4556														
17	4908	4177														

2. A transmitter (200) according to claim 1, further comprising:

a Bose Chaudhuri Hocquenghem BCH encoder (211) coupled to the LDPC encoder (203) and configured to provide an outer code to the LDPC code.

3. A transmitter (200) according to claim 1, wherein the modulated signal is transmitted over a satellite link (103) in support of a broadband satellite application.

4. A transmitting method for supporting transmission of a Low Density Parity Check LDPC coded signal, the method comprising the method steps of:

outputting, based on received information bits, an LDPC code using an LDPC encoder (203);
interleaving bits of the output LDPC code; and
modulating the LDPC coded signal according to a signal constellation that includes 8-Phase Shift Keying, 8-PSK;

characterised in that:

the method step of interleaving comprises serially writing data associated with the LDPC code column wise into a table and reading the data row-wise from left to right,

wherein the LDPC coded signal represents the interleaved LDPC code, and **in that** the method step of outputting comprises outputting the LDPC code with a code rate 3/5 and generating the LDPC code by accumulating the received information bits at parity bit addresses, the parity bit addresses being determined based on the following table specifying addresses of parity bit accumulators:

Address of Parity Bit Accumulators (Rate 3/5)																
2765	5713	6426	3596	1374	4811	2182	544	3394	2840	4310	771					
4951	211	2208	723	1246	2928	398	5739	265	5601	5993	2615					
210	4730	5777	3096	4282	6238	4939	1119	6463	5298	6320	4016					
4167	2063	4757	3157	5664	3956	6045	563	4284	2441	3412	6334					
4201	2428	4474	59	1721	736	2997	428	3807	1513	4732	6195					
2670	3081	5139	3736	1999	5889	4362	3806	4534	5409	6384	5809					
5516	1622	2906	3285	1257	5797	3816	817	875	2311	3543	1205					
4244	2184	5415	1705	5642	4886	2333	287	1848	1121	3595	6022					
2142	2830	4069	5654	1295	2951	3919	1356	884	1786	396	4738					
0	2161	2653														
1	1380	1461														
2	2502	3707														
3	3971	1057														
4	5985	6062														
5	1733	6028														
6	3786	1936														
7	4292	956														
8	5692	3417														
9	266	4878														
10	4913	3247														
11	4763	3937														
12	3590	2903														
13	2566	4215														
14	5208	4707														
15	3940	3388														
16	5109	4556														
17	4908	4177														

5. A method according to claim 4, further comprising:

performing Bose Chaudhuri Hocquenghem BCH encoding of the received information bits to provide an outer code to the LDPC code.

6. A method according to claim 5, wherein the modulated signal is transmitted over a satellite link (103) in support of a broadband satellite application.

Patentansprüche

1. Sendeeinrichtung (200) zur Durchführung einer Übertragung eines Low Density Parity Check LDPC-codierten Signals, welche folgendes enthält:

einen Low Density Parity Check LDPC-Codierer (203), welcher so konfiguriert ist, dass er auf der Basis empfangener Informationsbits einen LDPC-Code ausgibt;
 eine Bit-Zwischeneinordnungseinrichtung oder einen Bit-Interleaver (213); und
 einen Modulator (205), welcher so ausgebildet ist, dass er das LDPC-codierte Signal entsprechend einer Signalkonstellation moduliert, welche eine 8-Phasenverschiebungsverschlüsselung 8-PSK umfasst, **dadurch gekennzeichnet, dass** die Bit-Zwischeneinordnungseinrichtung oder der Bit-Interleaver (213) so ausgebildet ist, dass er Bits des ausgegebenen LDPC-Codes zwischeneinordnet, indem er seriell Daten, welche dem LDPC-Code zugeordnet sind, spaltenweise in eine Tabelle einschreibt und die Daten zeilenweise von rechts nach links liest, wobei das LDPC-codierte Signal den zwischeneingeordneten LDPC-Code repräsentiert und der LDPC-Codierer (203) so konfiguriert ist, dass er den LDPC-Code mit einer Coderate 3/5 ausgibt und den LDPC-Code durch Akkumulieren der empfangenen Informationsbits an den Paritätsbitadressen erzeugt, wobei die Paritätsbitadressen durch die folgende Tabelle bestimmt sind, welche die Adressen der Paritätsbitakkumulatoren angibt:

Adressen der Paritätsbitakkumulatoren (Rate 3/5)

2765 5713 6426 3596 1374 4811 2182 544 3394 2840 4310 771
4951 211 2208 723 1246 2928 398 5739 265 5601 5993 2615
210 4730 5777 3096 4282 6238 4939 1119 6463 5298 6320 4016
4167 2063 4757 3157 5664 3956 6045 563 4284 2441 3412 6334
4201 2428 4474 59 1721 736 2997 428 3807 1513 4732 6195
2670 3081 5139 3736 1999 5889 4362 3806 4534 5409 6384 5809
5516 1622 2906 3285 1257 5797 3816 817 875 2311 3543 1205
4244 2184 5415 1705 5642 4886 2333 287 1848 1121 3595 6022
2142 2830 4069 5654 1295 2951 3919 1356 884 1786 396 4738
0 2161 2653
1 1380 1461
2 2502 3707
3 3971 1057
4 5985 6062
5 1733 6028
6 3786 1936
7 4292 956
8 5692 3417
9 266 4878
10 4913 3247
11 4763 3937
12 3590 2903
13 2566 4215
14 5208 4707
15 3940 3388
16 5109 4556
17 4908 4177

2. Sendeeinrichtung (200) nach Anspruch 1, welche weiter folgendes umfasst;

einen Bose Chaudhuri-Hocquenghem-BCH-Codierer (211), welcher mit dem LDPC-Codierer (203) gekoppelt und so konfiguriert ist, dass er einen Ausgangscode an den LDPC-Code liefert.

3. Sendeeinrichtung (200) nach Anspruch 1, bei welcher das modulierte Signal über eine Satellitenverbindung (103) zur Unterstützung einer breitbandigen Satellitenanwendung gesendet wird.

4. Sendeverfahren zur Durchführung der Übertragung eines Low Density Parity Check LDPC-kodierten Signales, wobei das Verfahren die folgenden Verfahrensschritte umfasst:

Ausgabe, basierend auf empfangenen Informationsbits, eines LDPC-Codes unter Verwendung eines LDPC-Codierers (203);
 Zwischeneinordnen von Bits des ausgegebenen LDPC-Codes; und
 Modulieren der LDPC-codierten Signale gemäß einer Signalkonstellation, welche eine 8-Phasenverschiebungsverschlüsselung 8-PSK umfasst;

dadurch gekennzeichnet, dass der Verfahrensschritt des Zwischeneinordnens das serielle Schreiben von Daten, die dem LDPC-Code zugeordnet sind, spaltenweise in eine Tabelle, und das Lesen der Daten zeilenweise von links nach rechts umfasst, wobei das LDPC-codierte Signal den zwischeneingeordneten LDPC-Code repräsentiert, und dass der Verfahrensschritt der Ausgabe des LDPC-Codes mit einer Coderate 3/5 und das Erzeugen des LDPC-Codes durch Akkumulieren der empfangenen Informationsbits an den Paritätsbitadressen umfasst, wobei die Paritätsbitadressen basierend auf der folgenden Tabelle bestimmt werden, welche die Adressen der Paritätsbitakkumulatoren bestimmt:

Adressen der Paritätsbitakkumulatoren (Rate 3/5)

2765 5713 6426 3596 1374 4811 2182 544 3394 2840 4310 771
4951 211 2208 723 1246 2928 398 5739 265 5601 5993 2615
210 4730 5777 3096 4282 6238 4939 1119 6463 5298 6320 4016
4167 2063 4757 3157 5664 3956 6045 563 4284 2441 3412 6334
4201 2428 4474 59 1721 736 2997 428 3807 1513 4732 6195
2670 3081 5139 3736 1999 5889 4362 3806 4534 5409 6384 5809
5516 1622 2906 3285 1257 5797 3816 817 875 2311 3543 1205
4244 2194 5415 1705 5642 4886 2333 287 1848 1121 3595 6022
2142 2830 4069 5654 1295 2951 3919 1356 884 1786 396 4738
0 2161 2653
1 1380 1461
2 2502 3707
3 3971 1057
4 5985 6062
5 1733 6028
6 3786 1936
7 4292 956
8 5692 3417
9 266 4878
10 4913 3247
11 4763 3937
12 3590 2903
13 2566 4215
14 5208 4707
15 3940 3388
16 5109 4556
17 4908 4177

5. Verfahren nach Anspruch 4, welches weiter folgendes umfasst:

Durchführen einer Bose Chaudhuri Hocquenghem-BCH-Codierung der empfangenen Informationsbits zur Erzeugung eines äußeren Codes für den LDPC-Code.

6. Verfahren nach Anspruch 5, bei welchem das modulierte Signal über eine Satellitenverbindung (103) zur Unterstützung einer breitbandigen Satellitenanwendung übertragen wird.

Revendications

1. Emetteur (200) destiné à soutenir une émission d'un signal codé de vérification de parités à basse densité LDPC, comportant :

un codeur (203) de vérification de parités à basse densité LDPC configuré pour délivrer en sortie, sur la base de bits d'information reçus, un code LDPC;
un entrelaceur (213) de bits ; et
un modulateur (205) configuré pour moduler le signal codé LDPC conformément à une constellation de signaux qui comprend une modulation de phase à huit états, 8-PSK,

caractérisé en ce que l'entrelaceur de bits (213) est configuré pour entrelacer des bits du code LDPC de sortie en écrivant en série des données associées au code LDPC par colonnes dans une table et en lisant les données par rangée de la droite vers la gauche, le signal codé LDPC représentant le code LDPC entrelacé, et le codeur LDPC (203) est configuré pour délivrer en sortie le code LDPC avec un rapport de code 3/5 et pour générer le code LDPC en accumulant les bits d'information reçus à des adresses de bits de parité, les adresses de bits de parité étant déterminées sur la base de la table suivante spécifiant des adresses d'accumulateurs de bits de parité :

Adresse d'accumulateurs de bits de parité (rapport 3/5)

2765 5713 6426 3596 1374 4811 2182 544 3394 2840 4310 771
4951 211 2208 723 1246 2928 398 5739 265 5601 5993 2615
210 4730 5777 3096 4282 6238 4939 1119 6463 5298 6320 4016
4167 2063 4757 3157 5664 3956 6045 563 4284 2441 3412 6334
4201 2428 4474 59 1721 736 2997 428 3807 1513 4732 6195
2670 3081 5139 3736 1999 5889 4362 3806 4534 5409 6384 5809
5516 1622 2906 3285 1257 5797 3816 817 875 2311 3543 1205
4244 2184 5415 1705 5642 4886 2333 287 1848 1121 3595 6022
2142 2830 4069 5654 1295 2951 3919 1356 884 1786 396 4738
0 2161 2653
1 1380 1461
2 2502 3707
3 3971 1057
4 5985 6062
5 1733 6028
6 3786 1936
7 4292 956
8 5692 3417
9 266 4878
10 4913 3247
11 4763 3937
12 3590 2903
13 2566 4215
14 5208 4707
15 3940 3388
16 5109 4556
17 4908 4177

2. Emetteur (200) selon la revendication 1, comportant en outre :

un codeur (211) de Bose-Chaudhuri-Hocquenghem BCH couplé au codeur LDPC (203) et configuré pour fournir un code extérieur au code LDPC.

3. Emetteur (200) selon la revendication 1, dans lequel le signal modulé est transmis par une liaison par satellite (103)

en soutien d'une application de satellite à large bande.

4. Procédé d'émission pour soutenir une émission d'un signal codé de vérification de parité à basse densité LDPC, le procédé comprenant les étapes qui consistent à :

délivrer en sortie, sur la base de bits d'information reçus, un code LDPC utilisant un codeur LDPC (203) ;
entrelacer des bits du code LDPC de sortie ; et
moduler le signal codé LDPC conformément à une constellation de signaux qui comprend une modulation de phase à huit états, 8-PSK,

caractérisé en ce que :

l'étape de procédé d'entrelacement comprend l'écriture en série de données associées au code LDPC par colonnes dans une table et la lecture des données par rangée de la gauche vers la droite, le signal codé LDPC représentant le code LDPC entrelacé, et **en ce que** l'étape de procédé de délivrance en sortie comprend le fait de délivrer en sortie le code LDPC avec un rapport de code 3/5 et la génération du code LDPC en accumulant les bits d'information reçus à des adresses de bits de parité, les adresses de bits de parité étant déterminées sur la base de la table suivante spécifiant des adresses d'accumulateurs de bits de parité :

Adresse d'accumulateurs de bits de parité (rapport 3/5)																
2765	5713	6426	3596	1374	4811	2182	544	3394	2840	4310	771					
4951	211	2208	723	1246	2928	398	5739	265	5601	5993	2615					
210	4730	5777	3096	4282	6238	4939	1119	6463	5298	6320	4016					
4167	2063	4757	3157	5664	3956	6045	563	4284	2441	3412	6334					
4201	2428	4474	59	1721	736	2997	428	3807	1513	4732	6195					
2670	3081	5139	3736	1999	5889	4362	3806	4534	5409	6384	5809					
5516	1622	2906	3285	1257	5797	3816	817	875	2311	3543	1205					
4244	2184	5415	1705	5642	4886	2333	287	1848	1121	3595	6022					
2142	2830	4069	5654	1295	2951	3919	1356	884	1786	396	4738					
0	2161	2653														
1	1380	1461														
2	2502	3707														
3	3971	1057														
4	5985	6062														
5	1733	6028														
6	3786	1936														
7	4292	956														
8	5692	3417														
9	266	4878														
10	4913	3247														
11	4763	3937														
12	3590	2903														
13	2566	4215														
14	5208	4707														
15	3940	3388														
16	5109	4556														
17	4908	4177														

5. Procédé selon la revendication 4, comprenant en outre :

l'exécution d'un codage de Bose-Chaudhuri-Hocquenghem BCH des bits d'information reçus pour fournir un code extérieur au code LDPC.

6. Procédé selon la revendication 5, dans lequel le signal modulé est transmis par une liaison par satellite (103) en soutien d'une application par satellite à large bande.

5

10

15

20

25

30

35

40

45

50

55

FIG. 1




FIG. 2A





FIG. 2B

FIG. 2C




FIG. 2D




FIG. 3




FIG. 4

$$H = \begin{matrix} & n_1 & n_2 & n_3 & n_4 & n_5 & n_6 & n_7 & n_8 \\ \begin{bmatrix} m_1 \\ m_2 \\ m_3 \\ m_4 \end{bmatrix} & \begin{bmatrix} 1 & 0 & 0 & 1 & 1 & 0 & 0 & 1 \\ 0 & 1 & 1 & 0 & 1 & 0 & 1 & 0 \\ 1 & 0 & 1 & 0 & 0 & 1 & 0 & 1 \\ 0 & 1 & 0 & 1 & 0 & 1 & 1 & 0 \end{bmatrix} \end{matrix}$$

FIG. 5




FIG. 6

$$B = \begin{matrix} & 1 & & & & & & & \\ \begin{bmatrix} 1 \\ x \\ x \\ x \\ x \\ x \\ x \\ x \end{bmatrix} & \begin{bmatrix} x \\ x \\ x \\ x \\ x \\ x \\ x \\ x \end{bmatrix} & \begin{bmatrix} 1 \\ x \\ x \\ x \\ x \\ x \\ x \\ x \end{bmatrix} & \begin{bmatrix} & & & 1 \\ & & & x \\ & & & x \\ & & & x \\ & & & x \\ & & & x \\ & & & x \\ & & & x \end{bmatrix} & \begin{bmatrix} & & & & 1 \\ & & & & x \\ & & & & x \\ & & & & x \\ & & & & x \\ & & & & x \\ & & & & x \\ & & & & x \end{bmatrix} & \begin{bmatrix} & & & & & 1 \\ & & & & & x \\ & & & & & x \\ & & & & & x \\ & & & & & x \\ & & & & & x \\ & & & & & x \\ & & & & & x \end{bmatrix} \end{matrix}$$

FIG. 7




FIG. 8





FIG. 9



REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- US 10613824 B [0044]

Non-patent literature cited in the description

- **LE GOFF S.Y.** Channel capacity of bit-interleaved coded modulation scheme using 8-ary signal constellations. *IEE Electronic Letters*, 14 February 2002, vol. 38 (4) [0005]
- **LE GOFF S.Y.** Signal constellations for bit-interleaved coded modulation. *IEEE Trans. on Inf. Theory*, January 2003, vol. 49 (1), 307-313 [0006]
- **LE GOFF S.Y.** Signalling constellations for power-efficient bit-interleaved coded modulation schemes. *IEE PROCEEDINGS : COMMUNICATIONS, INSTITUTION OF ELECTRICAL ENGINEERS, GB*, 13 June 2003, 141-148 [0007]
- **HOU J. et al.** Capacity-approaching bandwidth-efficient coded modulation schemes based on low-density parity-check codes. *IEEE Trans. on Inform. Theory*, vol. 49 (9), 2141-2155 [0008]
- **RICHARDSON T.** The renaissance of Gallager's low-density parity-check codes. *IEEE Communications Magazine*, August 2003, 126-131 [0009]
- **CALZOLARI G.P.** Report on DVB-S2 channel coding standardization effort. *CCSDS Sub-Panel 1B Channel Coding*, 07 April 2003 [0010]