



(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
27.04.2005 Bulletin 2005/17

(51) Int Cl.7: **H03F 3/191, H03J 5/24**

(21) Application number: **04021028.8**

(22) Date of filing: **03.09.2004**

(84) Designated Contracting States:
AT BE BG CH CY CZ DE DK EE ES FI FR GB GR
HU IE IT LI LU MC NL PL PT RO SE SI SK TR
 Designated Extension States:
AL HR LT LV MK

(72) Inventor: **Behzad, Arya**
92064 Poway CA (US)

(74) Representative: **Jehle, Volker Armin, Dipl.-Ing.**
Patentanwälte
Bosch, Graf von Stosch, Jehle,
Flüggensstrasse 13
80639 München (DE)

(30) Priority: **23.10.2003 US 513798 P**
11.05.2004 US 842825

(71) Applicant: **Broadcom Corporation**
Irvine, California 92618-7013 (US)

(54) **Tuning RF circuits using switched inductors**

(57) A Radio Frequency (RF) circuit includes an active portion and a tuned portion. The active portion receives an RF signal and that operates upon the RF signal. The tuned portion couples to the active portion and includes a first inductor, a second inductor, and a switch. When the switch is closed, the second inductor couples to the first inductor and the tuned portion has first tuning characteristics. When the switch is open, the second inductor is decoupled from the first inductor and the tuned

portion has second tuning characteristics. The tuned portion may include lumped or parasitic capacitance. The tuned portion alternately includes an inductor having a first terminal, a second terminal, an intermediate tap, and a switch that couples between the second terminal and the intermediate tap. When the switch is closed the tuned portion has first tuning characteristics and when the switch is open, the tuned portion has second tuning characteristics.




FIG. 1

Description

Cross Reference to Related Application

[0001] This application claims priority to U.S. Provisional Patent Application Serial No. 60/513,798, filed October 23, 2003, which is incorporated herein by reference for all purposes.

BACKGROUND

1. Technical Field

[0002] This invention relates generally to communication systems and more particularly to tuned circuits used in components of radio frequency transceivers within such communication systems.

2. Related Art

[0003] Communication systems are known to support wireless and wire lined communications between wireless and/or wire lined communication devices. Such communication systems range from national and/or international cellular telephone systems to the Internet to point-to-point in-home wireless networks. Communication systems typically operate in accordance with one or more communication standards. For instance, wired communication systems may operate according to one or more versions of the Ethernet standard, the System Packet Interface (SPI) standard, or various other standards. Wireless communication systems may operate in accordance with one or more standards including, but not limited to, IEEE 802.11, Bluetooth, advanced mobile phone services (AMPS), digital AMPS, global system for mobile communications (GSM), code division multiple access (CDMA), local multi-point distribution systems (LMDS), multi-channel-multi-point distribution systems (MMDS), and/or variations thereof.

[0004] Depending on the type of wireless communication system, a wireless communication device, such as a cellular telephone, two-way radio, personal digital assistant (PDA), personal computer (PC), laptop computer, home entertainment equipment, et cetera communicates directly or indirectly with other wireless communication devices. For direct communications (also known as point-to-point communications), the participating wireless communication devices tune their receivers and transmitters to the same channel or channels (e.g., one of the plurality of radio frequency (RF) carriers of the wireless communication system) and communicate over that channel(s). For indirect wireless communications, each wireless communication device communicates directly with an associated base station (e.g., for cellular services) and/or an associated access point (e.g., for an in-home or in-building wireless network) via an assigned channel. To complete a communication connection between the wireless communica-

tion devices, the associated base stations and/or associated access points communicate with each other directly, via a system controller, via the public switch telephone network, via the Internet, and/or via some other wide area network.

[0005] For each wireless communication device to participate in wireless communications, it includes a built-in radio transceiver (i.e., receiver and transmitter) or is coupled to an associated radio transceiver (e.g., a station for in-home and/or in-building wireless communication networks, RF modem, etc.). Typically, the transceiver includes a data modulation stage and an RF stage. The data modulation stage converts between data and baseband signals in accordance with the particular wireless communication standard. The RF stage converts between baseband signals and RF signals. The RF stage may be a direct conversion transceiver that converts directly between baseband and RF or may include one or more intermediate frequency stages.

[0006] The RF stage must produce RF signals, and operate upon RF signals, in differing channels of an allocated frequency band. Thus, filtering and amplifying components of the RF stage are called upon to operate on a variety of center frequencies. In many RF stages, these filtering and amplifying components are tuned to operate at particular center frequencies. By tuning these filtering and amplifying components, the overall gain of the RF stage is optimized and power consumption is reduced. The manner in which the filtering and amplifying stages operate is temperature dependent, process dependent, and may be dependent upon the tuning of adjacent amplifying/filtering stages. Thus, their tuning is dependent upon each of these factors and cannot be adequately tuned via fixed settings.

BRIEF SUMMARY OF THE INVENTION

[0007] In order to meet the above-described shortcomings, among others of the prior devices, a Radio Frequency (RF) circuit constructed according to the present invention includes an active portion and a tuned portion. The active portion receives an RF signal and operates upon the RF signal. The tuned portion couples to the active portion and, in one embodiment, includes a first inductor, a second inductor, and a switch. With this embodiment, the switch couples/decouples the second inductor to/from the first inductor. When the switch is closed, the second inductor couples to the first inductor and the tuned portion has first tuning characteristics. When the switch is open, the second inductor is decoupled from the first inductor and the tuned portion has second tuning characteristics. This embodiment may further include at least one capacitance (lumped or parasitic) that couples to the first inductor and may include additional inductors (switched or non-switched) as well.

[0008] With some embodiments of the tuning portion of the RF circuit of the present invention, when the switch is closed, the RF circuit has a maximum gain at

a first frequency and when the switch is open, the RF circuit has a maximum gain at a second frequency.

[0009] In one structure of the RF circuit, the active portion includes at least one transistor that converts the RF signal from a voltage signal to a current signal. With this structure, the tuning portion provides an output node at which the current signal is converted to a voltage signal. The first tuning characteristics correspond to a maximum impedance at the output node at a first frequency while the second tuning characteristics correspond to a maximum impedance at the output node at a second frequency.

[0010] In another embodiment, the tuned portion includes an inductor having a first terminal, a second terminal, an intermediate tap, and switch. The switch couples between the second terminal and the intermediate tap. When the switch is closed the tuned portion has first tuning characteristics and when the switch is open, the tuned portion has second tuning characteristics. This embodiment may also include at least one capacitor that couples to the inductor and may include additional inductors as well. Each of these embodiments may be constructed in a single-ended or in a differential fashion.

[0011] The switch may be a PMOS transistor or, alternately, a series combination of an NMOS transistor and a dc-blocking capacitor. In some embodiments, all components of the active portion and the tuning portion are formed as monolithic integrated circuit. In other embodiments, the active portion is formed in the monolithic integrated circuit, the capacitor and the switch of the tuning portion are also formed in the monolithic integrated circuit, but the inductor of the tuning portion is formed external to the monolithic integrated circuit.

[0012] According to an aspect of the invention, a Radio Frequency (RF) circuit comprises:

an active portion that receives an RF signal and that operates upon the RF signal; and
a tuned portion coupled to the active portion, the tuned portion comprising:

a first inductor;
a second inductor; and
a switch coupled to the second inductor, wherein when the switch is closed the second inductor couples to the first inductor, and wherein when the switch is open the second inductor is decoupled from the first inductor.

[0013] According to an aspect of the invention, a Radio Frequency (RF) circuit is provided comprising:

an active portion that receives an RF signal and that operates upon the RF signal; and
a tuned portion coupled to the active portion, the tuned portion comprising:

a first inductor;

a second inductor; and

a switch coupled to the second inductor, wherein when the switch is closed the second inductor couples to the first inductor and the tuned portion has first tuning characteristics, and wherein when the switch is open the second inductor is decoupled from the first inductor and the tuned portion has second tuning characteristics.

[0014] Advantageously, the tuned portion further comprises a capacitance coupled to the first inductor.

[0015] Advantageously, when the switch is closed the RF circuit has a maximum gain at a first frequency; and when the switch is open, the RF circuit has a maximum gain at a second frequency.

[0016] Advantageously, the switch comprises a PMOS transistor.

[0017] Advantageously, the switch comprises a series combination of an NMOS transistor and a dc-blocking capacitor.

[0018] Advantageously, all components of the active portion and the tuning portion are formed in a monolithic integrated circuit.

[0019] Advantageously, the active portion is formed in a monolithic integrated circuit;

the switch of the tuning portion is formed in the monolithic integrated circuit; and

at least one of the first inductor and the second inductor of the tuning portion are formed external to the monolithic integrated circuit.

[0020] Advantageously, the active portion includes at least one transistor that converts the RF signal from a voltage signal to a current signal;

the tuning portion provides an output node at which the current signal is converted to a voltage signal;

the first tuning characteristics correspond to a maximum impedance at the output node at a first frequency; and

the second tuning characteristics correspond to a maximum impedance at the output node at a second frequency.

[0021] According to an aspect of the invention, a Radio Frequency (RF) circuit comprises:

an active portion that receives an RF signal and that operates upon the RF signal; and
a tuned portion coupled to the active portion, the tuned portion comprising:

an inductor having a first terminal, a second terminal, and an intermediate tap; and
a switch coupled between the second terminal and the intermediate tap, wherein when the switch is closed the tuned portion has first tuning characteristics, and wherein when the switch is open the tuned portion has second tuning characteristics.

[0022] Advantageously, the tuned portion further comprises at least one capacitor coupled to the inductor.

[0023] Advantageously, when the switch is closed the RF circuit has a maximum gain at a first frequency; and when the switch is open, the RF circuit has a maximum gain at a second frequency.

[0024] Advantageously, the switch comprises a PMOS transistor.

[0025] Advantageously, the switch comprises a series combination of an NMOS transistor and a dc-blocking capacitor.

[0026] Advantageously, all components of the active portion and the tuning portion are formed in a monolithic integrated circuit.

[0027] Advantageously, the active portion is formed in a monolithic integrated circuit;

the switch of the tuning portion is formed in the monolithic integrated circuit; and

the inductor of the tuning portion is formed external to the monolithic integrated circuit.

[0028] Advantageously, the active portion includes at least one transistor that converts the RF signal from a voltage signal to a current signal;

the tuning portion provides an output node at which the current signal is converted to a voltage signal;

the first tuning characteristics correspond to a maximum impedance at the output node at a first frequency; and

the second tuning characteristics correspond to a maximum impedance at the output node at a second frequency.

[0029] According to an aspect of the invention, a differential Radio Frequency (RF) circuit comprises:

a differential active portion that receives a differential RF signal and that operates upon the differential RF signal; and

a differential tuned portion coupled to the active portion having a first side and a second side, each side comprising:

a first inductor;

a second inductor; and

a switch coupled to the second inductor, wherein when the switch is open the second inductor couples in series with the first inductor and the tuned portion has first tuning characteristics, and wherein when the switch is closed the second inductor is decoupled from the first inductor and the tuned portion has second tuning characteristics.

[0030] Advantageously, the switch comprises a PMOS transistor.

[0031] Advantageously, the switch comprises a series combination of an NMOS transistor and a dc-blocking capacitor.

[0032] Advantageously, the each side of the differen-

tial tuned portion further comprises at least one capacitor coupled to the first inductor.

[0033] According to an aspect of the invention, a differential Radio Frequency (RF) circuit comprises:

a differential active portion that receives a differential RF signal and that operates upon the differential RF signal; and

a differential tuned portion coupled to the active portion having a first side and a second side, each side comprising:

an inductor having a first terminal, a second terminal, and an intermediate tap; and

a switch coupled to the intermediate tap, wherein when the switch is open the tuned portion has first tuning characteristics, and wherein when the switch is closed the tuned portion has second tuning characteristics.

[0034] Advantageously, the switch comprises a PMOS transistor.

[0035] Advantageously, the switch comprises a series combination of an NMOS transistor and a dc-blocking capacitor.

[0036] Advantageously, the each side of the differential tuned portion further comprises at least one capacitor coupled to the first inductor.

[0037] Other features and advantages of the present invention will become apparent from the following detailed description of the invention made with reference to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0038]

FIG. 1 is a schematic block diagram illustrating a wireless communication system in accordance with the present invention;

FIG. 2 is a schematic block diagram illustrating a wireless communication device in accordance with the present invention;

FIG. 3 is a schematic block diagram illustrating a differential tuned Radio Frequency (RF) circuit;

FIG. 4 is a schematic block diagram illustrating a switched capacitor bank of the RF circuit of FIG. 3;

FIG. 5A is a schematic block diagram generally illustrating an RF circuit constructed according to the present invention;

FIG. 5B is a schematic diagram illustrating another embodiment of the RF circuit of FIG. 5A;

FIG. 5C is a schematic diagram illustrating still another embodiment of the RF circuit of FIG. 5A;

FIG. 6A is a schematic diagram illustrating a differential embodiment of the RF circuit of FIG. 5A;

FIG. 6B is a schematic diagram illustrating another differential embodiment of the RF circuit of FIG. 5A;

FIG. 7 is a schematic diagram illustrating a differential embodiment of the tuned portion of the RF circuit of FIG. 5A;

FIG. 8 is a schematic diagram illustrating another differential embodiment of the tuned portion of the RF circuit of FIG. 5A;

FIG. 9 is a schematic diagram illustrating still another differential embodiment of the tuned portion of the RF circuit of FIG. 5A;

FIG. 10A is a schematic block diagram illustrating a single ended embodiment of an RF circuit having an NMOS transistor that serves as a switch according to the present invention;

FIG. 10B is a schematic diagram illustrating a differential embodiment of an RF circuit having an NMOS transistor switch constructed according to the present invention;

FIG. 11A is a schematic diagram illustrating another single ended embodiment of an RF circuit having an NMOS transistor that serves as a switch according to the present invention;

FIG. 11B is a schematic diagram illustrating another differential embodiment of an RF circuit having an NMOS transistor that serves as a switch according to the present invention;

FIG. 12A is a diagrammatic cross-sectional diagram taken along a channel of an NMOS transistor of a tuned portion of an RF circuit constructed according to the present invention;

FIG. 12B is a circuit diagram illustrating one particular embodiment of a circuit including an NMOS transistor constructed and operating according to the present embodiment.

DETAILED DESCRIPTION OF THE DRAWINGS

[0039] FIG. 1 is a schematic block diagram illustrating a communication system 10 that includes a plurality of base stations and/or access points 12-16, a plurality of wireless communication devices 18-32 and a network hardware component 34. The wireless communication devices 18-32 may be laptop host computers 18 and 26, personal digital assistant hosts 20 and 30, personal computer hosts 24 and 32, cellular telephone hosts 22 and 28, and/or any other type of device that supports wireless communications. The details of the wireless communication devices will be described with reference to FIG. 2.

[0040] The base stations or access points 12-16 are operably coupled to the network hardware 34 via local area network connections 36, 38 and 40. The network hardware 34, which may be a router, switch, bridge, modem, system controller, et cetera provides a wide area network connection 42 for the communication system 10. Each of the base stations or access points 12-16 has an associated antenna or antenna array to communicate with the wireless communication devices in its area. Typically, the wireless communication devices reg-

ister with a particular base station or access point 12-14 to receive services from the communication system 10. For direct connections (i.e., point-to-point communications), wireless communication devices communicate directly via an allocated channel.

[0041] Typically, base stations are used for cellular telephone systems and like-type systems, while access points are used for in-home or in-building wireless networks. Regardless of the particular type of communication system, each wireless communication device includes a built-in radio and/or is coupled to a radio. The radio includes a highly linear amplifiers and/or programmable multi-stage amplifiers as disclosed herein to enhance performance, reduce costs, reduce size, and/or enhance broadband applications.

[0042] FIG. 2 is a schematic block diagram illustrating a wireless communication device that includes the host device 18-32 and an associated radio 60. For cellular telephone hosts, the radio 60 is a built-in component. For personal digital assistants hosts, laptop hosts, and/or personal computer hosts, the radio 60 may be built-in or may be an externally coupled component that couples to the host device 18-32 via a communication link, e.g., PCI interface, PCMCIA interface, USB interface, or another type of interface.

[0043] As illustrated, the host device 18-32 includes a processing module 50, memory 52, radio interface 54, input interface 58, and output interface 56. The processing module 50 and memory 52 execute the corresponding instructions that are typically done by the host device. For example, for a cellular telephone host device, the processing module 50 performs the corresponding communication functions in accordance with a particular cellular telephone standard.

[0044] The radio interface 54 allows data to be received from and sent to the radio 60. For data received from the radio 60 (e.g., inbound data), the radio interface 54 provides the data to the processing module 50 for further processing and/or routing to the output interface 56. The output interface 56 provides connectivity to an output display device such as a display, monitor, speakers, et cetera, such that the received data may be displayed. The radio interface 54 also provides data from the processing module 50 to the radio 60. The processing module 50 may receive the outbound data from an input device such as a keyboard, keypad, microphone, et cetera via the input interface 58 or generate the data itself. For data received via the input interface 58, the processing module 50 may perform a corresponding host function on the data and/or route it to the radio 60 via the radio interface 54.

[0045] Radio 60 includes a host interface 62, digital receiver processing module 64, an analog-to-digital converter 66, a filtering/gain/attenuation module 68, an IF mixing down conversion stage 70, a receiver filter 71, a low noise amplifier 72, a transmitter/receiver switch 73, a local oscillation module 74, memory 75, a digital transmitter processing module 76, a digital-to-analog

converter 78, a filtering/gain/attenuation module 80, an IF mixing up conversion stage 82, a power amplifier 84, a transmitter filter module 85, and an antenna 86. The antenna 86 may be a single antenna that is shared by the transmit and receive paths as regulated by the Tx/Rx switch 77, or may include separate antennas for the transmit path and receive path. The antenna implementation will depend on the particular standard to which the wireless communication device is compliant.

[0046] The digital receiver processing module 64 and the digital transmitter processing module 76, in combination with operational instructions stored in memory 75, execute digital receiver functions and digital transmitter functions, respectively. The digital receiver functions include, but are not limited to, digital intermediate frequency to baseband conversion, demodulation, constellation demapping, decoding, and/or descrambling. The digital transmitter functions include, but are not limited to, scrambling, encoding, constellation mapping, modulation, and/or digital baseband to IF conversion. The digital receiver and transmitter processing modules 64 and 76 may be implemented using a shared processing device, individual processing devices, or a plurality of processing devices. Such a processing device may be a microprocessor, micro-controller, digital signal processor, microcomputer, central processing unit, field programmable gate array, programmable logic device, state machine, logic circuitry, analog circuitry, digital circuitry, and/or any device that manipulates signals (analog and/or digital) based on operational instructions. The memory 75 may be a single memory device or a plurality of memory devices. Such a memory device may be a read-only memory, random access memory, volatile memory, non-volatile memory, static memory, dynamic memory, flash memory, and/or any device that stores digital information. Note that when the processing module 64 and/or 76 implements one or more of its functions via a state machine, analog circuitry, digital circuitry, and/or logic circuitry, the memory storing the corresponding operational instructions is embedded with the circuitry comprising the state machine, analog circuitry, digital circuitry, and/or logic circuitry. The memory 75 stores, and the processing module 64 and/or 76 executes, operational instructions that facilitate functionality of the device. In some embodiments, the combination of the digital receiver processing module, the digital transmitter processing module, and the memory 75 may be referred to together as a "baseband processor."

[0047] In operation, the radio 60 receives outbound data 94 from the host device via the host interface 62. The host interface 62 routes the outbound data 94 to the digital transmitter processing module 76, which processes the outbound data 94 in accordance with a particular wireless communication standard (e.g., IEEE802.11a, IEEE802.11b, IEEE802.11g, Bluetooth, et cetera) to produce digital transmission formatted data 96. The digital transmission formatted data 96 will be a digital base-band signal or a digital low IF signal, where

the low IF typically will be in the frequency range of one hundred kilohertz to a few megahertz.

[0048] The digital-to-analog converter 78 converts the digital transmission formatted data 96 from the digital domain to the analog domain. The filtering/gain/attenuation module 80 filters and/or adjusts the gain of the analog signal prior to providing it to the IF mixing stage 82. The IF mixing stage 82 directly converts the analog baseband or low IF signal into an RF signal based on a transmitter local oscillation 83 provided by local oscillation module 74. The power amplifier 84 amplifies the RF signal to produce outbound RF signal 98, which is filtered by the transmitter filter module 85. The antenna 86 transmits the outbound RF signal 98 to a targeted device such as a base station, an access point and/or another wireless communication device.

[0049] The radio 60 also receives an inbound RF signal 88 via the antenna 86, which was transmitted by a base station, an access point, or another wireless communication device. The antenna 86 provides the inbound RF signal 88 to the receiver filter module 71 via the Tx/Rx switch 77, where the Rx filter 71 bandpass filters the inbound RF signal 88. The Rx filter 71 provides the filtered RF signal to low noise amplifier 72, which amplifies the signal 88 to produce an amplified inbound RF signal. The low noise amplifier 72 provides the amplified inbound RF signal to the IF mixing module 70, which directly converts the amplified inbound RF signal into an inbound low IF signal or baseband signal based on a receiver local oscillation 81 provided by local oscillation module 74. The down conversion module 70 provides the inbound low IF signal or baseband signal to the filtering/gain/attenuation module 68. The filtering/gain/attenuation module 68 may be implemented in accordance with the teachings of the present invention to filter and/or attenuate the inbound low IF signal or the inbound baseband signal to produce a filtered inbound signal.

[0050] The analog-to-digital converter 66 converts the filtered inbound signal from the analog domain to the digital domain to produce digital reception formatted data 90. The digital receiver processing module 64 decodes, descrambles, demaps, and/or demodulates the digital reception formatted data 90 to recapture inbound data 92 in accordance with the particular wireless communication standard being implemented by radio 60. The host interface 62 provides the recaptured inbound data 92 to the host device 18-32 via the radio interface 54.

[0051] As one of average skill in the art will appreciate, the wireless communication device of FIG. 2 may be implemented using one or more integrated circuits. For example, the host device may be implemented on one integrated circuit, the digital receiver processing module 64, the digital transmitter processing module 76 and memory 75 may be implemented on a second integrated circuit, and the remaining components of the radio 60, less the antenna 86, may be implemented on a third in-

tegrated circuit. As an alternate example, the radio 60 may be implemented on a single integrated circuit. As yet another example, the processing module 50 of the host device and the digital receiver and transmitter processing modules 64 and 76 may be a common processing device implemented on a single integrated circuit. Further, the memory 52 and memory 75 may be implemented on a single integrated circuit and/or on the same integrated circuit as the common processing modules of processing module 50 and the digital receiver and transmitter processing module 64 and 76.

[0052] FIG. 3 is a schematic block diagram illustrating a differential Radio Frequency (RF) circuit. The differential RF circuit 300 includes a first side and a second side, both of which are biased by current source 312. Transconductance devices, e.g., transistors 302 and 304, receive differential input RF voltage signals V_{in}^- and V_{in}^+ at their gates. The differential RF circuit produces output RF voltage signals V_o^- and V_o^+ at output nodes 314 and 316, respectively. The gain/attenuation of the RF circuit 300 is based upon the characteristics of transistors 302 and 304 and the impedance at nodes 314 and 316.

[0053] The differential RF circuit 300 further includes inductors 306 and 308 that couple in parallel with switched capacitor banks (SCBs) 310 and 312. The impedance at nodes 314 and 316 is dependent upon the characteristics of the inductors 306 and 308 and the SCBs 310 and 312. In order to provide a maximum impedance at output nodes 314 and 316 multiple selectable center frequencies, SCBs 310 and 312 are switchable to produce a desired capacitance.

[0054] FIG. 4 is a schematic block diagram illustrating a switched capacitor bank 310 or 312 of the differential RF circuit 300 of FIG. 3. The SCBs 310 or 312 of the differential RF circuit 300 of FIG. 3 each include a plurality of capacitors coupled in parallel. Each of the capacitors is switchable to be coupled to or decoupled from the other capacitors. Capacitors $C, 2C, \dots, NC$ provide significant adjustability in the overall capacitance of the SCB 310 or 312. Thus, via the various switch settings $V_{C1}, V_{C2}, \dots, V_{CN}$, the RF circuit 300 of FIG. 3 may be tuned for any particular center frequency in a designed operating range.

[0055] Referring again to FIG. 3, SCBs 310 and 312 are switched so that the impedance at output nodes 314 and 316 is a local maximum at a selected operating frequency. Resultantly, the gain of the differential RF circuit 300 is maximum at the selected operating frequency. With the approach of FIG. 3, inductors 306 and 308 must be sized such that with all SCB 310/312 switches closed, the RF circuit is tuned to the lowest desired center frequency. Assuming a fixed inductance and switched capacitors for tuning, if the desired tuning range is large, the signal amplitude at the low end of the frequency range would drop since the impedance of the tuned load is lower at the lower frequencies.

[0056] FIG. 5A is a schematic block diagram generally

illustrating an RF circuit constructed according to the present invention. The RF circuit 500 includes an active portion 502 and a tuned portion 504. The active portion 502 receives an RF signal at its input and operates upon the RF signal to produce an RF signal out. The RF circuit 500 of FIG. 5A also includes a tuned portion 504 that includes one or more switched inductors. The tuned portion 504 receives a control signal that switches the inductors in and out of the tuned portion 504 so that a particular frequency of operation may be selected.

[0057] The RF circuit 500 may be single-ended or differential. When the RF circuit 500 is single-ended, a single coupling line 506 couples the active portion 502 to the tuned portion 504. Alternately, when the RF circuit 500 is differential, coupling lines 508 and 510 couple the active portion 502 to the tuned portion 504. Further, when the RF circuit is differential, the active portion receives differential RF signals and produces differential RF signals. In some embodiments, the RF signal(s) is/are produced at a juncture of the active portion 502 and the tuned portion 504.

[0058] FIG. 5B is a schematic diagram illustrating another embodiment of the RF circuit of FIG. 5A. The active portion 502 includes transistor 552 and output node 560. The RF circuit 570 also includes current source 552. As distinguished from the circuit of FIG. 5B, the tuned portion 504 includes a first inductor 572, a second inductor 574, and a switch 576. The switch 576 couples/decouples the second inductor 574 to/from the first inductor 572. In combination, when the switch 576 is closed, the second inductor 574 couples in parallel with the first inductor 572 to produce first tuning characteristics. Further, when the switch 576 is open, the second inductor 574 is decoupled from the first inductor 572 such that the tuned portion 504 has second tuning characteristics. When the switch 576 is closed, the RF circuit 570 has a maximum gain at a first frequency. When the switch 576 is open, the RF circuit 570 has a maximum gain at a second frequency. The tuned portion 504 of the circuit of 570 may also include at least one capacitance 578 coupled in parallel with the first inductor 572. The capacitance 578 may be a single capacitor, a switched capacitor bank, or simply parasitic capacitance. When a lumped capacitance is used, a switch may couple the capacitance in and out of the circuit.

[0059] With the embodiment of FIG. 5B, the tuned portion 504 produces a maximum impedance at output node 560 that may be moved in frequency based upon the state of switch 576. Thus, the first tuning characteristics of the tuned portion 504 correspond a maximum impedance of the output node 560 at a first frequency while the second tuning characteristics of the tuned portion 504 correspond to a maximum impedance at the output node 560 at a second frequency.

[0060] Because the number of components of the tuned portion 504 of FIG. 5B are limited, only a pair of tuned frequencies are selectable. However, as will be described further with reference to FIGs. 7, 9, 11, by

adding additional switched capacitors and/or switched inductors, the RF circuit 570 may be tuned to a number of different operating frequencies to more precisely support a desired frequency band.

[0061] The RF circuit 570 may be a driver, a mixer, an amplifier, or another device within an RF transceiver 60, as were illustrated in FIG. 2. As will be described further with reference to FIGs. 7-12, the switch 576 may comprise a PMOS transistor, an NMOS transistor in combination with a dc-blocking capacitor, or a specially constructed NMOS transistor that provides appropriate ON conductance without requiring dc-blocking capacitors.

[0062] FIG 5C is a schematic diagram illustrating still another embodiment of the RF circuit of FIG. 5A. The RF circuit 580 includes an active portion 502 having components same or similar as the active portion 502 of FIG. 5B. The tuned portion 504 of the RF circuit 580 includes an inductor 582 having a first terminal, a second terminal, and an intermediate tap 586. The tuned portion 504 further includes a switch 584. The switch 584 couples between the second terminal (also coupled to V_{dd} in the embodiment) and the intermediate tap 586. When the switch 584 is closed, the tuned portion 504 has first tuning characteristic. When the switch 584 is open, the tuned portion 504 has second tuning characteristics. Effectively, the switch 584 couples/decouples a portion of the inductor 582 to/from the tuned portion 504. As with the embodiment of FIG. 5C, a capacitor 588 may be included in the tuned portion 504. As is also the case with the embodiments of FIG. 5B and 5C, the switch 584 may take the form of a PMOS transistor, an NMOS transistor in series with one or more dc-blocking capacitors, or an NMOS transistor formed according to the embodiments of FIGs. 10-12.

[0063] FIG. 6A is a schematic diagram illustrating a differential embodiment of the RF circuit of FIG. 5A. The differential RF circuit 600 includes a differential active portion 502 and a differential tuned portion 504. The differential active portion 502 receives a differential RF signal (V_{in}^+ and V_{in}^-). The RF circuit 600 produces differential RF signal (V_o^+ and V_o^-). The differential active portion 502 includes transistors 602 and 604 and output nodes 620 and 622. Current source 603 biases the other elements of the RF circuit 600. Coupling lines 508 and 510 couple the differential active portion 502 to the differential tuned portion 504. A first side of the differential tuned portion 504 includes first inductor 608, second inductor 609, capacitor 606, and switch 610. A second side of the differential tuned portion 504 includes capacitor 612, first inductor 614, second inductor 615, and switch 616. The structure of the differential circuit 600 of FIG. 6A is effectively a differential version of the RF circuit 570 of FIG. 5B. The capacitor 606 may be a lumped capacitance or simply parasitic capacitance.

[0064] FIG. 6B is a schematic diagram illustrating another differential embodiment of the RF circuit of FIG. 5A. The differential RF circuit 650 has an active portion 502 that is a cascode amplifier and that includes

transconductance transistors 652 and 654, cascode transistors 656 and 658, and output nodes 660 and 662. The cascode transistors 656 and 658 provide isolation to the transconductance transistors 652 and 654. The transistors 652 and 654 may, in other embodiments, be replaced by linearized transconductance devices having multiple transistors that provide more linear operation in a desired operating range. Current source 653 provides biasing for the active portion 502 and the tuned portion 504. The tuned portion 504 of the differential RF circuit 650 includes capacitors 606 and 612, inductors 608, 609, 614, and 615, and switches 610 and 616.

[0065] FIG. 7 is a schematic diagram illustrating a differential embodiment of the tuned portion 504 of the RF circuit of FIG. 5A. The differential tuned portion 504 may be used in conjunction with any differential RF circuit constructed according to the present invention. The differential tuned portion 504 includes current sources 714 and 716. Coupling lines 508 and 510 couple the differential tuned portion 504 to an differential active portion 502.

[0066] The differential tuned portion 504 includes inductors 702, 704, 706, 708, 718, and 720. The differential tuned portion 504 includes two switch legs that may be separately controlled via control signals $Control_1$ and $Control_2$. A first switch leg includes PMOS transistors 710 and 712 that are controlled by $Control_1$. When these PMOS transistors 710 and 712 are turned ON, they effectively short the upper terminals of inductors 702 and 704 such that remaining inductors 706, 708, 718, and 720 decoupled from inductors 702 and 704. When PMOS transistors 710 and 712 are turned OFF by $Control_1$ being logic high, inductors 706, 708, 718, and 720 may form a portion of the differential tuned portion 504 (depending upon the state of PMOS transistors 714 and 716).

[0067] The PMOS transistors 714 and 716, controlled by the signal $Control_2$, may be turned ON via a logic low signal so that they provide a short across the upper terminals of inductors 706 and 708 (lower terminals of inductors 718 and 720). As the reader will appreciate, by appropriate setting of $Control_1$ and $Control_2$, the tuning characteristics of the differential tuned portion 504 may be controlled to select a particular operating frequency. Center nodes 713 and 715 of the switch legs may be coupled to V_{dd} , to ground, or may be simply left floating, depending upon the particular implementation.

[0068] FIG. 8 is a schematic diagram illustrating another differential embodiment of the tuned portion 504 of the RF circuit of FIG. 5A. As contrasted to the switch legs of FIG. 7 that included PMOS transistors 710, 712, 714, and 716, the switch legs of the differential tuned portion 504 of FIG. 8 includes NMOS transistors 810 and 812 joined at center node 815. In some constructs, the tanks in which inductors 702, 704, 706, and 706 are constructed are tied to V_{dd} . Thus, to properly bias NMOS transistors 810 and 812 so that they may be turned ON and OFF, dc-blocking capacitors 804 and 806

must be employed. When the NMOS transistors 810 and 812 are turned ON by applying a logic high signal, i.e., V_{dd} , the lower terminals of inductors 706 and 708 (upper terminals of inductors 702 and 704) are effectively shorted so that inductors 706 and 708 are decoupled from inductors 702 and 704. With transistors 810 and 814 turned ON, therefore, tuning is provided by inductors 702 and 704. When NMOS transistors 810 and 812 are turned OFF, inductors 702, 706, 704, and 708 all participate in the operation of the differential tuned portion 504 and the tuning of the differential RF circuit.

[0069] FIG. 9 is a schematic diagram illustrating still another differential embodiment of the tuned portion 504 of the RF circuit of FIG. 5A. As contrasted to the prior illustrated embodiments, the differential tuned portion 504 of FIG. 9 includes tuning capacitors oriented along three separate switched legs. A first switched leg includes tuning capacitors 902 and 904 and NMOS transistors 906 and 908. These tuning capacitors 904 and 902 may be switched in and out of the differential tuned portion 504 via appropriate level of $Control_1$. Likewise, a second tuning leg includes tuning capacitors 910 and 912 controlled by NMOS transistors 914 and 916 via $Control_2$. Further, a third tuning leg includes tuning capacitors 918 and 920 controlled by NMOS transistors 922 and 924 via $Control_3$. Central nodes 915A, 915B, and 915C may be tied to ground, to V_{dd} , or may be allowed to float depending upon the embodiment. In other embodiments, each of the NMOS transistor pairs may be replaced by a single NMOS transistor.

[0070] Another difference of the embodiment of FIG. 9 is that the tuned portion stage 504 includes inductors 934 and 936 having a first terminal, a second terminal, and an intermediate tap. These inductors 934 and 936 have their intermediate taps coupled by transistors 930 and 932 and dc-blocking capacitors 926 and 928 that meet at center node 915D. When the NMOS transistors 932 and 930 are turned ON via appropriate $Control_4$ signal level, the intermediate taps of inductors 934 and 936 are coupled such that the effective inductance of the differential tuned portion 504 is reduced.

[0071] FIG. 10A is a schematic block diagram illustrating a single ended embodiment of an RF circuit 504 having an NMOS transistor 1002 that serves as a switch according to the present invention. The tuned portion 504 includes a first inductor 1008, a second inductor 1004, and the NMOS transistor 1002. The tuned portion 504 may optionally include a capacitor 1010 coupled/decoupled by switch 1011 as illustrated.

[0072] The second inductor 1004, as well as the first inductor 1008, is/are typically formed in a tank of a monolithic semi conductive substrate. The tank is typically tied to a first supply voltage V_{dd1} , e.g. 1.8V. In order to be able to switch the second inductor 1002 in and out of the tuned portion 504, PMOS transistors (FIG. 7) or NMOS transistors with dc-blocking capacitors (FIGs. 8-9) must be employed. However, PMOS transistors have several times the capacitance for a given ON re-

sistance as compared to NMOS transistors, such capacitance being undesirable. Further, the dc-blocking capacitors of FIGs. 8-9 require significant die area and have fairly large parasitic values. In order to avoid using PMOS transistors or NMOS transistors with dc-blocking capacitors, higher voltage, e.g., 3.3V NMOS transistors may be employed (and 3.3V logic used to turn them ON and OFF). The problem with this is that the 3.3V devices have much worse performance than lower voltage/thinner gate oxide devices, e.g., 1.8V devices.

[0073] Thus, according to the present invention, a novel technique is employed with an NMOS transistor 1002 used to switch inductor 1004 in and out of the tuned portion 504. In particular, NMOS transistor 1002 has a gate, a drain, a source, and a body. The structure of the NMOS transistor is illustrated in more detail in FIG. 12A, which will be described later herein. The drain and source terminals operably couple and decouple the second inductor 1004 to/from the first inductor 1008. With one embodiment, the body of the NMOS transistor 1002 (V_B) is tied to a first voltage supply V_{dd1} , e.g., 1.8V. The NMOS transistor 1002 is turned ON by applying a second voltage supply V_{dd2} , e.g., 3.3V, to the gate (V_G). The NMOS transistor is turned OFF by applying a reference voltage, e.g., gnd, to the gate V_G .

[0074] Thus, with V_{dd2} at 3.3 volts and V_{dd1} at 1.8 volts, the NMOS transistor 1002 is turned ON and the NMOS transistor 1002 effectively decouples second inductor 1004 from first inductor 1008 by applying a short across second inductor 1004. The NMOS transistor 1002 is turned OFF by applying the reference voltage (gnd) to the gate of the NMOS transistor 1002, the reference voltage (gnd) being less than the first voltage supply V_{dd1} . Thus, in all operations the NMOS transistor 1002 has no voltage greater than 1.8V across any two of its four terminals (Source, Drain, Gate, Body) and is therefore not compromised in its use for this purpose.

[0075] As an improved embodiment, control logic 1012 controls the body voltage V_B of the NMOS transistor 1002. The control logic 1012 runs on the 1.8V supply. When the NMOS transistor 1002 is turned ON the body is tied to 1.8V, V_t is reduced (with no body effect) and the ON resistance is minimized. However, when the NMOS transistor 1002 is turned OFF, V_B is tied to ground, which increases the reverse bias on the Source-Body and Drain-Body junctions reducing the effective junction capacitance of the NMOS transistor 1002 in the OFF mode. This biasing also guarantees that the Source-Body and Drain-Body junctions are not forward biased during normal operation with the device turned OFF with large signal swings present.

[0076] FIG. 10B is a schematic diagram illustrating a differential embodiment of an RF circuit having an NMOS transistor switch constructed according to the present invention. The differential tuned portion 504 may couple to an active portion of the RF circuit as has previously been illustrated in FIGs. 5A-9. The tuned portion 504 includes inductors 702, 704, 706, and 708. Cur-

rent sources 714 and 716 provide the proper biasing between the supply voltage V_{dd} and ground and for the differential signal format. According to the present invention, NMOS transistors 1052 and/or 1054 are controlled to adjust the effective inductance of the tuned portion 504. NMOS transistors 1052 and 1054 are turned OFF by applying a reference ground to the gates of the NMOS transistors 1052 and 1054. Holding the body of the transistors at the first voltage supply and applying the second supply voltage to the gates of the NMOS transistors 1052 and 1054 turns the NMOS transistors ON. With the NMOS transistors 1052 and 1054 turned ON, a short is effectively created across the lower terminals of inductor pair 706 and 708 (upper terminals of inductor pair 702 and 704) so that the inductor 706 and 708 are effectively removed from tuning of the tuned portion 504. Thus, an RF circuit having tuned portion 504 will have differing tuning characteristics when the NMOS transistors 1052 and 1054 are turned ON as compared to when the NMOS transistors 1052 and 1054 are turned OFF.

[0077] The NMOS transistors 1054 and 1052 may be constructed according to the structure of FIG. 12, in one embodiment. In another embodiment, a single NMOS transistor 1052 or 1054 may be employed to create an effective short at the junctions of the transistor pairs. The reader will appreciate the application of the particular NMOS switch structure for coupling in or decoupling inductors from a tuned portion of an RF circuit for the structures previously illustrated.

[0078] FIG. 11A is a schematic diagram illustrating another singled ended embodiment of an RF circuit having an NMOS transistor that serves as a switch according to the present invention. As shown, a tuned portion 504 includes an inductor 1104 having a first terminal, a second terminal, and an intermediate tap defining a first portion of the inductor 1104 and a second portion of the inductor 1104. An NMOS transistor 1102 has a gate, a drain, a source, and a body. The drain and source operably couple/decouple the second portion of the inductor to/from the first portion of the inductor. The body V_B of the NMOS transistor 1102 is tied to a first voltage supply V_{dd1} (at least when the transistor is turned ON). The NMOS transistor 1102 is turned ON by applying a second voltage supply to the gate V_G , while the NMOS transistor 1102 is turned OFF by applying a reference voltage, e.g., a reference ground, to the gate V_G of the NMOS transistor 1102. The reference ground is less than the second voltage supply V_{dd2} . According to another embodiment, as was described with reference to FIG. 10A for the singled ended embodiment, control logic may be employed. In such case, V_B is tied to V_{ddl} when the transistors 1052 and 1054 are turned ON and V_B is tied to gnd when the transistors 1052 and 1054 are turned OFF.

[0079] FIG. 11B is a schematic diagram illustrating another differential embodiment of an RF circuit having an NMOS transistor that serves as a switch according

to the present invention. The differential tuned portion 504 may employ NMOS transistors of the present invention to switch its inductors. Particularly, the tuned portion 504 of FIG. 11B differs from the structure of FIG. 9 in that NMOS transistors 1152 and 1154 are employed in one tuning leg to produce a short at the upper terminals of inductors 702 and inductors 706 (lower terminals of inductors 704 and 708). Further, NMOS transistors 1156 and 1158 serve in another tuning leg to produce a short at the junctions of inductors 706 and 718 and inductors 708 and 720. Remaining components in FIG. 11B are the same or similar as the components previously described with reference to FIG. 9.

[0080] As the reader will appreciate, the NMOS transistor structure of the present invention may be employed in any of the number of switched inductor applications within an RF circuit. However, additional structure included with the RF circuit may vary. For example, referring again to FIG. 11A, a tuning capacitor 1106 and switch 1107 may optionally be used. In such case, the particular tuning characteristics of the tuned portion 504 will differ with the addition of the capacitor 1106 and switch 1107.

[0081] Further, referring again to FIG. 11B, the NMOS transistors 918, 920, 910, and 912, that switch capacitors 914, 916, 904, and 906, need not have the particular NMOS transistor termination structure of the present invention in which the body of the transistor is tied to a reference supply voltage. Such is the case because the capacitors 904, 906, 918, and 920 provide isolation for the NMOS transistors 910, 912, 918, and 920, respectively.

[0082] FIG. 12A is a diagrammatic cross-sectional diagram taken along a channel of an NMOS transistor 1002 of a tuned portion of an RF circuit constructed according to the present invention. As is illustrated, the NMOS transistor 1002 includes a gate 1208, a source 1206, a drain 1210, and a body that resides in a p-well 1202. The p-well 1202 is formed within an n-well 1204, which is formed in a p-substrate 1200. The structure of FIG. 12 is generally referred to as a triple-well option. With such a structure, the NMOS transistor 1002 may further include a body contact 1212, which is a highly doped p-contact formed within the p-well 1202. According to some embodiments of the present invention, the body contact 1212 is controllably biased at the V_B supply voltage when the NMOS transistor 1002 is turned ON (or at all times) to correspond to the tank voltage of an inductor switched by the NMOS transistor 1002.

[0083] As is evidenced from the structure of FIG. 12A, with the body contact V_B tied to V_{dd1} , the first supply voltage, e.g., 1.8V, the NMOS transistor 1002 may be turned ON by applying the second voltage supply (V_{dd2} , e.g., 3.3V) at the gate 1208 V_G . Further, with the gate 1208 V_G coupled to a reference ground and the body contact V_B coupled to ground, the NMOS transistor 1002 is turned OFF, even when the tank containing the inductor 1004 is tied to V_{dd1} of 1.8 volts. Thus, the ON

conductance requirements and OFF isolation requirements are satisfied for the switched inductor circuit and also the protection requirements for the NMOS transistor 1002 are satisfied. Such is the case because the maximum voltage at any time in the operation of the NMOS transistor 1002 will not exceed 1.8 volts across any terminal pair (Source, Drain, Gate, Body) of the NMOS transistor 1002.

[0084] FIG. 12B is a circuit diagram illustrating one particular embodiment of a circuit including an NMOS transistor constructed and operating according to the present embodiment. NMOS transistor 1252 includes source and drain terminals that couple between nodes 1254 and 1258. The gate voltage V_G and body voltage V_B are controllable to turn on and turn off the transistor 1252 to resultantly apply a short or an open between nodes 1254 and 1258.

[0085] With drain and source terminals biased by supply voltage V_{dd1} via inductors 718 and 720, the drain and source terminals are held, effectively, at V_{dd1} , i.e., 1.8 volts (in the illustrated embodiment). With the embodiment of FIG. 12B (and with at least some of the previously described embodiments) transistor 1252 is turned on by applying 1.8 volts (V_{dd1}) to the body of the transistor 1252 and 3.3 volts (V_{dd2}) to the gate of the transistor 1252. Further, transistor 1252 is turned off by applying 0 volts to the body of the transistor 1252 and 0 volts to the gate of the transistor 1252.

[0086] By holding the body of transistor at 1.8 volts instead of at 0 volts, the ON resistance of the transistor 1252 between the source and drain terminals (due to body effect) is reduced. While the body of the transistor 1252 could be held at 1.8 volts at all times, such operation would be with risk of the parasitic diodes (formed in conjunction with the transistors) being turned on by large swings at nodes 1254 and 1258.

[0087] As one of average skill in the art will appreciate, the term "substantially" or "approximately," as may be used herein, provides an industry-accepted tolerance to its corresponding term. Such an industry-accepted tolerance ranges from less than one percent to twenty percent and corresponds to, but is not limited to, component values, integrated circuit process variations, temperature variations, rise and fall times, and/or thermal noise. As one of average skill in the art will further appreciate, the term "operably coupled", as may be used herein, includes direct coupling and indirect coupling via another component, element, circuit, or module where, for indirect coupling, the intervening component, element, circuit, or module does not modify the information of a signal but may adjust its current level, voltage level, and/or power level. As one of average skill in the art will also appreciate, inferred coupling (i.e., where one element is coupled to another element by inference) includes direct and indirect coupling between two elements in the same manner as "operably coupled." As one of average skill in the art will further appreciate, the term "compares favorably," as may be used herein, indicates that a com-

parison between two or more elements, items, signals, etc., provides a desired relationship. For example, when the desired relationship is that signal 1 has a greater magnitude than signal 2, a favorable comparison may be achieved when the magnitude of signal 1 is greater than that of signal 2 or when the magnitude of signal 2 is less than that of signal 1.

[0088] The invention disclosed herein is susceptible to various modifications and alternative forms. Specific embodiments therefore have been shown by way of example in the drawings and detailed description. It should be understood, however, that the drawings and detailed description thereto are not intended to limit the invention to the particular form disclosed, but on the contrary, the invention is to cover all modifications, equivalents and alternatives falling within the spirit and scope of the present invention as defined by the claims.

Claims

1. A Radio Frequency (RF) circuit comprising:

an active portion that receives an RF signal and that operates upon the RF signal; and
a tuned portion coupled to the active portion, the tuned portion comprising:

a first inductor;
a second inductor; and
a switch coupled to the second inductor, wherein when the switch is closed the second inductor couples to the first inductor, and wherein when the switch is open the second inductor is decoupled from the first inductor.

2. The RF circuit of claim 1, wherein when the switch is closed the second inductor couples to the first inductor and the tuned portion has first tuning characteristics, and wherein when the switch is open the second inductor is decoupled from the first inductor and the tuned portion has second tuning characteristics.

3. The RF circuit of claim 1 or 2, wherein the tuned portion further comprises a capacitance coupled to the first inductor.

4. The RF circuit of any of the preceding claims, wherein:

when the switch is closed the RF circuit has a maximum gain at a first frequency; and
when the switch is open, the RF circuit has a maximum gain at a second frequency.

5. A Radio Frequency (RF) circuit comprising:

an active portion that receives an RF signal and that operates upon the RF signal; and
a tuned portion coupled to the active portion, the tuned portion comprising:

an inductor having a first terminal, a second terminal, and an intermediate tap; and
a switch coupled between the second terminal and the intermediate tap, wherein
when the switch is closed the tuned portion has first tuning characteristics, and wherein
when the switch is open the tuned portion has second tuning characteristics.

6. The RF circuit of claim 5, wherein the tuned portion further comprises at least one capacitor coupled to the inductor.

7. A differential Radio Frequency (RF) circuit comprising:

a differential active portion that receives a differential RF signal and that operates upon the differential RF signal; and
a differential tuned portion coupled to the active portion having a first side and a second side, each side comprising:

a first inductor;
a second inductor; and
a switch coupled to the second inductor, wherein when the switch is open the second inductor couples in series with the first inductor and the tuned portion has first tuning characteristics, and wherein when the switch is closed the second inductor is decoupled from the first inductor and the tuned portion has second tuning characteristics.

8. The differential RF circuit of claim 7, wherein the switch comprises a PMOS transistor.

9. A differential Radio Frequency (RF) circuit comprising:

a differential active portion that receives a differential RF signal and that operates upon the differential RF signal; and
a differential tuned portion coupled to the active portion having a first side and a second side, each side comprising:

an inductor having a first terminal, a second terminal, and an intermediate tap; and
a switch coupled to the intermediate tap, wherein when the switch is open the tuned portion has first tuning characteristics, and

wherein when the switch is closed the tuned portion has second tuning characteristics.

10. The differential RF circuit of claim 9, wherein the switch comprises a PMOS transistor.




FIG. 1

10






FIG. 2








FIG. 5A






FIG. 6A





FIG. 6B







FIG. 8






FIG. 10B





FIG. 10A






FIG. 12A




FIG. 12B



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 04 02 1028

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
X	EP 1 282 227 A (NOKIA CORP) 5 February 2003 (2003-02-05) * paragraph [0015] - paragraph [0018] * * paragraph [0022] - paragraph [0028] * * figures 8-12 *	1-10	H03F3/191 H03J5/24
X	US 6 052 033 A (SCHNEIDER GERHARD) 18 April 2000 (2000-04-18) * column 5, line 27 - column 7, line 12 * * figures 3,4 *	1-10	
X	US 6 366 166 B1 (BELOT DIDIER) 2 April 2002 (2002-04-02) * column 3, line 4 - column 4, line 16 * * column 5, line 36 - column 6, line 62 * * figures 4,6,7 *	1-10	
X	EP 1 058 384 A (WHITAKER CORP) 6 December 2000 (2000-12-06) * paragraph [0008] - paragraph [0011] * * figure 1 *	5	
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
			H03F H03J
The present search report has been drawn up for all claims			
Place of search The Hague		Date of completion of the search 3 December 2004	Examiner Simon, V
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

2
EPO FORM 1503 03.82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 04 02 1028

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

03-12-2004

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 1282227	A	05-02-2003	US 2003025563 A1	06-02-2003
			EP 1282227 A2	05-02-2003

US 6052033	A	18-04-2000	NONE	

US 6366166	B1	02-04-2002	FR 2798016 A1	02-03-2001
			EP 1081849 A1	07-03-2001
			JP 3458835 B2	20-10-2003
			JP 2001119251 A	27-04-2001

EP 1058384	A	06-12-2000	CA 2310508 A1	03-12-2000
			EP 1058384 A2	06-12-2000
			JP 2001068969 A	16-03-2001
