



(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
11.05.2005 Bulletin 2005/19

(51) Int Cl.7: **B41J 2/175**

(21) Application number: **03024578.1**

(22) Date of filing: **28.10.2003**

(84) Designated Contracting States:
AT BE BG CH CY CZ DE DK EE ES FI FR GB GR
HU IE IT LI LU MC NL PT RO SE SI SK TR
 Designated Extension States:
AL LT LV MK

• **Chieh-Wen, Wang**
Hsinchu, R.O.C. (TW)
 • **Linyean, Lin**
Dadu Township
Taichung County 432, R.O.C (TW)

(71) Applicant: **International United Technology Co., Ltd.**
Chu-Pei City, Hsin-Chu Hsien,
Taiwan R.O.C. (TW)

(74) Representative: **Becker Kurig Straus**
Patentanwälte
Bavariastrasse 7
80336 München (DE)

(72) Inventors:
 • **Hung, Lieh Hu**
Hsinchu City 300, R.O.C. (TW)

(54) **Apparatus and method for determining status of inkjet print head identification circuit**

(57) An apparatus and a method for determining status of inkjet print head identification circuit are provided for an inkjet print head with a plurality of signal lines. The apparatus comprises: a status output terminal (605) outputting one bit data of the status of the inkjet print head identification circuit; a first blowing terminal (601) electrically coupled to the status output terminal

(605) via a first programmable switch (610); and a second blowing terminal (603) electrically coupled to the status output terminal (605) via a second programmable switch (615); wherein one of the first programmable switch (fuse) and the second programmable switch (fuse) being off to determine a voltage level of the status output terminal.




FIG. 7A

Description

BACKGROUND OF THE INVENTION

Field of the Invention

[0001] This invention generally relates to an inkjet print head, and more particularly to an apparatus and method for determining statuses of inkjet print head identification circuit.

Description of the Related Art

[0002] As the technology advances, more and more computer peripherals have been developed. Taking the inkjet printer as an example, to meet the different print requirements, several inkjet printers have been developed. Each inkjet printer has its specific inkjet print heads. The function of the inkjet print head is to spray the ink from the nozzle. There are two types of inkjet print heads - continuous and drop-on-demand type respectively - based on the different droplet ejection principles. To implement the different droplet ejection principles, each inkjet print head has its own structure, such as one inkjet print head for black ink and one inkjet print head for color ink, or inkjet print heads with different numbers of nozzles. For the purpose of identifying each inkjet print head, an identification code corresponding to the specific inkjet print head will be written into the print head. Hence, the inkjet printer can control the inkjet print head according to the identification code for printing works.

[0003] As mentioned above, the inkjet printer has to identify the type of the inkjet print head. Hence, an identification circuit is required in the inkjet print head for the inkjet printer to read the identification code. This identification circuit will be used when the inkjet print head is installed for the first time in the inkjet printer. After the inkjet printer identifies the inkjet print head, the identification circuit will not be used. Hence, the identification circuit will read the identification code via the signal lines for controlling the print head array circuit.

SUMMARY OF THE INVENTION

[0004] An object of the present invention is to provide an apparatus and method for determining statuses of inkjet print head identification circuit. The identification circuit can acquire the complete identification code without the limitation of the number of the signal lines. The apparatus provided by the present invention is suitable for an inkjet print head with a plurality of signal lines, comprising: a status output terminal for outputting a one bit data of the status of the inkjet print head identification circuit; a first blowing terminal electrically coupled to the status output terminal via a first programmable switch; and a second blowing terminal electrically coupled to the status output terminal via a second programmable

switch; and a switch circuit controlled by the signal lines for conducting an external power supply to program the first and second programmable switches.

[0005] In a preferred embodiment of the present invention, the switch circuit comprises: a first transistor, a first signal line of the plurality of signal lines determining whether to turn on/off the first transistor; and a second transistor, wherein when the first transistor is on, the voltage level of a second signal line of the plurality of signal lines determines whether to apply the external power supply to the first programmable switch and the second programmable switch. The first signal line may be or may not be the second signal line. The first and second switches include fuses or low-power resistor to store data bit 0 or 1 used for identification code output by inkjet print head.

[0006] In another embodiment of the present invention, the apparatus further comprises a status input circuit having a third blowing terminal, the status input circuit being electrically coupled to the plurality of signal lines, the status input circuit being controlled by the plurality of signal lines to conduct the external power supply to the third blowing terminal. The status input circuit further comprises: a third transistor, a third signal line of the plurality of signal lines for determining whether to turn on/off the third transistor; and a fourth transistor, when the third transistor is on, the voltage level of a fourth signal line of the plurality of signal lines determines whether to apply the external power supply to the third blowing terminal. The third signal line may be or may not be the fourth signal line. The first, second, third and fourth signal lines can be the same signal line or different.

[0007] The present invention also provides a method of determining statuses of inkjet print head identification circuit, for an inkjet print head with a plurality of signal lines, comprising: enabling two of the plurality of signal lines to conduct an external power supply; and coupling the external power supply to a first programmable switch and a second programmable switch which are electrically coupled to different voltages respectively, to turn off one of the first programmable switch and a second programmable switch; wherein the plurality of signal lines are not enabled simultaneously when the inkjet print head operates.

[0008] In another embodiment of the present invention, the step of coupling the external power supply to the first programmable switch and the second programmable switch comprises: floating one terminal of one of the first programmable switch and the second programmable switch, and applying the external power supply to another terminal of the one of the first programmable switch and the second programmable switch; and grounding one terminal of another first programmable switch and the second programmable switch, and applying the external power supply to another terminal of the other first programmable switch and the second programmable switch; wherein the grounded first program-

mable switch and the second programmable switch is off due to a voltage difference between the one terminal and the another terminal.

[0009] The present invention uses a pair of fuses or low power resistors less than approximately 0.3W, or uses a fuse and a low power resistor less than approximately 0.3W. The status output terminal will output 1 or 0 based on which one of the fuses (or resistors, or a fuse and a resistor) is blown. The apparatus provided by the present invention can be controlled by the signal line to determine which one of the fuses (or resistors, or a fuse and a resistor) is going to be blown, and receive the applied power supply to blow the fuse.

[0010] The above is a brief description of some deficiencies in the prior art and advantages of the present invention. Other features, advantages and embodiments of the invention will be apparent to those skilled in the art from the following description, accompanying drawings and appended claims. It is intended that the scope of the invention be limited by the claims and not by the preceding summary or the following detailed description.

BRIEF DESCRIPTION OF THE DRAWINGS

[0011] FIG. 1 is a block diagram of an identification system of an inkjet printer.

[0012] FIG. 2 is a conventional identification circuit of an inkjet print head.

[0013] FIG. 3 is another conventional identification circuit of an inkjet print head.

[0014] FIG. 4 is still another conventional identification circuit of an inkjet print head.

[0015] FIG. 5 is a timing sequence of the conventional identification circuit of an inkjet print head of FIG. 4.

[0016] FIG. 6 is further another conventional identification circuit of an inkjet print head.

[0017] FIG. 7A is an apparatus for determining the status of a one bit identification circuit of an inkjet print head in accordance with the first preferred embodiment of the present invention.

[0018] FIG. 7B is an apparatus for determining the status of a one bit identification circuit of an inkjet print head in accordance with another preferred embodiment of the present invention.

[0019] FIG. 7C shows how the status output terminal 605 outputs one bit data of the status of the inkjet print head identification circuit to the corresponding input terminal 605''' of one-bit shift registers.

[0020] FIG. 8A is an apparatus for determining the status of a one bit identification circuit of an inkjet print head in accordance with the second preferred embodiment of the present invention.

[0021] FIG. 8B shows the apparatus of FIG. 8A connected to the circuit of FIG. 4.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0022] In the following description of the invention, reference is made to the accompanying drawings, which form a part thereof, and in which is shown by way of illustration a specific example whereby the invention may be practiced. It is to be understood that other embodiments may be utilized and structural changes may be made without departing from the scope of the present invention. Before illustrating the present invention, to make one skilled in the art understanding the present invention, the structure of the current inkjet print head is described. FIG. 1 is a block diagram of an identification system of an inkjet printer. As shown in FIG. 1, the identification system includes a printer electronic 110 connected to the signal lines 133 and the temperature sensing output line 136, and a print head electronic 120. The printer electronic 110 includes the controller 113 and the driving circuit 116. The print head electronic 120 includes the print head array 123, the identification circuit 126 and the temperature sensing circuit 129.

[0023] The identification circuit 126 can be the one that has been disclosed in U.S. Patent Number 5,363,134 as shown in FIG. 2. The identification circuit 200 uses a plurality of fuses F1-F13 connected to the gates of a plurality of transistors Q1-Q13, respectively, to control the turning on of the transistors Q1-Q13. The identification code of the inkjet print head is stored by programming the fuses F1-F13. For example, assuming that the high level reading signal is sent via A13, if the fuse F13 is not blown, the transistor Q13 will be turned on. Hence, the temperature sensing output line 136 will be pulled to a low level and the data bit is "0". If the fuse F13 is blown, the transistor Q13 is turned off. Hence, the temperature sensing output line 136 will be pulled to high level and the data bit is "1". The other lines can also be read by the same way. However, each signal line of the identification circuit can only represent one bit. Hence, the number of bits for the identification code will be limited by the number of the signal lines.

[0024] To overcome this drawback, U.S. Patent Number 5,940,095 discloses another identification circuit as shown in FIG. 3. The identification circuit 300 uses a plurality of one-bit mask programmed shift registers 320a - 320d to implement the parallel-in-series-out identification circuit. The printer electronic 110 sends the control signal "Load" via the signal line 305, and the identification code was stored into the one-bit mask programmed shift registers 320a - 320d. Those shift registers are dynamic shift registers. When the first clock signal CLK1 and the second clock signal CLK2 are received via the signal lines 310 and 315, the data bit stored in the one-bit mask programmed shift register 320d will be shifted out via the signal line 330. The data bit stored in the one-bit mask programmed shift register 320c will be shifted out to the one-bit mask programmed shift register 320d. The data bit stored in the one-bit

mask programmed shift register 320b will be shifted out to the one-bit mask programmed shift register 320c. The data bit stored in the one-bit mask programmed shift register 320a will be shifted out to the one-bit mask programmed shift register 320b. Then the printer electronic 110 sends the control signal "Load" via the signal line 305, and sends the signal CLK1 and the second clock signal CLK2 via the signal lines 310 and 315. Then the identification code stored in the one-bit mask programmed shift registers 320a - 320d will be serially out-
 5 10

putted. Hence, this parallel-in-series-out identification circuit only requires three signal lines 305, 310, and 315 to read the identification code without the limitation of the number of the signal lines. It should be noted that this identification circuit is fabricated by mask program-
 15

[0025] FIG. 4 is still another conventional identifica-
 tion circuit of an inkjet print head. The identification cir-
 cuit 420 includes the counter 410, OR logic unit 430, and the programmable unit 420 consisting of fuses. The
 20 identification circuit 420 only requires four signal lines including a reset signal line 401 for transmitting Reset signal, a first clock signal line 402 for transmitting CLK1 signal, a second clock signal line 403 for transmitting CLK2 signal, and an identification code signal line 405 for transmitting ID signal. Hence, this identification cir-
 25

cuit can expand the bit number based on the identifica-
 tion code and will not be limited by the number of the
 signal lines.

[0026] The counter 410 is electrically coupled to the
 reset signal 401, the first clock signal line 402 and the
 second clock signal line 403. The counter 410 is an 8-bit
 counter with 8 output terminals b0-b7 for required
 number of identification codes. Each of output terminals
 b0-b7 is connected to the input terminals of the OR gate
 unit 430 via the fuses of the programmable unit 420. The
 input terminals of the OR gate unit 430 is electrically
 connected to the ground via the fuses of the program-
 mable unit 420. Further, the OR gate unit 430 includes
 an enable terminal EN to receive the second clock signal
 CLK2. For example, if the identification code is
 11101000, the fuses F10, F11, F12, F3, F14, F5, F6, and
 F7 have to be blown and the fuses F0, F1, F2, F13, F4,
 F15, F16, and F17 are kept intact, thereby programming
 the identification code into the programmable unit 420.
 The timing sequence is shown in FIG. 5.

[0027] When the counter 410 receives the reset signal
 Reset via the reset signal line 401, the counter 410 is
 reset to "0". When the counter receives the first and sec-
 ond clock signals CLK1 and CLK2 via the first and sec-
 ond clock signal line 402 and 403 respectively in se-
 quence, the output terminals b0-b7 of the counter 410
 will be set to "1" in sequence as shown in FIG. 5. When
 b0 is "1" and b1-b7 are "0", because the fuse F0 is intact
 when programming, the output terminal of the OR gate
 unit 430 will output the one bit data "1". Likewise, when
 b1 is "1" and the other output terminals are "0", because

the fuse F1 is intact when programming, the output ter-
 minal of the OR gate unit 430 will output the one bit data
 "1"; when b2 is "1" and the other output terminals are
 "0", because the fuse F2 is intact when programming,
 the output terminal of the OR gate unit 430 will output
 the one bit data "1". When b3 is "1" and the other output
 terminals are "0", because the fuse F3 is blown when
 programming, the output terminal of the OR gate unit
 430 will output the one bit data "0". Hence, the OR gate
 unit 430 can output the identification code 11101000 in
 sequence. The timing sequence is shown in FIG. 5.

[0028] FIG. 6 is another conventional identification
 circuit of an inkjet print head. The identification circuit
 700 includes a counter 710, a programmable unit 720
 consisting of a plurality of fuses, and several NMOSFET
 switches 731-737.

[0029] The identification circuit 700 only requires
 three signal lines including a reset signal line 701 for
 transmitting Reset signal, a first clock signal line 702 for
 transmitting CLK1 signal, a second clock signal line 703
 for transmitting CLK2 signal. The counter 710 is electri-
 cally coupled to the reset signal line 701, the first clock
 signal line 702 and the second clock signal line 703. The
 counter 710 is a 8-bit counter with 8 output terminals
 b0-b7 for required number of identification codes. Each
 of output terminals b0-b7 is connected to the gates of
 the switches 730-737 respectively to control the on/off
 of the switches 730-737. One of the source/drain of the
 switches 730-737 are connected to the power supply or
 ground via the fuses of the programmable unit 720 for
 inputting the identification code. The other source/drain
 of the switches 730-737 is connected to the identifica-
 tion code line to output the identification code.

[0030] For example, if the identification code is
 11101000, the fuses F10, F11, F12, F3, F14, F5, F6, and
 F7 have to be blown and the fuses F0, F1, F2, F13, F4,
 F15, F16, and F17 are kept intact, thereby programming
 the identification code into the programmable unit 720.
 The timing sequence is shown in FIG. 5.

[0031] When the counter 710 receives the reset signal
 Reset via the reset signal line 701, the counter 710 is
 reset to "0". When the counter receives the first and sec-
 ond clock signals CLK1 and CLK2 via the first and sec-
 ond clock signal lines 702 and 703 respectively in se-
 quence, the output terminals b0-b7 of the counter 710
 will be set to "1" in sequence as shown in FIG. 5.

[0032] When b0 is "1" and b1-b7 are "0", because the
 fuse F0 is intact when programming, the switch 730 will
 be turned on and the one bit data "1" will be outputted.
 Likewise, when b1 is "1" and the other output terminals
 are "0", because the fuse F1 is intact when program-
 ming, the switch 731 will be turned on and the one bit
 data "1" will be outputted; when b2 is "1" and the other
 output terminals are "0", because the fuse F2 is intact
 when programming, the switch 732 will be turned on and
 the one bit data "1" will be outputted. When b3 is "1" and
 the other output terminals are "0", because the fuse F3
 is blown when programming, the switch 733 will be

turned on and the one bit data "0" will be outputted. Hence, the identification code 11101000 will be outputted in sequence. The timing sequence is shown in FIG. 5.

[0033] In addition, Applicant also discloses several identification circuits in the European patent application (03250724.6). The content of that application can also be integrated into this application for reference.

First Embodiment

[0034] FIG. 7A is an apparatus for determining the status of one bit identification circuit of an inkjet print head in accordance with the first preferred embodiment of the present invention. The apparatus is applied to an inkjet print head as shown in FIG. 3 with a plurality of signal lines. The apparatus comprises a status output terminal 605, a first blowing terminal 601, a second blowing terminal 603, and a switch circuit 620. The status output terminal 605 outputs one bit data of the status of the inkjet print head identification circuit to the corresponding input terminal 605' of one-bit shift registers as exemplified in Fig. 7C. It is noted that the input terminal 605' of one-bit shift registers can be inside or outside the one-bit shift registers. For practical application, it can be connected to a one-bit shift register 320a-320d to provide the predetermined output for the one-bit shift register. The first blowing terminal 601 is electrically coupled to the status output terminal 605 via a first programmable switch 610. The second blowing terminal 603 is electrically coupled to the status output terminal 605 via a second programmable switch 615. The switch circuit 620 is controlled by the signal lines to conduct an external power supply Pin to program the first programmable switch 610 and said second programmable switch 615. The external power supply Pin can be a voltage supply or a current supply.

[0035] In a preferred embodiment of the present invention, the switch circuit 620 comprises a first transistor 623 and a second transistor 626. The first signal line A_{n+1} determines whether to turn on/off the first transistor 623, and when the first transistor 623 is on, the voltage level of the second signal line A_{n+2} determines whether to apply the external power supply Pin to the first programmable switch 610 and the second programmable switch 615. The first programmable switch 610 and the second programmable switch 615 can be fuses or low power resistors as shown in FIG. 7B.

[0036] The method to implement the embodiment mentioned above comprises the steps as follows. First, two of the signal lines, such as A_{n+1} and A_{n+2} will be enabled to conduct the external power supply Pin. Then the power supply Pin is used to program the first programmable switch 610 and the second programmable switch 615. By this step, one of the first programmable switch 610 and the second programmable switch 615 (such as a fuse or a low power resistor) will be blown. Hence, one of (a) the electrically connection between

the first blowing terminal 601 and the status output terminal 605 and (b) the electrically connection between the second blowing terminal 603 and the status output terminal 605 is open. The first programmable switch 610 and the second programmable switch 615 are connected to the different voltage levels. To blow the second programmable switch 615, the second blowing terminal 603 connected to the second programmable switch 615 is connected to the ground and the other terminal of the second programmable switch 615 is connected to the power supply Pin. The first blowing terminal 601 connected to the first programmable switch 610 is floated, and the other terminal of the first programmable switch 610 is connected to the power supply Pin. Hence, because the second blowing terminal 603 is grounded, the second programmable switch 603 will be blown due to the voltage difference so that the connection between the second blowing terminal 603 and the status output terminal 605 is broken.

[0037] Likewise, to blow the first programmable switch 610, the first blowing terminal 601 connected to the first programmable switch 610 is connected to the ground and the other terminal of the first programmable switch 610 is connected to the power supply Pin. The second blowing terminal 603 connected to the second programmable switch 615 is floated, and the other terminal of the second programmable switch 615 is connected to the power supply Pin. Hence, because the first blowing terminal 601 is grounded, the first programmable switch 615 will be blown due to the voltage difference so that the connection between the first blowing terminal 601 and the status output terminal 605 is broken.

[0038] It should be noted that when the inkjet print head operates under normal condition, the first blowing terminal 601 is connected to the operational voltage V_{DD} , and the second blowing terminal 603 is connected to the ground. If the first programmable switch 610 is blown, the output is "0" as the one bit of the identification code. If the second programmable switch 615 is blown, the output is "1" as the one bit of the identification code.

Second Embodiment

[0039] The apparatus shown in FIGs. 7A and 7B can also be applied to the identification circuit of FIG. 6. The first programmable switch and the second programmable switch can be deemed a pair of fuses (e.g., F0 and F10, F1 and F11, F2 and F12, F3 and F13, F4 and F14, F5 and F15, F6 and F16, and F7 and F17) of FIG. 6. Taking F7 and F17 as an example, the status output terminal of FIG. 7 is connected to the logic gate input terminal 605' of FIG. 6. The first programmable switch is F7, and the second programmable switch is F17. Hence, to blow one of the fuses, it can be performed as follows: First, two of the signal lines, such as A_{n+1} and A_{n+2} will be enabled to conduct the external power supply Pin. Then the power supply Pin is used to program the first programmable switch 610 and the second pro-

programmable switch 615. By this step, one of the first programmable switch 610 and the second programmable switch 615 (such as a fuse or a low power resistor) will be blown. Hence, one of (a) the electrically connection between the first blowing terminal 601 and the status output terminal 605 and (b) the electrically connection between the second blowing terminal 603 and the status output terminal 605 is open. The first programmable switch 610 and the second programmable switch 615 are connected to the different voltage levels. To blow the second programmable switch 615, the second blowing terminal 603 connected to the second programmable switch 615 is connected to the ground and the other terminal of the second programmable switch 615 is connected to the power supply Pin. The first blowing terminal 601 connected to the first programmable switch 610 is floated, and the other terminal of the first programmable switch 610 is connected to the power supply Pin. Hence, because the second blowing terminal 603 is grounded, the second programmable switch 615 will be blown due to the voltage difference so that the connection between the second blowing terminal 603 and the status output terminal 605 is broken.

[0040] Likewise, to blow the first programmable switch 610, the first blowing terminal 601 connected to the first programmable switch is connected to the ground and the other terminal of the first programmable switch 610 is connected to the power supply Pin. The second blowing terminal 603 connected to the second programmable switch 615 is floated, and the other terminal of the second programmable switch 615 is connected to the power supply Pin. Hence, because the first blowing terminal 601 is grounded, the first programmable switch 610 will be blown due to the voltage difference so that the connection between the first blowing terminal 601 and the status output terminal 605 is broken.

[0041] When the inkjet print head operates under normal condition, the first blowing terminal 601 is connected to the operational voltage V_{DD} , and the second blowing terminal 603 is connected to the ground. If the first programmable switch 610 is blown, the output is "0" as the one bit of the identification code. If the second programmable switch 615 is blown, the output is "1" as the one bit of the identification code.

Third Embodiment

[0042] FIG. 8A is an apparatus for determining the status of one bit identification circuit of an inkjet print head in accordance with the third preferred embodiment of the present invention. This apparatus can be applied to the one-bit identification circuit of FIG. 4. Compared to the first embodiment, this embodiment further includes a status input circuit 630. The status input circuit 630 is controlled by the signal lines A_{n+3} and A_{n+4} to conduct the external power supply to the third blowing point 607. The status input circuit 630 includes a third transistor 633 and a fourth transistor 636. The third sig-

nal line A_{n+3} determines whether to turn on/off the third transistor 633. When the third transistor 633 is on, the voltage level of the fourth signal line A_{n+4} determines whether to apply the external power supply to the third blowing terminal 607. The first, second, third, and fourth signal lines can be the same signal line or different signal lines.

[0043] FIG. 8B shows the apparatus of FIG. 8A connected to the circuit of FIG. 4, wherein the status output terminal 605 is coupled to the corresponding input terminal 605" of the OR gate

[0044] To blow one of the first and second programmable switches 610, 615, first, two of the signal lines, such as A_{n+1} and A_{n+2} will be enabled to conduct the external power supply Pin. Then the power supply Pin is used to program the first programmable switch 610 and the second programmable switch 615. By this step, one of the first programmable switch 610 and the second programmable switch 615 (such as a fuse or a low power resistor) will be blown. Hence, one of (a) the electrically connection between the second blowing terminal 603 and the status output terminal 605 and (b) the electrically connection between the third blowing terminal 607 and the status output terminal 605 is open. The first programmable switch 610 and the second programmable switch 615 are connected to the different voltage levels. To blow the second programmable switch 615, the second blowing terminal 603 connected to the second programmable switch 615 is connected to the ground and the other terminal of the second programmable switch 615 connected to the power supply Pin. The third blowing terminal 607 connected to the first programmable switch 610 is floated, and the other terminal of the first programmable switch 610 is connected to the power supply Pin. Hence, because the second blowing terminal 603 is grounded, the second programmable switch 615 will be blown due to the voltage difference so that the connection between the second blowing terminal 603 and the status output terminal 605 is broken.

[0045] Likewise, to blow the first programmable switch 610, the third blowing terminal 607 connected to the first programmable switch 610 is connected to the ground and the other terminal of the first programmable switch 610 is connected to the power supply Pin. The second blowing terminal 603 connected to the second programmable switch 615 is floated, and the other terminal of the second programmable switch 615 is connected to the power supply Pin. Hence, because the first blowing terminal 601 is grounded, the first programmable switch 610 will be blown due to the voltage difference so that the connection between the third blowing terminal 607 and the status output terminal 605 is broken.

[0046] It should be noted when the inkjet print head operates under normal condition, the third blowing terminal 607 is floated and the second blowing terminal is connected to the ground. If the first programmable switch 610 is blown, the output is "0" as the one bit of the identification code. If the second programmable

switch 615 is blown, the status output terminal 605 is electrically coupled to the output terminals b0-b7 of the counter so that the voltage level of the status output terminal 605 is the same as the output terminals b0-b7 of the counter.

[0047] Further, when the printer prints the works, no more than two signal lines will be enabled. Only when blowing the fuses and storing the identification code, more than two signal lines can be enabled.

[0048] The present invention uses a pair of fuses or low power resistors approximately less than 0.3W, or uses a fuse and a low power resistor approximately less than 0.3W. The status output terminal 605 will output 1 or 0 based on which one of the fuses (or resistors, or a fuse and a resistor) is blown by applying an external power supply Pin. The identification circuit of the present invention is programmable by inputting signals and external power supply for blowing the fuse. The identification circuit of the present invention uses programmable fuses or low power resistors to change the identification code. Hence, it provides flexibility by using the existent signal line pins to blow the fuses without additional pins. Hence the present invention can be used for mass production because it is much simpler than the conventional identification circuit.

[0049] The foregoing description of the preferred embodiment of the present invention has been presented for purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise form or to exemplary embodiments disclosed. Accordingly, the foregoing description should be regarded as illustrative rather than restrictive. Obviously, many modifications and variations will be apparent to practitioners skilled in this art. Similarly, any process steps described might be interchangeable with other steps in order to achieve the same result. The embodiment was chosen and described in order to best explain the principles of the invention and its best mode practical application, thereby to enable others skilled in the art to understand the invention for various embodiments and with various modifications as are suited to the particular use or implementation contemplated. It is intended that the scope of the invention be defined by the claims appended hereto and their equivalents. It should be appreciated that variations may be made in the embodiments described by workers skilled in the art without departing from the scope of the present invention as defined by the following claims. Moreover, no element, component, nor method step in the present disclosure is intended to be dedicated to the public regardless of whether the element, component, or method step is explicitly recited in the following claims.

Claims

1. An apparatus for determining statuses of an identification circuit of an inkjet print head with a plurality

of signal lines, wherein said identification circuit having at least one input terminal, comprising:

a status output terminal, outputting one bit data of said status of said inkjet print head identification circuit to said at least one input terminal corresponding to said status output terminal; a first blowing terminal, electrically coupled to said status output terminal via a first programmable switch; and a second blowing terminal, electrically coupled to said status output terminal via a second programmable switch;

wherein one of said first programmable switch and said second programmable switch being off to determine a voltage level of said status output terminal.

2. The apparatus of claim 1, further comprising a switch circuit, controlled by said plurality of said signal lines, conducting an external power supply to program said first programmable switch and said second programmable switch.

3. The apparatus of claim 2, wherein said switch circuit comprises:

a first transistor, a first signal line of said plurality of signal lines determining whether to turn on/off said first transistor; and a second transistor, wherein when said first transistor is on, the voltage level of a second signal line of said plurality of signal lines determines whether to apply said external power supply to said first programmable switch and said second programmable switch.

4. The apparatus of claim 3, wherein said first signal line is said second signal line.

5. The apparatus of claim 1, wherein said first and second programmable switches include fuses.

6. The apparatus of claim 1, further comprising a status input circuit having a third blowing terminal, said status input circuit being electrically coupled to said plurality of signal lines, said status input circuit being controlled by said plurality of signal lines to conduct said external power supply to said third blowing terminal.

7. The apparatus of claim 6, wherein said status input circuit further comprises:

a third transistor, a third signal line of said plurality of signal lines determining whether to turn on/off said third transistor; and

a fourth transistor, wherein when said third transistor is on, the voltage level of a fourth signal line of said plurality of signal lines determines whether to apply said external power supply to said third blowing terminal.

5

8. The apparatus of claim 7, wherein said third signal line is said fourth signal line.

9. The apparatus of claim 3, further comprising a status input circuit having a third blowing terminal, said status input circuit being electrically coupled to said plurality of signal lines, said status input circuit being controlled by said plurality of signal lines to conduct said external power supply to said third blowing terminal.

10

15

10. The apparatus of claim 9, wherein said status input circuit further comprises:

20

a third transistor, a third signal line of said plurality of signal lines determining whether to turn on/off said third transistor; and

a fourth transistor, wherein when said third transistor is on, the voltage level of a fourth signal line of said plurality of signal lines determines whether to apply said external power supply to said third blowing terminal.

25

11. The apparatus of claim 10, wherein said first, second, third, and fourth signal lines are a same signal line.

30

12. The apparatus of claim 1, wherein said inkjet print head identification circuit includes a shift register.

35

13. The apparatus of claim 1, wherein said inkjet print head identification circuit includes a counter.

14. The apparatus of claim 13, wherein said inkjet print head identification circuit includes a logic gate.

40

15. A method of determining a status of an identification circuit of an inkjet print head with a plurality of signal lines, comprising:

45

enabling two of said plurality of signal lines to conduct an external power supply; and coupling said external power supply to a first programmable switch and a second programmable switch to turn off one of said first programmable switch and a second programmable switch;

50

wherein said plurality of signal lines are not enabled simultaneously when said inkjet print head operates.

55

16. The method of claim 15, wherein said step of coupling said external power supply to said first programmable switch and said second programmable switch comprises:

floating one terminal of one of said first programmable switch and said second programmable switch, and applying said external power supply to another terminal of said one of said first programmable switch and said second programmable switch; and grounding one terminal of the other first programmable switch and said second programmable switch, and applying said external power supply to another terminal of said other first programmable switch and said second programmable switch;

wherein said grounded first programmable switch and said second programmable switch is off due to a voltage difference between said one terminal and said another terminal.

17. The method of claim 15, wherein two of said plurality of signal lines are same signal line.

18. The apparatus of claim 1, wherein said first programmable switch and said second programmable switch include low power resistors.

19. The apparatus of claim 1, wherein one of said first programmable switch and said second programmable switch is a low power resistor.





FIG. 1 (PRIOR ART)






FIG. 3 (PRIOR ART)




FIG. 4 (PRIOR ART)




FIG. 5 (PRIOR ART)




FIG. 6 (PRIOR ART)




FIG. 7A




FIG. 7B




FIG. 7C




FIG. 8A




FIG. 8B



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 03 02 4578

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
X	US 6 325 483 B1 (HARBOUR ROBERT ET AL) 4 December 2001 (2001-12-04) * column 1, line 66 - column 3, line 18; figure 2 *	1-19	B41J2/175
A	----- US 6 179 401 B1 (MARTINEZ MANEL ET AL) 30 January 2001 (2001-01-30) * column 11, line 16 - line 27 * * column 11, line 52 - column 12, line 15 * * figure 30 *	1,15	
A	----- US 2003/030687 A1 (HU HUNG-LIEH ET AL) 13 February 2003 (2003-02-13) * paragraph [0030] - paragraph [0033]; figures 7,11-13 * -----	1,15	
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
			B41J
The present search report has been drawn up for all claims			
Place of search Munich		Date of completion of the search 11 February 2004	Examiner Bridge, S
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

1
EPO FORM 1503 03.82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 03 02 4578

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

11-02-2004

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 6325483	B1	04-12-2001	BR 0103820 A	26-02-2002
			CN 1334548 A	06-02-2002
			EP 1174277 A2	23-01-2002
			TW 499369 B	21-08-2002

US 6179401	B1	30-01-2001	US 6076913 A	20-06-2000
			DE 69800173 D1	20-07-2000
			DE 69800173 T2	15-02-2001
			EP 0863009 A1	09-09-1998
			ES 2147035 T3	16-08-2000

US 2003030687	A1	13-02-2003	TW 514604 B	21-12-2002
