



(12) **CORRECTED EUROPEAN PATENT SPECIFICATION**

(15) Correction information:

Corrected version no 1 (W1 B1)
Corrections, see
Claims DE 1, 11, 13
Claims EN 1, 11, 13
Claims FR 1, 11, 13

(51) Int Cl.:

H04L 27/26 ^(2006.01) **H04L 25/02** ^(2006.01)
H04L 5/00 ^(2006.01)

(48) Corrigendum issued on:

08.06.2016 Bulletin 2016/23

(45) Date of publication and mention
of the grant of the patent:

17.12.2014 Bulletin 2014/51

(21) Application number: **09155364.4**

(22) Date of filing: **17.03.2009**

(54) **Reference signal generation using gold sequences**

Erzeugung von Referenzsignalen mittels Goldfolgen

Génération de signaux de référence à partir de séquences Gold.

(84) Designated Contracting States:

**AT BE BG CH CY CZ DE DK EE ES FI FR GB GR
HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL
PT RO SE SI SK TR**

(30) Priority: **17.03.2008 US 36998 P**

28.04.2008 US 48227 P

02.05.2008 US 49777 P

13.03.2009 KR 20090021828

(43) Date of publication of application:

23.09.2009 Bulletin 2009/39

(73) Proprietor: **LG Electronics Inc.**

Seoul 150-721 (KR)

(72) Inventors:

- **LEE, Jung Hoon**
431-749, Gyeonggi-do (KR)
- **LEE, Daewon**
431-749, Gyeonggi-do (KR)
- **KIM, Ki Jun**
431-749, Gyeonggi-do (KR)
- **AHN, Joon Kui**
431-749, Gyeonggi-do (KR)

(74) Representative: **Cabinet Plasseraud**

66, rue de la Chaussée d'Antin
75440 Paris Cedex 09 (FR)

(56) References cited:

WO-A1-2009/023792

- **ERICSSON: "Update of uplink reference-signal hopping, downlink reference signals, scrambling sequences, DwPTS/UpPTS lengths for TDD and control channel processing", 3GPP DRAFT; 36211_CR0003R1_(REL-8)_R1-081161, 3RD GENERATION PARTNERSHIP PROJECT (3GPP), MOBILE COMPETENCE CENTRE ; 650, ROUTE DES LUCIOLES ; F-06921 SOPHIA-ANTIPOLIS CEDEX ; FRANCE, vol. RAN WG1, no. Sorrento, Italy; 20080520, 4 March 2008 (2008-03-04), XP050109130, [retrieved on 2008-05-20]**
- **LG ELECTRONICS: "PRS sequence generation for downlink reference signal", 3GPP DRAFT; R1-081248 PRS SEQUENCE GENERATION FOR DL RS, 3RD GENERATION PARTNERSHIP PROJECT (3GPP), MOBILE COMPETENCE CENTRE ; 650, ROUTE DES LUCIOLES ; F-06921 SOPHIA-ANTIPOLIS CEDEX ; FRANCE, vol. RAN WG1, no. Shenzhen, China; 20080326, 26 March 2008 (2008-03-26), XP050109691, [retrieved on 2008-03-26]**

- LG ELECTRONICS ET AL: "Fast forwarding Gold sequence for random number sequence generation", 3GPP DRAFT; R1-081620 FAST FORWARDING GOLD SEQUENCE, 3RD GENERATION PARTNERSHIP PROJECT (3GPP), MOBILE COMPETENCE CENTRE ; 650, ROUTE DES LUCIOLES ; F-06921 SOPHIA-ANTIPOLIS CEDEX ; FRANCE, vol. RAN WG1, no. Shenzhen, China; 20080409, 9 April 2008 (2008-04-09), XP050110020, [retrieved on 2008-04-09]

Description

BACKGROUND

5 1. Field of the Invention

[0001] The present invention relates to wireless communications, and more particularly, to generation and application of a sequence for a reference signal in a wireless communication system.

10 2. Related Art

[0002] Wireless communication systems are widely spread all over the world to provide various types of communication services such as voice or data. In general, the wireless communication system is a multiple access system capable of supporting communication with multiple users by sharing available system resources (e.g., bandwidth, transmit power, etc.). Examples of the multiple access system include a code division multiple access (CDMA) system, a frequency division multiple access (FDMA) system, a time division multiple access (TDMA) system, an orthogonal frequency division multiple access (OFDMA) system, a single carrier frequency division multiple access (SC-FDMA) system, etc.

[0003] In the wireless communication system, a sequence is generally used in various usages such as a reference signal, a scrambling code, etc. The sequence used in the wireless communication system generally satisfies the following properties.

- (1) A good correlation property for providing high detection performance.
- (2) A low peak-to-average power ratio (PAPR) for increasing efficiency of a power amplifier.
- (3) Generation of a large number of sequences to transmit a large amount of information or to facilitate cell planning.

[0004] Although a constant amplitude and zero auto correlation (CAZAC) sequence having a good PAPR property has been proposed, the number of available sequences is limited. Therefore, many wireless communication systems use a sequence generated in a pseudo-random manner. A pseudo-random sequence has an advantage in that a large number of sequences are available, but has a problem of a high PAPR in a specific pattern.

[0005] Various binary or non-binary pseudo-random sequences have been used in the wireless communication system. The pseudo-random sequences can be easily generated using an m-stage linear feedback shift register (LFSR), and have a significantly excellent random property. An m-sequence is used as a scrambling code in a wideband CDMA (WCDMA) system since a structure of the m-sequence is simpler than the non-binary pseudo-random sequence.

[0006] A gold sequence is a pseudo-random sequence generated by using two different binary m-sequences. The gold sequence can be easily implemented by two m-stage LFSRs. The gold sequence has an advantage in that different pseudo-random sequences can be generated in accordance with a period while varying an initial state of each m-stage LFSR.

[0007] A Gold sequence is used for the generation of the reference-signal sequence in ERICSSON. Update of uplink reference-signal hopping, downlink reference signals, scrambling sequences, DwPTS/UpPTS lengths for TDD and control channel processing, 36.211, CR0003, R1-081161. 3GPP TSG-RAN WG1, Meeting #52. February 11-15, 2008. Sorrento, Italy.

[0008] Accordingly, there is a need for a method capable of generating a sequence with improved PAPR and correlation properties.

45 SUMMARY

[0009] The present invention provides a method and apparatus for transmitting a reference signal in a wireless communication system. In addition, a receiver for receiving the transmitted reference signal is also provided.

[0010] The present invention also provides a method and apparatus for transmitting a sequence in a wireless communication system. In addition, a receiver for receiving the transmitted sequence is also provided.

[0011] In an aspect, a method of transmitting a reference signal in a wireless communication system is provided. The method includes generating a reference signal sequence, mapping a portion or entirety of the reference signal sequence to at least one RB, and transmitting a reference signal in the at least one RB. The reference signal sequence is defined by

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

where n_s is a slot number within a radio frame, l is an orthogonal frequency division multiplexing (OFDM) symbol number within a slot and $N_{RB}^{\max, DL}$ is a maximum number of resource blocks (RBs). A pseudo-random sequence $c(i)$ is generated by a gold sequence generator which is initialized with initial values obtained by using $(2 N_{ID}^{\text{cell}} + 1)$, where N_{ID}^{cell} is a cell identifier.

[0012] The pseudo-random sequence $c(i)$ may be defined by

$$\begin{aligned} c(i) &= (x(i + Nc) + y(i + Nc)) \bmod 2 \\ x(i + 31) &= (x(i + 3) + x(i)) \bmod 2 \\ y(i + 31) &= (y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2 \end{aligned}$$

where $x(i)$ and $y(i)$ are m-sequences and Nc is a constant. The m-sequence $x(i)$ may be initialized with $x(0)=1$, $x(i)=0$, $i=1, 2, \dots, 30$, and the m-sequence y may be initialized with the initial values. The Nc may be a value in range from 1500 to 1800.

[0013] The initial values may vary as the OFDM symbol number varies. The initial values may be obtained by using $(2 N_{ID}^{\text{cell}} + 1)$. The size of the initial values may be 31 bits.

[0014] One RB may comprise 12 subcarriers in frequency domain. Two modulation symbols of the reference signal sequence may be mapped to two subcarriers in one RB.

[0015] The reference signal may be a cell common reference signal or a user equipment (UE) specific reference signal.

[0016] In another aspect, a transmitter includes a reference signal generator to generate a reference signal, and a transmit circuitry to transmit the reference signal. The reference signal generator generates the reference signal by generating a reference signal sequence which is defined by

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

where n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot and $N_{RB}^{\max, DL}$ is a maximum number of RBs. A pseudo-random sequence $c(i)$ is generated by a gold sequence generator which is initialized with initial values obtained by using $(2 N_{ID}^{\text{cell}} + 1)$, where N_{ID}^{cell} is a cell identifier. The reference signal generator maps a portion or entirety of the reference signal sequence to at least one RB.

[0017] In still another aspect, a receiver includes a receive circuitry to receive a reference signal and a receive signal, a channel estimator to estimate a channel by using the reference signal, and a data processor to process the receive signal by using the channel. The reference signal is generated based on a reference signal sequence which is defined by

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

where n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot and $N_{RB}^{max,DL}$ is a maximum number of RBs. A pseudo-random sequence $c(i)$ is generated by a gold sequence generator which is initialized with

5 initial values obtained by using $(2 N_{ID}^{cell} + 1)$, where N_{ID}^{cell} is a cell identifier.

[0018] A proposed sequence provides low peak-to-average power ratio (PAPR) and high cross-correlation properties. Therefore, transmit power can be effectively provided in a transmitter, and signal detection performance can be improved in a receiver. The proposed sequence can be used for a reference signal requiring high reliability and also can be used

10 for other scrambling codes.

BRIEF DESCRIPTION OF THE DRAWINGS

[0019]

FIG. 1 shows a wireless communication system.

FIG. 2 shows a structure of a radio frame in the 3GPP LTE.

FIG. 3 shows an example of a resource grid for one downlink slot.

FIG. 4 shows an exemplary structure of a downlink subframe.

FIG. 5 shows an exemplary structure of a downlink common reference signal when a BS uses one antenna.

FIG. 6 shows an exemplary structure of a downlink common reference signal when a BS uses two antennas.

FIG. 7 shows an exemplary structure of a downlink common reference signal when a BS uses four antennas.

FIG. 8 shows an example of a gold sequence generator.

FIG. 9 shows setting of the initial values of the second LFSR.

FIG. 10 is a graph for comparing sizes of a reference signal and any data when initial values of the second LFSR are all set to '0'.

FIG. 11 shows a problem caused by initial values of a gold sequence in a multi-cell environment.

FIG. 12 shows an example where bit sequences, which are cyclically mapped in QPSK modulation, are set to initial values.

FIG. 13 shows an example where the initial values of the first LFSR are set to 1's complements of the initial values of the second LFSR.

FIG. 14 shows that an offset of an available sequence varies according to a cell ID.

FIG. 15 shows that a basic sequence in use is cyclic shifted according to a cell ID.

FIG. 16 shows that the start point of the used sequence is changed according to the subframe number and/or the OFDM symbol number.

FIG. 17 shows setting of initial values of a gold sequence generator.

FIG. 18 is a flowchart showing a method of transmitting a reference signal according to an embodiment of the present invention.

FIG. 19 is a block diagram showing a transmitter and a receiver implementing for a method of transmitting and receiving a reference signal.

DESCRIPTION OF EXEMPLARY EMBODIMENTS

[0020] The technique described below can be used in various wireless access technologies such as code division multiple access (CDMA), frequency division multiple access (FDMA), time division multiple access (TDMA), orthogonal frequency division multiple access (OFDMA), single carrier frequency division multiple access (SC-FDMA), etc. The CDMA may be implemented with a radio technology such as Universal Terrestrial Radio Access (UTRA) or CDMA2000. The TDMA may be implemented with a radio technology such as Global System for Mobile communications (GSM)/ General Packet Radio Service (GPRS)/ Enhanced Data Rates for GSM Evolution (EDGE). The OFDMA may be implemented with a radio technology such as institute of electrical and electronics engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802-20, evolved-UTRA (E-UTRA) etc. The UTRA is a part of a universal mobile telecommunication system (UMTS). 3rd generation partnership project (3GPP) long term evolution (LTE) is a part of an evolved-UMTS (E-UMTS) using the E-UTRA. The 3GPP LTE employs the OFDMA in downlink and employs the SC-FDMA in uplink. LTE-advance (LTE-A) is an evolution of the 3GPP LTE.

[0021] For clarity, the following description will focus on the 3GPP LTE/LTE-A. However, technical features of the present invention are not limited thereto.

[0022] FIG. 1 shows a wireless communication system.

[0023] Referring to FIG. 1, a wireless communication system 10 includes at least one base station (BS) 11. The BSs 11 provide communication services to specific geographical regions (generally referred to as cells) 15a, 15b, and 15c. The cell can be divided into a plurality of regions (referred to as sectors). A user equipment (UE) 12 may be fixed or mobile, and may be referred to as another terminology, such as a mobile station (MS), a user terminal (UT), a subscriber station (SS), a wireless device, a personal digital assistant (PDA), a wireless modem, a handheld device, etc. The BS 11 is generally a fixed station that communicates with the UE 12 and may be referred to as another terminology, such as an evolved node-B (eNB), a base transceiver system (BTS), an access point, etc.

[0024] Hereinafter, a downlink is a communication link from the BS to the UE, and an uplink is a communication link from the UE to the BS. In the downlink, a transmitter may be a part of the BS, and a receiver may be a part of the UE. In the uplink, the transmitter may be a part of the UE, and the receiver may be a part of the BS.

[0025] FIG. 2 shows a structure of a radio frame in the 3GPP LTE.

[0026] Referring to FIG. 2, the radio frame includes 10 subframes. One subframe includes two slots. A time for transmitting one subframe is defined as a transmission time interval (TTI). For example, one subframe may have a length of 1 millisecond (ms), and one slot may have a length of 0.5 ms.

[0027] One slot includes a plurality of orthogonal frequency division multiplexing (OFDM) symbols in a time domain. Since the 3GPP LTE uses the OFDMA in the downlink, the OFDM symbol is for representing one symbol period. According to a system, the OFDM symbol can also be referred to as an SC-FDMA symbol or a symbol period. A resource block (RB) is a resource allocation unit, and includes a plurality of contiguous subcarriers in one slot.

[0028] The structure of the radio frame is shown for exemplary purposes only. Thus, the number of subframes included in the radio frame or the number of slots included in the subframe or the number of OFDM symbols included in the slot may be modified in various manners.

[0029] FIG. 3 shows an example of a resource grid for one downlink slot.

[0030] Referring to FIG. 3, the downlink slot includes a plurality of OFDM symbols in a time domain. It is described herein that one downlink slot includes 7 OFDM symbols, and one resource block (RB) includes 12 subcarriers in a frequency domain as an example. However, the present invention is not limited thereto.

[0031] Each element on the resource grid is referred to as a resource element. One RB includes 12x7 resource elements. The number N^{DL} of RBs included in the downlink slot depends on a downlink transmit bandwidth.

[0032] FIG. 4 shows an exemplary structure of a downlink subframe.

[0033] Referring to FIG. 4, the subframe includes two slots. A maximum of three OFDM symbols located in a front portion of a 1st slot within the subframe correspond to a control region to be assigned with control channels. The remaining OFDM symbols correspond to a data region to be assigned with a physical downlink shared channel (PDSCH).

[0034] Examples of downlink control channels used in the 3GPP LTE includes a physical control format indicator channel (PCFICH), a physical downlink control channel (PDCCH), a physical hybrid ARQ indicator channel (PHICH), etc. The PCFICH is transmitted at a first OFDM symbol of a subframe and carries information regarding the number of OFDM symbols used for transmission of control channels within the subframe. Control information transmitted through the PDCCH is referred to as downlink control information (DCI). The DCI includes uplink or downlink scheduling information or includes an uplink transmit power control command for arbitrary UE groups.

[0035] Now, a reference signal will be described.

[0036] When data is transmitted in a wireless communication system, the transmitted data may be distorted on a radio channel. In order for a receiver to restore the distorted data into original data, a channel state needs to be known so that distortion of a received signal is compensated for according to the channel state. To know the channel state, a signal known in advance to both a transmitter and the receiver is used. Such a signal is referred to as a reference signal or a pilot. Since the reference signal is an important signal to know the channel state, the transmitter transmits the reference signal with greater transmit power than other signals. In addition, to distinguish the reference signal transmitted between cells in a multi-cell environment, the reference signal has to have good peak-to-average power ratio (PAPR) and correlation properties.

[0037] The reference signal can be classified into a cell common reference signal and a UE specific reference signal. The cell common reference signal is a reference signal used by all UEs within a cell. The UE specific reference signal is a reference signal used by a UE within the cell or used by a UE group.

[0038] FIG. 5 shows an exemplary structure of a downlink common reference signal when a BS uses one antenna. FIG. 6 shows an exemplary structure of a downlink common reference signal when a BS uses two antennas. FIG. 7 shows an exemplary structure of a downlink common reference signal when a BS uses four antennas. This may be found in section 6.10.1 of 3GPP TS 36.211 V8.0.0 (2007-09) "Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation (Release 8)". R_p denotes a reference signal for a p-th antenna (herein, $p \in \{0, 1, 2, 3\}$). R_0 to R_3 do not overlap with one another. In one OFDM symbol, each R_p is positioned with a spacing of 6 subcarriers. Therefore, if one RB includes 12 subcarriers, a sequence having a length of 2 sequences (or two modulation symbols) is required for one RB. Within a subframe, the number of R_0 s is equal to the number of R_1 s, and the number of R_2 s is equal to the number of R_3 s. Within the subframe, the number of R_2 s and R_3 s is less than the number of R_0 s and R_1 s.

R_p is not used in transmission through antennas except for the pth antenna. This is to avoid interference between antennas.

[0039] Now, generation of a sequence for a reference signal will be described.

[0040] A reference signal generated by using a gold sequence generator is considered. A gold sequence can be implemented with two 31-stage linear feedback shift registers (LFSRs). It is assumed that a first LFSR 'x(30)x(29)x(28)...x(2)x(1)x(0)' of the two LFSRs is initialized with '000000000000000000000000000001'. In addition, initial values of a second LFSR are determined by a cell identifier (ID), a subframe number, and an OFDM symbol number. The cell ID denotes a cell specific ID. The subframe number denotes an index of a subframe within a radio frame. The OFDM symbol number denotes an index of an OFDM symbol within a subframe (or slot).

[0041] FIG. 8 shows an example of a gold sequence generator. A sequence generation polynomial $D^{31}+D^3+1$ is used for a first m-sequence x(i), and a sequence generation polynomial $D^{31}+D^3+D^2+D+1$ is used for a second m-sequence y(i). These two m-sequences are used to generate a pseudo-random sequence c(i). The pseudo-random sequence c(i) is generated by a generation polynomial of Equation 1 as shown:

[Equation 1]

$$c(i) = (x(i) + y(i)) \bmod 2$$

$$x(i+31) = (x(i+3) + x(i)) \bmod 2$$

$$y(i+31) = (y(i+3) + y(i+2) + y(i+1) + y(i)) \bmod 2$$

where $i = 0, 1, \dots, M_{\max}-1$, and M_{\max} is a length of a binary pseudo-random sequence generated using a gold sequence. In the pseudo-random sequence having a length of M_{\max} , only a portion of the sequence may be used. If M is a length of a sequence using only a portion of the pseudo-random sequence having a length of M_{\max} , then $M \leq M_{\max}$. M may vary depending on the number of RBs used for data transmission. The number of available RBs varies according to an available frequency band in a 3GPP LTE system, and thus the value M may also vary according to the number of allocated RBs.

[0042] In case of the first LFSR, the initial values are fixed to '000000000000000000000000000001' as described above. The initial values of the second LFSR are determined by the cell ID, the subframe number, and the OFDM symbol number.

[0043] FIG. 9 shows setting of the initial values of the second LFSR. Among the 31 bits of the initial values, 17 bits from a least significant bit (LSB) are initialized with a 9-bit cell ID, a 4-bit subframe number, and a 4-bit OFDM symbol number. The 3GPP LTE supports 504 unique cell IDs, and thus the cell ID ranges from 0 to 503. One radio frame includes 10 subframes, and thus the subframe number ranges from 0 to 9. One subframe can include up to 14 OFDM symbols, and thus the OFDM symbol number ranges from 0 to 13. The remaining 14 bits from a most significant bit (MSB) are initialized with '0'. The initial values of the second LFSR can be expressed by the following table.

[Table 1]

x(30) x(29) x(28) x(27) x(26) x(3)x(2)x(1)x(0)			
Set to zero	OFDM symbol number	Subframe Number	Cell ID
14bit	4bit	4 bit	9bit

[0044] In the above table 1, a range and/or bit number for cell ID, OFDM symbol number and subframe number are exemplary purposed only and are not limited thereto. For example, the subframe number may be represented as a slot number. Since a radio frame includes 20 slots, the slot number may be in a range of 0~19.

[0045] After determining the initial values of the first LFSR and the initial values of the second LFSR, a portion or entirety of the pseudo-random sequence generated by the gold sequence generator is used as a reference signal. The generated sequence is modulated into a modulation symbol through quadrature phase shift keying (QPSK) modulation, and then is mapped to each resource element. In this case, only a portion of a pre-generated, specific-sized gold sequence can be used. For example, as shown in FIG. 5, among the 12 subcarriers constituting one RB, the reference signal can be mapped to two subcarriers with a spacing of 6 subcarriers.

[0046] However, when the pseudo-random sequence is generated as described above, '0' and '1' may not be included with a similar ratio in the generated binary pseudo-random sequence, and thus the number of '0's may be greater than

the number of '1's or the number of '1's may be greater than the number of '0's. In this case, even if QPSK modulation is performed, a direct current (DC) component exists due to the biased pseudo-random sequence. As a result, the PAPR property may deteriorate through a process of inverse fast Fourier transform (IFFT). As a representative example, if the cell ID, the subframe number, and the OFDM symbol number are all '0', the 31 bits of the initial values of the second LFSR are all set to '0'.

[0047] FIG. 10 is a graph for comparing sizes of a reference signal and any data when initial values of the second LFSR are all set to '0'. When 31 bits of initial values of the gold sequence generator are all initialized with '0', a reference signal having a significantly large size than any other data is generated at some time samples, which implies degradation of the PAPR property.

[0048] FIG. 11 shows a problem caused by initial values of a gold sequence in a multi-cell environment. In the multi-cell environment, each cell has a unique cell ID. However, since only 9 bits out of 31 bits of the initial values are different, a pseudo-random sequence may be generated to be almost identical for each cell if the remaining 22 bits are identical. In particular, if the cell ID is contiguous in each cell, up to 30 bits output the 31 bits of the initial values may overlap. Therefore, the correlation property may deteriorate when the generated pseudo-random sequence is used as a reference signal.

[0049] Hereinafter, generation of a sequence and application of the generated sequence for solving the aforementioned problem will be described.

[0050] First, a method of generating a sequence by changing a most significant bit (MSB) of initial values of a gold sequence will be described.

[0051] When a pseudo-random sequence is generated using the gold sequence, 14 bits from the MSB are changed to a suitable value to equalize a ratio of '0' and '1' included in the initial values of the second LFSR. Since a cell ID, a subframe number, and an OFDM symbol number may be all set to '0' in some cases, the remaining 14 bits are changed to a suitable value to define a gold sequence having a good PAPR property. In case of using the gold sequence, the generated pseudo-random sequence is determined according to the initial values. Thus, it is important to set the initial values to generate a sequence having a good PAPR.

[0052] In one embodiment, 14 bits from the MSB may be all set to '1'. By doing so, the initial values of the gold sequence can be prevented from being all set to '0'. Thus, deterioration of the PAPR property can be avoided. Table 2 shows a PAPR when the 14 bits from the MSB are all set to '0'. Table 3 shows a PAPR when the 14 bits from the MSB are all set to '1'. In Table 2 and Table 3, a peak value is shown with respect to the number of RBs (i.e., 6, 12, 25, 50, and 100) when a reference signal in use is a basic sequence generated by differently setting 17 bits from the LSB of the gold sequence generator according to a cell ID, a subframe number, and an OFDM symbol number.

[Table 2]

# of RB	MSB	LSB	Peak value	PAPR
6	0000000000000000	10000110000100110	1.06	1.89
12	0000000000000000	10000011010110011	1.33	2.36
25	0000000000000000	00000000000000000	2.18	3.71
50	0000000000000000	00000000000000000	5.16	8.81
100	0000000000000000	00000000000000000	10.60	18.10

[Table 3]

# of RB	MSB	LSB	Peak value	PAPR
6	1111111111111111	10110000011101000	0.93	1.66
12	1111111111111111	10110101111110010	1.28	2.28
25	1111111111111111	10110110110110110	1.53	2.61
50	1111111111111111	10010100100100100	1.87	3.19
100	1111111111111111	00000000000000010	2.49	4.25

[0053] As shown in Table 2 and Table 3, when the 14 bits from the MSB are all set to '0', the PAPR property is superior to a case where the 14 bits from the MSB are all set to '1'.

[0054] In another embodiment, the 14 bits from the MSB may be set to a bit sequence that can be cyclically mapped on a QPSK constellation. Sequence values initially output from the gold sequence generator are the same as the initial values. Thus, when the initial values are uniformly arranged on 4 symbol positions on the QPSK constellation, modulation symbols of the generated pseudo-random sequence can be prevented from being concentrated on a specific QPSK modulation symbol.

[0055] FIG. 12 shows an example where bit sequences, which are cyclically mapped in QPSK modulation, are set to initial values. Assume that bit sequences '00', '01', '11', and '10' on the QPSK constellation respectively correspond to modulation symbols ①, ②, ③, and ④. The bit sequences are set so that 4 modulation symbols uniformly appear in 14 bits from an MSB. First, a first bit sequence '00011110000111' is defined so that the modulation symbols appear in an order of ①, ②, ③, ④, ①, ②, ③. In practice, an output of the gold sequence generator starts from an LSB. Thus, a second bit sequence '11100001111000' is defined by inversion of the first bit sequence. 17 bits from the LSB are set to values given according to a cell ID, a subframe number, and an OFDM symbol number, and one QPSK modulation symbol consists of 2 bits. Thus, a third sequence '11000011110001' is generated by cyclic-shifting the second bit sequence leftward by 1 bit. Among the 14 bits from the MSB, a bit nearest to the 17 bits from the LSB are randomly set, and bits subsequent to the nearest bit (i.e., a 19th bit from the LSB) are mapped to one modulation symbol in a unit of 2 bits. Consequently, if a modulation symbol is output starting from the LSB, in case of the third sequence, the modulation symbol is output in an order of ①, ②, ③, ④, ①, ②.

[0056] Table 4 shows the PAPR property according to the number of RBs when the 14 bits of the MSB are set to '11000011110001'.

[Table 4]

# of RB	MSB	LSB	Peak value	PAPR
6	11000011110001	1011000001011011	0.96	1.71
12	11000011110001	01100100010101001	1.31	2.33
25	11000011110001	01110101011011011	1.42	2.42
50	11000011110001	01111001101100100	1.70	2.90
100	11000011110001	00110000011001010	2.06	3.52

[0057] As shown in Table 4, the PAPR property is improved when the 14 bits from the MSB are set to proposed values.

[0058] In another embodiment, various combinations of the 14 bits from the MSB are proposed to improve the PAPR property. The 14 bits from the MSB can be changed from '00000000000000' to '11111111111111' in order to find a value having an optimal PAPR property for all possible cases, which results in significantly large complexity. It is assumed herein that the number of RBs is 6, 12, 25, 50, or 100, and a reference signal in use is a sequence having a length corresponding to the number of RBs. For each number of RBs, 17 bits from the LSB are differently set according to a cell ID, a subframe number, and an OFDM symbol number. The reference signal is subjected to an IFFT operation for OFDM modulation, and if a peak value of an OFDM symbol that is a time-domain signal exceeds a specific threshold, the OFDM symbol is removed from candidates.

[0059] Table 5 shows 14 bits from the MSB having a best PAPR property for each number of RBs (i.e., 6, 12, 25, 50, and 100).

[Table 5]

# of RB	MSB	LSB	Peak value	PAPR
6	00010001110001	00000001110000010	0.89	1.58
12	11001100100000	01000110110110101	1.10	1.96
25	01011111100110	00000011011100011	1.28	2.19
50	01100110010101	00010110100100101	1.42	2.42
100	00100001000101	01100100011010000	1.44	2.46

[0060] When an optimal value shown in Table 5 is used in the 14 bits from the MSB according to each number of RBs, increase of a PAPR caused by bias can be prevented.

[0061] Table 6 shows a peak value and a PAPR when the 14 bits from the MSB (i.e., '00010001110001') of Table 5

are used for each number of RBs. It shows that, when an optimal value for a specific number of RBs is used for a different number of RBs, the optimal value may not be optimal.

[Table 6]

# of RB	MSB	LSB	Peak value	PAPR
6	00010001110001	00000001110000010	0.89	1.58
12	00010001110001	01000011010101011	1.50	2.67
25	00010001110001	01000000010110001	1.51	2.58
50	00010001110001	10110011000011001	1.68	2.86
100	00010001110001	00010100111100111	1.75	2.99

[0062] To be selected as the optimal value, it is important to have uniform PAPR characteristics over multiple RBs. When the optimal value is set to a value which has the smallest sum of the peak values for each RB among values not to exceeds a specific threshold, the 14 bits from the MSB, '00111101101100', is selected as the optimal value. Table 7 shows a peak value and a PAPR when the 14 bits from the MSB, '00111101101100' of Table 7 are used for each number of RBs.

[Table 7]

# of RB	MSB	LSB	Peak value	PAPR
6	00111101101100	01100011010011001	0.89	1.59
12	00111101101100	00001000101010101	1.14	2.03
25	00111101101100	00000111111001000	1.40	2.40
50	00111101101100	01001001010101000	1.55	2.65
100	00111101101100	10010011111001000	1.56	2.66

[0063] The PAPR property deteriorates in comparison with the result of Table 5, which can be regarded as an optimum, but the PAPR property shows a better result than the result of Table 6 in which the 14 bits from the MSB (i.e., '00010001110001') are used. Thus, the peak value and the PAPR property are uniform as a whole. Accordingly, complexity can be lower than a case of using the 14 bits from the MSB differently according to the number of RBs, and has an advantage in that a memory size is reduced.

[0064] A method of improving the PAPR property by setting the initial values of the second LFSR of the gold sequence generator has been described above. Hereinafter, a method of improving the PAPR property of a sequence by setting the initial values of the first LFSR will be described.

[0065] In one embodiment, the initial value of the first LFSR can be defined to specific values. For example, bit sequences to which modulation symbols can be uniformly mapped on a QPSK constellation are set to the initial values. If bit sequences '00', '01', '11', and '10' are reversely sorted (this is because an LSB is first output in the gold sequence) and mapping is repeated only up to 31 bits, a resultant value is '1111000011110000111100001111000'. Table 8 shows a peak value and a PAPR according to the number of RBs and initial values of the first LFSR when the initial values of the first LFSR is '1111000011110000111100001111000'. The PAPR is significantly decreased in comparison with the result of Table 2.

[Table 8]

# of RB	MSB	LSB	Peak value	PAPR
6	000000000000000	00000011110010000	0.95	1.69
12	000000000000000	01110010110011100	1.16	2.07
25	000000000000000	01110001110001110	1.77	3.02
50	000000000000000	01100010011001001	1.86	3.18
100	000000000000000	10010111111011000	1.74	2.97

[0066] In another embodiment, the initial values of the first LFSR can be set to 1's complements of the initial values of the second LFSR. FIG. 13 shows an example where the initial values of the first LFSR are set to 1's complements of the initial values of the second LFSR. Even if the initial values of the second LFSR of the gold sequence generator are set to '0', the initial values of the first LFSR are all set to 1's complements of the initial values of the second LFSR. Accordingly, a sequence having a more random property can be generated, and thus deterioration of the PAPR property can be prevented. Table 9 shows a result when the initial values of the first LFSR are set to 1's complements of the initial values of the second LFSR.

[Table 9]

# of RB	MSB	LSB	Peak value	PAPR
6	0000000000000000	00000000000001000	0.97	1.72
12	0000000000000000	00010001010101010	1.27	2.26
25	0000000000000000	00010101010101010	2.22	3.78
50	0000000000000000	01110001110001110	2.98	5.08
100	0000000000000000	00010100100000110	3.91	6.68

[0067] Meanwhile, to distinguish a reference signal between cells or between UEs, the reference signal has to have a good correlation property. As described with reference to FIG. 11, in the initial values of the gold sequence generator, if only a cell ID differs and other values (i.e., a subframe number and an OFDM symbol number) are identical, a generated pseudo-random sequence may equally overlap in some periods. This occurs because only values of 9 bits of the initial values are different among 31 bits of the initial values. This problem may be solved by considering a fact that only a portion of a sequence generated as a reference signal is used. This is because, even if a pseudo-random sequence having a length of M_{\max} (this sequence is referred to as a basic sequence) is generated, a sequence having a length of M (this sequence is referred to as a used sequence) is used according to the number of RBs. Thus, if the used sequence is selected at different offsets from basic sequences generated according to the cell ID, it is possible to solve a problem in that the sequence overlaps in a portion of period due to almost identical initial values.

[0068] Now, a method of setting an offset of a sequence according to a cell ID will be described.

[0069] It is assumed that a basic sequence having a length of M_{\max} , i.e., a basic sequence $c(i)$ ($i=0,1,\dots, M_{\max}-1$), is generated by the gold sequence generator, and then a used sequence having a length of M is used. In this case, $M \leq M_{\max}$. An offset of the used sequence, i.e., a start point of the used sequence, is set differently according to the cell ID.

[0070] FIG. 14 shows that an offset of an available sequence varies according to a cell ID. Herein, an offset is placed with a spacing of N in a basic sequence having a length of M_{\max} according to the cell ID, and a used sequence having a length of M is selected. The used sequence is cyclic shifted when exceeding a range of the basic sequence. From the basic sequence $c(i)$ ($i=0,1,\dots, M_{\max}-1$), a used sequence $cu(i)$ ($i=0,1,\dots, M-1$) can be expressed as shown:

【Equation 2】

$$cu(i) = c((i + N \cdot N_{ID}^{\text{cell}}) \bmod (M_{\max} - 1))$$

where 'mod' is a modulo operation, N is an offset interval, and N_{ID}^{cell} is a cell ID. Although the same offset is defined for each cell ID herein, this is for exemplary purposes only, and thus the offset may be defined differently for each cell ID.

[0071] By varying a start point of the used sequence according to the cell ID, the used sequence may vary even if initial values are similar. Therefore, a random property can be guaranteed, and the PAPR property can be prevented from deterioration.

[0072] Equation 2 above can be expressed in a format of a reference signal for the 3GPP LTE system in which resources are allocated in an RB unit, which is shown in the following equation.

【Equation 3】

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m + 1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

$$a_{k,l}^{(p)} = r_{l,n_s}(m')$$

$$m = 0, 1, \dots, 2 \cdot N_{RB}^{DL} - 1$$

$$m' = (m + N_{Interval}^{RS} N_{ID}^{cell}) \bmod (2 \cdot N_{RB}^{\max, DL} - 1)$$

[0073] Herein, n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot, r_{l,n_s} is a reference signal sequence, $N_{RB}^{\max, DL}$ is a maximum number of RBs, m is an index of the reference signal sequence, m' is an index for taking a portion of the reference signal sequence, N_{RB}^{DL} is the number of RBs in use, $\alpha_{k,l}(p)$ is modulation symbols used as a reference symbol for a p -th antenna port at a slot n_s , k is a subcarrier index used for transmission of a reference signal, and $N_{RS}^{interval}$ is an interval of a start point based on a cell ID N_{cell}^{ID} . $r_{l,n_s}(m)$ may be a basic sequence, and $r_{l,n_s}(m')$ may be a used sequence.

[0074] FIG. 15 shows that a basic sequence in use is cyclic shifted according to a cell ID. A basic sequence having a length of M_{\max} (i.e., a basic sequence $c(i)$ ($i=0, 1, \dots, M_{\max}-1$)) is generated by the gold sequence generator. Thereafter, a cyclic shift amount N is determined according to the cell ID. Then, the basic sequence is cyclic shifted by the cyclic shift amount N . In this case, a start point of the used sequence may always be placed at the same position. From the basic sequence $c(i)$ ($i=0, 1, \dots, M_{\max}-1$), an used sequence $cu(i)$ ($i=0, 1, \dots, M-1$) can be expressed by the following equation:

【Equation 4】

$$c_{shift}((i + N \cdot N_{ID}^{cell}) \bmod (M_{\max} - 1)) = c(i)$$

$$cu(i) = c_{shift}(i)$$

where $c_{shift}(i)$ is a sequence obtained by cyclic shifting the basic sequence by the cyclic shift amount N .

[0075] Equation 4 above can be expressed in a format of a reference signal for the 3GPP LTE system in which resources are allocated in an RB unit, which is shown in the following equation.

【Equation 5】

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

$$a_{k,l}^{(p)} = r_{l,n_s}(m')$$

$$m = 0, 1, \dots, 2 \cdot N_{RB}^{DL} - 1$$

$$m' = (m + N_{Interval}^{RS} N_{ID}^{cell} + N_{RB}^{\max, DL} - N_{RB}^{DL}) \bmod (2 \cdot N_{RB}^{\max, DL} - 1)$$

【0076】 In another embodiment, when a pseudo-random sequence is generated by the gold sequence generator, some sequences generated initially can be excluded. A sequence having a length of N_c may be removed from an initially generated gold sequence, and a subsequence sequence may be used as a reference signal sequence. Initial values have a great effect on the initially generated sequences, and thus PAPR property deterioration caused by similar initial values can be avoided. This can be expressed by the following equation.

【Equation 6】

$$c'(i) = c(i + N_c)$$

【0077】 Equation 6 above can be expressed in a form of Equation 1 above, which is shown in the following equation.

【Equation 7】

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

$$y(i + 31) = (y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

【0078】 A value N_c may be set to a length which is generated sufficiently randomly so that a generated pseudo-random sequence is not affected by initial values. For example, the value N_c may range from 1500 to 1800.

【0079】 Equation 7 above can be expressed in a format of a reference signal for the 3GPP LTE system in which resources are allocated in an RB unit by using the pseudo-random sequence $c(i)$, which is shown in the following equation.

【Equation 8】

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

$$a_{k,l}^{(p)} = r_{l,n_s}(m')$$

$$m = 0, 1, \dots, 2 \cdot N_{RB}^{DL} - 1$$

$$m' = m + N_{RB}^{\max, DL} - N_{RB}^{DL}$$

【0080】 Now, the cross-correlation property between generated pseudo-random sequences is described.

【0081】 A pseudo-random sequence $G(D)$ generated using two m-sequences $X(D)$ and $Y(D)$ is expressed by the following polynomial form.

【Equation 9】

$$G(D) = c_0 + c_1 D + c_2 D^2 + \dots$$

$$G(D) = X(D) \oplus Y(D)$$

【0082】 Herein, a first m-sequence $X(D)$ is $l_1(D)/g_1(D)$, and a second m-sequence $Y(D)$ is $l_2(D)/g_2(D)$. $g_1(D)$ and $g_2(D)$ are primitive polynomials for generating $X(D)$ and $Y(D)$, and are defined as follows.

【Equation 10】

$$g_1(D) = 1 + D^{-3} + D^{-31}$$

$$g_2(D) = 1 + D^{-1} + D^{-2} + D^{-3} + D^{-31}$$

【0083】 $l_1(D)$ and $l_2(D)$ are initial values for generating $X(D)$ and $Y(D)$, and are defined by the following equation.

【Equation 11】

$$I_1(D) = 1$$

$$I_2(D) = I(\text{CELLID}) \oplus I(N_{sf})D^9$$

【0084】 Herein, $I(\text{CELLID})$ is an initial value according to a cell ID CELLID, and $I(N_{sf})D^9$ is an initial value according to a slot number and an OFDM symbol number.

[0085] In a synchronous environment where timing is identical between multiple cells, neighboring cells have the same slot number and the same OFDM symbol number. If it is assumed that the same slot number and the same OFDM symbol number are used, a cross-correlation between pseudo-random sequences generated in two neighboring cells having different cell IDs CELLID1 and CELLID2 is obtained by the following equation.

【Equation 12】

$$\begin{aligned}
 G_1(D) \oplus G_2(D) &= X(D) \oplus Y_1(D) \oplus X(D) \oplus Y_2(D) \\
 &= Y_1(D) \oplus Y_2(D) \\
 &= I_{2,cell1}(D)/g(D) \oplus I_{2,cell2}(D)/g(D) \\
 &= [I(CELLID1) \oplus I(N_{sf})D^9]/g(D) \oplus [I(CELLID2) \oplus I(N_{sf})D^9]/g(D) \\
 &= I(CELLID1)/g(D) \oplus I(N_{sf})D^9/g(D) \oplus I(CELLID2)/g(D) \oplus I(N_{sf})D^9/g(D) \\
 &= I(CELLID1)/g(D) \oplus I(CELLID2)/g(D)
 \end{aligned}$$

[0086] The above equation shows that the cross-correlation property is determined only by the cell ID. Since there is no change in the cross-correlation property between cells according to changes in the slot number and the OFDM symbol number, it may be difficult to obtain a sequence having a good cross-correlation property in this method.

[0087] When modulated sequences consisting of modulation symbols obtained by performing QPSK modulation on generated pseudo-random sequences are denoted as R1[n] and R2[n] for two cells, respectively, the modulated sequences can be expressed by the following equation:

【Equation 13】

$$\begin{aligned}
 R1[n] &= S[2n]X1[2n] + jS[2n+1]X1[2n+1] \\
 R2[n] &= S[2n]X2[2n] + jS[2n+1]X2[2n+1]
 \end{aligned}$$

where S[n] is a cell common sequence depending on a subframe number and an OFDM symbol number, and X1[n] and X2[n] are cell specific sequences obtained from each cell ID. A cross-correlation for the above sequences R1[n] and R2[n] can be obtained by the following equation:

【Equation 14】

$$\begin{aligned}
 R1[n]R2[n]^* &= (S[2n]X1[2n] + jS[2n+1]X1[2n+1])(S[2n]X2[2n] + jS[2n+1]X2[2n+1])^* \\
 &= X1[2n]X2[2n]^* + X1[2n+1]X2[2n+1]^* + j(S[2n+1]X1[2n+1]S[2n]^* X2[2n]^* \\
 &\quad - S[2n+1]X2[2n+1]S[2n]^* X1[2n]^*)
 \end{aligned}$$

where () * denotes a complex conjugate. A cross-correlation result of the two modulated sequences R1[n] and R2[n] shows that a cell common sequence component that varies by a subframe number and an OFDM symbol number exists without alteration in a Q-axis whereas the cell common sequence component is removed in an I-axis. Therefore, it is difficult to obtain a good cross-correlation property between cells.

[0088] Accordingly, a method is proposed to improve the cross-correlation property between generated pseudo-random sequences.

[0089] In one embodiment, a start point of a used sequence can be changed according to a subframe number and/or an OFDM symbol number. FIG. 16 shows that the start point of the used sequence is changed according to the subframe

number and/or the OFDM symbol number. A long pseudo-random sequence is generated according to each cell ID. A plurality of basic sequences, each having a length of M_{\max} , capable of supporting a maximum number of RBs are obtained from the long pseudo-random sequence according to the subframe number and the OFDM symbol number. A used sequence having a length of M , which is used for transmission of an actual reference signal, is obtained from a basic sequence. Accordingly, the cross-correlation property of a reference signal between cells can be improved.

[0090] The reference sequence can be expressed in a format of a reference signal for the 3GPP LTE system in which resources are allocated in an RB unit, which is shown in the following equation:

【Equation 15】

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m + l')) + j \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m + 1 + l')) ,$$

$$l' = 4N_{\text{RB}}^{\text{max,DL}} \cdot (N_{\text{symb}}^{\text{DL}} \cdot n_s + l) \quad \text{and} \quad m = 0, 1, \dots, 2N_{\text{RB}}^{\text{max,DL}} - 1$$

where n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot, r_{l,n_s} is a reference signal sequence, $N_{\text{RB}}^{\text{max,DL}}$ is a maximum number of RBs, m is an index of the reference signal sequence, and $N_{\text{symb}}^{\text{DL}}$ is the number of OFDM symbols included in a slot. A basic sequence $c(i)$ generated by the gold sequence generator is initialized with $N_{\text{ID}}^{\text{cell}} + 1$ at the start of each OFDM symbol.

[0091] In another embodiment, initial values used in generation of a basic sequence can be changed to improve the cross-correlation property. If a subframe number and/or an OFDM symbol number are identical in a synchronous environment where timing is identical between multiple cells, the initial values depending on the subframe number and/or the OFDM symbol number are similar between cells, which may result in a poor correlation property. In addition, in an asynchronous environment, a transmit time difference between neighboring cells needs to be taken into consideration so that the initial values are not contiguously identical.

[0092] The initial values may vary differently according to changes in the subframe number and/or the OFDM symbol number between cells. For example, a first cell may be configured so that an initial value is increased or decreased as the number of OFDM symbol number is increased, and a second cell may also be configured so that an initial value is increased or decreased as the OFDM symbol number is increased. For example, a cell having a cell ID of CELLID1 is configured so that an initial value is increased by n as the OFDM symbol number is increased by 1. In addition, a cell having a cell ID of CELLID2 is configured so that an initial value is increased by $n+1$ as the OFDM symbol number is increased by 1.

[0093] The OFDM symbol number may be extended in a radio frame unit instead of existing within a subframe or a slot, so that changes of initialization are different as the OFDM symbol number varies. If N_{symb} OFDM symbols exist for each subframe, a q -th OFDM symbol number of a k -th subframe of a radio frame can be expressed by $k \cdot N_{\text{symb}} + q$.

[0094] In a system in which the number of OFDM symbols included in each subframe varies, a maximum number $N_{\text{symb,max}}$ of OFDM symbols for each subframe can be defined. In this case, the q -th OFDM symbol number of the k -th subframe of the radio frame can be expressed by $k \cdot N_{\text{symb,max}} + q$. The reason above is to allow each OFDM symbol to have a unique OFDM symbol number in one radio frame.

[0095] The gold sequence generator may increase or decrease an initial value of an m -sequence by a predetermined interval as the OFDM symbol number is increased. For example, a cell having a cell ID of CELLID1 is allowed to increase an initial value by a predetermined value such as CELLID1 or CELLID1+1 as the OFDM symbol number is increased by 1. In addition, a cell having a cell ID of CELLID2 is allowed to increase an initial value by a predetermined value such as CELLID2 or CELLID2+1 as the OFDM symbol number is increased by 1. However, this may be problematic when a cell ID between cells has a difference of about two times. For example, if CELLID1=5, CELLID2=11 and the predetermined values are CELLID1+1 and CELLID2+1 respectively, then initial values increased as the OFDM symbol number is increased are respectively 6 and 12, which shows a difference of two times. This can be expressed in a binary format in which one bit is shifted. This is because 6 is '0110' in a binary format, and 12 is '1100' in a binary format. When one bit is shifted, the cross-correlation property deteriorates in case of using QPSK modulation due to overlapping between an I-axis component of a reference signal of a first cell and a Q-axis component of a reference signal of a second cell.

[0096] Therefore, as the OFDM symbol number and/or the subframe number are increased, there is a need to set the initial values such that an increment of one cell is not two times an increment of another cell. This can be easily implemented

by allowing the initial value to be increased or decreased in odd multiples as the OFDM symbol number and/or the subframe number are increased. For example, an initial value of the gold sequence generator having a cell ID of n is allowed to be increased or decreased by $(2n+1)$ times as the OFDM symbol number is increased or decreased.

[0097] This can be expressed in a format of a reference signal for the 3GPP LTE system in which resources are allocated in an RB unit, which is shown in the following equation.

【Equation 16】

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

[0098] Herein, n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot, r_{l,n_s} is a reference signal sequence, and $N_{RB}^{\max, DL}$ is a maximum number of RBs. In this case, the sequence generator can be initialized by the following equation:

【Equation 17】

$$c_{init} = 2^9 \cdot (l' + 1) \cdot (2 \cdot N_{ID}^{cell} + 1) + N_{ID}^{cell}$$

where l' is defined as $8n_s + l$ and is an OFDM symbol number within a radio frame.

[0099] Meanwhile, a cross-correlation between pseudo-random sequences depends on a binary addition result of initial values used to generate two pseudo-random sequences, which is shown in the following equation.

【Equation 18】

$$\begin{aligned} G_1(D) \oplus G_2(D) &= X(D) \oplus Y_1(D) \oplus X(D) \oplus Y_2(D) \\ &= Y_1(D) \oplus Y_2(D) \\ &= I_{2,cell1}(D) / g(D) \oplus I_{2,cell2}(D) / g(D) \\ &= (I_{2,cell1}(D) \oplus I_{2,cell2}(D)) / g(D) \end{aligned}$$

[0100] Therefore, if the pseudo-random sequences are generated by varying the initial values according to each OFDM symbol number, a good cross-correlation property is obtained when the binary addition result of the initial values of the respective cells varies as the OFDM symbol number varies. This implies that an initial value $c_{init}(n_1, l)$ of a first cell and an initial value $c_{init}(n_2, l)$ of a second cell vary as the OFDM symbol number l varies. Herein, n_1 is a cell ID of the first cell, and n_2 is a cell ID of the second cell. In addition, in consideration of QPSK modulation, the good cross-correlation property can be obtained when $(2 \cdot c_{init}(n_1, l)) \oplus c_{init}(n_2, l)$ and $c_{init}(n_1, l) \oplus (2 \cdot c_{init}(n_2, l))$ vary according to the OFDM symbol number l .

[0101] FIG. 17 shows setting of initial values of a gold sequence generator. 31 bits of initial values of the second LFSR are divided into two regions (i.e., a region #1 and a region #2). Each region consists of 14 bits. The region #2 is positioned in an LSB side. Any value can be set to the remaining 4 bits from an MSB. Each of the region #1 and the region #2 includes a binary sequence of a cell ID. In the region #1, the binary sequence of the cell ID is cyclic shifted by a first cyclic shift m_1 according to the OFDM symbol number l . In the region #2, the binary sequence of the cell ID is cyclic shifted by a second cyclic shift m_2 according to the OFDM symbol number l . For example, in the region #1, the binary sequence of the cell ID can be cyclic shifted by a cyclic shift $1m_1$, and in the region #2, the binary sequence of the cell ID can be cyclic shifted by a cyclic shift $1m_2$. By dividing the initial values into two regions and by including a binary

sequence of a cell ID for which a different cyclic shift is used for in each region, $c_{init}(n_1, l) \oplus c_{init}(n_2, l)$ is allowed to be changed according to the OFDM symbol number l .

[0102] If b_1 denotes a size of the region #1 and b_2 denotes a size of the region #2, then $b_1=b_2=14$. The sizes of the regions #1 and #2 can be arbitrarily defined within a range of the initial value. To increase a generation period of a gold sequence, b_1 and b_2 may be set to be relatively prime. In addition, m_1 and b_1 as well as m_2 and b_2 may also be set to be relatively prime.

[0103] This can be expressed in a format of a reference signal for the 3GPP LTE system in which resources are allocated in an RB unit, which is shown in the following equation:

【Equation 19】

$$r_{l, n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

where $c_{init} = 2^{14} \cdot CS_{13}(2N_{ID}^{\text{cell}} + 1, 11 \cdot l') + CS_{14}(2N_{ID}^{\text{cell}} + 1, 3 \cdot l')$ at the start of each OFDM symbol,

$l' = 2 \cdot n_s + \lfloor (2 \cdot l) / N_{\text{sybm}}^{\text{DL}} \rfloor$, and $CS_b(M, a) = (2^{a \bmod b} \cdot M) \bmod 2^b + \lfloor (2^{a \bmod b} \cdot M) / 2^b \rfloor$. l' is an OFDM symbol number within a radio frame, $CS_b(M, a)$ is a cyclic shift function, and $\lfloor x \rfloor$ denotes a floor function which give a largest integer smaller than x .

[0104] Although it has been described that the proposed sequence is used for a downlink reference signal of the 3GPP LTE/LTE-A, the proposed sequence can also be used for an uplink reference signal. In addition, although PAPR and cross-correlation properties have been described for a reference signal between cells, these properties can also be equally used for a reference signal between UEs and/or between antennas.

[0105] A reference signal used for the proposed sequence may be either a cell common reference signal or a UE specific reference signal.

[0106] FIG. 18 is a flowchart showing a method of transmitting a reference signal according to an embodiment of the present invention. This method may be performed by a transmitter. The transmitter may a part of a BS when a downlink reference signal is transmitted, or may a part of a UE when an uplink reference signal is transmitted. In step S510, a reference signal sequence is generated. The reference signal sequence can be defined by the following equation.

【Equation 20】

$$r_{l, n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

[0107] Herein, n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot, r_{l, n_s} is a reference signal sequence, and $N_{RB}^{\max, DL}$ is a maximum number of RBs. The pseudo-random sequence $c(i)$ can be defined by

Equation 7 above. Herein, the m-sequence $x(i)$ can be initialized with initial values expressed by $x(0)=1$, $x(i)=0$, $i=1, 2, \dots, 30$, and the m-sequence $y(i)$ can be initialized with initial values obtained from $(2N_{ID}^{\text{cell}}+1)$, where N_{ID}^{cell} is a cell ID. The initial values of the m-sequence $y(i)$ varies as the OFDM symbol number l varies. Therefore, the initial values of the m-sequence $y(i)$ can be obtained from $1(2N_{ID}^{\text{cell}}+1)$.

[0108] In step S520, a portion or entirety of the reference signal sequence is mapped to at least one RB. One RB can include 12 subcarriers. In case of a cell common reference signal, two modulation symbols of the reference sequence can be mapped to two subcarriers within one RB. In case of a UE specific reference signal, three modulation symbols of the reference signal sequence can be mapped to three subcarriers within one RB.

[0109] In step S530, the reference signal is transmitted using the RB. A proposed reference signal sequence provides improved PAPR and cross-correlation properties. Therefore, transmit power efficiency of a transmitter can be increased,

and a receiver can be provided with higher detection performance.

[0110] FIG. 19 is a block diagram showing a transmitter and a receiver implementing for a method of transmitting and receiving a reference signal. A transmitter 800 includes a data processor 810, a reference signal generator 820, and a transmit circuitry 830. The data processor 810 processes an information bit to generate a transmit signal. The reference signal generator 820 generates a reference signal. The reference signal generation of FIG. 18 may be performed by the reference signal generator 820. The transmit circuitry 830 transmits the transmit signal and/or the reference signal.

[0111] A receiver 910 includes a data processor 910, a channel estimator 920, and a receive circuitry 930. The receive circuitry 930 receives a reference signal and a receive signal. The channel estimator 920 estimates a channel by using the received reference signal. The data processor 910 processes the receive signal by using the estimated channel.

[0112] Although a proposed sequence is used for a reference signal as an example in the aforementioned embodiment, the proposed sequence can be used for various signals. For example, the proposed sequence can be used for a scrambling code, a synchronous signal, a preamble, a masking code, etc. Based on the pseudo-random sequence $c(i)$ of Equation 7, a base sequence of Equation 20 may be generated. The m -sequence $y(i)$ for the pseudo-random sequence $c(i)$ may be initialized with initial values obtained from $(2N_{ID}^{cell}+1)$, where N_{ID}^{cell} is a cell ID. The base sequence may be applied with a target signal or a target code. To apply the base sequence with the target signal or the target code, a portion or entirety of the reference signal sequence may be used according to allocated resources or the length (or size) of the target signal or the target code. Applied sequence is transmitted. The transmitted sequence may be used as various applications by a receiver.

[0113] The present invention can be implemented with hardware, software, or combination thereof. In hardware implementation, the present invention can be implemented with one of an application specific integrated circuit (ASIC), a digital signal processor (DSP), a programmable logic device (PLD), a field programmable gate array (FPGA), a processor, a controller, a microprocessor, other electronic units, and combination thereof, which are designed to perform the aforementioned functions. In software implementation, the present invention can be implemented with a module for performing the aforementioned functions. Software is storable in a memory unit and executed by the processor. Various means widely known to those skilled in the art can be used as the memory unit or the processor.

[0114] While the present invention has been particularly shown and described with reference to exemplary embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the scope of the invention as defined by the appended claims. The exemplary embodiments should be considered in descriptive sense only and not for purposes of limitation. Therefore, the scope of the invention is defined not by the detailed description of the invention but by the appended claims, and all differences within the scope will be construed as being included in the present invention.

Claims

1. A method of transmitting a reference signal in a wireless communication system, the method comprising:

generating a reference signal sequence (S510) which is defined by

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{\max, DL} - 1$$

where n_s is a slot number within a radio frame, l is an orthogonal frequency division multiplexing, OFDM, symbol number within a slot and $N_{RB}^{\max, DL}$ is a maximum number of resource blocks, RBs, wherein a pseudo-random sequence $c(i)$ is generated by a gold sequence generator which is initialized with initial values obtained by using $(2N_{ID}^{cell} + 1)$, where N_{ID}^{cell} is a cell identifier; mapping a portion or entirety of the reference signal sequence to at least one RB (S520); and transmitting a reference signal (S530) in the at least one RB.

2. The method of claim 1, wherein the pseudo-random sequence $c(i)$ is defined by

$$c(i) = (x(i + Nc) + y(i + Nc)) \bmod 2$$

5

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

10

$$y(i + 31) = (y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

where $x(i)$ and $y(i)$ are m-sequences and Nc is a constant.

15

3. The method of claim 2, wherein the m-sequence $x(i)$ is initialized with $x(0)=1$, $x(i)=0$, $i=1,2,\dots,30$, and the m-sequence (y) is initialized with the initial values.

4. The method of claim 2, wherein the Nc is a value in range from 1500 to 1800.

20

5. The method of claim 1, wherein the initial values varies as the OFDM symbol number varies.

6. The method of claim 5, wherein the initial values are obtained by using $1 (2 N_{ID}^{cell} + 1)$.

7. The method of claim 1, wherein the size of the initial values is 31 bits.

25

8. The method of claim 1, wherein one RB comprises 12 subcarriers in frequency domain.

9. The method of claim 8, wherein two modulation symbols of the reference signal sequence are mapped to two subcarriers in one RB.

30

10. The method of claim 1, wherein the reference signal is a cell common reference signal or a user equipment (UE) specific reference signal.

11. A transmitter (800) comprising:

35

a reference signal generator (820) to generate a reference signal; and
a transmit circuitry (830) to transmit the reference signal,
wherein the reference signal generator generates the reference signal by
generating a reference signal sequence (S510) which is defined by

40

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

45

where n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot and $N_{RB}^{max,DL}$ is a maximum number of RBs,

wherein a pseudo-random sequence $c(i)$ is generated by a gold sequence generator which is initialized with

50

initial values obtained by using $(2 N_{ID}^{cell} + 1)$, where N_{ID}^{cell} is a cell identifier; and

mapping a portion or entirety of the reference signal sequence to at least one RB (S520).

12. The transmitter of claim 11, wherein the pseudo-random sequence $c(i)$ is defined by

55

$$c(i) = (x(i + Nc) + y(i + Nc)) \bmod 2$$

$$x(i+31) = (x(i+3) + x(i)) \bmod 2$$

5

$$y(i+31) = (y(i+3) + y(i+2) + y(i+1) + y(i)) \bmod 2$$

where $x(i)$ and $y(i)$ are m-sequences and N_c is a constant.

10

13. A receiver (900) comprising:

a receive circuitry (930) to receive a reference signal and a receive signal;
a channel estimator (920) to estimate a channel by using the reference signal; and
a data processor (910) to process the receive signal by using the channel,
wherein the reference signal is generated based on a reference signal sequence which is defined by

15

20

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

where n_s is a slot number within a radio frame, l is an OFDM symbol number within a slot and $N_{RB}^{max,DL}$ is a

25

maximum number of RBs,

wherein a pseudo-random sequence $c(i)$ is generated by a gold sequence generator which is initialized with
initial values obtained by using $(2 \cdot N_{ID}^{cell} + 1)$, where N_{ID}^{cell} is a cell identifier.

30

14. The receiver of claim 13, wherein the pseudo-random sequence $c(i)$ is defined by

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

35

$$x(i+31) = (x(i+3) + x(i)) \bmod 2$$

40

$$y(i+31) = (y(i+3) + y(i+2) + y(i+1) + y(i)) \bmod 2$$

where $x(i)$ and $y(i)$ are m-sequences and N_c is a constant.

45

Patentansprüche

1. Verfahren zum Übertragen eines Referenzsignals in einem drahtlosen Kommunikationssystem, wobei das Verfahren aufweist:

50

Erzeugen einer Referenzsignalfolge (S510), die definiert ist durch:

55

$$r_{l,n_s} = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m+1)), \quad m = 0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

wobei n_s eine Schlitznummer innerhalb eines Funkrahmens ist, l eine orthogonale Frequenzteilungsmultiplex-,

OFDM-, Symbolnummer innerhalb eines Schlitzes ist, und $N_{RB}^{max,DL}$ eine maximale Anzahl von Ressourcenblöcken, RBs, ist,
wobei durch einen Goldfolgengenerator, der mit Anfangswerten initialisiert wird, die unter Verwendung von
 $(2N_{ID}^{Zelle} + 1)$ erhalten werden, eine pseudozufällige Folge $c(i)$ erzeugt wird, wobei N_{ID}^{Zelle} eine Zellenkennung ist;
Abbilden eines Abschnitts oder der Gesamtheit der Referenzsignalfolge auf wenigstens einen RB (S520); und
Übertragen eines Referenzsignals (S530) in dem wenigstens einen RB.

2. Verfahren nach Anspruch 1, wobei die pseudozufällige Folge $c(i)$ definiert ist durch:

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

$$y(i + 31) = y(y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

wobei $x(i)$ und $y(i)$ m-Folgen sind und N_c eine Konstante ist.

3. Verfahren nach Anspruch 2, wobei die m-Folge $x(i)$ mit $x(0) = 1$ initialisiert wird, $x(i) = 0$, $i = 1, 2, \dots, 30$, und die m-Folge (y) mit den Anfangswerten initialisiert wird.
4. Verfahren nach Anspruch 2, wobei N_c ein Wert im Bereich von 1500 bis 1800 ist.
5. Verfahren nach Anspruch 1, wobei die Anfangswerte sich ändern, wenn die OFDM-Symbolnummer sich ändert.
6. Verfahren nach Anspruch 5, wobei die Anfangswerte unter Verwendung von $(2N_{ID}^{Zelle} + 1)$ erhalten werden.
7. Verfahren nach Anspruch 1, wobei die Größe der Anfangswerte 31 Bit beträgt.
8. Verfahren nach Anspruch 1, wobei ein RB 12 Subträger in der Frequenzdomäne aufweist.
9. Verfahren nach Anspruch 8, wobei zwei Modulationssymbole der Referenzsignalfolge auf zwei Subträger in einem RB abgebildet werden.
10. Verfahren nach Anspruch 1, wobei das Referenzsignal ein zellengemeinsames Referenzsignal oder ein Benutzergerät- (UE-) spezifisches Referenzsignal ist.

11. Sender (800), der aufweist:

einen Referenzsignalgenerator (820), um ein Referenzsignal zu erzeugen; und
eine Sendeschaltungsanordnung (830), um das Referenzsignal zu senden,
wobei der Referenzsignalgenerator das Referenzsignal erzeugt durch:

$$r_{l,n_s} = \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m + 1)), \quad m = 0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

wobei n_s eine Schlitznummer innerhalb eines Funkrahmens ist, l eine orthogonale Frequenzteilungsmultiplex-, OFDM-, Symbolnummer innerhalb eines Schlitzes ist, und $N_{RB}^{max,DL}$ eine maximale Anzahl von Ressourcenblöcken RBs ist,
 wobei durch einen Goldfolgengenerator, der mit Anfangswerten initialisiert wird, die unter Verwendung von $(2N_{ID}^{Zelle} + 1)$ erhalten werden, eine pseudozufällige Folge $c(i)$ erzeugt wird, wobei N_{ID}^{Zelle} eine Zellenkennung ist; und
 Abbilden eines Abschnitts oder der Gesamtheit der Referenzsignalfolge auf wenigstens einen RB (S520).

12. Sender nach Anspruch 11, wobei die pseudozufällige Folge $c(i)$ definiert ist durch:

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

$$y(i + 31) = y(y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

wobei $x(i)$ und $y(i)$ m-Folgen sind und N_c eine Konstante ist.

13. Empfänger (900), der aufweist:

eine Empfangsschaltungsanordnung (930), um ein Referenzsignal und ein Empfangssignal zu empfangen;
 eine Kanalschätzeinrichtung (920), um unter Verwendung des Referenzsignals einen Kanal zu schätzen; und
 eine Datenverarbeitungseinrichtung (910), um das Empfangssignal unter Verwendung des Kanals zu empfangen,
 wobei das Referenzsignal basierend auf der Referenzsignalfolge erzeugt wird, die definiert ist durch

$$r_{l,n_s} = \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m + 1)), \quad m = 0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

wobei n_s eine Schlitznummer innerhalb eines Funkrahmens ist, l eine orthogonale Frequenzteilungsmultiplex-, OFDM-, Symbolnummer innerhalb eines Schlitzes ist, und $N_{RB}^{max,DL}$ eine maximale Anzahl von Ressourcenblöcken RBs ist,
 wobei durch einen Goldfolgengenerator, der mit Anfangswerten initialisiert wird, die unter Verwendung von $(2N_{ID}^{Zelle} + 1)$ erhalten werden, eine pseudozufällige Folge $c(i)$ erzeugt wird, wobei N_{ID}^{Zelle} eine Zellenkennung ist.

14. Empfänger nach Anspruch 13, wobei die pseudozufällige Folge $c(i)$ definiert ist durch:

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

5

$$y(i + 31) = y(y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

wobei $x(i)$ und $y(i)$ m-Folgen sind und N_c eine Konstante ist.

10 Revendications

1. Procédé de transmission d'un signal de référence dans un système de communication sans fil, le procédé comprenant :

15

la génération d'une séquence de signaux de référence (S510) qui est définie par

20

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m + 1)), m=0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

25

où n_s est un numéro d'intervalle à l'intérieur d'une trame radio, l est un numéro de symbole de multiplexage par répartition de fréquence orthogonale, OFDM, à l'intérieur d'un intervalle et $N_{RB}^{max,DL}$ est un nombre maximum de blocs de ressources, RB, dans lequel une séquence pseudo-aléatoire $c(i)$ est générée par un générateur de séquence Gold qui est initialisé avec des valeurs initiales obtenues en utilisant $(2N_{ID}^{cell} + 1)$, où N_{ID}^{cell} est un identifiant de cellule ;
le mappage d'une portion ou de l'intégralité de la séquence de signaux de référence sur au moins un RB (S520) ;
et
la transmission d'un signal de référence (S530) dans l'au moins un RB.

30

2. Procédé selon la revendication 1, dans lequel la séquence pseudo-aléatoire $c(i)$ est définie par :

35

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

40

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

45

$$y(i + 31) = (y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

où $x(i)$ et $y(i)$ sont des m-séquences et N_c est une constante.

50

3. Procédé selon la revendication 2, dans lequel la m-séquence $x(i)$ est initialisée avec $x(0)=1$, $x(i)=0$, $i=1, 2, \dots, 30$, et la m-séquence (y) est initialisée avec les valeurs initiales.
4. Procédé selon la revendication 2, dans lequel N_c est une valeur dans la plage de 1500 à 1800.
5. Procédé selon la revendication 1, dans lequel les valeurs initiales varient en fonction de la variation du numéro de symbole OFDM.
- 6.

55

Procédé selon la revendication 5, dans lequel les valeurs initiales sont obtenues en utilisant $1 (2N_{ID}^{cell} + 1)$.

7. Procédé selon la revendication 1, dans lequel la taille des valeurs initiales est de 31 bits.

8. Procédé selon la revendication 1, dans lequel un RB comprend 12 sous-porteuses dans le domaine de fréquence.

9. Procédé selon la revendication 8, dans lequel deux symboles de modulation de la séquence de signaux de référence sont mappés sur deux sous-porteuses dans un RB.

10. Procédé selon la revendication 1, dans lequel le signal de référence est un signal de référence commun de cellule ou un signal de référence spécifique à un équipement utilisateur, UE.

11. Emetteur (800) comprenant :

un générateur de signal de référence (820) pour générer un signal de référence ; et
une circuiterie de transmission (830) pour transmettre le signal de référence,
dans lequel le générateur de signal de référence génère le signal de référence par :

la génération d'une séquence de signaux de référence (S510) qui est définie par

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}} (1 - 2 \cdot c(2m + 1)), m=0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

où n_s est un numéro d'intervalle à l'intérieur d'une trame radio, l est un numéro de symbole OFDM à l'intérieur d'un intervalle et $N_{RB}^{max,DL}$ est un nombre maximum de RBs,

dans lequel une séquence pseudo-aléatoire $c(i)$ est générée par un générateur de séquence Gold qui est initialisé avec des valeurs initiales obtenues en utilisant

$(2N_{ID}^{cell} + 1)$, où N_{ID}^{cell} est un identifiant de cellule ; et

le mappage d'une portion ou de l'intégralité de la séquence de signaux de référence sur au moins un RB (S520).

12. Emetteur selon la revendication 11, dans lequel la séquence pseudo-aléatoire $c(i)$ est définie par :

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

$$y(i + 31) = (y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

où $x(i)$ et $y(i)$ sont des m-séquences et N_c est une constante.

13. Récepteur (900) comprenant :

une circuiterie de réception (930) pour recevoir un signal de référence et un signal de réception ;
un estimateur de canal (920) pour estimer un canal en utilisant le signal de référence ; et
un processeur de données (910) pour traiter le signal de réception en utilisant le canal, dans lequel le signal de référence est généré sur la base d'une séquence de signaux de référence qui est définie par :

$$r_{l,n_s}(m) = \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m)) + j \frac{1}{\sqrt{2}}(1 - 2 \cdot c(2m + 1)), m=0, 1, \dots, 2N_{RB}^{max,DL} - 1$$

5

où n_s est un numéro d'intervalle à l'intérieur d'une trame radio, l est un numéro de symbole OFDM à l'intérieur d'un intervalle et $N_{RB}^{max,DL}$ est un nombre maximum de RBs,

10

dans lequel une séquence pseudo-aléatoire $c(i)$ est générée par un générateur de séquence Gold qui est initialisé avec des valeurs initiales obtenues en utilisant $(2N_{ID}^{cell} + 1)$, où N_{ID}^{cell} est un identifiant de cellule.

14. Récepteur selon la revendication 13, dans lequel la séquence pseudo-aléatoire $c(i)$ est définie par :

15

$$c(i) = (x(i + N_c) + y(i + N_c)) \bmod 2$$

20

$$x(i + 31) = (x(i + 3) + x(i)) \bmod 2$$

25

$$y(i + 31) = (y(i + 3) + y(i + 2) + y(i + 1) + y(i)) \bmod 2$$

où $x(i)$ et $y(i)$ sont des m-séquences et N_c est une constante.

30

35

40

45

50

55

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18





FIG. 19



REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Non-patent literature cited in the description

- Update of uplink reference-signal hopping, downlink reference signals, scrambling sequences, DwPTS/UpPTS lengths for TDD and control channel processing, 36.211, CR0003, R1-081161. 3GPP TSG-RAN WG1, Meeting #52, 11 February 2008
[0007]