



(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
18.07.2018 Bulletin 2018/29

(51) Int Cl.:
H04B 5/00 (2006.01)

(21) Application number: **18000014.3**

(22) Date of filing: **08.01.2018**

(84) Designated Contracting States:
AL AT BE BG CH CY CZ DE DK EE ES FI FR GB GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL PT RO RS SE SI SK SM TR
Designated Extension States:
BA ME
Designated Validation States:
MA MD TN

(72) Inventors:
• **Yukimasa, Koji**
Tokyo (JP)
• **Eguchi, Tadashi**
Tokyo (JP)
• **Asai, Hitoshi**
Tokyo (JP)

(30) Priority: **11.01.2017 JP 2017002712**
24.11.2017 JP 2017225480

(74) Representative: **WESER & Kollegen**
Radeckestraße 43
81245 München (DE)


(71) Applicant: **CANON KABUSHIKI KAISHA**
Tokyo (JP)

(54) **WIRELESS COMMUNICATION SYSTEM, COMMUNICATION APPARATUS, AND COMMUNICATION METHOD**

(57) A wireless communication system includes a first communication apparatus including a first antenna and a second antenna, a second communication apparatus including a third antenna and a fourth antenna, a first communication control unit configured to control wireless communication based on electric field coupling or magnetic field coupling between the first antenna and the third antenna, and a second communication control unit configured to control wireless communication based

on electric field coupling or magnetic field coupling between the second antenna and the fourth antenna. The first antenna, the second antenna, the third antenna, and the fourth antenna are positioned in such a manner that an electric signal transmitted from the first antenna and received by the second antenna has weaker strength than strength of an electric signal transmitted from the first antenna and received by the third antenna.

FIG.1



Description**BACKGROUND OF THE INVENTION****Field of the Invention**

[0001] The present invention relates to a wireless communication system.

Description of the Related Art

[0002] In recent years, there has been proposed a near-field wireless communication system carrying out communication based on electromagnetic field coupling between a pair of antennas placed in proximity to each other. Japanese Patent Application Laid-Open No. 2009-268022 discusses a method for transmitting an electric signal without modulating it according to the baseband method in the wireless communication based on the electromagnetic field coupling, thereby realizing high-speed and low-delay communication with a simple circuit configuration.

[0003] However, in recent years, a data amount that should be communicated has been increasing, and realization of further high-speed communication in the wireless communication system has been demanded.

SUMMARY OF THE INVENTION

[0004] According to a first aspect of the present invention, there is provided a wireless communication system as specified in claims 1 to 20.

[0005] Further features of the present invention will become apparent from the following description of exemplary embodiments with reference to the attached drawings.

BRIEF DESCRIPTION OF THE DRAWINGS**[0006]**

Fig. 1 is a block diagram illustrating a system configuration of a wireless communication system 100. Figs. 2A and 2B illustrate a configuration example of couplers in the wireless communication system 100.

Figs. 3A, 3B, 3C, 3D, 3E, and 3F illustrate electric signals communicated in the wireless communication system 100.

Fig. 4 illustrates a system configuration of a wireless communication system 400.

Fig. 5 is a block diagram illustrating a system configuration of a wireless communication system 500.

Fig. 6 is a block diagram illustrating a system configuration of a wireless communication system 600.

Figs. 7A, 7B, 7C, 7D, 7E, and 7F illustrate interference of the electric signals communicated in the wireless communication system 100.

Figs. 8A and 8B illustrate a configuration example of the wireless communication system 100 for preventing or reducing the interference of the electric signals.

Figs. 9A, 9B, 9C, and 9D illustrate a configuration example of the wireless communication system 100 for preventing or reducing the interference of the electric signals.

Figs. 10A and 10B illustrate a configuration example of the wireless communication system 100 including parallelly movable couplers.

Figs. 11A, 11B, and 11C illustrate a configuration example of the wireless communication system 100 including rotatably movable couplers.

Figs. 12A, 12B, and 12C illustrate examples of structures of the couplers.

Figs. 13A, 13B, and 13C illustrate a configuration example of the wireless communication system 100 for preventing or reducing the interference of the electric signals with use of a shield conductor.

Figs. 14A, 14B, and 14C illustrate a configuration example of the wireless communication system 100 for preventing or reducing the interference of the electric signals with use of a shield conductor having a slit.

Figs. 15A and 15B illustrate another configuration example of the wireless communication system 100 including the parallelly movable couplers.

Figs. 16A, 16B, and 16C illustrate another configuration example of the wireless communication system 100 including the rotatably movable couplers.

Figs. 17A and 17B illustrate another configuration example of the wireless communication system 100 including the rotatably movable couplers.

Figs. 18A and 18B illustrate another configuration example of the wireless communication system 100 including the rotatably movable couplers.

Figs. 19A, 19B, and 19C illustrate a simulation result regarding the interference of the electric signals in the wireless communication system 100 including the rotationally movable couplers.

Figs. 20A, 20B, and 20C illustrate a simulation result regarding the interference of the electric signals in the wireless communication system 100 including the rotationally movable couplers in a case where the shield conductor is used.

Figs. 21A, 21B, and 21C illustrate a simulation result regarding the interference of the electric signals in the wireless communication system 100 including the rotationally movable couplers in a case where the shield conductor having the slit is used.

DESCRIPTION OF THE EMBODIMENTS**<System Configuration>**

[0007] In the following description, an exemplary embodiment of the present invention will be described with

reference to the drawings. Fig. 1 illustrates a system configuration of a wireless communication system 100 (hereinafter referred to as a system 100) according to the present exemplary embodiment. The system 100 includes a communication apparatus 101, and a communication apparatus 102 that carries out wireless communication with the communication apparatus 101. The communication apparatus 101 includes a transmission circuit 103, a transmission coupler 104, a reception circuit 107, a reception coupler 108, and a control unit 111. Similarly, the communication apparatus 102 includes a reception circuit 105, a reception coupler 106, a transmission circuit 109, a transmission coupler 110, and a control unit 112. The communication apparatus 101 and the communication apparatus 102 may be a first portion and a second portion of a single apparatus.

[0008] In the present exemplary embodiment, the system 100 has a structure for supporting the communication apparatus 101 and the communication apparatus 102 so as to maintain a predetermined positional relationship therebetween (e.g., such a positional relationship that a distance between the couplers is kept substantially constant). More specifically, the communication apparatus 101 is a pan head portion of a network camera, and the communication apparatus 102 is an imaging portion of the network camera. Further, as another example, the communication apparatus 101 is a hand portion of a robot arm, and the communication apparatus 102 is an arm portion coupled with the hand portion. Further, as another example, the communication apparatus 101 is a print head portion of a printer, and the communication apparatus 102 is a main body portion of the printer. However, how the system 100 is applied is not limited to these examples.

[0009] The transmission coupler 104, the transmission coupler 110, the reception coupler 106, and the reception coupler 108 are each a plate-like conductor functioning as an antenna. However, the shapes of the couplers are not limited thereto. The transmission coupler 104 functions as an antenna for carrying out wireless communication based on electromagnetic field coupling with the reception coupler 106, and the transmission coupler 110 functions as an antenna for carrying out wireless communication based on electromagnetic field coupling with the reception coupler 108.

[0010] The electromagnetic field coupling according to the present exemplary embodiment includes both electric field coupling and magnetic field coupling. In other words, the wireless communication between the couplers may be carried out based on the electric field coupling, may be carried out based on the magnetic field coupling, or may be carried out based on both the electric field coupling and the magnetic field coupling. In Fig. 1, the communication apparatus 101 and the communication apparatus 102 each include the two couplers for transmission and reception, but at least any one of the communication apparatus 101 and the communication apparatus 102 may include three or more couplers.

[0011] The control unit 111 of the communication apparatus 101 controls the transmission circuit 103 to perform processing for transmitting data to the communication apparatus 102, and controls the reception circuit 107 to perform processing for receiving data from the communication apparatus 102. Similarly, the control unit 112 of the communication apparatus 102 controls the transmission circuit 109 to perform processing for transmitting the data to the communication apparatus 101, and controls the reception circuit 105 to perform processing for receiving the data from the communication apparatus 101. The control unit 111 may control a not-illustrated functional unit included in the communication apparatus 101 based on the data that the communication apparatus 101 receives by controlling the reception circuit 107. Similarly, the control unit 112 may control a not-illustrated functional unit included in the communication apparatus 102 based on the data that the communication apparatus 102 receives by controlling the reception circuit 105. Here, examples of the not-illustrated functional unit include a display control unit that causes an image based on the received data to be displayed on a display unit, and a transfer unit that transfers the received data to an external apparatus.

[0012] The transmission circuit 103 generates an electric signal based on the control by the control unit 111, and transmits the electric signal according to the baseband method, which transmits the electric signal without modulating it, from the transmission coupler 104 to the reception coupler 106. Similarly, the transmission circuit 109 generates an electric signal based on the control by the control unit 112, and transmits the electric signal according to the baseband method from the transmission coupler 110 to the reception coupler 108. The reception circuit 107 transmits the electric signal received by the reception coupler 108 to the control unit 111. Similarly, the reception circuit 105 transmits the electric signal received by the reception coupler 106 to the control unit 112.

[0013] Figs. 2A and 2B illustrate a configuration example of the transmission and reception couplers in the system 100. Fig. 2A is a perspective view of a part of the system 100, and Fig. 2B illustrates the part of the system 100 as viewed from an X-axis positive direction of a coordinate system 200 defined by an X axis, a Y axis, and a Z axis orthogonal to one another. The transmission coupler 104 and the reception coupler 108 are mounted on the same surface of a plate-like member included in the communication apparatus 101, and are positioned on substantially the same plane. Further, the transmission coupler 110 and the reception coupler 106 are mounted on the same surface of a plate-like member included in the communication apparatus 102, and are positioned on substantially the same plane.

[0014] The transmission coupler 104 and the reception coupler 106 are located in proximity to each other and positioned so as to face each other in an Z-axis direction. In other words, the transmission coupler 104 and the re-

ception 106 at least partially overlap each other when being viewed from the Z-axis direction. Similarly, the transmission coupler 110 and the reception coupler 108 are located in proximity to each other and positioned so as to face each other in the Z-axis direction. In such a configuration, the data transmission from the communication apparatus 101 to the communication apparatus 102 is realized by the transmission of the electric signal from the transmission coupler 104 to the reception coupler 106 in a Z-axis positive direction. Further, the data transmission from the communication apparatus 102 to the communication apparatus 101 is realized by the transmission of the electric signal from the transmission coupler 110 to the reception coupler 108 in a Z-axis negative direction.

[0015] In Figs. 2A and 2B, each of the couplers is illustrated as having a long side substantially in parallel with an X-axis direction, but the shape and the mounting direction of each of the couplers are not limited thereto and may be a different shape and a different direction as long as the corresponding transmission coupler and reception coupler can establish the electromagnetic field coupling therebetween. For example, the transmission coupler 110 and the reception coupler 108 may each have a long side substantially in parallel with a Y-axis direction, and the transmission coupler 104 and the reception coupler 106 may each have the long side substantially in parallel with the X-axis direction. Alternatively, the transmission coupler 110 and the reception coupler 106 may be arranged linearly in the X-axis direction, and the transmission coupler 104 and the reception coupler 108 may be arranged linearly in the X-axis direction. Further, the shape of the coupler may be a U-shape, an L-shape, or other shapes.

[0016] Figs. 3A to 3F illustrate examples of waveforms of the electric signals transmitted and received when the communication apparatus 101 and the communication apparatus 102 carry out the communication based on the electric field coupling. A horizontal axis in each of Figs. 3A to 3F indicates time. First, a first transmission signal illustrated in Fig. 3A that is generated by the transmission circuit 103 is input to the transmission coupler 104. The reception coupler 106 is coupled with the transmission coupler 104 by the electric field coupling, so that a first reception signal illustrated in Fig. 3B is generated at the reception coupler 106 according to the input of the first transmission signal to the transmission coupler 104. The reception circuit 105 performs conversion processing on this first reception signal to generate a first conversion-completed signal illustrated in Fig. 3C, which has a similar waveform to the first transmission signal. The conversion processing by the reception circuit 105 includes, for example, processing for converting a received analog signal into a digital signal by comparing this analog signal with a threshold value with use of a comparator. Transmission of a first electric signal from the communication apparatus 101 to the communication apparatus 102 is realized by the above-described process.

[0017] Transmission of a second electric signal from the communication apparatus 102 to the communication apparatus 101 is also realized by a similar process. More specifically, a second reception signal illustrated in Fig. 3E is generated at the reception coupler 108 according to an input of a second transmission signal illustrated in Fig. 3D, which is generated by the transmission circuit 109, to the transmission coupler 110. Then, the reception circuit 107 performs the conversion processing on this second reception signal to generate a second conversion-completed signal illustrated in Fig. 3F, which has a similar waveform to the second transmission signal.

[0018] In this manner, the provision of the transmission coupler and the reception coupler to each of the communication apparatus 101 and the communication apparatus 102 allows bidirectional communication to be carried out between the communication apparatus 101 and the communication apparatus 102. Further, the communication apparatus 101 can carry out the data transmission and the data reception with use of the different couplers for each of them asynchronously, and therefore can realize high-speed communication compared to, for example, alternately carrying out the transmission and the reception with use of a single coupler in a time-sharing manner.

[0019] Further, in the above description, the present exemplary embodiment has been described referring to the system 100 in which the communication apparatus 101 and the communication apparatus 102 carry out the bidirectional communication therebetween, but two or more pairs of couplers may be used for unidirectional communication. Fig. 4 illustrates a system configuration of a wireless communication system 400 (hereinafter referred to as a system 400) in which the unidirectional communication is carried out between a communication apparatus 401 and a communication apparatus 402. The communication apparatus 401 includes the transmission circuit 103, the transmission coupler 104, the transmission circuit 109, the transmission coupler 110, and the control unit 111. The communication apparatus 402 includes the reception circuit 105, the reception coupler 106, the reception circuit 107, the reception coupler 108, and the control unit 112. Details of each of the components of the communication apparatus 401 and the communication apparatus 402 are similar to each of the components identified by the same reference numerals in Fig. 1. However, the control unit 111 does not have to perform the data reception processing, and the control unit 112 does not have to perform the data transmission processing.

[0020] In the system 400, an electric signal is transmitted from the transmission coupler 104 of the communication apparatus 401 to the reception coupler 106 of the communication apparatus 402, and, further, an electric signal is transmitted from the transmission coupler 110 of the communication apparatus 401 to the reception coupler 108 of the communication apparatus 402. If the communication apparatus 401 transmits different electric

signals from the transmission coupler 104 and the transmission coupler 110 simultaneously, the system 400 allows a larger data amount to be transmitted per unit time than transmitting the electric signals from the single transmission coupler, thereby succeeding in realizing further high-speed communication.

[0021] On the other hand, if the communication apparatus 401 transmits the same electric signals from the transmission coupler 104 and the transmission coupler 110, even when the data transmission using one of the transmission couplers has failed due to an influence of noise or the like, the system 400 allows the data to be transmitted to the communication apparatus 402 with use of the other of the transmission couplers. By this effect, the system 400 can reduce processing for retransmitting the data, which would be performed, for example, according to the failure in the communication, thereby realizing further high-speed communication, compared to transmitting the electric signal from the single transmission coupler.

[0022] In Fig. 4, the communication apparatus 401 includes the two couplers for the transmission and the communication apparatus 402 includes the two couplers for the reception, but the communication apparatus 401 may include three or more couplers for the transmission and the communication apparatus 402 may include three or more couplers for the reception. Alternatively, the communication apparatus 401 may include two or more couplers for the transmission and one or more couplers for the reception, and the communication apparatus 402 may include one or more couplers for the transmission and two or more couplers for the reception.

[0023] Further, in Figs. 1 and 4, the present exemplary embodiment has been described referring to the system 100 and the system 400 in which the communication is carried out between the two communication apparatuses, but the communication may be carried out among three or more communication apparatuses. Fig. 5 illustrates a system configuration of a wireless communication system 500 (herein after referred to as a system 500), in which the communication is carried out among three communication apparatuses, i.e., a communication apparatus 501, a communication apparatus 502, and a communication apparatus 503. The communication apparatus 501 includes the transmission circuit 103, the transmission coupler 104, and the control unit 111. The communication apparatus 502 includes the reception circuit 105, the reception coupler 106, the transmission circuit 109, the transmission coupler 110, and the control unit 112. The communication apparatus 503 includes the reception circuit 107, the reception coupler 108, and a control unit 113.

[0024] Details of each of the components of the communication apparatus 501, the communication apparatus 502, and the communication apparatus 503 are similar to each of the components identified by the same reference numerals in Fig. 1. The control unit 113 performs similar communication processing to the control

unit 111 and the control unit 112. However, the control unit 111 does not have to perform the data reception processing, and the control unit 113 does not have to perform the data transmission processing. In the system 500, an electric signal is transmitted from the transmission coupler 104 of the communication apparatus 501 to the reception coupler 106 of the communication apparatus 502, and an electric signal is transmitted from the transmission coupler 110 of communication apparatus 502 to the reception coupler 108 of the communication apparatus 503.

[0025] Further, in Figs. 1, 4, and 5, the present exemplary embodiment has been described referring to the example in which the coupler for the transmission and the coupler for the reception are used while being distinguished from each other, but one coupler may be used for both the transmission and the reception. For example, the system 100 illustrated in Fig. 1 may be configured in such a manner that the reception circuit 107 has both the function as the circuit for the reception and the function as the circuit for the transmission, and the control unit 111 switches whether to cause the reception circuit 107 to function as the circuit for the transmission or function as the circuit for the reception. When the reception circuit 107 functions as the circuit for the transmission, an electric signal is transmitted from the reception coupler 108 to the transmission coupler 110.

[0026] In the case where such processing for switching the transmission and the reception is performed in the communication apparatus 101, in the communication apparatus 102, the transmission circuit 109 also has both the function as the circuit for the transmission and the function as the circuit for the reception, and the processing for switching the transmission and the reception is also performed by the control unit 112. In other words, whether to transmit the electric signal from the transmission coupler 110 to the reception coupler 108 or transmit the electric signal from the reception coupler 108 to the transmission coupler 110 is controlled by the control unit 111 and the control unit 112.

[0027] With such a configuration, the system 100 can control whether to carry out the bidirectional communication or carry out the unidirectional communication between the communication apparatus 101 and the communication apparatus 102. For example, one conceivable situation is that the data that should be transmitted from the communication apparatus 102 to the communication apparatus 101 occurs less frequently than the data that should be transmitted from the communication apparatus 101 to the communication apparatus 102 occurs. Under such a situation, the system 100 may carry out the bidirectional communication by transmitting the data from the transmission coupler 104 to the reception coupler 106 and also transmitting the data from the transmission coupler 110 to the reception coupler 108 during a time period when there is the data that should be transmitted from the communication apparatus 102. On the other hand, the system 100 may carry out the unidirectional

tional communication by transmitting the data from the transmission coupler 104 to the reception coupler 106 and also transmitting the data from the reception coupler 108 to the transmission coupler 110 during a time period when there is not the data that should be transmitted from the communication apparatus 102. By operating in this manner, the system 100 can efficiently use the coupler according to the data that should be communicated, thereby realizing the high-speed communication.

[0028] Further, the present exemplary embodiment is being described focusing on the example in which the wireless communication is carried out by single-ended transmission, but is not limited thereto and the wireless communication may be carried out by differential transmission. For example, in a case where the differential transmission is applied to the system 100 illustrated in Fig. 1, the system 100 is modified as indicated by a system 600 illustrated in Fig. 6 with each of the transmission coupler 104, the reception coupler 106, the reception coupler 108, and the transmission coupler 110 being replaced with two couplers for transmitting signals opposite in phase from each other. In Fig. 6, similar components to the system 100 illustrated in Fig. 1 are identified by the same reference numerals.

[0029] In the system 600, the communication apparatus 101 includes a transmission coupler 114 and a reception coupler 118, and the communication apparatus 102 includes a reception coupler 116 and a transmission coupler 120, in addition to the configuration of the system 100. The transmission coupler 114 functions as an antenna for carrying out wireless communication based on electromagnetic field coupling with the reception coupler 116, and the transmission coupler 120 functions as an antenna for carrying out wireless communication based on electromagnetic field coupling with the reception coupler 118.

[0030] The transmission circuit 103 transmits a signal opposite in phase from the electric signal transmitted from the transmission coupler 104 to the reception coupler 106, from the transmission coupler 114 to the reception coupler 116. Further, the transmission circuit 109 transmits a signal opposite in phase from the electric signal transmitted from the transmission coupler 110 to the reception coupler 108, from the transmission coupler 120 to the reception coupler 118. Then, the reception circuit 105 transfers a potential difference between the electric signal received by the reception coupler 106 and the electric signal received by the reception coupler 116 to the control unit 112. Similarly, the reception circuit 107 transfers a potential difference between the electric signal received by the reception coupler 108 and the electric signal received by the reception coupler 118 to the control unit 111.

[0031] The configuration like the system 600 allows the communication apparatus 101 and the communication apparatus 102 to carry out the wireless communication by the differential transmission therebetween. Using the differential transmission achieves a lower influence

of external noise in the wireless communication than using the single-ended transmission. In Fig. 6, the system 600 has been described referring to the example in which the differential transmission is applied to the system 100 illustrated in Fig. 1, but the differential transmission may similarly be applied to the system 400 illustrated in Fig. 4 and the system 500 illustrated in Fig. 5. Further, the differential transmission may be applied to the system including the above-described couplers capable of switching the transmission and the reception.

<Prevention or Reduction of Interference>

[0032] In the descriptions of the above-described drawings, Figs. 3A to 3F, the waveforms have been described referring to the examples of the waveforms in the case where no interference occurs in the electric signals transmitted and received between the two pairs of couplers. On the other hand, interference may occur in the transmitted and received electric signals depending on, for example, the positional relationship among the individual couplers. For example, suppose that, in Fig. 2, the transmission coupler 104 and the reception coupler 108 are located just a short distance away from each other in the Y-axis direction, and the reception coupler 106 and the transmission coupler 110 are located just a short distance away from each other in the Y-axis direction. In such a case, the electric signal transmitted from the transmission coupler 104 may be accidentally received by the reception coupler 108, and the electric signal transmitted from the transmission coupler 110 may be accidentally received by the reception coupler 106.

[0033] Figs. 7A to 7F illustrate examples of waveforms of the electric signals transmitted and received between the communication apparatus 101 and the communication apparatus 102 of the system 100 in the case where the interference has occurred. A horizontal axis in each of Figs. 7A to 7F indicates time. First, a first transmission signal illustrated in Fig. 7A that is generated by the transmission circuit 103 is input to the transmission coupler 104, and a second transmission signal illustrated in Fig. 7D that is generated by the transmission circuit 109 is input to the transmission coupler 110. At this time, the reception coupler 106 also receives the signal transmitted from the transmission coupler 110 accidentally in addition to the signal transmitted from the transmission coupler 104, and noise 701 is contained in the first reception signal generated at the reception coupler 106 as illustrated in Fig. 7B. When the conversion processing by the reception circuit 105 is performed on this first reception signal, a first conversion-completed signal containing noise 702 therein is generated as illustrated in Fig. 7C. Similarly, noise 703 is contained in the second reception signal generated at the reception coupler 108 due to an influence of the signal transmitted from the transmission coupler 104, as illustrated in Fig. 7E. Then, when the conversion processing by the reception circuit 107 is performed on the second reception signal, a second con-

version-completed signal containing noise 704 therein is generated as illustrated in Fig. 7F.

[0034] In the following description, a configuration of the system 100 for preventing or reducing the occurrence of the noise due to the interference of the electric signals like the examples illustrated in Figs. 7A to 7F will be described. The configuration that will be described below not only can be applied to the system 100 illustrated in Fig. 1 but also can be applied to the above-described configurations such as the system 400 illustrated in Fig. 4 and the system 600 illustrated in Fig. 6 in a similar manner.

[0035] A configuration example of the system 100 for preventing or reducing the interference of the electric signals will be described with reference to Figs. 8A and 8B. Fig. 8A is a perspective view of a part of the system 100, and Fig. 8B illustrates the part of the system 100 as viewed from the X-axis positive direction of the coordinate system 200. In Figs. 8A and 8B, similar components to Figs. 2A and 2B are identified by the same reference numerals.

[0036] In Figs. 8A and 8B, the communication apparatus 101 includes a ground 801 positioned between the transmission coupler 104 and the reception coupler 108, and the communication apparatus 102 includes a ground 802 positioned between the reception coupler 106 and the transmission coupler 110, to prevent or reduce the above-described interference. Each of the ground 801 and the ground 802 is, for example, a conductor connected to a reference potential point. In Figs. 8A and 8B, the ground 801 and the ground 802 have shapes longer in length in the X-axis direction than the couplers, but the shapes of the ground 801 and the ground 802 are not limited thereto.

[0037] The provision of the ground 801 to the communication apparatus 101 weakens the electromagnetic field coupling between the transmission coupler 104 and the reception coupler 108, thereby contributing to preventing or reducing the occurrence of the noise in the electric signal received by the reception coupler 108. Similarly, the provision of the ground 802 to the communication apparatus 102 weakens the electromagnetic field coupling between the transmission coupler 110 and the reception coupler 106, thereby contributing to preventing or reducing the occurrence of the noise in the electric signal received by the reception coupler 106. The system 100 may include only any one of the ground 801 and the ground 802.

[0038] Alternatively, as another configuration example for preventing or reducing the interference, the couplers may be disposed in such a manner that the distance between the transmission coupler 104 and the reception coupler 108 in the Y-axis direction, and the distance between the reception coupler 106 and the transmission coupler 110 in the Y-axis direction match or exceed a predetermined distance. The above-described predetermined distance is set according to, for example, strength of the transmitted signal and/or allowable strength of

noise.

[0039] Alternatively, as another configuration example for preventing or reducing the interference, the transmission and the reception may be carried out in a time-sharing manner in the communication between the communication apparatus 101 and the communication apparatus 102. More specifically, the control unit 111 and the control unit 112 may control the transmission circuit 103 and the transmission circuit 109, respectively, so as to prevent the electric signals from being simultaneously transmitted from the transmission coupler 104 to the reception coupler 106 and from the transmission coupler 110 to the reception coupler 108.

[0040] In the above description with reference to Figs. 8A and 8B, the ground 801 and the ground 802 each connected to the reference potential point are assumed to be used as the conductor disposed between the transmission coupler and the reception coupler. However, the conductor disposed between the transmission coupler and the reception coupler is not limited thereto, and a conductor isolated from a so-called electric ground of the transmission circuit or the reception circuit in terms of a direct current or an alternating current may be disposed on at least one of a position between the transmission coupler 104 and the reception coupler 108 and a position between the transmission coupler 110 and the reception coupler 106.

[0041] Next, as another configuration example for preventing or reducing the interference, the system 100 including couplers having different lengths from Figs. 2A and 2B will be described with reference to Figs. 9A to 9D. Fig. 9A is a perspective view of a part of the system 100, and Fig. 9B illustrates the part of the system 100 as viewed from the X-axis positive direction of the coordinate system 200. Further, Fig. 9C illustrates the part of the system 100 as viewed from the Z-axis positive direction, and Fig. 9D illustrates the part of the system 100 as viewed from the Z-axis negative direction. In Figs. 9A to 9D, similar components to Figs. 2A and 2B are identified by the same reference numerals. In Figs. 9B to 9D, a reception coupler 906 and the transmission coupler 110 of the communication apparatus 102 are illustrated in white for illustrative purposes.

[0042] In the configuration illustrated in Figs. 9A to 9D, the reception coupler 106 and the reception coupler 108 illustrated in Figs. 2A and 2B are replaced with the reception coupler 906 and a reception coupler 908 having shorter lengths in the X-axis direction. Here, each of the couplers has a flat shape as illustrated in Fig. 9B, and therefore an area of a portion of the transmission coupler 110 that faces the reception coupler 908 is larger than an area of a portion of the transmission coupler 110 that faces the reception coupler 906. With such a configuration, weaker electromagnetic field coupling is established between the transmission coupler 110 and the reception coupler 906 than the electromagnetic field coupling between the transmission coupler 110 and the reception coupler 106 illustrated in Figs. 2A and 2B. Similarly,

weaker electromagnetic field coupling is established between the transmission coupler 104 and the reception coupler 908 than the electromagnetic field coupling between the transmission coupler 104 and the reception coupler 108 illustrated in Figs. 2A and 2B. As a result, the system 100 can prevent or reduce the occurrence of the noise due to the interference of the electric signals transmitted and received between the communication apparatus 101 and the communication apparatus 102.

<Movement of Coupler Position>

[0043] In the above description, the present exemplary embodiment has been described referring to the example in which a positional relationship between the couplers is fixed, but relative positions of the couplers may be variable. In the following description, a configuration of the system 100 that can move the relative positions of the couplers while maintaining the state capable of carrying out the wireless communication will be described. The configuration that will be described below can also be applied to the above-described configurations such as the system 400 illustrated in Fig. 4 and the system 600 illustrated in Fig. 6 in a similar manner.

[0044] A configuration example of the system 100 including parallelly movable couplers will be described with reference to Figs. 10A and 10B. In Figs. 10A and 10B, similar components to Figs. 2A and 2B are identified by the same reference numerals. Unlike the configuration in the case of Figs. 2A and 2B, the transmission coupler 104 and the reception coupler 108 are mounted on opposite sides of the surface of the plate-like member included in the communication apparatus 101 from each other. Then, the communication apparatus 102 includes two plate-like members so as to vertically surround the plate-like member included in the communication apparatus 101, with a transmission coupler 1010 mounted on one of these two plate-like members and a reception coupler 1006 mounted on the other of these two plate-like members. In other words, the transmission coupler 1010 and the reception coupler 1006 are positioned on opposite sides of the surface of the plate-like member included in the communication apparatus 101 from each other.

[0045] With such a configuration, weaker electromagnetic field coupling is established between the transmission coupler 1010 and the reception coupler 1006 than the electromagnetic field coupling between the transmission coupler 110 and the reception coupler 106 illustrated in Figs. 2A and 2B. Further, weaker electromagnetic field coupling is established between the transmission coupler 104 and the reception coupler 108 than the electromagnetic field coupling in the case of Figs. 2A and 2B. As a result, the system 100 prevents or reduces interference between an electric signal transmitted from the transmission coupler 1010 to the reception coupler 108 and an electric signal transmitted from the transmission coupler 104 to the reception coupler 1006.

[0046] Further, the interference of the electric signals

can be further prevented or reduced by setting up a ground at a position between the transmission coupler 104 and the reception coupler 108, such as an inner layer of the plate-like member included in the communication apparatus 101. In the case where the interference can be prevented or reduced in this manner, the distance between the transmission coupler 104 and the reception coupler 108 in the Y-axis direction can be shortened by, for example, mounting the transmission coupler 104 and the reception coupler 108 at corresponding positions on a back surface and a front surface of the plate-like member, respectively. As a result, this configuration also allows the communication apparatus 101 and the communication apparatus 102 to be reduced in size in the Y-axis direction.

[0047] The transmission coupler 1010 and the reception coupler 1006 illustrated in Figs. 10A and 10B are shorter in length in the X-axis direction than the transmission coupler 110 and the reception coupler 106 illustrated in Figs. 2A and 2B. Therefore, the transmission coupler 1010 is shorter in length in the X-axis direction than the reception coupler 108, and the reception coupler 1006 is shorter in length in the X-axis direction than the transmission coupler 104. This allows the communication apparatus 102 to be reduced in size in the X-axis direction.

[0048] Then, the communication apparatus 102 is movable in the X-axis direction of the coordinate system 200 while keeping the transmission coupler 1010 and the reception coupler 108 facing each other and the transmission coupler 104 and the reception coupler 1006 facing each other. Control of the movement of the communication apparatus 102 can be realized by, for example, controlling a not-illustrated driving unit included in the communication apparatus 102 by the control unit 112. This control of the movement allows a position of the transmission coupler 1010 relative to the reception coupler 108, and a position of the transmission coupler 104 relative to the reception coupler 1006 to be moved in the X-axis direction.

[0049] The communication apparatus 101 may be moved in the X-axis direction instead of the communication apparatus 102, or both the communication apparatus 101 and the communication apparatus 102 may be moved. Further, the direction in which the couplers are moved is not limited to the X-axis direction and may be another direction. Further, without being limited to the range that keeps the transmission coupler and the reception coupler facing each other, the couplers may be moved in a range that allows the communication based on the electromagnetic field coupling to be carried out between the transmission coupler and the reception coupler. Further, in the system 100 described with reference to Figs. 2A and 2B, 8A and 8B, and 9A, 9B, 9C, and 9D, at least any one of the communication apparatus 101 and the communication apparatus 102 may be moved in the X-axis direction.

[0050] Next, a configuration example of the system 100

including rotationally movable couplers will be described with reference to Figs. 11A, 11B, and 11C. Fig. 11A is a perspective view of a part of the system 100. Fig. 11B illustrates the part of the system 100 as viewed from the Z-axis positive direction of the coordinate system 200. Fig. 11C illustrates the part of the system 100 as viewed from the Z-axis negative direction. In Figs. 11A, 11B, and 11C, components similar to those in Figs. 2A and 2B are identified by the same reference numerals.

[0051] A transmission coupler 1104 and a reception coupler 1108 are mounted on a cylindrical member included in the communication apparatus 101, and a transmission coupler 1110 and a reception coupler 1106 are mounted on a cylindrical member included in the communication apparatus 102. Here, the cylindrical member included in the communication apparatus 101 and the cylindrical member included in the communication apparatus 102 have central axes substantially coinciding with each other and different diameters from each other. Then, the transmission coupler 1104 faces the reception coupler 1106, and the transmission coupler 1110 faces the reception coupler 1108. In other words, the reception coupler 1108 and the transmission coupler 1110 are positioned substantially on circumferences of circles centered at the same point as each other and having different diameters from each other, respectively. Further, the transmission coupler 1104 and the reception coupler 1106 are positioned substantially on circumferences of circles centered at the same point as each other and having different diameters from each other, respectively.

[0052] In such a configuration, an electric signal is transmitted from the transmission coupler 1104 to the reception coupler 1106 based on electromagnetic field coupling, and an electric signal is transmitted from the transmission coupler 1110 to the reception coupler 1108 based on electromagnetic field coupling. A diameter of a cylinder along a portion of which the transmission coupler 1104 is mounted, and a diameter of a cylinder along a portion of which the reception coupler 1108 is mounted may be different from each other. Similarly, a diameter of a cylinder along a portion of which the transmission coupler 1110 is mounted, and a diameter of a cylinder along a portion of which the reception coupler 1106 is mounted may be different from each other.

[0053] The communication apparatus 102 is rotationally movable around the central axis of the cylindrical member (axis in the Z-axis direction) while keeping the transmission coupler 1104 and the reception coupler 1106 to face each other and the transmission coupler 1110 and the reception coupler 1108 to face each other. Control of the movement of the communication apparatus 102 can be realized by, for example, controlling a not-illustrated driving unit included in the communication apparatus 102 by the control unit 112. This control of the movement allows the transmission coupler 1110 and the reception coupler 1106 to be rotationally moved. The communication apparatus 101 may be rotationally moved around the central axis of the cylindrical member

instead of the communication apparatus 102, thereby causing the transmission coupler 1104 and the reception coupler 1108 to be rotationally moved. Alternatively, both the communication apparatus 101 and the communication apparatus 102 may be rotationally moved.

[0054] As illustrated in Figs. 11B and 11C, the reception coupler 1106 and the reception coupler 1108 each have an arc shape from a viewpoint of a reference direction (Z-axis direction) substantially in parallel with the central axis of the cylindrical member. Further, the transmission coupler 1104 and the transmission coupler 1110 each have a substantially circular shape from the viewpoint of this reference direction. The transmission coupler 1104 having the substantially circular shape allows the transmission coupler 1104 and the reception coupler 1106 to face each other regardless of how large the rotational angle is with respect to the rotational movement of the reception coupler 1106. Further, the reception coupler 1106 having the arc shape can weaken the electromagnetic field coupling between the transmission coupler 1110 and the reception coupler 1106 compared to the reception coupler 1106 having a substantially circular shape. The same applies to the shapes of the transmission coupler 1110 and the reception coupler 1108. As a result, the system 100 prevents or reduces the interference between the electric signal transmitted from the transmission coupler 1104 to the reception coupler 1106, and the electric signal transmitted from the transmission coupler 1110 to the reception coupler 1108.

[0055] Further, the interference can be further prevented or reduced by disposing a ground on at least any one of a position between the transmission coupler 1104 and the reception coupler 1108 of the communication apparatus 101 and a position between the reception coupler 1106 and the transmission coupler 1110 of the communication apparatus 102.

[0056] The shape of each of the couplers is not limited to the example illustrated in Figs. 11A, 11B, and 11C. For example, at least any one of the transmission coupler 1104 and the transmission coupler 1110 may have an arc shape, and at least any one of the reception coupler 1106 and the reception coupler 1108 may have a substantially circular shape. Alternatively, both the transmission coupler 1104 and the reception coupler 1106 may each have an arc shape. In this case, the couplers may be rotationally moved only in a range that allows the transmission coupler 1104 and the reception coupler 1106 to face each other or a range that allows the communication based on the electromagnetic field coupling to be carried out between the transmission coupler 1104 and the reception coupler 1106. The same applies in a case where both the transmission coupler 1110 and the reception coupler 1108 each have an arc shape.

[0057] Further, as an exemplary modification of the configuration illustrated in Figs. 11A, 11B, and 11C, the system 100 may be configured as if the configuration illustrated in Figs. 10A and 10B is rounded around the Y-axis direction. More specifically, the configuration illus-

trated in Figs. 11A, 11B, and 11C may be configured in the following manner. The reception coupler 108 and the transmission coupler 104 are mounted on an inner surface and an outer surface of a cylindrical member included in the communication apparatus 101, respectively. Further, the communication apparatus 102 sandwiches this cylindrical member in such a manner that the transmission coupler 1010 mounted on the communication apparatus 102 is positioned inside this cylindrical member and the reception coupler 1006 mounted on the communication apparatus 102 is positioned outside this cylindrical member. Similarly, the transmission coupler 104 and the reception coupler 108 may be mounted on the inner surface and the outer surface of the cylindrical member included in the communication apparatus 101, respectively. In such a configuration, at least any one of the communication apparatus 101 and the communication apparatus 102 may be rotationally moved around the Y-axis direction.

[0058] In this exemplary modification, the interference of the electric signals can be prevented or reduced by further disposing a ground between the transmission coupler 104 and the reception coupler 108, such as the inner layer of the cylindrical member included in the communication apparatus 101. In the case where the interference can be prevented or reduced in this manner, the distance between the transmission coupler 104 and the reception coupler 108 in the Y-axis direction can be shortened by, for example, mounting the transmission coupler 104 and the reception coupler 108 at corresponding positions on the inner surface and the outer surface of the cylindrical member, respectively. As a result, this configuration also allows the communication apparatus 101 and the communication apparatus 102 to be reduced in size in the Y-axis direction.

<Specific Configuration Example of Coupler>

[0059] Figs. 12A, 12B, and 12C illustrate specific configuration examples of the couplers in the wireless communication system 600 to which the differential transmission is applied, which has been described above with reference to Fig. 6. Figs. 12A, 12B, and 12C illustrate specific configuration examples of the couplers in cases where the wireless communication is realized by the electric field coupling, the magnetic field coupling, and the electric field and magnetic field coupling, respectively. Hereinafter, the couplers illustrated in Figs. 12A, 12B, and 12C will be referred to as a coupler for electric field coupling, a coupler for magnetic field coupling, and a coupler for electromagnetic field coupling, respectively.

[0060] In the coupler for electric field coupling illustrated in Fig. 12A, the transmission coupler formed by the two conductors (transmission coupler 104 and transmission coupler 114) is electrically opened at an opposite end from a power supply point (P1) connected to the transmission circuit 103. Similarly, the reception coupler formed by the two conductors (reception coupler 106 and

reception coupler 116) is electrically opened at an opposite end from a power supply point (P2) connected to the reception circuit 105. On the other hand, in the coupler for magnetic field coupling illustrated in Fig. 12B, the opposite ends of the transmission coupler and the reception coupler from the power supply points (P1 and P2) are electrically shortcircuited by a conductor 1200 and a conductor 1201, respectively. Further, in the coupler for electromagnetic field coupling illustrated in Fig. 12C, a resistor 1202 substantially matching a characteristic impedance of a transmission line connecting the transmission circuit 103 and the transmission coupler therebetween is inserted at the opposite end of the transmission coupler from the power supply point (P1). Similarly, a resistor 1203 substantially matching a characteristic impedance of a transmission line connecting the reception circuit 105 and the reception coupler therebetween is inserted at the opposite end of the reception coupler from the power supply point (P2).

[0061] The shapes of the couplers according to each of the methods illustrated in Figs. 12A to 12C are just one example, and are not limited thereto as long as the couplers have the above-described characteristics. Further, the wireless communication using the couplers configured as illustrated in Figs. 12A, 12B, and 12C is not limited to the differential transmission, and the wireless communication by the single-ended transmission may be carried out with use of the couplers configured as illustrated in Figs. 12A, 12B, and 12C.

<Prevention or Reduction of Interference by Shield Insertion>

[0062] The configuration of the system 100 for preventing or reducing the interference of the electric signals has been described above with reference to Figs. 8A and 8B, and 9A, 9B, 9C, and 9D, and, in the following description, another configuration example of the system 100 for preventing or reducing the interference will be described with reference to Figs. 13A, 13B, and 13C. Fig. 13A is a perspective view of a part of the system 100, and Fig. 13B illustrates the part of the system 100 as viewed from the X-axis positive direction of the coordinate system 200. Further, Fig. 13C illustrates the part of the system 100 as viewed from the Z-axis positive direction of the coordinate system 200. In Fig. 13C, the configuration of the communication apparatus 101 side is omitted and only the configuration of the communication apparatus 102 side is illustrated.

[0063] In the configuration illustrated in Figs. 13A, 13B, and 13C, the communication apparatus 101 includes a plate-like shield conductor 1300. The shield conductor 1300 is disposed so as to overlap the transmission coupler 104 and the reception coupler 108 when being viewed from the Z-axis positive direction, and is also disposed on an opposite side of the transmission coupler 104 and the reception coupler 108 from the transmission coupler 110 and the reception coupler 106. In other

words, the shield conductor 1300 is disposed so as to cover the transmission coupler 104 and the reception coupler 108 when being viewed from the Z-axis negative direction. Similarly, the communication apparatus 102 includes a shield conductor 1301, and the shield conductor 1301 is disposed so as to cover the transmission coupler 110 and the reception coupler 106 when being viewed from the Z-axis positive direction.

[0064] The interference of the electric signals that is generated between the transmission coupler 104 and the reception coupler 108 like the example described with reference to Figs. 7A to 7F can be prevented or reduced by disposing the shield conductor close to the couplers in the above-described manner. The shield conductors 1300 and 1301 may be any members as long as they are conductors, and, for example, are made with use of aluminum, copper, or the like. Further, in a case where a substrate pattern such as Flame Retardant Type 4 (FR4) is used, the shield conductors 1300 and 1301 may be each formed with use of a conductor layer that is a surface layer different from the layer on which the couplers are formed or an inner layer. Further, the shield conductors 1300 and 1301 may be connected in terms of a direct current to or isolated in terms of a direct current/alternating current from the electric ground of the transmission circuit or the reception circuit. Further, the shield conductor may be provided to only any one of the communication apparatus 101 and the communication apparatus 102. Further, the shield conductors 1300 and 1301 do not have to entirely cover the transmission coupler and the reception coupler when being viewed from the Z-axis direction, and may be configured in a different manner as long as at least a part of the transmission coupler or the reception coupler and the shield conductor overlap each other.

[0065] Further, the interference of the electric signals between the couplers can be further prevented or reduced by using a shield conductor having a slit. This configuration will be described with reference to Figs. 14A, 14B, and 14C. Fig. 14A is a perspective view of a part of the system 100, and Fig. 14B illustrates the part of the system 100 as viewed from the X-axis positive direction of the coordinate system 200. Further, Fig. 14C illustrates the part of the system 100 as viewed from the Z-axis positive direction of the coordinate system 200. In Fig. 14C, the configuration of the communication apparatus 101 side is omitted and only the configuration of the communication apparatus 102 side is illustrated.

[0066] In the configuration illustrated in Figs. 14A, 14B, and 14C, the communication apparatus 101 and the communication apparatus 102 include a shield conductor 1400 and a shield conductor 1401 with slits inserted therein, respectively. The slit included in the shield conductor 1400 is positioned between the transmission coupler 104 and the reception coupler 108 when being viewed from the Z-axis direction. Similarly, the slit included in the shield conductor 1401 is positioned between the transmission coupler 110 and the reception coupler 106 when being viewed from the Z-axis direction.

[0067] The interference of the electric signals due to the coupling between the transmission coupler 104 and the reception coupler 108 via the shield conductor 1400 can be prevented or reduced by disposing the shield conductor 1400 having the slit close to the couplers in the above-described manner. The methods for preventing or reducing the interference of the electric signals between the couplers that have been described with reference to Figs. 13A, 13B, and 13C, and 14A, 14B, and 14C are especially effective in the case where the coupler for electric field coupling is used.

<Sliding Movement of Coupler>

[0068] The configuration example of the system 100 including the parallelly movable couplers has been described above with reference to Figs. 10A and 10B, and an example in a case where couplers configured in a different manner from Figs. 10A and 10B are applied to the parallelly movable system 100 will be described with reference to Figs. 15A and 15B. Fig. 15A is a perspective view of a part of the system 100, and Fig. 15B illustrates the part of the system 100 as viewed from the X-axis positive direction of the coordinate system 200.

[0069] In the configuration illustrated in Figs. 15A and 15B, the transmission coupler 104 and the reception coupler 108 included in the communication apparatus 101 are substantially equal in length, and are arranged side by side in the Y-axis direction. Further, the transmission coupler 104 and the reception coupler 108 are shorter in length in the X-axis direction compared to a transmission coupler 1510 and a reception coupler 1506 included in the communication apparatus 102. The communication apparatus 101 is movable in the X-axis direction in a range where the transmission coupler 104 and the reception coupler 1506 overlap each other and the transmission coupler 1510 and the reception coupler 108 overlap each other when being viewed from the Z-axis positive direction, i.e., a range where the communication apparatus 101 and the communication apparatus 102 are efficiently communicable with each other. The communication apparatus 102 may be moved in a similar range instead of the communication apparatus 101, or both the communication apparatus 101 and the communication apparatus 102 may be moved.

[0070] In the configuration example illustrated in Figs. 15A and 15B, a ground conductor may be disposed between the transmission coupler 104 and the reception coupler 108 and/or between the transmission coupler 1510 and the reception coupler 1506 as described with reference to Figs. 8A and 8B for the purpose of preventing or reducing the interference of the electric signal between the couplers. Alternatively, in the configuration example illustrated in Figs. 15A and 15B, a shield conductor may be provided as described with reference to Figs. 13A, 13B, and 13C, and 14A, 14B, and 14C for the purpose of preventing or reducing the interference of the electric signal between the couplers.

[0071] Further, in the configuration examples illustrated in Figs. 9A, 9B, 9C, and 9D, and 10A and 10B, the configuration for preventing or reducing the interference such as the above-described ground and shield may be applied for the purpose of preventing or reducing the interference of the electric signal between the couplers. Further, the plurality of above-described methods for preventing or reducing the interference may be used in combination in a single system.

<Rotationally Movable System (Three-dimensional Type)>

[0072] In the above description made referring to Figs. 11A, 11B, and 11C, the configuration that allows the couplers to be rotationally moved by disposing them on the cylindrical members has been described focusing on the example in which the transmission coupler and the reception coupler have different lengths from each other, but is not limited thereto. For example, in a case where the transmission coupler and the reception coupler are disposed away from each other by a distance long enough to raise no problem regarding the interference of the electric signals between the transmission coupler and reception coupler disposed on one of the communication apparatuses 101 and 102, the transmission coupler and the reception coupler may have equal lengths to each other as illustrated in Figs. 16A, 16B, and 16C. In the configuration illustrated in Figs. 16A, 16B, and 16C, the communication apparatus 101 includes a transmission coupler 1604 and a reception coupler 1608, and the communication apparatus 102 includes a transmission coupler 1610 and a reception coupler 1606. Then, the transmission coupler 1604 carries out communication with the reception coupler 1606, and the transmission coupler 1610 carries out communication with the reception coupler 1608. Such a configuration also allows the communication to be carried out while at least one of the communication apparatus 101 and the communication apparatus 102 is rotationally moved around the Z axis similarly to the configuration described above with reference to Figs. 11A, 11B, and 11C.

[0073] In the configuration example illustrated in Figs. 16A, 16B, and 16C, a ground conductor may be disposed between the transmission coupler 1604 and the reception coupler 1608 and/or the reception coupler 1606 and the transmission coupler 1610 as described with reference to Figs. 8A and 8B for the purpose of preventing or reducing the interference of the electric signal between the couplers. Alternatively, in the configuration example illustrated in Figs. 16A, 16B, and 16C, a shield conductor may be provided as described with reference to Figs. 13A, 13B, and 13C, and 14A, 14B, and 14C for the purpose of preventing or reducing the interference of the electric signal between the couplers.

[0074] Further, in the configuration illustrated in Figs. 16A, 16B, and 16C, the transmission coupler and the reception coupler are assumed to be disposed on the

same surface of the cylindrical member in each of the communication apparatus 101 and the communication apparatus 102. However, the positions of the transmission coupler and the reception coupler are not limited thereto, and the transmission coupler and the reception coupler may be disposed on different surfaces of the cylindrical member as illustrated in Figs. 17A and 17B for the purpose of preventing or reducing the interference of the electric signal between the couplers. In the configuration illustrated in Figs. 17A and 17B, the communication apparatus 101 includes a cylindrical member A and a cylindrical member B, and the communication apparatus 102 includes a cylindrical member C. Then, the cylindrical member C is disposed inside the cylindrical member A, and the cylindrical member B is disposed further inside the cylindrical member C. A transmission coupler 1704 included in the communication apparatus 101 is disposed on an inner surface of the cylindrical member A, and carries out communication with a reception coupler 1706 included in the communication apparatus 102 that is disposed on an outer surface of the cylindrical member C. Further, a transmission coupler 1710 included in the communication apparatus 102 is disposed on an inner surface of the cylindrical member C, and carries out communication with a reception coupler 1708 included in the communication apparatus 101 that is disposed on an outer surface of the cylindrical member B.

[0075] Such a configuration also allows the communication to be carried out while at least one of the communication apparatus 101 and the communication apparatus 102 is rotationally moved around the Z axis similarly to the configurations described with reference to Figs. 11A, 11B, and 11C, and 16A, 16B, and 16C. In this case, each of the cylindrical members is supported by a structure not obstructing the rotational movement so that a positional relationship thereof is not largely changed.

[0076] A cylindrical shield conductor may be provided inside the cylindrical member C so as to be sandwiched between the reception coupler 1706 and the transmission coupler 1710 for the purpose of preventing or reducing the interference of the electric signals between the reception coupler 1706 and the transmission coupler 1710 included in the communication apparatus 102. This shield conductor may be connected in terms of a direct current to or may be configured to be isolated in terms of a direct current/alternating current from the electric ground of the transmission circuit or the reception circuit. Further, in the configuration examples illustrated in Figs. 11A, 11B, and 11C, 16A, 16B, and 16C, and 17A and 17B, the plurality of configurations for preventing or reducing the interference of the electric signal between the couplers may be used in combination.

<Rotationally Movable System (Planar Type)>

[0077] Another configuration example in which the couplers are rotationally movable will be described with

reference to Figs. 18A and 18B. Fig. 18A is a perspective view of a part of the system 100, and Fig. 18B illustrates the part of the system 100 as viewed from the X-axis positive direction of the coordinate system 200. In the configuration example illustrated in Figs. 18A and 18B, the communication apparatus 101 includes a disk-like member, and a transmission coupler 1804 and a reception coupler 1808 are disposed substantially concentrically around a point 1900. Further, the communication apparatus 102 also includes a disk-like member, and a transmission coupler 1810 and a reception coupler 1806 are also disposed substantially concentrically around a point 1901. The point 1900 and the point 1901 are points overlapping each other as viewed from the Z-axis positive direction of the coordinate system 200. Then, communication is carried out between the transmission coupler 1804 and the reception coupler 1806, and communication is carried out between the transmission coupler 1810 and the reception coupler 1808. Employing such a configuration allows the communication to be carried out between the communication apparatus 101 and the communication apparatus 102 while at least one of the disk-like member included in the communication apparatus 101 and the disk-like member included in the communication apparatus 102 is rotationally moved around an axis in the Z-axis direction that passes through the point 1900 and the point 1901.

[0078] In the configuration example illustrated in Figs. 18A and 18B, a ground conductor may be disposed between the transmission coupler 1804 and the reception coupler 1808 and/or the transmission coupler 1810 and the reception coupler 1806 as described with reference to Figs. 8A and 8B for the purpose of preventing or reducing the interference of the electric signal between the couplers. Alternatively, in the configuration example illustrated in Figs. 18A and 18B, a shield conductor may be provided to the communication apparatus 101 and/or the communication apparatus 102 as described with reference to Figs. 13A, 13B, and 13C, and 14A, 14B, and 14C for the purpose of preventing or reducing the interference of the electric signal between the couplers.

[0079] Further, in the configuration example illustrated in Figs. 18A and 18B, the system 100 may be configured in such a manner that the transmission coupler and the reception coupler supposed to communicate with each other have different lengths from each other as described with reference to Figs. 9A, 9B, 9C, and 9D for the purpose of preventing or reducing the interference of the electric signal between the couplers. For example, even with the transmission coupler 1810 shortened and shaped into an arc shape, the reception coupler 1808 having the circular shape allows the communication to be carried out between transmission coupler 1810 and the reception coupler 1808 even when the coupler is rotationally moved around the Z axis. Conversely, the transmission coupler 1810 and the reception coupler 1808 may have a circular shape and an arc shape, respectively. Further, the transmission coupler 1804 and the reception coupler 1806

may have different lengths from each other. Further, in the configuration example illustrated in Figs. 18A and 18B, the plurality of configurations for preventing or reducing the interference of the electric signals between the couplers may be used in combination.

<Effect of Preventing or Reducing Interference due to Shield Conductor>

[0080] An effect of preventing or reducing the interference by the shield conductor described with reference to Figs. 13A, 13B, and 13C, and 14A, 14B, and 14C will be described with reference to Figs. 19A, 19B, and 19C to Figs. 21A, 21B, and 21C. Figs. 19A, 19B, and 19C to Figs. 21A, 21B, and 21C illustrate models and results of a simulation in the case where the rotationally movable coupler structure described with reference to Figs. 18A and 18B is used. Figs. 19A, 20A, and 21A are perspective views of models regarding the coupler portion of the communication apparatus 101, and Figs. 19B, 20B, and 21B illustrate models when the coupler portion of the communication apparatus 101 is viewed from the Z-axis positive direction. These models are constructed assuming that the coupler is the coupler for electric field coupling capable of carrying out the wireless communication by the differential transmission, and a conductor 2000 and a conductor 2001 form the transmission coupler 1804 and a conductor 2002 and a conductor 2003 form the reception coupler 1808. The transmission coupler 1804 has a power supply point P20, and the reception coupler 1808 has a power supply point P21.

[0081] In each of the models of the simulation illustrated in Figs. 19A, 19B, and 19C to 21A, 21B, and 21C, the transmission coupler 1804 and the reception coupler 1808 are formed as patterns on one surface (front surface) of a circular substrate included in the communication apparatus 101. Further, in the model of the simulation illustrated in Figs. 20A, 20B, and 20C, a shield conductor 2100 is formed as a pattern on the other surface (back surface) of the circular substrate. Further, in the model of the simulation illustrated in Figs. 21A, 21B, and 21C, a shield conductor 2200 having a slit is formed as a pattern on the other surface (back surface) of the circular substrate. The coupler portion of the communication apparatus 102 disposed so as to face the coupler portion of the communication apparatus 101 is also configured in a similar manner.

[0082] In the present simulation, the circular substrate has an outer shape of 95 mm and an inner diameter of 56 mm. An outermost diameter of the coupler (diameter of the conductor 2003) is 79 mm, and an innermost diameter of the coupler (diameter of the conductor 2000) is 59 mm. Widths of the conductor 2000 and the conductor 2001 are each 1.5 mm, and widths of the conductor 2002 and the conductor 2003 are each 1.0 mm. An interval between the conductor 2000 and the conductor 2001 and an interval between the conductor 2002 and the conductor 2003 are each 1.5 mm, and an interval

between the conductor 2001 and the conductor 2002 is 2.0 mm. An outermost diameter and an innermost diameter of each of the shield conductor 2100 and the shield conductor 2200 are 80 mm and 57 mm, respectively. A width and a diameter of the slit of the shield conductor 2200 are 0.5 mm and 69 mm, respectively. Further, an interval between the circular substrate included in the communication apparatus 101 and the circular substrate included in the communication apparatus 102 is 0.5 mm.

[0083] Figs. 19C, 20C, and 21C are graphs each indicating a simulation result regarding a characteristic of the transmission between the couplers facing each other in a case where the coupler portion of the communication apparatus 101 and the coupler portion of the communication apparatus 102 are arranged so as to face each other in proximity to each other. A vertical axis and a horizontal axis of the graph indicate a gain and a frequency of the transmitted electric signal, respectively. Further, a solid line and a dotted line in the graph indicate a characteristic of the transmission between the transmission coupler 1804 and the reception coupler 1806, and a characteristic of the transmission between the transmission coupler 1804 and the reception coupler 1808, respectively. This graph means that a degree of preventing or reducing the interference of the electric signal between the couplers is large if the gain of the characteristic of the transmission between the couplers adjacent to each other that is indicated by the dotted line is small compared to the gain of the characteristic of the transmission between the couplers facing each other that is indicated by the solid line (if a difference between the gains is large).

[0084] Figs. 19A, 19B, and 19C illustrate the model and the result of the simulation in the case where no shield conductor is disposed. When the frequency of the electric signal is 100 MHz, the characteristic of the transmission between the couplers facing each other (solid line) is -12.6 dB while the characteristic of the transmission between the couplers adjacent to each other (dotted line) is -33.4 dB, so that a difference of 20.8 dB is generated therebetween.

[0085] On the other hand, Figs. 20A, 20B, and 20C illustrate the model and the result of the simulation in the case where the shield conductor 2100 is disposed so as to overlap the couplers. When the frequency of the electric signal is 100 MHz, the characteristic of the transmission between the couplers facing each other is -15.3 dB while the characteristic of the transmission between the couplers adjacent to each other is -46.5 dB, so that a difference of 31.2 dB is generated therebetween. In other words, this simulation indicates such a result that an effect of reducing the interference by 10.4 dB can be acquired compared to the configuration in the case where no shield conductor is used (in the case of Figs. 19A, 19B, and 19C).

[0086] Further, Figs. 21A, 21B, and 21C illustrate the model and the result of the simulation in the case where the shield conductor 2200 having the slit is disposed so as to overlap the couplers. When the frequency of the

electric signal is 100 MHz, the characteristic of the transmission between the couplers facing each other is -15.3 dB while the characteristic of the transmission between the couplers adjacent to each other is -49.0 dB, so that a difference of 33.7 dB is generated therebetween. In other words, this simulation indicates such a result that an effect of further reducing the interference by 2.5 dB can be acquired compared to the configuration in the case where the shield conductor 2100 having no slit is used (in the case of Figs. 20A, 20B, and 20C).

[0087] In the above-described manner, the wireless communication system according to the present exemplary embodiment (system 100, system 400, system 500, and system 600) includes a first antenna and a second antenna. Further, the wireless communication system includes a third antenna for carrying out wireless communication based on electromagnetic field coupling with the first antenna, and a fourth antenna for carrying out wireless communication based on electromagnetic field coupling with the second antenna. With such a configuration, further high-speed communication can be realized in the wireless communication system carrying out the communication based on the electromagnetic field coupling. Further, disposing each of the antennas with use of the above-described various kinds of methods for preventing or reducing the interference causes an electric signal transmitted from the first antenna and received by the second antenna to have weaker strength than strength of an electric signal transmitted from the first antenna and received by the third antenna. In other words, the wireless communication system can prevent or reduce interference of the electric signal between the first antenna and the second antenna, and interference of the electric signal between the third antenna and the fourth antenna.

[0088] In the present exemplary embodiment, the wireless communication system has been described based on the example in which the electric signal is transmitted and received between the transmission coupler and the reception coupler according to the baseband method. According to the baseband method, the electric signal does not have to be modulated and demodulated, and therefore a circuit scale can be reduced. However, the communication method is not limited thereto, and, for example, carrier communication may be carried out by modulating a carrier wave to be transmitted from the transmission coupler to the reception coupler based on the electric signal generated by the transmission circuit. In the case where the carrier communication is carried out, the interference of the communication can be prevented or reduced by using different frequencies as a frequency of a carrier wave transmitted between one pair of transmission and reception couplers and a frequency of a carrier wave transmitted between another pair of transmission and reception couplers.

[0089] According to the above-described exemplary embodiment, further high-speed communication can be realized in the wireless communication system.

[0090] While the present invention has been described with reference to exemplary embodiments, it is to be understood that the invention is not limited to the disclosed exemplary embodiments. The scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.

Claims

1. A wireless communication system comprising:

a first communication apparatus including a first antenna and a second antenna;
 a second communication apparatus including a third antenna and a fourth antenna;
 a first communication control means configured to control wireless communication based on electric field coupling or magnetic field coupling between the first antenna and the third antenna; and
 a second communication control means configured to control wireless communication based on electric field coupling or magnetic field coupling between the second antenna and the fourth antenna,
 wherein the first antenna, the second antenna, the third antenna, and the fourth antenna are positioned in such a manner that an electric signal transmitted from the first antenna and received by the second antenna has weaker strength than strength of an electric signal transmitted from the first antenna and received by the third antenna.

2. The wireless communication system according to claim 1,

wherein an area of a portion of the first antenna that faces the third antenna is larger than an area of a portion of the first antenna that faces the second antenna, and
 wherein each of the second antenna and the third antenna is shorter than the first antenna.

3. The wireless communication system according to claim 2,

wherein the first antenna and the second antenna are positioned on a surface of a first plate-like member, and
 wherein the third antenna and the fourth antenna are positioned on a surface of a second plate-like member facing the first plate-like member.

4. The wireless communication system according to claim 3, further comprising a movement control

means configured to move at least one of the first plate-like member and the second plate-like member in a predetermined movement direction substantially parallel with the surface of the first plate-like member and the surface of the second plate-like member,

wherein each of the second antenna and the third antenna is shorter in length in the movement direction than the first antenna.

5. The wireless communication system according to claim 3, further comprising a movement control means configured to rotationally move at least one of the first plate-like member and the second plate-like member around a predetermined axis substantially perpendicular to the surface of the first plate-like member and the surface of the second plate-like member,

wherein the first antenna has a ring shape centered on the predetermined axis, and
 wherein the second antenna and the third antenna each have an arc shape from a viewpoint of a direction of the predetermined axis.

6. The wireless communication system according to claim 2, further comprising a movement control means configured to rotationally move at least one of a first cylindrical member extending around a predetermined axis serving as a central axis thereof and a second cylindrical member having a central axis substantially coinciding with that of the cylindrical member and a different diameter from the cylindrical member, around the predetermined axis,

wherein the first antenna and the second antenna are positioned on a surface of the first cylindrical member,
 wherein the third antenna and the fourth antenna are positioned on a surface of the second cylindrical member,
 wherein the first antenna has a ring shape centered on the predetermined axis, and
 wherein the second antenna and the third antenna each have an arc shape from a viewpoint of a direction of the predetermined axis.

7. The wireless communication system according to claim 1,

wherein the first antenna is positioned on a surface of a first member,
 wherein the second antenna is positioned on an opposite side of the surface of the first member from the first antenna, and
 wherein the third antenna is positioned on the same side of the surface of the first member as the first antenna.

8. The wireless communication system according to claim 7,
 wherein the first member is a plate-like member,
 and
 wherein the second antenna is positioned on an opposite surface of the first member on which the first antenna is positioned. 5
9. The wireless communication system according to claim 8, further comprising a movement control means configured to move the first member in a predetermined movement direction substantially parallel with the surface of the first member. 10
10. The wireless communication system according to claim 7, further comprising a movement control means configured to rotationally move the first member around a predetermined axis,
 wherein the first member is a cylindrical member extending around the predetermined axis serving as a central axis thereof,
 wherein the first antenna is positioned on an inner surface of the first member,
 wherein the second antenna is positioned on an outer surface of the first member, and
 wherein the third antenna is positioned on a surface of a cylindrical second member having a central axis substantially coinciding with that of the first member and a different diameter from the first member. 15 20 25 30
11. The wireless communication system according to claim 1, further comprising a conductor overlapping the first antenna and the second antenna from a viewpoint of a specific direction substantially perpendicular to a plane on which the first antenna and the second antenna are positioned. 35
12. The wireless communication system according to claim 11,
 wherein the first antenna and the second antenna are positioned on a surface of a first plate-like member, and
 wherein the third antenna and the fourth antenna are positioned on a surface of a second plate-like member facing the first plate-like member. 40 45
13. The wireless communication system according to claim 12, further comprising a movement control means configured to move at least one of the first plate-like member and the second plate-like member in a predetermined movement direction substantially parallel with the surface of the first plate-like member and the surface of the second plate-like member. 50 55
14. The wireless communication system according to claim 12, further comprising a movement control means configured to rotationally move at least one of the first plate-like member and the second plate-like member around a predetermined axis substantially perpendicular to the surface of the first plate-like member and the surface of the second plate-like member.
15. The wireless communication system according to claim 12, wherein the conductor is positioned on an opposite surface of the first plate-like member on which the first antenna and the second antenna are positioned.
16. The wireless communication system according to claim 11, wherein the conductor includes a slit at a position between the first antenna and the second antenna from the viewpoint of the specific direction.
17. The wireless communication system according to claim 1, further comprising a conductor configured to serve as an electric ground positioned between the first antenna and the second antenna.
18. The wireless communication system according to claim 1, wherein a distance between the first antenna and the third antenna is shorter than a distance between the first antenna and the second antenna.
19. The wireless communication system according to claim 1,
 wherein the first communication control means controls the wireless communication by differential transmission of a baseband method between the first antenna and the third antenna, and
 wherein the second communication control means controls the wireless communication by the differential transmission of the baseband method between the second antenna and the fourth antenna.
20. The wireless communication system according to claim 1, further comprising a support means configured to support the first communication apparatus and the second communication apparatus in such a manner that the first communication apparatus and the second communication apparatus maintain a predetermined positional relationship therebetween.

FIG.1




FIG.2A




FIG.2B




FIG.3A



FIG.3B




FIG.3C



FIG.3D



FIG.3E




FIG.3F



FIG.4




FIG.5




FIG.6

600




FIG.7A



FIG.7B




FIG.7C




FIG.7D



FIG.7E




FIG.7F




FIG.8A




FIG.8B




FIG.9A




FIG.9B




FIG.9C




FIG.9D




FIG.10A




FIG.10B




FIG.11A




FIG.11B




FIG.11C










FIG.12A**FIG.12B****FIG.12C**








FIG.15A




FIG.15B




FIG.16A




FIG.16B




FIG.16C




FIG.17A




FIG.17B




FIG.18A




FIG.18B




FIG.19A




FIG.19B




FIG.19C




FIG.20A




FIG.20B




FIG.20C




FIG.21A




FIG.21B





FIG.21C





EUROPEAN SEARCH REPORT

Application Number
EP 18 00 0014

5

10

15

20

25

30

35

40

45

50

55

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (IPC)
X	EP 2 581 993 A1 (TYCO ELECTRONICS NEDERLAND BV [NL]; TYCO ELECTRONICS AMP GMBH [DE]) 17 April 2013 (2013-04-17) * paragraph [0038] - paragraph [0048] * * paragraph [0116] - paragraph [0118] * * paragraph [0122] - paragraph [0134] * * figures 1a, 1b, 4a, 4b *	1,7-9, 11-13, 17-20	INV. H04B5/00
X	WO 2012/155135 A2 (WAVECONNEX INC [US]; MCCORMACK GARY D [US]; KYLES IAN A [US]) 15 November 2012 (2012-11-15) * page 1, line 17 - line 26 * * page 11, line 1 - line 13 * * page 17, line 5 - page 19, line 12 * * page 21, line 15 - page 22, line 27 * * figures 7, 17-22, 28, 29 *	1-4,18, 19	
X	US 2015/264515 A1 (UCHIDA SHIGENORI [JP]) 17 September 2015 (2015-09-17) * paragraph [0002] - paragraph [0006] * * paragraph [0026] - paragraph [0031] * * paragraph [0060] - paragraph [0065] * * figures 1, 4 *	1-4,18, 19	TECHNICAL FIELDS SEARCHED (IPC) H04B
X	WO 2016/070204 A1 (MIMOTECH PTY LTD [ZA]) 6 May 2016 (2016-05-06) * page 13, line 4 - line 13 * * page 14, line 12 - line 19 * * figures 5, 6A-6C *	1-3,18, 19	
A	EP 2 890 020 A2 (HOSIDEN CORP [JP]) 1 July 2015 (2015-07-01) * paragraph [0060] - paragraph [0064] * * paragraph [0093] - paragraph [0097] * * paragraph [0119] * * paragraph [0145] * * paragraph [0154] - paragraph [0156] * * paragraph [0172] - paragraph [0174] * * figures 1B, 2A, 5, 8A, 9 *	1-20	
The present search report has been drawn up for all claims			
Place of search Munich		Date of completion of the search 8 May 2018	Examiner Marzenke, Marco
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

EPO FORM 1503 03.82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 18 00 0014

5

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

08-05-2018

10

15

20

25

30

35

40

45

50

55

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 2581993	A1	17-04-2013	CN 104145384 A	12-11-2014
			EP 2581993 A1	17-04-2013
			JP 6045595 B2	14-12-2016
			JP 2015503254 A	29-01-2015
			US 2014252876 A1	11-09-2014
			WO 2013053731 A1	18-04-2013

WO 2012155135	A2	15-11-2012	CN 103650362 A	19-03-2014
			CN 106059634 A	26-10-2016
			EP 2707968 A2	19-03-2014
			JP 5951756 B2	13-07-2016
			JP 2014516221 A	07-07-2014
			JP 2016106496 A	16-06-2016
			JP 2016106497 A	16-06-2016
			KR 20140035398 A	21-03-2014
			TW 201249293 A	01-12-2012
			WO 2012155135 A2	15-11-2012

US 2015264515	A1	17-09-2015	JP 6138076 B2	31-05-2017
			JP 2015177419 A	05-10-2015
			US 2015264515 A1	17-09-2015
			US 2016241305 A1	18-08-2016

WO 2016070204	A1	06-05-2016	EP 3213420 A1	06-09-2017
			WO 2016070204 A1	06-05-2016

EP 2890020	A2	01-07-2015	CN 104753186 A	01-07-2015
			EP 2890020 A2	01-07-2015
			JP 2015144409 A	06-08-2015
			KR 20150076071 A	06-07-2015
			TW 201539921 A	16-10-2015
			US 2015188608 A1	02-07-2015

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- JP 2009268022 A [0002]