



(11) **EP 4 037 235 B9**

(12) **CORRECTED EUROPEAN PATENT SPECIFICATION**

(15) Correction information:
Corrected version no 1 (W1 B1)
Corrections, see
Claims EN 1, 4, 7, 10, 11, 13, 16, 17

(51) International Patent Classification (IPC):
H04L 5/00 ^(2006.01) **H04W 72/04** ^(2023.01)

(52) Cooperative Patent Classification (CPC):
H04L 5/0007; H04L 5/0048; H04L 5/0091;
H04W 72/04; H04L 5/0023

(48) Corrigendum issued on:
29.11.2023 Bulletin 2023/48

(45) Date of publication and mention
of the grant of the patent:
20.09.2023 Bulletin 2023/38

(21) Application number: **21217358.7**

(22) Date of filing: **13.05.2016**

(54) **METHOD AND DEVICE FOR DEMODULATION OF BEAMFORMED CONTROL CHANNEL**

SIGNALÜBERTRAGUNGSVERFAHREN, NETZWERKVORRICHTUNG UND
ENDGERÄTEVORRICHTUNG

PROCÉDÉ DE TRANSMISSION DE SIGNAUX, DISPOSITIF DE RÉSEAU ET DISPOSITIF TERMINAL

(84) Designated Contracting States:
AL AT BE BG CH CY CZ DE DK EE ES FI FR GB
GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO
PL PT RO RS SE SI SK SM TR

(43) Date of publication of application:
03.08.2022 Bulletin 2022/31

(60) Divisional application:
23192062.0

(62) Document number(s) of the earlier application(s) in
accordance with Art. 76 EPC:
20170761.9 / 3 745 633
16901336.4 / 3 451 762

(73) Proprietor: **Huawei Technologies Co., Ltd.**
Shenzhen, Guangdong 518129 (CN)

(72) Inventor: **HE, Chuanfeng**
Shenzhen 518129 (CN)

(74) Representative: **Roth, Sebastian**
Mitscherlich PartmbB
Patent- und Rechtsanwälte
Karlstraße 7
80333 München (DE)

(56) References cited:
• **MOTOROLA: "PDCCH Beamforming for LTE-A",**
3GPP DRAFT; R1-091331, no. Seoul, Korea;
20090318, 18 March 2009 (2009-03-18),
XP050338929,
• **QUALCOMM INC: "Beamformed CSI-RS for**
support of FD-MIMO", 3GPP DRAFT; R1-153880 ,
vol. RAN WG1, no. Beijing, China; 20150824 -
20150828 23 August 2015 (2015-08-23),
XP051001316, Retrieved from the Internet:
URL:http://www.3gpp.org/ftp/Meetings_3GPP_
SYNC/RAN1/Docs/ [retrieved on 2015-08-23]

Note: Within nine months of the publication of the mention of the grant of the European patent in the European Patent Bulletin, any person may give notice to the European Patent Office of opposition to that patent, in accordance with the Implementing Regulations. Notice of opposition shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

EP 4 037 235 B9

Description

TECHNICAL FIELD

[0001] Embodiments of the present invention relate to the field of communications technologies, and in particular, to a communication method, communication device, non-transitory computer-readable medium, and system.

BACKGROUND

[0002] In wireless communications, in a scenario of using a low-frequency carrier, a wireless signal has a relatively small path loss, and a beam formed at each antenna port is a wide beam; and therefore, users of an entire cell can be covered. For example, as shown in FIG. 1, a broadcast channel, a system message, paging, and the like of a network device may be transmitted by using a wide beam, to better cover a terminal device 1 and a terminal device 2.

[0003] However, in a high-frequency scenario, as shown in FIG. 2, a path loss of a wireless signal increases. If a wide beam is still used for transmission, cell coverage becomes very small and cannot cover a relatively remote terminal device 3 and terminal device 4.

[0004] An antenna distance may become smaller in high frequency, so that a unit area can accommodate more antennas. Therefore, a large antenna gain may be obtained by using a massive multiple-input multiple-output (massive MIMO) beamforming (beamforming) technology, to compensate for the path loss. There may be a large quantity of antennas even hundreds of antennas in massive MIMO. When a large antenna gain is obtained, a formed beam (beam) is very narrow in width. One narrow beam can cover only a part of an area, but cannot cover all users in a cell. For example, as shown in FIG. 3, a beam B2 can cover only a terminal device 5, but cannot cover a terminal device 6.

[0005] In a high-frequency multi-beam transmission scenario, to serve the users in the cell, different beams may need to serve the users in the cell in a time division manner, and the beams need common channels such as a broadcast channel, a synchronization channel, and a control channel to cover all the users in the cell, so that the users in the cell are synchronized and obtain a necessary system message to access the cell

[0006] A beamformed control channel is sent by using an existing method for sending a control channel. For example, an existing control channel is a physical downlink control channel (physical downlink control channel, PDCCH), and a beamformed control channel is a beamformed (beamformed) PDCCH. In this case, in one sub-frame, there may be both the PDCCH with large coverage used to serve an old terminal device, and the beamformed PDCCH used to serve a terminal device in enlarged coverage. The PDCCH with wide coverage is demodulated by using a common reference signal (cell-specific reference signals, CRS) with wide coverage. How-

ever, the beamformed PDCCH cannot be demodulated by using the existing CRS, and needs to be demodulated by using a beamformed reference signal. Therefore, when the beamformed PDCCH is used, UE cannot correctly receive the beamformed PDCCH if there is no corresponding beamformed reference signal.

[0007] Therefore, how to transmit a beamformed control channel and a reference signal of the beamformed control channel becomes a problem that urgently needs to be resolved.

[0008] MOTOROLA, "PDCCH Beamforming for LTE-A", 3GPP DRAFT; R1-091331, (20090318), no. Seoul, Korea; 20090318, discloses a PDCCH transmission method for LTE-A, wherein it is proposed, in a general manner, to perform PDCCH beamforming to achieve said performance enhancement.

[0009] QUALCOMM INC, "Beamformed CSI-RS for support of FD-MIMO", vol. RAN WG1, no. Beijing, China; 20150824 - 20150828, (20150823), 3GPP DRAFT; R1-153880, URL: http://www.3gpp.org/ftp/Meetings_3GPP_SYNC/RAN1/Docs/, (20150823), discloses several beamformed CSI-RS based schemes.

SUMMARY

[0010] Aspects of the present invention are provided in the independent claims. Preferred embodiments are provided in the dependent claims.

[0011] The present invention is defined by the method, device, non-transitory computer-readable medium, and system of independent claims. Additional features of the invention are presented in the dependent claims. The scope of the present invention is determined by the scope of the appended claims.

[0012] by using the claimed solution, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0013] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0014] It should be noted that the term "candidate resource" according to this embodiment of the present invention is defined as follows:

[0015] One time-frequency resource set may be divided into a plurality of time-frequency resource subsets, and the candidate resource is a resource that includes one or more time-frequency resource subsets selected based on a specific rule.

[0016] For example, in a Long Term Evolution (Long Term Evolution, LTE) system, the time-frequency re-

source set may be time-frequency resources corresponding to first three orthogonal frequency division multiplexing (orthogonal frequency division multiplexing, OFDM) symbols in a subframe. The time-frequency resource subset may be a control channel element (control channel element, CCE) or an enhanced control channel element (enhanced control channel element, ECCE). The candidate resource is one or more subsets selected based on the specific rule. For example, the candidate resource includes one CCE, two CCEs, four CCEs, or eight CCEs, and a corresponding aggregation level is respectively 1, 2, 4, or 8.

[0017] For example, a network device may determine the first time-frequency resource based on an existing method for determining a PDCCH resource in LTE.

[0018] Optionally, the determining a first time-frequency resource includes:

determining an aggregation level, where the aggregation level is used to indicate a size of the candidate resource; and

selecting one candidate resource from a set of the plurality of candidate resources corresponding to the aggregation level, and using the candidate resource as the first time-frequency resource.

[0019] Specifically, the network device may first determine the aggregation level. The aggregation level is used to indicate the size of the candidate resource. For example, the network device may first determine a PDCCH format (format). A PDCCH format corresponds to a specific aggregation level, the aggregation level corresponds to a quantity of CCEs carrying a PDCCH, and the quantity of CCEs corresponds to a size of a candidate resource in the PDCCH format.

[0020] Then, the candidate resource is selected from the set of the plurality of candidate resources corresponding to the aggregation level, and the candidate resource is used as the first time-frequency resource.

[0021] It should be understood that the aggregation level may include 4 and 8; 1, 2, 4, and 8; or the like. For detailed description of the aggregation level, refer to a definition in an existing standard. Details are not described herein.

[0022] It should be understood that the first time-frequency resource may include a plurality of (a quantity corresponds to an aggregation level) resource element (resource element, RE) sets, and each of the plurality of RE sets includes a same fixed quantity of REs.

[0023] For example, in LTE, an RE set is a control channel element CCE, a PDCCH is carried by at least one CCE, and a quantity of CCEs carrying the PDCCH is determined by an aggregation level. For example, a quantity of CCEs may be 1, 2, 4, or 8. One CCE includes nine resource element groups (resource element group, REG), and one REG includes four REs. In other words, one RE set may include 36 REs. Only LTE is used as an example herein for description. In different systems, one

RE set may include another quantity of REs. This embodiment of the present invention is not limited thereto.

[0024] In the LTE system, the first time-frequency resource may be obtained through respectively aggregating one control channel element CCE, two consecutive CCEs, four consecutive CCEs, or eight consecutive CCEs in first three orthogonal frequency division multiplexing OFDM symbols in a subframe for an aggregation level 1, 2, 4, or 8. For example, as shown in FIG. 5, the first time-frequency resource includes eight CCEs, respectively CCE 0 to CCE 7.

[0025] In other words, the candidate resource set herein may correspond to an existing resource set carrying an existing PDCCH.

BRIEF DESCRIPTION OF DRAWINGS

[0026] To describe the technical solutions in the embodiments of the present invention more clearly, the following briefly describes the accompanying drawings required for describing the embodiments of the present invention. Apparently, the accompanying drawings in the following description show merely some embodiments of the present invention, and a person of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.

FIG. 1 is a schematic diagram of beam coverage; FIG. 2 is another schematic diagram of beam coverage;

FIG. 3 is another schematic diagram of beam coverage;

FIG. 4 is a schematic flowchart of a signal transmission method according to an embodiment of the present invention;

FIG. 5 is a schematic diagram of resource distribution according to an embodiment of the present invention;

FIG. 6 is a schematic diagram of resource distribution according to another embodiment of the present invention;

FIG. 7 is a schematic diagram of resource distribution according to another embodiment of the present invention;

FIG. 8 is a schematic flowchart of a signal transmission method according to another embodiment of the present invention;

FIG. 9 is a schematic diagram of resource distribution according to another embodiment of the present invention;

FIG. 10 is a schematic block diagram of a network device according to an embodiment of the present invention;

FIG. 11 is a schematic block diagram of a terminal device according to an embodiment of the present invention;

FIG. 12 is a schematic block diagram of a network device according to another embodiment of the

present invention;

FIG. 13 is a schematic block diagram of a terminal device according to another embodiment of the present invention;

FIG. 14 is a schematic block diagram of a network device according to another embodiment of the present invention;

FIG. 15 is a schematic block diagram of a terminal device according to another embodiment of the present invention;

FIG. 16 is a schematic block diagram of a network device according to another embodiment of the present invention; and

FIG. 17 is a schematic block diagram of a terminal device according to another embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

[0027] The following clearly and completely describes the technical solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are some but not all of the embodiments of the present invention. All other embodiments obtained by a person of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

[0028] It should be understood that the technical solutions of the embodiments of the present invention can be applied to various communications systems such as a Global System for Mobile Communications (Global System for Mobile Communications, GSM) system, a Code Division Multiple Access (Code Division Multiple Access, CDMA) system, a Wideband Code Division Multiple Access (Wideband Code Division Multiple Access, WCDMA) system, a general packet radio service (general packet radio service, GPRS), a Long Term Evolution (Long Term Evolution, LTE) system, an LTE frequency division duplex (frequency division duplex, FDD) system, LTE time division duplex (time division duplex, TDD), a Universal Mobile Telecommunications System (Universal Mobile Telecommunications System, UMTS), and a Worldwide Interoperability for Microwave Access (Worldwide Interoperability for Microwave Access, WiMAX) communications system. In the embodiments of the present invention, only LTE is used as an example for description. The present invention is not limited thereto.

[0029] It should also be understood that, in the embodiments of the present invention, a network device may be a base transceiver station (base transceiver station, BTS) in a GSM system or a Code Division Multiple Access (Code Division Multiple Access, CDMA) system, a NodeB (NodeB, NB) in a WCDMA system, an evolved NodeB (Evolved NodeB, eNB, or eNodeB) in an LTE system, or a radio controller in a cloud radio access network (cloud radio access network, CRAN). Alternatively, a net-

work device may be a relay station, an access point, an in-vehicle device, a wearable device, a network-side device in a future 5G network, a network device in a future evolved public land mobile network (public land mobile network, PLMN), or the like.

[0030] A terminal device may be referred to as an access terminal, user equipment (user equipment, UE), a subscriber unit, a subscriber station, a mobile station, a mobile console, a remote station, a remote terminal, a mobile device, a user terminal, a terminal, a wireless communications device, a user agent, a user apparatus, or the like. The access terminal may be a cellular phone, a cordless phone, a Session Initiation Protocol (Session Initiation Protocol, SIP) phone, a wireless local loop (wireless local loop, WLL) station, a personal digital assistant (personal digital assistant, PDA), a handheld device having a wireless communications function, a computing device, another processing device connected to a wireless modem, an in-vehicle device, a wearable device, a terminal device in a future 5G network, a terminal device in a future evolved public land mobile network (public land mobile network, PLMN), or the like.

[0031] It should be noted that the term "candidate resource" according to the embodiments of the present invention is defined as follows:

One time-frequency resource set may be divided into a plurality of time-frequency resource subsets, and the candidate resource is a resource that includes one or more time-frequency resource subsets selected based on a specific rule.

[0032] For example, in an LTE system, the time-frequency resource set may be time-frequency resources corresponding to first three OFDM symbols in a sub-frame. The time-frequency resource subset may be a CCE or an ECCE. The candidate resource is one or more subsets selected based on the specific rule. The candidate resource includes one CCE, two CCEs, four CCEs, or eight CCEs, and a corresponding aggregation level is respectively 1, 2, 4, or 8.

[0033] FIG. 4 is a schematic flowchart of a signal sending method according to an embodiment of the present invention. The method shown in FIG. 4 may be applied to the foregoing various communications systems. In FIG. 4, a detailed description is provided by using only an example in which a control channel is a PDCCH in an LTE system. However, this embodiment of the present invention is not limited thereto. In other words, various terms in this embodiment of the present invention may have different names in different systems. This is not limited in this embodiment of the present invention. A communications system in this embodiment of the present invention includes a network device and a terminal device. A method 400 shown in FIG. 4 includes the following steps.

[0034] 410. The network device determines a first time-frequency resource.

[0035] Specifically, the network device determines the first time-frequency resource. The first time-frequency re-

source is a first candidate resource in a plurality of candidate resources.

[0036] In other words, the first time-frequency resource is a candidate resource in a set of the plurality of candidate resources.

[0037] For example, the network device may determine the first time-frequency resource based on an existing method for determining a PDCCH resource in LTE.

[0038] Specifically, the network device may first determine an aggregation level. The aggregation level is used to indicate a size of the candidate resource. For example, the network device may first determine a PDCCH format (format). A PDCCH format corresponds to a specific aggregation level, the aggregation level corresponds to a quantity of CCEs carrying a PDCCH, and the quantity of CCEs corresponds to a size of a candidate resource in the PDCCH format.

[0039] Then, the candidate resource is selected from a set of a plurality of candidate resources corresponding to the aggregation level, and the candidate resource is used as the first time-frequency resource.

[0040] It should be understood that the aggregation level may include 4 and 8; 1, 2, 4, and 8; or the like. For detailed description of the aggregation level, refer to a definition in an existing standard. Details are not described herein.

[0041] It should be understood that the first time-frequency resource may include a plurality of (a quantity corresponds to an aggregation level) resource element RE sets, and each of the plurality of RE sets includes a same fixed quantity of REs.

[0042] For example, in LTE, an RE set is a control channel element CCE, a PDCCH is carried by at least one CCE, and a quantity of CCEs carrying the PDCCH is determined by an aggregation level. For example, a quantity of CCEs may be 1, 2, 4, or 8. One CCE includes nine resource element groups (resource element group, REG), and one REG includes four REs. In other words, one RE set may include 36 REs. Only LTE is used as an example herein for description. In different systems, one RE set may include another quantity of REs. This embodiment of the present invention is not limited thereto.

[0043] In the LTE system, the first time-frequency resource may be obtained through respectively aggregating one control channel element CCE, two consecutive CCEs, four consecutive CCEs, or eight consecutive CCEs in first three orthogonal frequency division multiplexing OFDM symbols in a subframe for an aggregation level 1, 2, 4, or 8. For example, as shown in FIG. 5, the first time-frequency resource includes eight CCEs, respectively CCE 0 to CCE 7.

[0044] In other words, the candidate resource set herein may correspond to an existing resource set carrying an existing PDCCH.

[0045] In this embodiment of the present invention, the first time-frequency resource may be used to carry a beamformed PDCCH, and may be used to carry a reference signal of the beamformed PDCCH.

[0046] It should be understood that the plurality of candidate resources in this embodiment of the present invention may include candidate resources corresponding to all aggregation levels, or may include candidate resources corresponding to one aggregation level. This is not limited in this embodiment of the present invention.

[0047] It should be understood that the foregoing describes a process of determining the first time-frequency resource based on the existing method for determining a PDCCH resource in LTE, and describes an example in which the first time-frequency resource may include a plurality of CCEs. In this embodiment of the present invention, alternatively, the first time-frequency resource may be the first time-frequency resource that is determined by the network device based on an existing method for determining an EPDCCH resource in LTE. The EPDCCH is carried by at least one ECCE. A quantity of ECCEs carrying the EPDCCH is determined based on an EPDCCH format. Each EPDCCH format corresponds to a specific aggregation level, and the aggregation level corresponds to a specific quantity of ECCEs. An EPDCCH candidate resource set may correspond to a resource set that includes a specific quantity of ECCEs corresponding to an EPDCCH format. Each ECCE may include four or eight REGs. The aggregation level corresponding to the EPDCCH format includes 1, 2, 4, 8, 16, and 32. In other words, a corresponding first time-frequency resource may include 1, 2, 4, 8, 16, and 32 ECCEs.

[0048] Therefore, in this embodiment of the present invention, based on the existing method, the first resource is determined for carrying a beamformed control channel and a reference signal subsequently. Because this is the same as an existing manner, sending a beamformed control channel and a reference signal of the beamformed control channel in this embodiment of the present invention has no impact on or has slight impact on compatibility of a conventional terminal device.

[0049] 420. The network device obtains a second time-frequency resource and a third time-frequency resource.

[0050] Specifically, the network device obtains the second time-frequency resource and the third time-frequency resource based on the first time-frequency resource and a preset rule. The third time-frequency resource includes at least one resource element RE at a predefined location in the first time-frequency resource, and the second time-frequency resource includes a resource other than the third time-frequency resource in the first time-frequency resource. The preset rule indicates the predefined location. The second time-frequency resource is used to carry a beamformed control channel, and the third time-frequency resource is used to carry a reference signal of the beamformed control channel.

[0051] In other words, in this embodiment of the present invention, the existing first time-frequency resource carrying a control channel carries both the beamformed control channel and the reference signal of the beamformed control channel, to send the beamformed

control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in the existing system.

[0052] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0053] It should be understood that the preset rule in this embodiment of the present invention may be a rule preset in the system. In other words, the preset rule may be a rule on which the network device and the terminal device preagree. After the first resource is determined, the network device and the terminal device may obtain the second resource and the third resource based on the preset rule.

[0054] Specifically, the third time-frequency resource may include the at least one resource element RE in the first time-frequency resource, and the second time-frequency resource includes the resource other than the third time-frequency resource in the first time-frequency resource.

[0055] Specifically, the third time-frequency resource may include an RE in at least one of the foregoing plurality of RE sets.

[0056] For example, the third time-frequency resource may include only one RE in one RE set; or may include REs in a plurality of RE sets, where one RE set has only one RE that belongs to the third time-frequency resource; or may include an RE in each RE set.

[0057] For another example, the third time-frequency resource may include an RE at a preset location in each of the foregoing plurality of RE sets.

[0058] For example, in the LTE system, the preset location may be an n^{th} RE in each REG in each CCE. Herein, n may be 1, 2, 3, or 4. For example, as shown in FIG. 6, the first time-frequency resource includes eight CCEs, and the third time-frequency resource may include a second RE (for example, an RE 1 in a REG 0) in each REG in each CCE. In FIG. 3, for ease of description, a CCE 3 is used as an example to show REs included in the first time-frequency resource. REs at corresponding locations in other CCEs all belong to the third time-frequency resource. This is not shown in FIG. 6.

[0059] It should be understood that in FIG. 6, for ease of description, a description is provided in a case in which preset locations in RE sets are the same, to be specific, the preset locations are a second RE in each REG. However, in this embodiment of the present invention, preset locations in different RE sets may be the same or may be different. This is not limited in this embodiment of the present invention.

[0060] Alternatively, the third time-frequency resource may include all REs in at least one of the foregoing plurality of RE sets.

[0061] For example, the third time-frequency resource may include only all REs in one RE set, or may include all REs in the plurality of RE sets.

[0062] For example, when the first time-frequency resource includes a plurality of CCEs, the third time-frequency resource may include all REs in at least one of the plurality of CCEs.

[0063] It should be understood that the third time-frequency resource may include all the REs in the at least one of the plurality of CCEs provided that the third time-frequency resource is less than the first time-frequency resource; and the resource other than the third time-frequency resource in the first time-frequency resource is the second time-frequency resource. Similarly, in this embodiment of the present invention, the second resource also needs to be less than the first time-frequency resource, and a resource other than the second time-frequency resource in the first time-frequency resource is the third time-frequency resource.

[0064] For example, as shown in FIG. 7, the first time-frequency resource includes eight CCEs, and the third time-frequency resource may include one CCE, for example, all REs in the CCE 3.

[0065] It should be understood that the preset rule may be a rule on which the network device and the terminal device preagree. After the first resource is determined, the network device and the terminal device may obtain the second resource and the third resource based on the preset rule. Alternatively, the preset rule may be notified by the network device to the terminal device by using signaling. To be specific, the network device sends a message in advance to agree on the preset rule with the terminal device.

[0066] Correspondingly, in another embodiment, before 410, the method may further include: sending an indication message to the terminal device, where the indication message indicates the predefined location.

[0067] For example, the indication message may be an RRC signaling message. This embodiment of the present invention is not limited thereto.

[0068] 430. Send a beamformed control channel and a reference signal of the beamformed control channel.

[0069] Specifically, the network device respectively transmits, to the terminal device by using the second time-frequency resource and the third time-frequency resource, the beamformed control channel and the reference signal RS corresponding to the beamformed control channel.

[0070] Therefore, the terminal device may demodulate the beamformed control channel based on the received reference signal of the beamformed control channel. For example, the terminal device receives a signal on a candidate resource in the candidate resource set in searching space. When blind detection is performed on a candidate resource, for example, the candidate resource

may be the first time-frequency resource. The terminal device demodulates, based on the reference signal on the third time-frequency resource at the predefined location, the control channel carried in the second time-frequency resource; decodes information bits of the received control channel; performs CRC check based on an ID of the terminal device; and if the check succeeds, it indicates that the control channel that is sent to the terminal device is successively received, in other words, the blindly detected candidate resource is the first time-frequency resource. If the check fails, it indicates that a base station does not send the control channel on the candidate resource to the terminal device, in other words, the blindly detected candidate resource is not the first time-frequency resource.

[0071] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0072] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0073] The foregoing describes in detail the signal sending method according to the embodiments of the present invention with reference to FIG. 4 to FIG. 7. The following describes in detail a signal sending method according to another embodiment of the present invention with reference to FIG. 8.

[0074] It should be understood that a difference between FIG. 7 and FIG. 8 is that a first time-frequency resource in FIG. 7 is used to transmit both a beamformed control channel and a reference signal of the beamformed control channel, but a first time-frequency resource in FIG. 8 is used to carry only a beamformed control channel, and the beamformed control channel may be carried in another resource, for example, a candidate resource in a candidate resource set or a resource used to carry another channel or a reference signal. Specifically, the following describes the signal sending method in detail with reference to FIG. 8.

[0075] FIG. 8 is a schematic flowchart of a signal sending method according to an embodiment of the present invention. The method shown in FIG. 8 may be applied to the foregoing various communications systems. In FIG. 8, a detailed description is provided by using only an example in which a control channel is a PDCCH in an LTE system. However, this embodiment of the present

invention is not limited thereto. In other words, various terms in this embodiment of the present invention may have different names in different systems. This is not limited in this embodiment of the present invention. A communications system in this embodiment of the present invention includes a network device and a terminal device. A method 800 shown in FIG. 8 includes the following steps.

[0076] 810. The network device determines a first time-frequency resource.

[0077] Specifically, the network device determines the first time-frequency resource. The first time-frequency resource is a first candidate resource in a plurality of candidate resources, and the first time-frequency resource is used to carry a beamformed control channel.

[0078] In other words, the first time-frequency resource is a candidate resource in a set of the plurality of candidate resources.

[0079] For example, the network device may determine the first time-frequency resource based on an existing method for determining a PDCCH resource in LTE.

[0080] Specifically, the network device may first determine an aggregation level. The aggregation level is used to indicate a size of the candidate resource. For example, the network device may first determine a PDCCH format (format). A PDCCH format corresponds to a specific aggregation level, the aggregation level corresponds to a quantity of CCEs carrying a PDCCH, and the quantity of CCEs corresponds to a size of a candidate resource in the PDCCH format.

[0081] Then, the candidate resource is selected from a set of a plurality of candidate resources corresponding to the aggregation level, and the candidate resource is used as the first time-frequency resource.

[0082] It should be understood that the aggregation level may include 4 and 8; 1, 2, 4, and 8; or the like. For detailed description of the aggregation level, refer to a definition in an existing standard. Details are not described herein.

[0083] It should be understood that the first time-frequency resource may include a plurality of (a quantity corresponds to an aggregation level) resource element RE sets, and each of the plurality of RE sets includes a same fixed quantity of REs.

[0084] For example, in LTE, an RE set is a control channel element CCE, a PDCCH is carried by at least one CCE, and a quantity of CCEs carrying the PDCCH is determined by an aggregation level. For example, a quantity of CCEs may be 1, 2, 4, or 8. One CCE includes nine resource element groups (resource element group, REG), and one REG includes four REs. In other words, one RE set may include 36 REs. Only LTE is used as an example herein for description. In different systems, one RE set may include another quantity of REs. This embodiment of the present invention is not limited thereto.

[0085] In the LTE system, the first time-frequency resource may be obtained through respectively aggregating one control channel element CCE, two consecutive

CCEs, four consecutive CCEs, or eight consecutive CCEs in first three orthogonal frequency division multiplexing OFDM symbols in a subframe for an aggregation level 1, 2, 4, or 8. For example, as shown in FIG. 5, the first time-frequency resource includes eight CCEs, respectively CCE 0 to CCE 7.

[0086] In other words, the candidate resource set herein may correspond to an existing resource set carrying an existing PDCCH.

[0087] In this embodiment of the present invention, the first time-frequency resource may be used to carry a beamformed PDCCH.

[0088] It should be understood that the plurality of candidate resources in this embodiment of the present invention may include candidate resources corresponding to all aggregation levels, or may include candidate resources corresponding to one aggregation level. This is not limited in this embodiment of the present invention.

[0089] It should be understood that the foregoing describes a process of determining the first time-frequency resource based on the existing method for determining a PDCCH resource in LTE, and describes an example in which the first time-frequency resource may include a plurality of CCEs. In this embodiment of the present invention, alternatively, the first time-frequency resource may be the first time-frequency resource that is determined by the network device based on an existing method for determining an EPDCCH resource in LTE. The EPDCCH is carried by at least one ECCE. A quantity of ECCEs carrying the EPDCCH is determined based on an EPDCCH format. Each EPDCCH format corresponds to a specific aggregation level, and the aggregation level corresponds to a specific quantity of ECCEs. An EPDCCH candidate resource set may correspond to a resource set that includes a specific quantity of ECCEs corresponding to an EPDCCH format. Each ECCE may include four or eight EREGs. The aggregation level corresponding to the EPDCCH format includes 1, 2, 4, 8, 16, and 32. In other words, a corresponding first time-frequency resource may include 1, 2, 4, 8, 16, and 32 ECCEs.

[0090] Therefore, in this embodiment of the present invention, based on the existing method, the first resource is determined for carrying a beamformed control channel subsequently. Because this is the same as an existing manner, sending a beamformed control channel in this embodiment of the present invention has no impact on or has slight impact on compatibility of a conventional terminal device.

[0091] 820. The network device determines a second time-frequency resource.

[0092] Specifically, the second time-frequency resource is a second candidate resource in the plurality of candidate resources, or the second time-frequency resource is a resource other than the plurality of candidate resources configured for the terminal device, and the second time-frequency resource is used to carry a reference signal of the beamformed control channel.

[0093] In other words, the second time-frequency resource may be a resource other than the first time-frequency resource and a third time-frequency resource, and the third time-frequency resource includes a time-frequency resource corresponding to a reference signal of another control channel other than the beamformed control channel. A beam of the another control channel is different from a beam of the beamformed control channel.

[0094] The following separately describes in detail a case in which the second time-frequency resource is the second candidate resource and a case in which the second time-frequency resource is the resource other than the plurality of candidate resources configured for the terminal device.

[0095] When the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource may be the second candidate resource predefined in the plurality of candidate resources.

[0096] In other words, the second time-frequency resource is a predefined resource, and the predefined resource is one of the plurality of candidate resources, namely, the second candidate resource.

[0097] In other words, the second resource is a predefined resource, to be specific, a resource predefined in the system or a resource on which the network device and the terminal device preagree. Both the network device and the terminal device learn of a location of the second resource in advance, and the second resource carries the reference signal of the beamformed control channel.

[0098] It should be understood that the second time-frequency resource and the first time-frequency resource may have a same size (for example, a same aggregation level) or may have different sizes. This is not limited in this embodiment of the present invention.

[0099] For example, the second time-frequency resource and the first time-frequency resource may have a same size (for example, a same aggregation level). In other words, the second time-frequency resource is a candidate resource other than the first time-frequency resource in the set of the plurality of candidate resources corresponding to the first time-frequency resource. For example, in the LTE system, each of aggregation levels of the first time-frequency resource and the second time-frequency resource is 1, 2, 4, 8, or the like.

[0100] For another example, a size of the second time-frequency resource is different from a size of the second time-frequency resource. In other words, the second time-frequency resource is a candidate resource in another set of candidate resources. For example, in the LTE system, an aggregation level of the first time-frequency resource is 2, and an aggregation level of the second candidate resource is 4 or the like.

[0101] In addition, when the second time-frequency resource is the second candidate resource in the plurality

of candidate resources,

the second time-frequency resource is the second candidate resource configured for the terminal device.

[0102] For example, the network device may send, to the terminal device, a message that is used to configure the second resource as the second candidate resource. For example, the message may be an RRC signaling message. However, this embodiment of the present invention is not limited thereto.

[0103] In addition, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the network device may determine the second candidate time-frequency resource based on a preset mapping relationship between the first time-frequency resource and the second time-frequency resource.

[0104] In a case, the second candidate time-frequency resource may be one of candidate resources that have a same size as the first time-frequency resource and that are in the plurality of candidate resources.

[0105] For example, the network device may determine the second time-frequency resource based on the preset mapping relationship between the first time-frequency resource and the second time-frequency resource. The second time-frequency resource is another candidate resource other than the first time-frequency resource in the candidate resources that have a same size.

[0106] For example, the mapping relationship indicates that the second time-frequency resource may be a candidate resource adjacent to the first time-frequency resource, a time-frequency resource at a fixed distance from the first time-frequency resource, or the like.

[0107] For example, as shown in FIG. 9, the candidate resource set includes 10 candidate resources, respectively a candidate resource 1 to a candidate resource 10. If the mapping relationship indicates that the second time-frequency resource may be a first right-adjacent candidate resource of the first time-frequency resource, the second time-frequency resource is a candidate resource 6 when the first time-frequency resource is a candidate resource 5.

[0108] For another example, if the mapping relationship indicates that the second time-frequency resource may be a candidate resource at a distance of 2 to the first time-frequency resource on the right, the second time-frequency resource is a candidate resource 8 at a distance of 2 to a candidate resource 5 on the right when the first time-frequency resource is the candidate resource 5.

[0109] It should be noted that different candidate resources may overlap in actual application, there may be a distance between adjacent candidate resources, and FIG. 9 describes only an example of candidate resources for ease of description. However, this is not limited in this embodiment of the present invention.

[0110] It should be understood that the mapping relationship may be preagreed on by the network device and

the terminal device, for example, may be sent by the network device to the terminal device in advance. This is not limited in this embodiment of the present invention.

[0111] In another case, the second candidate time-frequency resource is a candidate resource that is in candidate resources of a specified size in the plurality of candidate resources and that does not overlap with the first time-frequency resource.

[0112] For example, the specified size may be an aggregation level 1, 2, 4, 8, or the like. The specified size may be the same as or different from the size of the first time-frequency resource. This is not limited in this embodiment of the present invention.

[0113] For example, the specified size may be an aggregation level 4, and the second time-frequency resource may be a candidate resource that is in a plurality of candidate resources whose aggregation levels are 4 and that has a smallest or a largest number in candidate resources that do not overlap with the first time-frequency resource. This embodiment of the present invention is not limited thereto. However, it should be understood that the network device and the terminal device need to have a consistent rule for determining the second time-frequency resource. For example, both the network device and the terminal device agree that the second time-frequency resource is a candidate resource that has a smallest number in a set of a plurality of candidate resources of a specified size and that does not overlap with the first time-frequency resource.

[0114] When the second time-frequency resource is the resource other than the plurality of candidate resources configured for the terminal device, the second time-frequency resource includes a resource other than the first time-frequency resource configured by the network device for the terminal device.

[0115] For example, the second time-frequency resource includes a time-frequency resource corresponding to another reference signal other than a common reference signal CRS, or the second time-frequency resource includes a time-frequency resource corresponding to a data channel.

[0116] Specifically, the network device may send an indication message for configuration to the terminal device. The indication message indicates a location of the second time-frequency resource. For example, the indication message may be an RRC signaling message. However, this embodiment of the present invention is not limited thereto.

[0117] For example, in LTE, the second time-frequency resource may be a time-frequency resource in a fourth to a 14th OFDM symbols in a subframe.

[0118] For example, the second time-frequency resource may include a resource that corresponds to a PDSCH and that is in the fourth to the 14th OFDM symbols in the subframe.

[0119] Specifically, the second time-frequency resource may include at least one RE in a zero-power user status information-reference signal zero-power CSI-RS

resource configured for the user equipment.

[0120] Alternatively, the third time-frequency resource may include at least one RE that is in the fourth to the 14th OFDM symbols in the subframe and that is in a non-zero power user status information-reference signal non-zero power CSI-RS resource configured for the user equipment.

[0121] Therefore, in this embodiment of the present invention, the existing first time-frequency resource carrying a control channel carries the beamformed control channel, and another resource (the second time-frequency resource) carries the reference signal of the beamformed control channel, to send the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in the existing system.

[0122] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0123] 830. Send a beamformed control channel and a reference signal of the beamformed control channel.

[0124] Specifically, the network device respectively transmits, to the terminal device by using the first time-frequency resource and the second time-frequency resource, the beamformed control channel and the reference signal RS corresponding to the beamformed control channel.

[0125] Therefore, the terminal device may demodulate the beamformed control channel based on the received reference signal of the beamformed control channel. For example, the terminal device receives a signal on a candidate resource in the candidate resource set in searching space. When blind detection is performed on a candidate resource, for example, the candidate resource may be the first time-frequency resource.

[0126] The terminal device detects the second time-frequency resource. The terminal device may determine the reference signal on the second time-frequency resource in one of the foregoing four manners. The terminal device demodulates, based on the reference signal on the second time-frequency resource, the control channel carried in the first time-frequency resource; decodes information bits of the received control channel; performs CRC check based on an ID of the terminal device; and if the check succeeds, it indicates that the control channel that is sent to the terminal device is successively received, in other words, the blindly detected candidate resource is the first time-frequency resource. If the check fails, it indicates that a base station does not send the control channel on the candidate resource to the terminal

device, in other words, the blindly detected candidate resource is not the first time-frequency resource.

[0127] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0128] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0129] The foregoing describes in detail the signal sending method according to the embodiments of the present invention with reference to FIG. 4 to FIG. 9. The following describes a device configured for signal phase synchronization in a communications system according to embodiments of the present invention with reference to FIG. 10 to FIG. 17.

[0130] FIG. 10 is a schematic block diagram of a network device 1000 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 10, the network device 1000 includes:

a determining unit 1010, configured to determine a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources;

an obtaining unit 1020, configured to obtain a second time-frequency resource and a third time-frequency resource based on the first time-frequency resource and a preset rule, where the third time-frequency resource includes at least one resource element RE at a predefined location in the first time-frequency resource, the second time-frequency resource includes a resource other than the third time-frequency resource in the first time-frequency resource, the preset rule indicates the predefined location, the second time-frequency resource is used to carry a beamformed control channel, and the third time-frequency resource is used to carry a reference signal of the beamformed control channel; and

a sending unit 1030, configured to respectively transmit the beamformed control channel and the reference signal of the beamformed control channel to a terminal device by using the second time-frequency resource and the third time-frequency resource.

[0131] Therefore, in this embodiment of the present invention, resources carrying the beamformed control

channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0132] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0133] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes an RE at a preset location in each of the plurality of RE sets.

[0134] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes all REs in at least one of the plurality of RE sets.

[0135] Optionally, the sending unit is further configured to: before the determining unit determines the first time-frequency resource, send an indication message to the terminal device. The indication message indicates the preset rule.

[0136] Optionally, the determining unit is specifically configured to:

- determine an aggregation level, where the aggregation level is used to indicate a size of the candidate resource; and
- select one candidate resource from a set of the plurality of candidate resources corresponding to the aggregation level, and use the candidate resource as the first time-frequency resource.

[0137] It should be understood that the network device 1000 shown in FIG. 10 can implement processes related to the network device in the embodiment of FIG. 4. Operations and/or functions of modules of the network device 1000 are respectively used for implementing corresponding processes in the method embodiment of FIG. 4. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0138] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beam-

forming in an existing system.

[0139] FIG. 11 is a schematic block diagram of a terminal device 1100 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 11, the terminal device 1100 includes:

a detection unit 1110, configured to detect a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources;

an obtaining unit 1120, configured to obtain a second time-frequency resource and a third time-frequency resource based on the first time-frequency resource and a preset rule, where the third time-frequency resource includes at least one resource element RE at a predefined location in the first time-frequency resource, the second time-frequency resource includes a resource other than the third time-frequency resource in the first time-frequency resource, the preset rule indicates the predefined location, the second time-frequency resource is used to carry a beamformed control channel, and the third time-frequency resource is used to carry a reference signal of the beamformed control channel; and

a demodulation unit 1130, configured to demodulate, based on the reference signal that is of the beamformed control channel and that is carried in the third time-frequency resource, the beamformed control channel carried in the second time-frequency resource.

[0140] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0141] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes an RE at a preset location in each of the plurality of RE sets.

[0142] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes all REs in at least one of the plurality of RE sets.

[0143] Optionally, the terminal device may further include:

a receiving unit, configured to: before the detection unit detects the first time-frequency resource, receive an indication message, where the indication message indicates the preset rule.

[0144] It should be understood that the terminal device 1100 shown in FIG. 11 can implement processes related to the terminal device in the embodiment of FIG. 4. Op-

erations and/or functions of modules of the terminal device 1100 are respectively used for implementing corresponding processes in the method embodiment of FIG. 4. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0145] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0146] FIG. 12 is a schematic block diagram of a network device 1200 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 12, the network device 1200 includes:

a first determining unit 1210, configured to determine a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources, and the first time-frequency resource is used to carry a beamformed control channel;

a second determining unit 1220, configured to determine a second time-frequency resource, where the second time-frequency resource is a second candidate resource in the plurality of candidate resources, or the second time-frequency resource is a resource other than the plurality of candidate resources configured for a terminal device, a third time-frequency resource includes a time-frequency resource corresponding to a reference signal of another control channel other than the beamformed control channel, and the second time-frequency resource is used to carry a reference signal of the beamformed control channel; and

a sending unit 1230, configured to respectively transmit the beamformed control channel and the reference signal of the beamformed control channel to the terminal device by using the first time-frequency resource and the second time-frequency resource.

[0147] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0148] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve

coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0149] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource is the second candidate resource predefined in the plurality of candidate resources.

[0150] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource is the second candidate resource configured for the terminal device.

[0151] Optionally, when the second time-frequency resource is the resource other than the plurality of candidate resources configured for the terminal device, the second time-frequency resource includes a time-frequency resource corresponding to another reference signal other than a common reference signal CRS, or the second time-frequency resource includes a time-frequency resource corresponding to a data channel.

[0152] Optionally, the sending unit is further configured to: before the second determining unit determines the second time-frequency resource, send an indication message to the terminal device. The indication message indicates a location of the second time-frequency resource.

[0153] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second determining unit is specifically configured to:

determine the second candidate time-frequency resource based on a preset mapping relationship between the first time-frequency resource and the second time-frequency resource.

[0154] Optionally, the second candidate time-frequency resource is one of candidate resources that have a same size as the first time-frequency resource and that are in the plurality of candidate resources.

[0155] Optionally, the second candidate time-frequency resource is a candidate resource that is in candidate resources of a specified size in the plurality of candidate resources and that does not overlap with the first time-frequency resource.

[0156] Optionally, the first determining unit is specifically configured to:

determine an aggregation level, where the aggregation level is used to indicate a size of the candidate resource; and

select one candidate resource from a set of the plurality of candidate resources corresponding to the aggregation level, and use the candidate resource as the first time-frequency resource.

[0157] It should be understood that the network device

1200 shown in FIG. 12 can implement processes related to the network device in the embodiment of FIG. 8. Operations and/or functions of modules of the network device 1200 are respectively used for implementing corresponding processes in the method embodiment of FIG. 8. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0158] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0159] FIG. 13 is a schematic block diagram of a terminal device 1300 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 13, the terminal device 1300 includes:

a first detection unit 1310, configured to detect a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources, and the first time-frequency resource is used to carry a beamformed control channel;

a second detection unit 1320, configured to detect a second time-frequency resource, where the second time-frequency resource is a second candidate resource in the plurality of candidate resources, or the second time-frequency resource is a resource other than the plurality of candidate resources configured for the terminal device, and the second time-frequency resource is used to carry a reference signal of the beamformed control channel; and

a demodulation unit 1330, configured to demodulate, based on the reference signal that is of the beamformed control channel and that is carried in the second time-frequency resource, the beamformed control channel carried in the first time-frequency resource.

[0160] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0161] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource is the second candidate resource predefined in the plurality of candidate resources.

[0162] Optionally, when the second time-frequency re-

source is the second candidate resource in the plurality of candidate resources,

the second time-frequency resource is the second candidate resource configured for the terminal device.

[0163] Optionally, when the second time-frequency resource is the resource other than the plurality of candidate resources configured for the terminal device, the second time-frequency resource includes a time-frequency resource corresponding to another reference signal other than a common reference signal CRS, or the second time-frequency resource includes a time-frequency resource corresponding to a data channel.

[0164] Optionally, the terminal device further includes: a receiving unit, configured to: before the second detection unit detects the second time-frequency resource, receive an indication message sent by the network device, where the indication message indicates a location of the second time-frequency resource.

[0165] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources,

the second time-frequency resource is the second candidate resource determined based on a preset mapping relationship between the first time-frequency resource and the second time-frequency resource.

[0166] Optionally, the second candidate time-frequency resource is one of candidate resources that have a same size as the first time-frequency resource and that are in the plurality of candidate resources.

[0167] Optionally, the second candidate time-frequency resource is a candidate resource that is in candidate resources of a specified size in the plurality of candidate resources and that does not overlap with the first time-frequency resource.

[0168] It should be understood that the terminal device 1300 shown in FIG. 13 can implement processes related to the terminal device in the embodiment of FIG. 8. Operations and/or functions of modules of the terminal device 1300 are respectively used for implementing corresponding processes in the method embodiment of FIG. 8. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0169] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0170] FIG. 14 is a schematic block diagram of a network device 1400 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 14, the network device 1400 includes a processor 1410 and a transceiver 1420. The processor 1410 is connected to the transceiver 1420. Optionally, the network device 1400 further includes a memory 1430. The mem-

ory 1430 is connected to the processor 1410. Optionally, the apparatus 1400 further includes a bus system 1440. The processor 1410, the memory 1430, and the transceiver 1420 may be connected by using the bus system 1440. The memory 1430 may be configured to store an instruction. The processor 1410 is configured to execute the instruction stored in the memory 1430, to control the transceiver 1420 to send information or a signal.

[0171] The processor 1410 is configured to: determine a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources; and obtain a second time-frequency resource and a third time-frequency resource based on the first time-frequency resource and a preset rule, where the third time-frequency resource includes at least one resource element RE at a predefined location in the first time-frequency resource, the second time-frequency resource includes a resource other than the third time-frequency resource in the first time-frequency resource, the preset rule indicates the predefined location, the second time-frequency resource is used to carry a beamformed control channel, and the third time-frequency resource is used to carry a reference signal of the beamformed control channel.

[0172] The transceiver 1420 is configured to respectively transmit the beamformed control channel and the reference signal of the beamformed control channel to a terminal device by using the second time-frequency resource and the third time-frequency resource.

[0173] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0174] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0175] It should be understood that in this embodiment of the present invention, the processor 1410 may be a central processing unit (central processing unit, CPU for short), or the processor 1410 may be another general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field programmable gate array (FPGA) or another programmable logic device, a discrete gate or a transistor logic device, a discrete hardware component, or the like. The general-purpose processor may be a microprocessor, or the processor may be any conventional processor, or the like.

[0176] The memory 1430 may include a read-only memory and a random access memory, and provides an instruction and data for the processor 1410. A part of the memory 1430 may further include a nonvolatile random access memory. For example, the memory 1430 may further store information about a device type.

[0177] In addition to a data bus, the bus system 1440 may further include a power bus, a control bus, a status signal bus, and the like. However, for clarity of description, various buses are marked as the bus system 1440 in the figure.

[0178] In an implementation process, the steps of the foregoing method may be completed by using a hardware integrated logic circuit or an instruction in a software form in the processor 1410. The steps of the method disclosed with reference to the embodiments of the present invention may be directly implemented by using a hardware processor, or may be implemented by using a combination of a hardware module and a software module in the processor. The software module may be located in a mature storage medium in the art such as a random memory, a flash memory, a read-only memory, a programmable read-only memory, an electrically erasable programmable memory, or a register. The storage medium is located in the memory 1430. The processor 1410 reads information from the memory 1430, and completes the steps of the foregoing method in combination with hardware of the processor 1410. To avoid repetition, details are not described herein.

[0179] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes an RE at a preset location in each of the plurality of RE sets.

[0180] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes all REs in at least one of the plurality of RE sets.

[0181] Optionally, the sending unit is further configured to: before the determining unit determines the first time-frequency resource, send an indication message to the terminal device. The indication message indicates the preset rule.

[0182] Optionally, the processor 1410 is specifically configured to:

determine an aggregation level, where the aggregation level is used to indicate a size of the candidate resource; and

select one candidate resource from a set of the plurality of candidate resources corresponding to the aggregation level, and use the candidate resource as the first time-frequency resource.

[0183] It should be understood that the network device 1400 shown in FIG. 14 can implement processes related to the network device in the embodiment of FIG. 4. Op-

erations and/or functions of modules of the network device 1400 are respectively used for implementing corresponding processes in the method embodiment of FIG. 4. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0184] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0185] FIG. 15 is a schematic block diagram of a network device 1500 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 15, the network device 1500 includes a processor 1510 and a transceiver 1520. The processor 1510 is connected to the transceiver 1520. Optionally, the network device 1500 further includes a memory 1530. The memory 1530 is connected to the processor 1510. Optionally, the apparatus 1500 further includes a bus system 1540. The processor 1510, the memory 1530, and the transceiver 1520 may be connected by using the bus system 1540. The memory 1530 may be configured to store an instruction. The processor 1510 is configured to execute the instruction stored in the memory 1530, to control the transceiver 1520 to send information or a signal.

[0186] The processor 1510 is configured to: detect a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources;

obtain a second time-frequency resource and a third time-frequency resource based on the first time-frequency resource and a preset rule, where the third time-frequency resource includes at least one resource element RE at a predefined location in the first time-frequency resource, the second time-frequency resource includes a resource other than the third time-frequency resource in the first time-frequency resource, the preset rule indicates the predefined location, the second time-frequency resource is used to carry a beamformed control channel, and the third time-frequency resource is used to carry a reference signal of the beamformed control channel; and

demodulate, based on the reference signal that is of the beamformed control channel and that is carried in the third time-frequency resource, the beamformed control channel carried in the second time-frequency resource.

[0187] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed

control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0188] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0189] It should be understood that in this embodiment of the present invention, the processor 1510 may be a central processing unit (central processing unit, CPU for short), or the processor 1510 may be another general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field programmable gate array (FPGA) or another programmable logic device, a discrete gate or a transistor logic device, a discrete hardware component, or the like. The general-purpose processor may be a microprocessor, or the processor may be any conventional processor, or the like.

[0190] The memory 1530 may include a read-only memory and a random access memory, and provides an instruction and data for the processor 1510. Apart of the memory 1530 may further include a nonvolatile random access memory. For example, the memory 1530 may further store information about a device type.

[0191] In addition to a data bus, the bus system 1540 may further include a power bus, a control bus, a status signal bus, and the like. However, for clarity of description, various buses are marked as the bus system 1540 in the figure.

[0192] In an implementation process, the steps of the foregoing method may be completed by using a hardware integrated logic circuit or an instruction in a software form in the processor 1510. The steps of the method disclosed with reference to the embodiments of the present invention may be directly implemented by using a hardware processor, or may be implemented by using a combination of a hardware module and a software module in the processor. The software module may be located in a mature storage medium in the art such as a random memory, a flash memory, a read-only memory, a programmable read-only memory, an electrically erasable programmable memory, or a register. The storage medium is located in the memory 1530. The processor 1510 reads information from the memory 1530, and completes the steps of the foregoing method in combination with hardware of the processor 1510. To avoid repetition, details are not described herein.

[0193] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes an

RE at a preset location in each of the plurality of RE sets.

[0194] Optionally, the first time-frequency resource includes a plurality of resource element RE sets, each of the plurality of RE sets includes a same fixed quantity of REs, and the third time-frequency resource includes all REs in at least one of the plurality of RE sets.

[0195] Optionally, the transceiver 1520 is configured to: before the detection unit detects the first time-frequency resource, receive an indication message. The indication message indicates the preset rule.

[0196] It should be understood that the terminal device 1500 shown in FIG. 15 can implement processes related to the terminal device in the embodiment of FIG. 4. Operations and/or functions of modules of the terminal device 1500 are respectively used for implementing corresponding processes in the method embodiment of FIG. 4. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0197] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0198] FIG. 16 is a schematic block diagram of a network device 1600 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 16, the network device 1600 includes a processor 1610 and a transceiver 1620. The processor 1610 is connected to the transceiver 1620. Optionally, the network device 1600 further includes a memory 1630. The memory 1630 is connected to the processor 1610. Optionally, the apparatus 1600 further includes a bus system 1640. The processor 1610, the memory 1630, and the transceiver 1620 may be connected by using the bus system 1640. The memory 1630 may be configured to store an instruction. The processor 1610 is configured to execute the instruction stored in the memory 1630, to control the transceiver 1620 to send information or a signal.

[0199] The processor 1610 is configured to: determine a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources, and the first time-frequency resource is used to carry a beamformed control channel; and

determine a second time-frequency resource, where the second time-frequency resource is a second candidate resource in the plurality of candidate resources, or the second time-frequency resource is a resource other than the plurality of candidate resources configured for a terminal device, and the second time-frequency resource is used to carry a reference signal of the beamformed control channel.

[0200] The transceiver 1620 is configured to respectively transmit the beamformed control channel and the

reference signal of the beamformed control channel to the terminal device by using the second time-frequency resource and the third time-frequency resource.

[0201] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0202] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0203] It should be understood that in this embodiment of the present invention, the processor 1610 may be a central processing unit (central processing unit, CPU for short), or the processor 1610 may be another general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field programmable gate array (FPGA) or another programmable logic device, a discrete gate or a transistor logic device, a discrete hardware component, or the like. The general-purpose processor may be a microprocessor, or the processor may be any conventional processor, or the like.

[0204] The memory 1630 may include a read-only memory and a random access memory, and provides an instruction and data for the processor 1610. A part of the memory 1630 may further include a nonvolatile random access memory. For example, the memory 1630 may further store information about a device type.

[0205] In addition to a data bus, the bus system 1640 may further include a power bus, a control bus, a status signal bus, and the like. However, for clarity of description, various buses are marked as the bus system 1640 in the figure.

[0206] In an implementation process, the steps of the foregoing method may be completed by using a hardware integrated logic circuit or an instruction in a software form in the processor 1610. The steps of the method disclosed with reference to the embodiments of the present invention may be directly implemented by using a hardware processor, or may be implemented by using a combination of a hardware module and a software module in the processor. The software module may be located in a mature storage medium in the art such as a random memory, a flash memory, a read-only memory, a programmable read-only memory, an electrically erasable programmable memory, or a register. The storage medium is located in the memory 1630. The processor 1610 reads information from the memory 1630, and completes the steps of

the foregoing method in combination with hardware of the memory 1630. To avoid repetition, details are not described herein.

[0207] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource is the second candidate resource predefined in the plurality of candidate resources.

[0208] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource is the second candidate resource configured for the terminal device.

[0209] Optionally, when the second time-frequency resource is the resource other than the plurality of candidate resources configured for the terminal device, the second time-frequency resource includes a time-frequency resource corresponding to another reference signal other than a common reference signal CRS, or the second time-frequency resource includes a time-frequency resource corresponding to a data channel.

[0210] Optionally, the sending unit is further configured to: before the second determining unit determines the second time-frequency resource, send an indication message to the terminal device. The indication message indicates a location of the second time-frequency resource.

[0211] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the processor 1610 is specifically configured to: determine the second candidate time-frequency resource based on a preset mapping relationship between the first time-frequency resource and the second time-frequency resource.

[0212] Further, the second candidate time-frequency resource is one of candidate resources that have a same size as the first time-frequency resource and that are in the plurality of candidate resources.

[0213] Alternatively, the second candidate time-frequency resource is a candidate resource that is in candidate resources of a specified size in the plurality of candidate resources and that does not overlap with the first time-frequency resource.

[0214] Optionally, the processor 1610 is specifically configured to:

determine an aggregation level, where the aggregation level is used to indicate a size of the candidate resource; and
select one candidate resource from a set of the plurality of candidate resources corresponding to the aggregation level, and use the candidate resource as the first time-frequency resource.

[0215] It should be understood that the network device 1600 shown in FIG. 16 can implement processes related

to the network device in the embodiment of FIG. 8. Operations and/or functions of modules of the network device 1600 are respectively used for implementing corresponding processes in the method embodiment of FIG. 8. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0216] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0217] FIG. 17 is a schematic block diagram of a network device 1700 for transmitting a signal according to an embodiment of the present invention. As shown in FIG. 17, the network device 1700 includes a processor 1710 and a transceiver 1720. The processor 1710 is connected to the transceiver 1720. Optionally, the network device 1700 further includes a memory 1730. The memory 1730 is connected to the processor 1710. Optionally, the apparatus 1700 further includes a bus system 1740. The processor 1710, the memory 1730, and the transceiver 1720 may be connected by using the bus system 1740. The memory 1730 may be configured to store an instruction. The processor 1710 is configured to execute the instruction stored in the memory 1730, to control the transceiver 1720 to send information or a signal.

[0218] The processor 1710 is configured to: detect a first time-frequency resource, where the first time-frequency resource is a first candidate resource in a plurality of candidate resources, and the first time-frequency resource is used to carry a beamformed control channel;

detect a second time-frequency resource, where the second time-frequency resource is a second candidate resource in the plurality of candidate resources, or the second time-frequency resource is a resource other than the plurality of candidate resources configured for a terminal device, and the second time-frequency resource is used to carry a reference signal of the beamformed control channel; and
demodulate, based on the reference signal that is of the beamformed control channel and that is carried in the second time-frequency resource, the beamformed control channel carried in the first time-frequency resource.

[0219] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0220] In addition, a design of the beamformed control channel and the reference signal used for demodulating the beamformed control channel is used in this embodiment of the present invention, to improve coverage and performance of the control channel in comparison with a conventional control channel, and especially, to improve coverage of a cell using a high-frequency carrier. In addition, introduction of the beamformed control channel has no impact on or has slight impact on compatibility of a conventional terminal device.

[0221] It should be understood that in this embodiment of the present invention, the processor 1710 may be a central processing unit (central processing unit, CPU for short), or the processor 1710 may be another general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field programmable gate array (FPGA) or another programmable logic device, a discrete gate or a transistor logic device, a discrete hardware component, or the like. The general-purpose processor may be a microprocessor, or the processor may be any conventional processor, or the like.

[0222] The memory 1730 may include a read-only memory and a random access memory, and provides an instruction and data for the processor 1710. A part of the memory 1730 may further include a nonvolatile random access memory. For example, the memory 1730 may further store information about a device type.

[0223] In addition to a data bus, the bus system 1740 may further include a power bus, a control bus, a status signal bus, and the like. However, for clarity of description, various buses are marked as the bus system 1740 in the figure.

[0224] In an implementation process, the steps of the foregoing method may be completed by using a hardware integrated logic circuit or an instruction in a software form in the processor 1710. The steps of the method disclosed with reference to the embodiments of the present invention may be directly implemented by using a hardware processor, or may be implemented by using a combination of a hardware module and a software module in the processor. The software module may be located in a mature storage medium in the art such as a random memory, a flash memory, a read-only memory, a programmable read-only memory, an electrically erasable programmable memory, or a register. The storage medium is located in the memory 1730. The processor 1710 reads information from the memory 1730, and completes the steps of the foregoing method in combination with hardware of the memory 1730. To avoid repetition, details are not described herein.

[0225] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources, the second time-frequency resource is the second candidate resource predefined in the plurality of candidate resources.

[0226] Optionally, when the second time-frequency resource is the second candidate resource in the plurality

of candidate resources,

the second time-frequency resource is the second candidate resource configured for the terminal device.

[0227] Optionally, when the second time-frequency resource is the resource other than the plurality of candidate resources configured for the terminal device, the second time-frequency resource includes a time-frequency resource corresponding to another reference signal other than a common reference signal CRS, or the second time-frequency resource includes a time-frequency resource corresponding to a data channel.

[0228] Optionally, the transceiver 1720 is configured to: before the processor 1710 detects the second time-frequency resource, receive an indication message sent by the network device, where the indication message indicates a location of the second time-frequency resource.

[0229] Optionally, when the second time-frequency resource is the second candidate resource in the plurality of candidate resources,

the second time-frequency resource is the second candidate resource determined based on a preset mapping relationship between the first time-frequency resource and the second time-frequency resource.

[0230] Further, the second candidate time-frequency resource is one of candidate resources that have a same size as the first time-frequency resource and that are in the plurality of candidate resources.

[0231] Alternatively, the second candidate time-frequency resource is a candidate resource that is in candidate resources of a specified size in the plurality of candidate resources and that does not overlap with the first time-frequency resource.

[0232] It should be understood that the terminal device 1700 shown in FIG. 17 can implement processes related to the terminal device in the embodiment of FIG. 8. Operations and/or functions of modules of the terminal device 1700 are respectively used for implementing corresponding processes in the method embodiment of FIG. 8. For details, refer to the description of the method embodiment. To avoid repetition, detailed description is properly omitted herein.

[0233] Therefore, in this embodiment of the present invention, resources carrying the beamformed control channel and the reference signal of the beamformed control channel are determined, to transmit the beamformed control channel and the reference signal of the beamformed control channel. In this way, it becomes possible to improve coverage of a control channel through beamforming in an existing system.

[0234] It should be understood that "one embodiment" or "an embodiment" mentioned in the whole specification means that particular features, structures, or characteristics related to the embodiment are included in at least one embodiment of the present invention. Therefore, "in one embodiment" or "in an embodiment" appearing throughout this specification may be not necessarily a same embodiment. In addition, these particular features, structures, or characteristics may be combined in one or

more embodiments in any appropriate manner. It should be understood that sequence numbers of the foregoing processes do not mean execution sequences in various embodiments of the present invention. The execution sequences of the processes should be determined based on functions and internal logic of the processes, and should not be construed as any limitation on the implementation processes of the embodiments of the present invention.

[0235] In addition, the terms "system" and "network" are interchangeable in this specification. The term "and/or" in this specification describes only an association relationship for describing associated objects and represents that three relationships may exist. For example, A and/or B may represent the following three cases: Only A exists, both A and B exist, and only B exists. In addition, the character "/" in this specification generally indicates an "or" relationship between the associated objects.

[0236] It should be understood that in the embodiments of the present invention, "B corresponding to A" indicates that B is associated with A, and B may be determined based on A. However, it should further be understood that determining B based on A does not mean that B is determined based on A only, to be specific, B may also be determined based on A and/or other information.

[0237] A person of ordinary skill in the art may be aware that, in combination with the examples described in the embodiments disclosed in this specification, units and algorithm steps may be implemented by electronic hardware, computer software, or a combination thereof. To clearly describe the interchangeability between the hardware and the software, compositions and steps of each example are generally described above based on functions. Whether the functions are performed by hardware or software depends on particular applications and design constraint conditions of the technical solutions. A person skilled in the art may use different methods to implement the described functions for each particular application, but it should not be considered that the implementation goes beyond the scope of the present invention.

[0238] It may be clearly understood by a person skilled in the art that, for the purpose of convenient and brief description, for a detailed working process of the foregoing system, apparatus, and unit, refer to a corresponding process in the foregoing method embodiments, and details are not described herein again.

[0239] In the several embodiments provided in this application, it should be understood that the disclosed system, apparatus, and method may be implemented in other manners. For example, the described apparatus embodiment is merely an example. For example, the unit division is merely logical function division and may be other division in actual implementation. For example, a plurality of units or components may be combined or integrated into another system, or some features may be ignored or not performed. In addition, the displayed or

discussed mutual couplings or direct couplings or communications connections may be implemented through some interfaces. The indirect couplings or communication connections between the apparatuses or units may be electrical connections, mechanical connections, or connections in other forms.

[0240] The units described as separate parts may or may not be physically separate, and parts displayed as units may or may not be physical units, may be located in one position, or may be distributed on a plurality of network units. A part or all of the units may be selected based on actual requirements to achieve the objectives of the solutions of the embodiments of the present invention.

[0241] In addition, functional units in the embodiments of the present invention may be integrated into one processing unit, or each of the units may exist alone physically, or two or more units are integrated into one unit. The integrated unit may be implemented in a form of hardware, or may be implemented in a form of a software functional unit.

[0242] From description of the foregoing implementations, a person skilled in the art may clearly understand that the present invention may be implemented by hardware, firmware or a combination thereof. When the present invention is implemented by software, the foregoing functions may be stored in a computer-readable medium or transmitted as one or more instructions or code in the computer-readable medium. The computer-readable medium includes a computer storage medium and a communications medium. The communications medium includes any medium that enables a computer program to be transmitted from one place to another. The storage medium may be any available medium accessible to a computer. The following is used as an example but not a limitation: The computer-readable medium may include a RAM, a ROM, an EEPROM, a CD-ROM or another optical disc storage, a disk storage medium or another magnetic storage device, or any other medium that can carry or store expected program code in a form of an instruction or a data structure and that can be accessed by a computer. In addition, any connection may be appropriately defined as a computer-readable medium. For example, if software is transmitted from a website, a server, or another remote source by using a coaxial cable, an optical fiber/cable, a twisted pair, a digital subscriber line (DSL), or wireless technologies such as infrared ray, radio, and microwave, the coaxial cable, optical fiber/cable, twisted pair, DSL, or wireless technologies such as infrared ray, radio, and microwave are included in fixation of a medium to which they belong. For example, a disk (disk) and disc (disc) used in the present invention includes a compact disc (CD), a laser disc, an optical disc, a digital versatile disc (DVD), a floppy disk, and a Blu-ray disc. The disk generally copies data by using a magnetic means, and the disc copies data optically by using a laser means. The foregoing combination should also be included in the protection scope of the

computer-readable medium.

[0243] In summary, the foregoing description is merely example embodiments of the technical solutions of the present invention, but is not intended to limit the protection scope of the present invention. The scope of the present invention is determined by the scope of the appended claims.

Claims

1. A communication method, performed by a communication device, the method comprising:

determining a first time-frequency resource, wherein the first time-frequency resource is a physical downlink control channel, PDCCH, candidate in a plurality of PDCCH candidates, wherein the first time-frequency resource comprises a second time-frequency resource used to carry a beamformed control channel and a third time-frequency resource used to carry a reference signal of the beamformed control channel, wherein the first time-frequency resource consists of a plurality of source element, RE sets, each RE set of the plurality of RE sets comprises a same fixed quantity of REs, each RE set of the plurality of RE sets comprises a plurality of RE groups, REGs, each of the plurality of REGs consists of same quantity of REs, and wherein the third time-frequency resource is located at a preset location in each of the plurality of REGs, the preset location in each of the plurality of REGs is the same, and at least one resource in the first time-frequency resource other than the third time-frequency resource is the second time-frequency resource; and demodulating the beamformed control channel according to the reference signal, wherein the beamformed control channel is received in the second time-frequency resource and the reference signal is received in the third time frequency resource.

2. The method according to claim 1, wherein each RE set is associated with a control resource element, CCE, the first time-frequency resource is associated with one or more CCEs, and a number of the one or more CCEs is equal to an aggregation level.
3. The method according to claim 2, wherein the aggregation level is one of 1, 2, 4, 8, 16, or 32.
4. The method according to any one of claims 1 to 3, wherein the second time-frequency resource and the third time-frequency resource are determined according to a first rule, and the first rule indicates the preset location.

5. The method according to any one of claims 1 to 4, further comprising:
receiving the beamformed control channel in the second time-frequency resource and receiving the reference signal in the third time-frequency resource.

6. The method according to any one of claims 1 to 5, wherein every four adjacent REs in each of the plurality of REGs are represented as RE0, RE1, RE2 and RE3, wherein RE0, RE1, RE2 and RE3 are respectively from low frequency to high frequency in frequency domain, and the third frequency resource is located in RE1.

7. A communication device, comprising:

a non-transitory storage medium including executable instructions; and
a processor, wherein the executable instructions, when executed by the processor, cause the communication device to:

determine a first time-frequency resource, wherein the first time-frequency resource is a physical downlink control channel, PDCCH, candidate in a plurality of PDCCH candidates, wherein the first time-frequency resource comprises a second time-frequency resource used to carry a beamformed control channel and a third time-frequency resource used to carry a reference signal of the beamformed control channel, wherein the first time-frequency resource consists of a plurality of resource element, RE sets, each RE set of the plurality of RE sets comprises a same fixed quantity of REs, each RE set of the plurality of RE sets comprises a plurality of RE groups, REGs, each of the plurality of REGs consists of same quantity of REs, and wherein the third time-frequency resource is located at a preset location in each of the plurality of REGs, the preset location in each of the plurality of REGs is the same, and at least one resource in the first time-frequency resource other than the third time-frequency resource is the second time-frequency resource; and demodulate the beamformed control channel according to the reference signal, wherein the beamformed control channel is received in the second time-frequency resource and the reference signal is received in the third time frequency resource.

8. The communication device according to claim 7, wherein each RE set is associated with a control resource element, CCE, the first time-frequency resource is associated with one or more CCEs, and a

number of the one or more CCEs is equal to an aggregation level.

9. The communication device according to claim 8, wherein the aggregation level is one of 1, 2, 4, 8, 16, or 32. 5
10. The communication device according to any one of claims 7 to 9, wherein the second time-frequency resource and the third time-frequency resource are determined according to a first rule, and the first rule indicates the preset location. 10
11. The communication device according to any one of claims 7 to 10, further comprising:
a receiver configured to receive the beamformed control channel in the second time-frequency resource and to receive the reference signal in the third time-frequency resource. 15
12. The communication device according to any one of claims 7 to 11, wherein every four adjacent REs in each of the plurality of REGs are represented as RE0, RE1, RE2 and RE3, wherein RE0, RE1, RE2 and RE3 are respectively from low frequency to high frequency in frequency domain, and the third frequency resource is located in RE1. 20
13. A non-transitory computer-readable medium, wherein the non-transitory computer-readable medium stores instructions that, when executed by a processor, cause the processor to:

determine a first time-frequency resource, wherein the first time-frequency resource is a physical downlink control channel, PDCCH, candidate in a plurality of PDCCH candidates, wherein the first time-frequency resource comprises a second time-frequency resource used to carry a beamformed control channel and a third time-frequency resource used to carry a reference signal of the beamformed control channel, wherein the first time-frequency resource consists of a plurality resource element, RE sets, each RE set of the plurality of RE sets comprises a same fixed quantity of REs, each RE set of the plurality of RE sets comprises a plurality of RE groups, REGs, each of the plurality of REGs consists of same quantity of REs, and wherein the third time-frequency resource is located at a preset location in each of the plurality of REGs, the preset location in each of the plurality of REGs is the same, and at least one resource in the first time-frequency resource other than the third time-frequency resource is the second time-frequency resource; and demodulate the beamformed control channel according to the reference signal, wherein the 30
35
40
45
50
55

beamformed control channel is received in the second time-frequency resource and the reference signal is received in the third time frequency resource.

14. The non-transitory computer-readable medium according to claim 13, wherein each RE set is associated with a control resource element, CCE, the first time-frequency resource is associated with one or more CCEs, and a number of the one or more CCEs is equal to an aggregation level.
15. The non-transitory computer-readable medium according to claim 14, wherein the aggregation level is one of 1, 2, 4, 8, 16, or 32.
16. The non-transitory computer-readable medium according to any one of claims 13 to 15, wherein the second time-frequency resource and the third time-frequency resource are determined according to a first rule, and the first rule indicates the preset location.
17. The non-transitory computer-readable medium according to any one of claims 13 to 16, wherein the instructions, when executed by the processor, further cause the processor to:
receive the beamformed control channel in the second time-frequency resource and receive the reference signal in the third time-frequency resource.
18. The non-transitory computer-readable medium according to any one of claims 13 to 17, wherein every four adjacent REs in each of the plurality of REGs are represented as RE0, RE1, RE2 and RE3, wherein RE0, RE1, RE2 and RE3 are respectively from low frequency to high frequency in frequency domain, and the third frequency resource is located in RE1.
19. A communication system, comprising a network device and a user equipment, wherein the user equipment is configured to perform the method of any one of claims 1 to 5.

Patentansprüche

1. Kommunikationsverfahren, das durch eine Kommunikationsvorrichtung durchgeführt wird, wobei das Verfahren umfasst:

Bestimmen einer ersten Zeit-Frequenz-Ressource, wobei die erste Zeit-Frequenz-Ressource ein physikalischer Downlink-Steuerkanal-Kandidat, PDCCH-Kandidat, in einer Vielzahl von PDCCH-Kandidaten ist, wobei die erste Zeit-Frequenz-Ressource eine zweite Zeit-Fre-

- quenz-Ressource, die verwendet wird, um einen strahlgeformten Steuerkanal zu tragen, und eine dritte Zeit-Frequenz-Ressource, die verwendet wird, um ein Referenzsignal des strahlgeformten Steuerkanals zu tragen, umfasst, wobei die erste Zeit-Frequenz-Ressource aus einer Vielzahl von Ressourcenelement-Sätzen, RE-Sätzen, besteht, wobei jeder RE-Satz der Vielzahl von RE-Sätzen eine gleiche feste Menge an REs umfasst, wobei jeder RE-Satz der Vielzahl von RE-Sätzen eine Vielzahl von RE-Gruppen, REGs, umfasst, wobei jede der Vielzahl von REGs aus einer gleichen Menge an REs besteht, und wobei sich die dritte Zeit-Frequenz-Ressource an einer voreingestellten Stelle in jeder der Vielzahl von REGs befindet, wobei die voreingestellte Stelle in jeder der Vielzahl von REGs gleich ist und mindestens eine Ressource in der ersten Zeit-Frequenz-Ressource, mit Ausnahme der dritten Zeit-Frequenz-Ressource, die zweite Zeit-Frequenz-Ressource ist; und Demodulieren des strahlgeformten Steuerkanals gemäß dem Referenzsignal, wobei der strahlgeformte Steuerkanal in der zweiten Zeit-Frequenz-Ressource empfangen wird und das Referenzsignal in der dritten Zeit-Frequenz-Ressource empfangen wird.
2. Verfahren nach Anspruch 1, wobei jeder RE-Satz mit einem Steuerressourcenelement, CCE, verknüpft ist, die erste Zeit-Frequenz-Ressource mit einem oder mehreren CCEs verknüpft ist und eine Anzahl des einen oder der mehreren CCEs gleich einer Aggregationsebene ist.
3. Verfahren nach Anspruch 2, wobei die Aggregationsebene eine von 1, 2, 4, 8, 16 oder 32 ist.
4. Verfahren nach einem der Ansprüche 1 bis 3, wobei die zweite Zeit-Frequenz-Ressource und die dritte Zeit-Frequenz-Ressource gemäß einer ersten Regel bestimmt werden und die erste Regel die voreingestellte Stelle angibt.
5. Verfahren nach einem der Ansprüche 1 bis 4, das ferner umfasst:
Empfangen des strahlgeformten Steuerkanals in der zweiten Zeit-Frequenz-Ressource und Empfangen des Referenzsignals in der dritten Zeit-Frequenz-Ressource.
6. Verfahren nach einem der Ansprüche 1 bis 5, wobei alle vier angrenzenden REs in jeder der Vielzahl von REGs als RE0, RE1, RE2 und RE3 dargestellt werden, wobei RE0, RE1, RE2 und RE3 jeweils von niederfrequent zu hochfrequent in einem Frequenzbereich liegen, und sich die dritte Frequenz-Ressource
- in RE1 befindet.
7. Kommunikationsvorrichtung, die umfasst:
ein nichtflüchtiges Speichermedium, das ausführbare Anweisungen einschließt; und einen Prozessor, wobei die ausführbaren Anweisungen, wenn sie durch den Prozessor ausgeführt werden, die Kommunikationsvorrichtung veranlassen zum:
Bestimmen einer ersten Zeit-Frequenz-Ressource, wobei die erste Zeit-Frequenz-Ressource ein physikalischer Downlink-Steuerkanal-Kandidat, PDCCH-Kandidat, in einer Vielzahl von PDCCH-Kandidaten ist, wobei die erste Zeit-Frequenz-Ressource eine zweite Zeit-Frequenz-Ressource, die verwendet wird, um einen strahlgeformten Steuerkanal zu tragen, und eine dritte Zeit-Frequenz-Ressource, die verwendet wird, um ein Referenzsignal des strahlgeformten Steuerkanals zu tragen, umfasst, wobei die erste Zeit-Frequenz-Ressource aus einer Vielzahl von Ressourcenelement-Sätzen, RE-Sätzen, besteht, wobei jeder RE-Satz der Vielzahl von RE-Sätzen eine gleiche feste Menge an REs umfasst, wobei jeder RE-Satz der Vielzahl von RE-Sätzen eine Vielzahl von RE-Gruppen, REGs, umfasst, wobei jede der Vielzahl von REGs aus der gleichen Menge an REs besteht, und wobei sich die dritte Zeit-Frequenz-Ressource an einer voreingestellten Stelle in jeder der Vielzahl von REGs befindet, wobei die voreingestellte Stelle in jeder der Vielzahl von REGs gleich ist und mindestens eine Ressource in der ersten Zeit-Frequenz-Ressource, mit Ausnahme der dritten Zeit-Frequenz-Ressource, die zweite Zeit-Frequenz-Ressource ist; und Demodulieren des strahlgeformten Steuerkanals gemäß dem Referenzsignal, wobei der strahlgeformte Steuerkanal in der zweiten Zeit-Frequenz-Ressource empfangen wird und das Referenzsignal in der dritten Zeit-Frequenz-Ressource empfangen wird.
8. Kommunikationsvorrichtung nach Anspruch 7, wobei jeder RE-Satz mit einem Steuerressourcenelement, CCE, verknüpft ist, die erste Zeit-Frequenz-Ressource mit einem oder mehreren CCEs verknüpft ist und eine Anzahl des einen oder der mehreren CCEs gleich einer Aggregationsebene ist.
9. Kommunikationsvorrichtung nach Anspruch 8, wobei die Aggregationsebene eine von 1, 2, 4, 8, 16 oder 32 ist.

10. Kommunikationsvorrichtung nach einem der Ansprüche 7 bis 9, wobei die zweite Zeit-Frequenz-Ressource und die dritte Zeit-Frequenz-Ressource gemäß einer ersten Regel bestimmt werden und die erste Regel die voreingestellte Stelle angibt.
11. Kommunikationsvorrichtung nach einem der Ansprüche 7 bis 10, die ferner umfasst:
einen Empfänger, der konfiguriert ist, um den strahlgeformten Steuerkanal in der zweiten Zeit-Frequenz-Ressource zu empfangen und das Referenzsignal in der dritten Zeit-Frequenz-Ressource zu empfangen.
12. Kommunikationsvorrichtung nach einem der Ansprüche 7 bis 11, wobei alle vier angrenzenden REs in jeder der Vielzahl von REGs als RE0, RE1, RE2 und RE3 dargestellt werden, wobei RE0, RE1, RE2 und RE3 jeweils von niederfrequent zu hochfrequent in einem Frequenzbereich liegen, und sich die dritte Frequenz-Ressource in RE1 befindet.
13. Nichtflüchtiges computerlesbares Medium, wobei das nichtflüchtige computerlesbare Medium Anweisungen speichert, die, wenn sie durch einen Prozessor ausgeführt werden, den Prozessor veranlassen zum:
- Bestimmen einer ersten Zeit-Frequenz-Ressource, wobei die erste Zeit-Frequenz-Ressource ein physikalischer Downlink-Steuerkanal-Kandidat, PDCCH-Kandidat, in einer Vielzahl von PDCCH-Kandidaten ist, wobei die erste Zeit-Frequenz-Ressource eine zweite Zeit-Frequenz-Ressource, die verwendet wird, um einen strahlgeformten Steuerkanal zu tragen, und eine dritte Zeit-Frequenz-Ressource, die verwendet wird, um ein Referenzsignal des strahlgeformten Steuerkanals zu tragen, umfasst, wobei die erste Zeit-Frequenz-Ressource aus einer Vielzahl von Ressourcenelement-Sätzen, RE-Sätzen, besteht, wobei jeder RE-Satz der Vielzahl von RE-Sätzen eine gleiche feste Menge an REs umfasst, wobei jeder RE-Satz der Vielzahl von RE-Sätzen eine Vielzahl von RE-Gruppen, REGs, umfasst, wobei jede der Vielzahl von REGs aus der gleichen Menge an REs besteht, und wobei sich die dritte Zeit-Frequenz-Ressource an einer voreingestellten Stelle in jeder der Vielzahl von REGs befindet, wobei die voreingestellte Stelle in jeder der Vielzahl von REGs gleich ist und mindestens eine Ressource in der ersten Zeit-Frequenz-Ressource, mit Ausnahme der dritten Zeit-Frequenz-Ressource, die zweite Zeit-Frequenz-Ressource ist; und Demodulieren des strahlgeformten Steuerkanals gemäß dem Referenzsignal, wobei der strahlgeformte Steuerkanal in der zweiten Zeit-

Frequenz-Ressource empfangen wird und das Referenzsignal in der dritten Zeit-Frequenz-Ressource empfangen wird.

14. Nichtflüchtiges computerlesbares Medium nach Anspruch 13, wobei jeder RE-Satz mit einem Ressourcenelement, CCE, verknüpft ist, die erste Zeit-Frequenz-Ressource mit einem oder mehreren CCEs verknüpft ist und eine Anzahl des einen oder der mehreren CCEs gleich einer Aggregationsebene ist.
15. Nichtflüchtiges computerlesbares Medium nach Anspruch 14, wobei die Aggregationsebene eine von 1, 2, 4, 8, 16 oder 32 ist.
16. Nichtflüchtiges computerlesbares Medium nach einem der Ansprüche 13 bis 15, wobei die zweite Zeit-Frequenz-Ressource und eine dritte Zeit-Frequenz-Ressource gemäß einer ersten Regel bestimmt werden und die erste Regel die voreingestellte Stelle angibt.
17. Nichtflüchtiges computerlesbares Medium nach einem der Ansprüche 13 bis 16, wobei die Anweisungen, wenn sie durch den Prozessor ausgeführt werden, den Prozessor ferner veranlassen zum:
Empfangen des strahlgeformten Steuerkanals in der zweiten Zeit-Frequenz-Ressource und Empfangen des Referenzsignals in der dritten Zeit-Frequenz-Ressource.
18. Nichtflüchtiges computerlesbares Medium nach einem der Ansprüche 13 bis 17, wobei alle vier angrenzenden REs in jeder der Vielzahl von REGs als RE0, RE1, RE2 und RE3 dargestellt werden, wobei RE0, RE1, RE2 und RE3 jeweils von niederfrequent zu hochfrequent in einem Frequenzbereich liegen, und sich die dritte Frequenz-Ressource in RE1 befindet.
19. Kommunikationssystem, das eine Netzwerkvorrichtung und eine Benutzereinrichtung umfasst, wobei die Benutzereinrichtung konfiguriert ist, um das Verfahren nach einem der Ansprüche 1 bis 5 durchzuführen.

Revendications

1. Procédé de communication effectué par un dispositif réseau, le procédé comprenant :
- la détermination d'une première ressource temps-fréquence, la première ressource temps-fréquence étant un candidat au canal physique de commande de liaison descendante, PDCCH, dans une pluralité de candidats PDCCH, la pre-

- mière ressource temps-fréquence comprenant une deuxième ressource temps-fréquence utilisée pour transporter un canal de commande formé par faisceau et une troisième ressource temps-fréquence utilisée pour transporter un signal de référence du canal de commande formé par faisceau, la première ressource temps-fréquence étant constituée d'une pluralité d'ensembles d'éléments de ressources, RE, chaque ensemble RE de la pluralité d'ensembles RE comprenant une même quantité fixe de RE, chaque ensemble RE de la pluralité d'ensembles RE comprenant une pluralité de groupes RE, REG, chacun de la pluralité de REG étant constitué de la même quantité de RE, et la troisième ressource temps-fréquence étant située à un emplacement prédéfini dans chacun de la pluralité de REG, l'emplacement prédéfini dans chacun de la pluralité de REG étant le même, et au moins une ressource de la première ressource temps-fréquence autre que la troisième ressource temps-fréquence étant la deuxième ressource temps-fréquence ; et la démodulation du canal de commande formé par faisceau selon le signal de référence, le canal de commande formé par faisceau étant reçu dans la deuxième ressource temps-fréquence et le signal de référence étant reçu dans la troisième ressource temps-fréquence.
2. Procédé selon la revendication 1, dans lequel chaque ensemble RE est associé à un élément de ressource de commande, CCE, la première ressource temps-fréquence est associée à un ou plusieurs CCE, et un nombre du ou des CCE est égal à un niveau d'agrégation.
3. Procédé selon la revendication 2, dans lequel le niveau d'agrégation est l'un parmi 1, 2, 4, 8, 16 ou 32.
4. Procédé selon l'une quelconque des revendications 1 à 3, dans lequel la deuxième ressource temps-fréquence et la troisième ressource temps-fréquence sont déterminées selon une première règle, et la première règle indique l'emplacement prédéfini.
5. Procédé selon l'une quelconque des revendications 1 à 4, comprenant en outre : la réception du canal de commande formé par faisceau dans la deuxième ressource temps-fréquence et la réception du signal de référence dans la troisième ressource temps-fréquence.
6. Procédé selon l'une quelconque des revendications 1 à 5, dans lequel tous les quatre RE adjacents dans chacun de la pluralité de REG sont représentés par RE0, RE1, RE2 et RE3, RE0, RE1, RE2 et RE3 étant respectivement de basse fréquence à haute fréquence dans le domaine fréquentiel, et la troisième ressource de fréquence étant située dans RE1.
7. Dispositif de communication, comprenant :
- un support de stockage non transitoire comportant des instructions exécutables ; et un processeur, les instructions exécutables, lorsqu'elles sont exécutées par le processeur, amenant le dispositif de communication à :
- déterminer une première ressource temps-fréquence, la première ressource temps-fréquence étant un candidat au canal physique de commande de liaison descendante, PDCCCH, dans une pluralité de candidats PDCCCH, la première ressource temps-fréquence comprenant une deuxième ressource temps-fréquence utilisée pour transporter un canal de commande formé par faisceau et une troisième ressource temps-fréquence utilisée pour transporter un signal de référence du canal de commande formé par faisceau, la première ressource temps-fréquence étant constituée d'une pluralité d'ensembles d'éléments de ressources, RE, chaque ensemble RE de la pluralité d'ensembles RE comprenant une même quantité fixe de RE, chaque ensemble RE de la pluralité d'ensembles RE comprenant une pluralité de groupes RE, REG, chacun de la pluralité de REG étant constitué de la même quantité de RE, et la troisième ressource temps-fréquence étant située à un emplacement prédéfini dans chacun de la pluralité de REG, l'emplacement prédéfini dans chacun de la pluralité de REG étant le même, et au moins une ressource de la première ressource temps-fréquence autre que la troisième ressource temps-fréquence étant la deuxième ressource temps-fréquence ; et démoduler le canal de commande formé par faisceau selon le signal de référence, le canal de commande formé par faisceau étant reçu dans la deuxième ressource temps-fréquence et le signal de référence étant reçu dans la troisième ressource temps-fréquence.
8. Dispositif de communication selon la revendication 7, dans lequel chaque ensemble RE est associé à un élément de ressource de commande, CCE, la première ressource temps-fréquence est associée à un ou plusieurs CCE, et un nombre du ou des CCE est égal à un niveau d'agrégation.
9. Dispositif de communication selon la revendication

- 8, dans lequel le niveau d'agrégation est l'un parmi 1, 2, 4, 8, 16 ou 32.
10. Dispositif de communication selon l'une quelconque des revendications 7 à 9, dans lequel la deuxième ressource temps-fréquence et la troisième ressource temps-fréquence sont déterminées selon une première règle, et la première règle indique l'emplacement prédéfini. 5
11. Dispositif de communication selon l'une quelconque des revendications 7 à 10, comprenant en outre : un récepteur configuré pour recevoir le canal de commande formé par faisceau dans la deuxième ressource temps-fréquence et pour recevoir le signal de référence dans la troisième ressource temps-fréquence. 15
12. Dispositif de communication selon l'une quelconque des revendications 7 à 11, dans lequel tous les quatre RE adjacents dans chacun de la pluralité de REG sont représentés par RE0, RE1, RE2 et RE3, RE0, RE1, RE2 et RE3 étant respectivement de basse fréquence à haute fréquence dans le domaine fréquentiel, et la troisième ressource fréquentielle étant située dans RE1. 20 25
13. Support non transitoire lisible par ordinateur, dans lequel le support non transitoire lisible par ordinateur stocke des instructions qui, lorsqu'elles sont exécutées par un processeur, amènent le processeur à : 30
- déterminer une première ressource temps-fréquence, la première ressource temps-fréquence étant un candidat au canal physique de commande de liaison descendante, PDCCH, dans une pluralité de candidats PDCCH, la première ressource temps-fréquence comprenant une deuxième ressource temps-fréquence utilisée pour transporter un canal de commande formé par faisceau et une troisième ressource temps-fréquence utilisée pour transporter un signal de référence du canal de commande formé par faisceau, la première ressource temps-fréquence étant constitué d'une pluralité d'ensembles d'éléments de ressources, RE, chaque ensemble RE de la pluralité d'ensembles RE comprenant une même quantité fixe de RE, chaque ensemble RE de la pluralité d'ensembles RE comprenant une pluralité de groupes RE, REG, chacun de la pluralité de REG étant constitué de la même quantité de RE, et la troisième ressource temps-fréquence étant située à un emplacement prédéfini dans chacun de la pluralité de REG, l'emplacement prédéfini dans chacun de la pluralité de REG étant le même, et au moins une ressource dans la première ressource temps-fréquence autre que la troisième ressource 35 40 45 50 55
- ce temps-fréquence étant la deuxième ressource temps-fréquence ; et
- démoduler le canal de commande formé par faisceau selon le signal de référence, le canal de commande formé par faisceau étant reçu dans la deuxième ressource temps-fréquence et le signal de référence étant reçu dans la troisième ressource temps-fréquence.
14. Support non transitoire lisible par ordinateur selon la revendication 13, dans lequel chaque ensemble RE est associé à un élément de ressource de commande, CCE, la première ressource temps-fréquence est associée à un ou plusieurs CCE, et un nombre du ou des CCE est égal à un niveau d'agrégation. 10 15
15. Support non transitoire lisible par ordinateur selon la revendication 14, dans lequel le niveau d'agrégation est l'un parmi 1, 2, 4, 8, 16 ou 32.
16. Support non transitoire lisible par ordinateur selon l'une quelconque des revendications 13 à 15, dans lequel la deuxième ressource temps-fréquence et la troisième ressource temps-fréquence sont déterminées selon une première règle, et la première règle indique l'emplacement prédéfini.
17. Support non transitoire lisible par ordinateur selon l'une quelconque des revendications 13 à 16, dans lequel les instructions, lorsqu'elles sont exécutées par le processeur, amènent en outre le processeur à : 30
- recevoir le canal de commande formé par faisceau dans la deuxième ressource temps-fréquence et recevoir le signal de référence dans la troisième ressource temps-fréquence. 35 40 45 50 55
18. Support non transitoire lisible par ordinateur selon l'une quelconque des revendications 13 à 17, dans lequel tous les quatre RE adjacents dans chacun de la pluralité de REG sont représentés par RE0, RE1, RE2 et RE3, RE0, RE1, RE2 et RE3 étant respectivement de basse fréquence à haute fréquence dans le domaine fréquentiel, et la troisième ressource fréquentielle étant située dans RE1.
19. Système de communication, comprenant un dispositif réseau et un équipement utilisateur, l'équipement utilisateur étant configuré pour effectuer le procédé selon l'une quelconque des revendications 1 à 5.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Non-patent literature cited in the description

- **MOTOROLA.** PDCCH Beamforming for LTE-A. *3GPP DRAFT; R1-091331*, 18 March 2009, (Seoul [0008])
- **QUALCOMM INC.** Beamformed CSI-RS for support of FD-MIMO. *3GPP DRAFT; R1-153880*, 23 August 2015, vol. RAN WG1 (Beijing, http://www.3gpp.org/ftp/Meetings_3GPP_SYNC/RAN1/Docs [0009])