

(19)



(11)

EP 3 407 502 A1

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:

28.11.2018 Bulletin 2018/48

(51) Int Cl.:

H04B 3/54 (2006.01)

(21) Application number: **18173581.2**

(22) Date of filing: **22.05.2018**

(84) Designated Contracting States:

**AL AT BE BG CH CY CZ DE DK EE ES FI FR GB
GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO
PL PT RO RS SE SI SK SM TR**

Designated Extension States:

BA ME

Designated Validation States:

KH MA MD TN

(30) Priority: **22.05.2017 US 201762509411 P**

(71) Applicant: **Solaredge Technologies Ltd.
4673335 Herzeliya (IL)**

(72) Inventors:

- **Braginsky, David
4673335 Herzeliya (IL)**
- **Galin, Yoav
4673335 Herzeliya (IL)**
- **Yoscovich, Ilan
4673335 Herzeliya (IL)**

(74) Representative: **V.O.**

**P.O. Box 87930
Carnegieplein 5
2508 DH Den Haag (NL)**

(54) **METHOD AND APPARATUS TO ENABLE COMMUNICATION AND CONTROL IN A POWER SYSTEM**

(57) A network unit may be operatively attached to power lines of an interconnected power system and/or a device such as a power module that may further include a communication interface. The network unit may be operable to superimpose a first signal representative of a sensed parameter of the power system onto the power

lines, thereby to transmit the first signal to other power modules in the interconnected power system or to a power device in interconnected power system. The network unit may receive a second signal of the parameter superimposed onto the power lines from another network unit.

EP 3 407 502 A1

Description

RELATED APPLICATIONS

[0001] This application claims priority to U.S. provisional application serial number 62/509,411, filed May 22, 2017, entitled "Method and Apparatus to Enable Communication and Control in a Power System", the entire contents of which are incorporated herein by reference.

BACKGROUND

[0002] Generally, PLC (Power Line Communication) is a method that transmits a communication signal modulated using a carrier wave on power distribution lines of a power system installed outdoors or indoors. Distribution lines are used to enable the transmission and reception of signals, and the information provided in those signals is used for various purposes related to the power system.

SUMMARY

[0003] The following is a short summary of some of the inventive concepts for illustrative purposes only, and is not intended to limit or constrain the inventions and examples in the detailed description. One skilled in the art will recognize other novel combinations and features from the detailed description.

[0004] Illustrative embodiments disclosed herein may include a system used to supply power to a load, a storage device and/or one or more direct current (DC) to direct current converters and/or one or more DC to alternating current (AC) converters (e.g., inverters, micro-inverters). The system may include various devices and may implement methods for the devices to enable communication within the system and with other systems. The system may include various interconnections of groups of DC power sources that also may be connected in various series, parallel, series parallel, and/or parallel series combinations, for example.

[0005] In some illustrative embodiments disclosed herein, a power line communication (PLC) device may be magnetically coupled to power lines, and the magnetic coupling might not require direct electrical connection to the power lines. As such, the PLC devices may be attached and re-attached at various locations in a power system as part of a possible retrofit of the power system in order to provide monitoring and control of the power system.

[0006] In some illustrative embodiments disclosed herein, a PLC device may be integrated as part of an electrical device, such as a string combiner box where safety devices and termination blocks are used to connect power cables of strings of interconnected power sources together as part of a power system. The string combiner box may include additional connections to power modules, controllers and their connections to the safe-

ty devices and termination blocks for example. The PLC devices may connect to the power cables and may enable communications between various parts of the power system in order to provide monitoring and control of the various devices within the power system.

[0007] As noted above, this Summary is merely a summary of some of the features described herein. It is not exhaustive, and it is not to be a limitation on the claims.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] These and other features, aspects, and advantages of the present disclosure will become better understood with regard to the following description, claims, and drawings. The present disclosure is illustrated by way of example, and not limited by, the accompanying figures.

Fig. 1A illustrates a power system, according to one or more illustrative embodiments.

Fig. 1B shows further details of a power module, according to one or more illustrative embodiments.

Fig. 1C shows a buck+boost circuit implementation for a power circuit, according to one or more illustrative embodiments.

Fig. 2A shows an isometric view of a network unit, according to one or more illustrative embodiments.

Fig. 2B shows an isometric view of a network unit, according to one or more illustrative embodiments.

Fig. 2C, 2D and 2E show further details of network units, according to one or more illustrative embodiments.

Fig. 2F shows an isometric view of a network unit, according to one or more illustrative embodiments.

Fig. 2G shows an isometric view of a magnetic core, according to one or more illustrative embodiments.

Fig. 2H shows a plan view of a network unit, according to one or more illustrative embodiments.

Fig. 2I shows a cross sectional view of a network unit, according to one or more illustrative embodiments.

Fig. 3A shows another isometric view of details of a network unit, according to one or more illustrative embodiments.

Fig. 3B shows multiple network units attached to a mounting plate, according to one or more illustrative embodiments.

Fig. 3C shows multiple network units mounted in a connection box, according to one or more illustrative embodiments.

Fig. 4A shows a block diagram of a power system, according to one or more illustrative embodiments.

Fig. 4B shows further details of a network unit, according to one or more illustrative embodiments.

DETAILED DESCRIPTION

[0009] In the following description of various illustrative embodiments, reference is made to the accompanying drawings, which form a part hereof, and in which is shown, by way of illustration, various embodiments in which aspects of the disclosure may be practiced. It is to be understood that other embodiments may be used and structural and functional modifications may be made, without departing from the scope of the present disclosure.

[0010] The term "multiple" as used here in the detailed description indicates the property of having or involving several parts, elements, or members. The claim term "a plurality of" as used herein in the claims section finds support in the description with use of the term "multiple" and/or other plural forms. Other plural forms may include for example regular nouns that form their plurals by adding either the letter 's' or 'es' so that the plural of converter is converters or the plural of switch is switches for example.

[0011] Reference is made to Fig. 1A, which shows a block diagram of a power system **100**, according one or more illustrative embodiments. A connection configuration **111** of the power system **100** may include multiple power sources **101** with direct current (DC) output terminals connected to the input terminals of power modules **103**. DC output terminals of power modules **103** in connection configuration **111** may be connected in series with power lines **120** to form a series string of power module **103** outputs. Multiple connection configurations **111** may be connected in parallel across the input of power device **107**. Power device **107** may include, for example, a direct current (DC) to DC converter, a DC string combiner box, and/or a DC to alternating current (AC) inverter supplying power to load **109**. Load **109** may be, for example, a battery, an alternating current (AC) grid or a DC grid, or a DC to AC inverter.

[0012] A network unit **112** may be attached to power lines **120** at various locations such as the top of a series string of power module **103** outputs, at connection nodes A and/or B, or at an input to power device **107**. In general, any number of network units **112** may be attached to power lines **120** at any number of locations of power system **100**. The attachment of network units **112** to power lines **120** may include electrical-mechanical and electromagnetic-mechanical mechanisms. Descriptions below concerning other network units consider include optoe-

lectronic-mechanical mechanisms.

[0013] Network unit **112** may be used to enable communication of both transmitted and received signals between power modules **103** and/or between power modules **103** and power devices **107**, for example. The signals transmitted and received may include control signals, signals which identify a particular power module **103** and/or power device **107**, signals representing a parameter (e.g., voltage, current, power, coulombic charge, level of solar irradiance or temperature) sensed at various locations in power system **100**. According to various features described below, network units **112** may also be integrated into power modules **103**, power lines **120** and/or power devices **107**.

[0014] In the descriptions that follow, by way of non-limiting example, power source **101** may be a photovoltaic (PV) generator (for example, a PV cell, a series string of PV cells, a parallel connection of serially connected PV strings of PV cells, a photovoltaic or solar panel), a DC generator, a battery, or a fuel cell. Load **109** may be variously implemented, for example, using a battery, super capacitor, flywheel and/or ULTRABATTERY™. Load **109** may comprise one or more DC load circuits. Power device **107** may comprise communication equipment (e.g., a cellular base-station) or other devices deployed in a location that might not be connected to an electrical grid. Power source **101** may be, for example, a wind turbine that produces alternating current (AC), and power modules **103** may serve as AC-to-DC converters such as rectifiers and/or include use of switched mode power supply, for example.

[0015] Reference is now made to Fig. 1B, which illustrates circuitry that may be found in a power device such as power module **103**, according to an illustrative embodiment. Power module **103** may be similar to or the same as power device **107** shown in Fig. 1A. In some embodiments, power module **103** may include power circuit **135**. Power circuit **135** may include a direct current to direct current (DC/DC) converter such as a Buck, Boost, Buck/Boost, Buck + Boost, Cuk, Flyback, and/or forward converter. In some embodiments, power circuit **135** may include a direct current - alternating current (DC/AC) converter (also known as an inverter), such as a micro-inverter. Power circuit **135** may have two input terminals and two output terminals, which may be the same as the input terminals and output terminals of power module **103**. In some embodiments, power circuit **135** might be featured with the two input terminals of power module **103** directly coupled to the two output terminals of power module **103** so that power module **103** functions without power conversion. In some embodiments, power circuit **135** may feature a switch to disconnect the input terminals from the output terminals. In some embodiments, power module **103** may include Maximum Power Point Tracking (MPPT) circuit **138**, which is configured to extract increased power from a power source the power device is coupled to. In some embodiments, power circuit **135** may include MPPT functionality. In some em-

bodiments, MPPT circuit **138** may implement impedance matching algorithms to extract increased power from a power source the power device is coupled to. Power module **103** may further include controller **105** such as a microprocessor, Digital Signal Processor (DSP), Application-Specific Integrated Circuit (ASIC), and/or a Field Programmable Gate Array (FPGA).

[0016] Referring still to Fig. 1B, controller **105** may control and/or communicate with other elements of power module **103** over common bus **190**. In some embodiments, power module **103** may include circuitry and/or sensors/sensor interfaces **125** configured to measure parameters directly or receive measured parameters from connected sensors and/or sensor interfaces configured to measure parameters on or near the power source, such as the voltage and/or current output by the power source and/or the power output by the power source. In some embodiments, the power source may be a photovoltaic (PV) generator comprising PV cells, and a sensor unit (e.g., one or more sensors and/or sensor interfaces) may directly measure or receive measurements of the irradiance received by the PV cells, and/or the temperature on or near the PV generator.

[0017] Referring still to Fig. 1B, in some embodiments, power module **103** may include communication interface **129**, which is configured to transmit and/or receive data and/or commands from other devices. Communication interface **129** may communicate using Power Line Communication (PLC) technology that enables sending data over existing power cables, or wireless technologies such as ZigBee™, Wi-Fi, cellular communication or other wireless methods. Communication interface **129** may also include a mechanism for opto-electronic communication that includes optical fibers to convey data and/or commands from other devices.

[0018] In some embodiments, power module **103** may include memory device **123**, for logging measurements taken by sensor(s)/sensor interfaces **125** to store code, operational protocols or other operating information. Memory device **123** may be Flash, Electrically Erasable Programmable Read-Only Memory (EEPROM), Random Access Memory (RAM), Solid State Devices (SSD), or other types of appropriate memory devices.

[0019] Referring still to Fig. 1B, in some embodiments, power module **103** may include safety devices **160** (e.g., fuses, circuit breakers and Residual Current Detectors). Safety devices **160** may be passive or active. For example, safety devices **160** may include one or more passive fuses disposed within power module **103** and designed to melt when a certain amount of current flows through it, disconnecting part of power module **103** to avoid damage. In some embodiments, safety devices **160** may include active disconnect switches, which are configured to receive commands from a controller (e.g., controller **105**, or an external controller) to disconnect portions of power module **103**, or configured to disconnect portions of power module **103** in response to a measurement measured by a sensor (e.g., a measurement measured

or obtained by sensors/sensor interfaces **125**). In some embodiments, power module **103** may include auxiliary power circuit **162**, which is configured to receive power from a power source coupled to power module **103**, and output power suitable for operating other circuitry components (e.g., controller **105**, communication interface **129**, etc.). Communication, electrical coupling and/or data-sharing between the various components of power module **103** may be carried out over common bus **190**.

[0020] Referring still to Fig. 1B, in some embodiments, power module **103** may include bypass unit **Q9** coupled between the inputs of power circuit **135** and/or between the outputs of power circuit **135**. Bypass unit **Q9** and/or power circuit **135** may be a junction box to terminate power lines **120** or to provide a safety feature such as fuses or residual current devices. Bypass unit **Q9** may also be an isolation switch, for example. Bypass units **Q9** may be controlled by controller **105**. If an unsafe condition is detected, controller **105** may set bypass unit **Q9** to ON, short-circuiting the input and/or output of power circuit **135**. In a case in which power sources **101** are photovoltaic (PV) generators, each PV generator provides an open-circuit voltage at its output terminals. When bypass unit **Q9** is ON, the PV generator connected to module **103** may be short-circuited, to provide a voltage of about zero to power circuit **135**. In both scenarios, a safe voltage may be maintained, and the two scenarios may be staggered to alternate between open-circuiting and short-circuiting PV generators. This mode of operation may allow continuous power supply to system control devices, as well as provide backup mechanisms for maintaining a safe voltage (i.e., operation of bypass unit **Q9** may allow continued safe operating conditions).

[0021] Sensor/sensor interface **125** operatively attached to controller **105** may include analog to digital converters (not shown) that may be connected to sensors. The sensors may be configured to sense electrical parameters such as current, voltage and/or power of load **109**, power device **107** and the input and/or output parameters of power circuit **135** and power source **101**. Optionally, sensor/sensor interface may also include an energy gauge to count coulombs (amperes per second) when either charging or discharging a battery for example. The sensors may optionally be located and integrated inside power circuit **135** and/or network unit **112** and in other network units described below. The sensors may be optionally spatially located in the vicinity of power device **107** and load **109** respectively. Similarly, a sensor may be spatially located in the vicinity of power source **101**. Additional sensors may be added and configured to sense, for example, temperature, humidity and luminance.

[0022] Reference is made to Fig. 1C, which shows a buck+boost circuit implementation for power circuit **135**, according to one or more illustrative embodiments. Capacitor **C1** may connect in parallel across the positive and negative input terminals of the buck+boost circuit where the voltage is indicated as **VIN**. Capacitor **C2** may

connect in parallel across the positive and negative output terminals of the buck+boost circuit where the voltage is indicated as **VOUT**. The sources of insulated gate field effect transistors (IGFETs) **S3** and **S2** connect to the common negative output and input terminals of the buck+boost circuit. The drain of switch **S1** may connect to the positive input terminal, and the source of switch **S1** may connect to the drain of switch **S3**. The drain of switch **S4** may connect to the positive output terminal, and the source of switch **S4** may connect to the drain of switch **S2**. Inductor **L1** may connect respectively between the drains of switches **S3** and **S4**. The gates of switches **S1**, **S2**, **S3** and **S4** may be operatively connected to controller **105** (see also Fig. 1B).

[0023] Switches **S1**, **S2**, **S3** and **S4** may be implemented, for example, using metal oxide semiconductor field effect transistors (MOSFETs), insulated gate bipolar transistors (IGBTs), bipolar junction transistors (BJTs), Darlington transistor, diode, silicon controlled rectifier (SCR), Diac, Triac or other semi-conductor switches. Similarly, implementation for power circuit **135** may include, for example, a buck circuit, a boost circuit, a buck/boost circuit, a Flyback circuit, a Forward circuit, a charge pump, a Cuk converter or any other circuit that may be used to convert power on the input of power circuit **135** to the output of power circuit **135**.

[0024] Power circuit **135** may include or be operatively attached to a maximum power point tracking (MPPT) circuit **138**. MPPT circuit **138** may also be operatively connected to controller **105** or another controller. MPPT circuit **138** under control of controller **105**, or a central controller may be used to increase power extraction from power sources **101** and/or to control voltage and/or current supplied to load **109** and power device **107** in order to avoid damage to load **109** and power device **107**. Control of voltage and/or current to load **109** and power device **107**, might not necessarily use the feature of increasing power from power sources **101**, but rather may use MPPT circuit **138** to operate at a point in order to shed some of the power produced by power sources **101**.

[0025] In the various aspects described above for power system **100**, a communication protocol used by communication interface **129** of Fig. 1B in one primary power module **103** may communicatively control one or more other power modules **103** that are known as secondary power modules **103**. Once a primary/secondary relationship is established, a direction of control may be from the primary power module **103** to the secondary power modules **103**. When one primary power module **103** experiences a reduction of power input (e.g., due to shading in the case of photovoltaic panels used for power sources **101**), and the outputs of power modules **103** are connected in series, the power supply to power the primary module **130** may be taken from the other power module **103** outputs (e.g., by coupling auxiliary power circuit **162** to an output of power circuit **135**, which may be coupled to conductors carrying power from other power modules **103**. In the case of shading of a panel in a series string

including power modules **103** and/or other power modules as described below, a current bypass may be applied to the respective power module **103** and panel.

[0026] A communication protocol may be implemented for the direction of control between power modules and/or for transferring data and/or commands between power modules **103** and power device **107** using, for example power line communication (PLC) techniques over power lines of power system **100** and other power systems as described below. The communication protocol may be implemented using near field communication (NFC), Wi-Fi™ to connect to a wireless local area network (WLAN), BLUETOOTH™, ZIGBEE™, WIMAX™, controller area network (CAN) bus, local interconnect network (LIN), or as described later optical communication protocols such as Fiber Channel(FC), Synchronous Digital Hierarchy (SDH), Synchronous Optical Networking (SONET) or Optical Transport Network (OTN), for example. In some embodiments, communications may be implemented using acoustic communication technology.

[0027] Power system **100** may be operably connected to a central controller (not shown), according to one or more illustrative embodiments. The central controller may include a controller **105** coupled to a memory device **123** and a communication interface **129**. The central controller **105** may receive power supply in order to operate from power modules **103**, from an additional auxiliary power supply or from power device **107**. Central controller **105** may receive (e.g., from each power module **103**) measured electrical parameters (e.g., current, voltage and/or power of load **109**, power device **107** and/or the input and/or output of power circuit **135** and power source **101**) sensed by the sensors. In response to the sensed electrical parameters of each power module **103**, the central controller may send appropriate control signals to each power module **103** of power system **100**. Power modules **103**, central controller **105** and in descriptions of other power modules that follow, may derive their power needed to operate on the output side of the power modules, from power device **107** and/or auxiliary power circuits **162**. Auxiliary power circuits **162** may similarly derive their power needed to operate from the input side or output side of the power modules or from a power device **107**.

[0028] Reference is now made to Fig. 2A, which shows an isometric drawing of details of network unit **112**, according to one or more illustrative embodiments. Network unit **112** may include an upper housing **220a** and a lower housing **220b**. Network unit **112** may include a magnetic core that may include upper member **22a** and lower member **22b** that are respectively housed in upper housing **220a** and lower housing **220b**. Upper member **22a** may be separable from lower member **22b** at an opening opposite hinge **24**. Hinge is mounted to upper housing **220a** and lower housing **220b**. Upper member **22a** may be magnetically joined to lower member **22b** at the opening opposite hinge **24** by use of fastener **28** that may establish a magnetic path in the magnetic core. Alternatively,

the magnetic core may be constructed of one piece instead of two pieces such as upper member **22a** and lower member **22b** and the one piece housed in a single housing. In case the magnetic core is constructed as one monolithic piece, a power line 120 may be passed through the magnetic core without utilizing a hinge.

[0029] Reference is now made to Fig. 2B, which shows another isometric drawing of details of network unit **112**, according to one or more illustrative embodiments. Upper housing **220a** is shown attached to lower housing **220b**. Upper housing **220a** may be separable from lower housing **220b** at an opening opposite hinge **24**, by use of hinge **28**. A partial portion of power line **120** is shown inserted through the aperture between upper housing **220a** and lower housing **220b**. Connection wires **23** may provide power and/or connection to associated transmitter, receiver and/or transceiver circuits (not shown) located in lower housing **220b**.

[0030] Power to connection wires **23** in the descriptions that follow for the various embodiments of network units described herein may be supplied by a local power source for each network unit **112**, to auxiliary power circuit **162**, existing DC or AC bus or power in proximity to a network unit **112** that may be converted to DC power. Connection wires **23** may be self-fed by extracting magnetic power from power lines **120**. For example, a strong PLC signal may be used to feed the power requirements of network unit **112**. Alternatively, where DC plus and minus power lines **120** are available, a direct electrical contact of connection wires may be made to supply the power requirements of network unit **112**. Coupling to superimpose and receive signals onto power lines **120** may not be via direct electrical contact to power lines **120**. In some embodiments, connection wires might not be used, with power for operating network unit **112** provided by power lines **120** and communication taking place over power lines **120** and/or via wireless communications.

[0031] Reference is now made to Fig. 2C, which shows further details of network unit **112**, according to one or more illustrative embodiments. Network unit **112** may include a magnetic core that further includes upper member **22a** and lower member **22b**. Upper and lower housings **220a** and **220b** are not shown in order to simplify the drawing. Upper member **22a** may be separable from lower member **22b** at opening **26**. Upper member **22a** and lower member **22b** may pivot about hinge **24** as shown by respective arrows **24a** and **24b**. Upper member **22a** may be magnetically joined to lower member **22b** at opening **26** by use of fastener **28** to establish magnetic path **MP1**. A cross section of power line **120** is shown located in the aperture **29** formed between upper member **22a** and lower member **22b** when upper member **22a** is fastened to lower member **22b** with fastener **28**. The aperture **29** formed between upper member **22a** and lower member **22b** when upper member **22a** is fastened to lower member **22b** may be rectangular as shown, or aperture **29** formed between upper member **22a** and lower member **22b** may be circular, elliptical, triangular,

square, rectangular, or in a different polygon shape.

[0032] Network unit **112** may further include an inductor **L2** that may be wound to form a coil around upper member **22a** and may be connected to transceiver **20**. Transceiver **20** may be connected bi-directionally to communication interface **129** so that signals from communication interface **129** to transceiver **20** may be transmitted by transceiver **20** and signals received by the receiver of transceiver **20** may be sent to communication interface **129**. Aperture **29** between upper member **22a** and lower member **22b** may be of such a size so that upper member **22a** when fastened to lower member **22b** may cause power line **120** to be firmly clamped between upper member **22a** and lower member **22b**. A number of network units **112** may further be further mechanically mountable within a connection box, for example, or a number of network units **112** may be mechanically attached to each other. Alternatively, the magnetic core may be constructed of one piece instead of two pieces, such as upper member **22a** and lower member **22b**.

[0033] A magnetic coupling or transformer effect between power line **120** and inductor **L2** may allow signals from communication interface **129** transmitted by the transmitter part of transceiver **20**, to be induced into power line **120**. Similarly, inductor **L2** may allow signals present on power line **120** to be induced into inductor **L2** and therefore to be received by receiver portion of transceiver **20**, which may then be passed into communication interface **129**. Connection wires **23** of Fig. 2B (not explicitly shown) may provide power to transceiver **20** and/or allow the passing of communication signals.

[0034] Reference is now made to Fig. 2D, which shows further details of network unit **112**, according to one or more illustrative embodiments. Upper and lower housings **220a** and **220b** are not shown in order to simplify the drawing. Transceiver **20** may be separated into a separate receiver **20a** and transmitter **20b**. Both receiver **20a** and transmitter **20b** may be connected to communication interface **129** and respective inductors **L3** and **L4**. Inductor **L3** may be wound to form a coil around upper member **22a** and inductor **L4** may be wound to form a coil around lower member **22b**. A magnetic coupling or transformer effect between power line **120** and inductor **L3** may allow signals from communication interface **129** transmitted by transmitter **20b**, to be induced into power line **120**. Similarly, inductor **L4** may allow signals present on power line **120** to be induced into inductor **L4** and therefore to be received by receiver **20a**, which may then be passed into communication interface **129**. Connection wires **23** of Fig. 2B (not explicitly shown) may provide power to transceiver **20**, receiver **20a** and transmitter **20b** and/or allow the passing of communication signals.

[0035] Reference is now made to Fig. 2E, which shows further details of network unit **112**, according to one or more illustrative embodiments. Upper and lower housings **220a** and **220b** are not shown in order to simplify the drawing. Fig. 2E includes the same component parts as Fig. 2D, but both inductors **L3** and **L4** connected to

respective receiver **20a** and transmitter **20b** are both wound to form a coil around upper member **22a**. Receiver **20a** and transmitter **20b** both may connect to communication interface **129**. Communication interface **129**, previously has been described as being part of power modules **103** but may additionally be a part of power devices **107** and network units **112**. Communication signals conveyed between network units **112** and respective communication interfaces **129** in general may include control signals to control power modules **103**, for example, and to convey data to and from a controller or between power modules **103**. The communication signals applied by network units **112** for communication signals may be re-conditioned and re-repeated between network units **112** placed at various locations in a power system installation. Signals transmitted and received may include control signals, signals that identify a particular power module **103** and/or power devices **107**. Identification of power modules **103** and/or power devices **107** may allow an association between a group of power modules **103** and a particular power device **107** for example. Signals may also represent a parameter sensed in power system **100** at the various electrical connections of power system **100** and/or various topographic locations of power sources **101**, for example. The parameter may include voltage, current, power, coulombic charge, level of solar irradiance or temperature for example. For example, sensing of current may use a Hall effect sensor. Control signals based on the parameters sensed in power systems **100** may then be conveyed to particular power modules **103** to control the distribution of power to particular loads **109** or charge storage devices, for example.

[0036] Connection wires **23** of Fig. 2B (not explicitly shown) may provide power to transceiver **20**, receiver **20a** and transmitter **20b** and/or allow the passing of communication signals.

[0037] While Figs. 2C, 2D and 2E show inductive coupling, alternatives to inductive coupling may be used, which may include capacitive coupling or by direct coupling by wire or resistor, for example. Further aspects of coupling to superimpose and receive signals onto power lines **120** may be by a variable capacitance which may be configured to substantially match both lumped and distributed impedances of the power lines **120** at various points in power system **100**. The matching of distributed and lumped impedances of and connected to the power lines **120** at various points in power system **100** may be done to ensure that substantially most of the signal power of signals may be superimposed and received respectively onto and from power lines **120**. Substantially most of the signal power of signals superimposed and received respectively onto and from power lines **120** may be at least one way of improving signal to noise ratios (SNRs) at various points in power system **100**. The variable capacitance may be by a varicap diode and/or the variable capacitance may be provided by a switched capacitor circuit controlled by controller **105** or a central controller. Measurement of the various electrical parameters at var-

ious points in power system **100** by sensors/sensor interfaces **125** and subsequent analysis may deem that both the lumped and distributed impedances of the power lines **120** and devices attached to power lines **120** at various points to be detrimental for effective communications. For example, the communications applied by network units **112** for facilitating monitoring, supplying and control of powers to loads **109** from power modules **103** and power devices **107** may therefore be, according to features described above, to enable dynamic and/or statically predefined configurations of power system **100**.

[0038] Reference is now made to Fig. 2F, which shows an isometric view of a network unit **112**, according to one or more illustrative embodiments. Network unit **112** is made from a single housing **220**, but may also be made from two housings **220a** and **220b** as described previously above with respect to Figs. 2A and 2B. Elliptical apertures **25** are shown that go through housing **220** where optional connection wires (e.g., connection wires **23** of Fig. 2B) may be inserted and connected to provide power to transceiver **20**, receiver **20a** and/or transmitter **20b** (not shown) that may be located in housing **220**. Two power lines **120** are shown inserted through the aperture of housing **220**, and network unit **112** may receive and/or transmit communication signals over power lines **120**.

[0039] Reference is now made to Fig. 2G, which shows an isometric view of a magnetic core **22**, according to one or more illustrative embodiments. In some embodiments, magnetic core **22** may comprise two parts, an upper member and a lower member, similarly to as shown previously in Figs. 2A, 2B, 2C, 2D and 2E. In some embodiments, magnetic core **22** may comprise a single, monolithic member. Inductors **L3** and **L4** may be wound around magnetic core **22** to form respective coils around magnetic core **22**. Inductors **L3** and **L4** may be further connected to respective receiver **20a** and transmitter **20b** (not shown). Magnetic core **22** may be located and housed in a housing (e.g., **220**). Alternatively, more than one magnetic core **22** may be located and housed in a housing (e.g. **220**) such that for example, one magnetic core **20** may have inductor **L3** connected to receiver **20a**, while another magnetic core **20** may have inductor **L4** connected to transmitter **20b** (both not shown).

[0040] Reference is now made to Fig. 2H, which shows a plan view and Fig. 2I which shows a cross sectional view **A-A** of network unit **112**, according to one or more illustrative embodiments. With respect to the plan view, two power lines **120** are shown going through the aperture of housing **220**. With respect to the cross sectional view **A-A**, inductors **L3** and **L4** are shown wrapped around in coils of respective members of magnetic **22** shown located and mounted in housing **220**. Power lines **120** are shown going through the aperture of housing **220**. Space between housing **220** and magnetic core **22** may allow for the mounting and connection of additional component such as sensors/sensor interfaces **125**, controllers **105**, communication interfaces **129**, receiver **20a**, transmitter **20b**, and/or transceiver **20** (all not shown).

[0041] Reference is now made to Fig. 3A, which shows another isometric drawing of details of two network units **112**, according to one or more illustrative embodiments. A partial part of power line **120** is shown inserted in between two upper and lower housings **220a** and **220b** of each network **112**. Partial parts of upper members **22a** (shown by dotted lines) may be located in respective upper housings **220a**. Alternatively, the housing of the magnetic core and the magnetic core for a network unit **112** may each be constructed of one piece of material instead of two pieces, such as upper member **22a**/upper housing **220a** and lower member **22b**/lower housing **220b**. The cross section of the aperture formed between upper housing **220a** and lower housing **220b** may be circular, elliptical, triangular, square, rectangular, or in a different geometric shape. Similarly, if both the housing of the magnetic core and the magnetic core for network unit **112** are each constructed of one piece of material instead of two, the aperture through a housing of the magnetic core and the magnetic core may be circular, elliptical, triangular, square, rectangular, or in a different geometric shape. The aperture formed between upper housing **220a** and lower housing **220b** may or might not physically clamp power lines **120**. The apertures described above may accommodate the insertion of one or more power lines **120**.

[0042] Power line **120** also may connect to a safety circuit **340** that may be a fuse, circuit breaker or isolation switch, for example. Inductors **L3** and **L4** may be wound around the respective magnetic cores of upper members **22a** and may be further connected to respective receiver **20a** and transmitter **20b**. Alternatively, inductor **L3** may be wound around the magnetic core of lower member **22b** and may be further connected to a transceiver **20** as shown in Fig. 2C, for example. Elliptical apertures **25** are shown that go through lower housings **220a** where connection wires **23** may be inserted and connected to provide power to transceiver **20**, receiver **20a**, and/or transmitter **20b**.

[0043] Fig. 3A, which shows details of two network units **112** with each network units having separate magnetic cores, whereby one network unit **112** houses receiver **20a**/inductor **L3** and one network unit **112** houses transmitter **20b**/inductor **L4**. Alternatively, one network unit **112** may house both transmitter **20b** and receiver **20a** and/or transceiver **20**/inductor **L2** on one magnetic core on various locations of a magnetic core as shown in Figs. 2C, 2D and 2E. Alternatively, one network unit **112** may additionally house sensors/sensor interfaces **125**, controllers **105**, and/or communication interfaces **129**. Separating receiver **20a** and transmitter **20b** into separate network units may be desirable, for example, in order to provide network units to a particular system using network units **112** for transmission only (e.g., transmitting monitored parameters to a logging and/or monitoring databases) or for reception only (e.g., to receive operational commands from a central controller).

[0044] Reference is now made to Fig. 3B, which shows

multiple network units **112** attached to a mounting plate **342**, according to one or more illustrative embodiments. Partial portions of power lines **120** are shown passing through network units **112** and may be attached to safety circuits **340**. Mounting plate **342** may be mounted in a connection box (not shown) located at nodes **A** and **B** for example with reference to Fig. 1A. Other network units described below may be similarly mounted in connection boxes at various points in a power system for example. At nodes **A** and **B** for example, multiple power lines **120** from multiple parallel connection configurations **111** may all be present in the connection box (e.g., a string combiner box). In the connection box, the multiple power lines **120** may be often in close physical proximity to each other. The close proximity of power lines **120** to each other may allow reduced costs by coupling power lines **120** to network units **112** on a common mount or rack such as mounting plate **342**, for example.

[0045] In terms of communications, the multiple network units **112** connection wires **23** may be further interconnected between elliptical apertures **25** and attached to the communication interface of a power device **107**, power modules **103**, and/or central controller that may be located within the connection box and/or in proximity to the connection box.

[0046] By way of example, a pair of networks units **112** may be located in parallel to each other on respective corresponding positive and negative power lines **120** used in power system **100**. A differential comparison of currents and/or voltages in positive and negative power lines may indicate the possibility of leakage voltages and/or currents and/or arcing taking place in power system **100**. All of the considerations described for the connection box may be applied to the descriptions that follow.

[0047] Reference is made to Fig. 3C, which shows multiple network units **112** mounted in a connection box **350**, according to one or more illustrative embodiments. The multiple network units **112** are shown mounted on a DIN (Deutsches Institut für Normung) rail **354** that is mountably attached to the back panel of connection box **350**. Similarly, multiple circuit breakers **356** are shown mounted on a DIN rail **354** that is mountably attached to the back panel of connection box **350**. Multiple power lines **120** may be inserted through respective apertures of each network unit **112** and terminated in a respective circuit breaker **356**. Power lines **120** are shown entering through the bottom panel of connection box **350** through cable openings **352**. Connection box **350** may additionally include safety circuits **340** (as shown in Fig. 3B) that may further include electrical isolators, circuit breakers **356**, and residual current devices (RCDs). Connection box **350** may additionally include additional DIN rail **354** to mount additional terminal blocks for interconnecting power lines **120**. Connection box **350** may additionally provide housing and connection of power modules, power devices, and control units.

[0048] Reference is made to Fig. 4A, which shows a block diagram of a power system **400a**, according to one

or more illustrative embodiments. A connection configuration **111a** includes a power source **101** with direct current (DC) output terminals that may be connected to the input terminals of power module **103**. The input of power module **103a** may similarly be connected to the output of a power source **101**. DC output terminals of power modules **103** and the DC output terminals of power module **103a** in connection configuration **111a** may be connected in series to give a series connection. The series connection may include the DC outputs of power modules **103** connected in series with power lines **120** to the bottom DC input of power module **103a**, and the top DC output of power module **103a** connected to the electrical portion of power line **420a** (shown by solid line) that includes a fiber optic portion (shown by dotted line). Multiple connection configurations **111a** may be connected in parallel across the input of power device **107** that may be a direct current (DC) to DC converter or may be a DC to alternating current (AC) inverter supplying power to load **109**. Load **109** may be a battery, an alternating current (AC) grid or a DC grid, or a DC to AC inverter. Network unit **112** may be attached to power lines **120/420a** at various locations such as the top of a series string of power module **103** outputs, at connection nodes **A** and/or **B** or at power device **107**. In general, any number of network units **112/412a** may be attached to power lines **120/420a** at any number of locations of power system **400a**. The attachment of network units **112/412a** to power lines **120/420a** may include electrical-mechanical, optoelectronic-mechanical, and electromagnetic-mechanical mechanisms.

[0049] Power module **103a** may be the same as power module **103** but may also further include a network unit **412a** operatively attached to a communication interface similar to a communication interface **129** of a power module **103**. Network unit **412a** may be an integral part of a power module **103a**. Network unit **412a** may be operatively attached to communication interface **129** of a power module **103** or operably attached to a similar communication interface of power device **107**.

[0050] Network unit **412a** may be attached to power lines **420a** at various locations such as the top of the series string of power modules **103/103a** outputs, at connection nodes **A** and/or **B** or at power device **107**. In general, any number of network units **412a** may be attached to power lines **420a** at any number of locations. Power lines **420a** may include a fiber optic cable (shown in dotted line) integrated with a power cable (shown by solid line) that is similar to power line **120**.

[0051] Network unit **412a** may be connected to a network unit **112** to enable communication of both transmitted and received signals between respective power modules **103a** and power modules **103**. A feature of network unit **412a** may be to combine an optical-cable integrated power line with electro-magnetic circuitry of network unit **112** so as to transmit and receive signals using power line communications over power lines **120** and the power cable portion (shown by solid line) of power line **420a** as

described above with respect to the features of network unit **112**) as described above with respect Figs. 2C, 2D and 2E.

[0052] Network unit **412a** may be further used to enable communication of both transmitted and received signals between power modules **103a** and power devices **107** connected by power line **420a**. The connection to enable communication between power modules **103a** and power devices **107** may use the fiber optic portion of power line **420a** (shown by dotted line) or use the electrically conductive portion of power line **420a** (shown by solid line) for power line communications (PLCs) as described above with respect Figs. 2C, 2D and 2E.

[0053] The signals transmitted and received may include control signals, signals which identify a particular power module **103/103a** and/or power device **107**. Identification of power modules **103/103a** and/or power device **107** may allow an association between a group of power modules **103/103a** and a particular power device **107**, for example. Signals may also represent a parameter sensed in power systems **100/400a** at the various electrical connections of power system **100** and/or topographic locations of power sources **101**, for example. The parameter may include voltage, current, power, coulombic charge, level of solar irradiance, or temperature, for example. Control signals based on the parameters sensed in power systems **100/400a** may then be conveyed to particular power modules **103/103a** to control the parameters sensed in power systems **100/400a**.

[0054] Reference is made to Fig. 4B, which shows further details of network unit **412a**, according to one or more illustrative embodiments. Network unit **412a** includes a connection housing **440** for a fiber optic connector **F1**. Connection housing **440** may include a receiver **450a** connected to a photo-diode **PD1** that receives light from fiber optic connector **F1**. Fiber optic connector **F1** may connect to the fiber optic cable of power line **420a**. Photodiode **PD1** may convert the received light from fiber optic connector **F1** into an electrical signal that is applied to the input of receiver **450a**. Receiver **450a** may decode the electrical signal into data on data output **430** and may provide indication of a detected signal at detected signal output **432**. Both data output **430** and detected signal output **432** may be coupled to a communications interface such as communications interface **129**.

[0055] Network unit **412a** may further include a connection housing **442** for a fiber optic connector **F2**. Connection housing **442** includes a transmitter **420b** connected to a laser diode **LD1** that transmits light from fiber optic connector **F2**. Fiber optic connector **F2** may connect to the fiber optic cable of power line **420a**. Laser diode **LD1** converts the data on data input **434** from an electrical signal to a light signal for transmission on fiber optic connector **F2**. Multiple connection housings **440** and **442** may be included in network unit **412a**.

[0056] Transmitter **420b** and receiver **450a** of network unit **412a** may be operatively attached to a communica-

tion interface similar to a communication interface **129** of a power module **103**. The communication interface in power modules **103/103a** and power devices **107** may be operatively attached to transmitter **420b** and receiver **450a** of network unit **412a**. In general, according to various features described above, network units **112** and/or **412a** may be integrated into power modules **103/103a**, and/or power devices **107**.

[0057] Communication interfaces **129** may be attached to or be an integral part of power modules **103/103a**, power devices **107** and network units **112/412a**. As such, communication interfaces **129** according to embodiments described above are able to interface to allow communication of signals using Power Line Communication (PLC) technology that enables sending data over existing power cables, or wireless technologies such as ZIGBEE™, Wi-Fi, cellular communication or other wireless methods. Communication interface **129** may also include a mechanism for opto-electronic communication that includes optical fibers to convey data and/or commands from and to other devices. Network units **112/412a** may be connected to various parts of power systems **100/400a** installation via communication interfaces **129** that may be configured to enable signals to be superimposed onto power lines **120/420a** and to be received from off power lines **120/420a** via network units **112/412a**. Coupling between the network units **112/412a** and the power lines **120/420a** may be an electromagnetic coupling, a capacitive or a direct coupling.

[0058] Sensors/sensor interfaces **125** connected to communication interfaces **129** and network units **112/412a** may enable sensing of parameters such as powers, currents, voltages, coulombs, characteristic impedance and temperatures of their respective inputs and outputs, and may be used to assess the best way of superimposing communication and control signals onto power lines **120/420a** and receiving communication and control signals off power lines **120/420a**. Based on the assessment, signals may be conveyed instead via wireless technology or by use of fiber optic transceivers and fiber optic cables, for example. The fiber optic cables may be an integral part of the power lines **120/420a**. Communication signals in general may include control signals to control power modules **103/103a**, for example, and to convey data to and from a controller **105** or between power modules **103/103a**. The communication signals applied by the network units **112/412a** for communication signals maybe re-conditioned and re-repeated between network units **112/412a**. Network units **112/412a** placed at various locations in the power systems **100/400a** installations, for example.

[0059] According to some illustrative embodiments, DC power sources are connected to a load and/or a storage device via multiple power modules to for a power system. Network units placed at various points in power system may allow communication between various parts of power system to allow the sensing and conveying of

sensed parameters to a controller to monitor and control, for example, the power modules. The power modules may control power such that a load and/or a storage device may match the DC power from the DC power sources, in which power may be shed from the load and/or the storage device. Optionally, DC power from the storage device may be matched and supplied to the load, or optionally DC power from the DC power sources may be matched and supplied to the load. To control power, the power modules may include sensors capable of sensing parameters such as powers, currents, voltages, coulombs, and temperatures of their respective inputs and outputs.

[0060] According to some illustrative embodiments, network units may be connected to various parts of a power system installation and may be configured to enable signals to be superimposed onto power lines and to be received from off power lines. Coupling between the network units and the power lines may be an electromagnetic coupling, a capacitive or a direct coupling. Sensors capable of sensing parameters such as powers, currents, voltages, coulombs, characteristic impedance and temperatures of their respective inputs and outputs may be used to assess the feasibility of superimposing communication and control signals onto power lines and receiving communication and control signals off power lines. Based on the assessment, signals may be conveyed instead via wireless technology or by use of fiber optic transceivers and fiber optic cables, for example. The fiber optic cables may be an integral part of the power lines. Communication signals in general may include control signals to control power modules for example and to convey data to and from a controller or between power modules. The communication signals applied by the network units for communication signals maybe re-conditioned and re-repeated between network units placed at various locations in the power system installation.

[0061] According to some illustrative embodiments, the state of charge of storage devices may be sensed and communicated between various parts of the power system by use of the network units. Upon the sensed charge of the storage device being above a first predetermined level of state of charge, the power stored in the storage device may be supplied to a load, whereby the stored charge of the storage device is discharged to the load. Upon the sensed charge of the storage device being below a second predetermined level of state of charge, the storage device may then be charged and power to the load may be supplied responsive to the measured power.

[0062] According to some illustrative embodiments, a power circuit may be connected at its output to a load and to a storage device. A switch may be provided at an output terminal of the power circuit, to enable connection or disconnection between the output terminal of the power circuit and an input terminal of the storage device. Control of the switch may be based on communications between network units in the power system, which may

convey measured parameters of the power system to a controller. With the switch in an ON position, the load and the storage device are connected in parallel across an output terminal of the power circuit. With the switch in an OFF position, the load remains connected across the output terminal of the power circuit, and the storage device is disconnected from the output terminal of the power circuit. In the context of a photovoltaic (PV) panel implementation of a power system, operation of the switch in the ON position may allow power to be supplied to the load and to the storage device when power from a power source (e.g., solar panel) providing power to the power circuit is sufficient (e.g., during the daytime). Operation of the switch in an OFF position may allow power to be supplied to the load if charging of the storage device is to be avoided, such as when the storage device is already substantially fully charged, or to reduce the number of charging cycles of the storage device, or when power from the power source supplying power to the power circuit is insufficient to both power the load and the charge the storage device. When power from the power source is insufficient (e.g., during the nighttime), the switch may be placed in the ON position, allowing power from the storage device to be applied to the load.

[0063] According to some illustrative embodiments, the groups of DC power sources may include groups of DC power sources where the direct current to supply a load and/or a storage device may be derived from renewable energy sources such as sunlight, wind, rain, tides, waves, and geothermal heat. Devices that convert these renewable energy sources include for example photovoltaic solar generators, wind generators and wind turbines. The groups of DC power sources may also include groups of DC power sources where the direct current is derived from non-renewable energy sources. Devices that convert these non-renewable energy sources into DC power to supply a load and/or a storage device may include petrol, oil and gas generators and/or turbines for example. The direct current may also be derived from rectified or converted sources of alternating current provided from a switched mode power supply, dynamo or alternator for example.

[0064] According to some illustrative embodiments, DC power sources in a DC power system are interconnected to various groups of DC sources. Each group of DC sources may contain different types of DC power derived from both renewable and non-renewable energy sources, so that the DC power generated may be configured to meet the criteria of providing an uninterruptable source of DC power to a load from the DC power sources and/or to store some of the DC power in a storage device. A part of the criteria may be to utilize energy previously stored in the storage device to subsequently supply power and what might be considered to be emergency power to the load when the DC sources are not able to produce power owing to lack of sunlight, wind and/or fuel for example.

[0065] According to some illustrative embodiments,

DC power sources may include a connection of DC sources to a load and/or storage device via multiple power modules. The power modules may control power responsive to sensed parameters communicated between various parts of the power system by use of the network units. Control may be such that the load and/or storage may match the DC power from the DC power sources, power may be shed from the load and/or storage. Optionally DC power from storage device may be matched and supplied to the load or optionally DC power from the DC power sources may be matched and supplied to the load. To control power, the power modules may include the capability of sensing parameters such as powers, currents, voltages, coulombs, temperatures of their respective inputs and outputs via sensors to a controller.

[0066] According to some illustrative embodiments, the power modules may control power to the load and/or storage device according to a load profile. The load profile may include an information update via communication interfaces included in the power modules that communicate with each other via the network units to receive weather information such as present and forecasted temperature, wind speed, cloud cover and amount of sunlight for example. The load profile may also include updated information with regards to an updatable load demand history of the power system with reference to daily and nightly demand, weekday demand and monthly demand. The updatable load demand history of the power system may also take into account the amount of fuel and cost of fuel available to utilize petrol, oil and gas generators and/or turbines instead of using other types of DC power provisioning, for example.

[0067] According to some illustrative embodiments, the power modules may control power to the load and/or storage device according to a charge profile of a storage device. Using the example of a battery for the storage device, the charge profile may ensure optimal charging of the battery that may prefer a constant voltage level or constant current for at least a minimum period of time. The charge profile may also specify control of the temperature of the battery during charging via the network units, which may improve the performance and/or reliability of the battery, since the battery may need to stay cool when being charged so as to ensure optimal charging.

[0068] According to some illustrative embodiments, consideration may be given to different types of batteries when charging and discharging to ensure that correct voltages, currents, temperatures and appropriate time periods of charge and discharge are monitored, controlled via the network units and applied to batteries so as to avoid damage to the batteries. In addition, the charge profile may include reconfiguration of the charge profile based on data of the transfer of charge and/or discharge of a battery in order to access the ageing and use of batteries. Such data logging via the network units may then be used to provide an estimate of projected battery life and timing of battery maintenance and replacement

for example.

[0069] According to some illustrative embodiments, the power modules may be configurable via the network units to control the delivery of power of the DC sources to a load and/or a storage device. The power modules may be configurable via the network units to control the delivery of power to a load from energy previously stored in the storage device. The power modules may be configurable to control the delivery of power to a load from both the DC power sources and the storage device together.

[0070] According to some illustrative embodiments, a method for a power system that may include a controller, multiple DC power sources, multiple DC power modules, multiple bi-directional power modules and multiple storage devices. In the method, each of the power sources may be coupled to a respective DC power module. The power modules outputs may be coupled in a connection that may be a series connection of the power modules outputs, to form thereby, a serial string of power module outputs. The connection may also be a parallel connection of the power modules outputs. The serial string or the parallel connection may be coupled to a load and may be also coupled to the bi-directional power modules. Each of the bi-directional power modules may be coupled to respective storage devices. Power of each of the power sources may be measured by sensors provided with each of the power modules.

[0071] According to some illustrative embodiments, upon the power being measured, a signal may be transmitted by a network unit to the power module and/or a bi-directional power modules. The signal sent to power modules via the network units may serve the function of instructing the power modules to shut down completely (e.g., using an explicit message) due, for example, to a safety condition in the power system, to reduce power (e.g., an explicit message or lack of a signal) in order to shed power, to let the power modules to continue to control power at the present level or to increase power to a load and/or storage device. In general, the supply of power to the load and/or storage device may be controlled responsive to the power measured. The load may comprise multiple loads, and multiple DC power modules may be respectively coupled between the serial string and the loads so that loads with different voltage levels and current requirements may be accommodated. Similarly, different types of storage devices may also include respective bi-direction power modules so as to accommodate the different voltage levels and current level requirements such as constant voltage or constant current for charging the storage device for example. The bi-directional nature of the power modules of respective storage devices also allow the accommodation and provision of the different voltage levels and current level requirements of the multiple loads, when power to the loads is provided from the storage devices.

[0072] According to some illustrative embodiments, the control of power supplied to the load via a network

unit may further include at least one of the storage devices to be depleted prior to subsequent charging of the at least one storage device, thereby mitigating damage to the at least one storage device. The at least one storage device depleted may additionally demand that at least one of the other the storage devices remains substantially charged so that it may be used in an emergency situation for example or to satisfy a requirement that a minimal amount energy is always available to be supplied.

[0073] It is noted that various connections are set forth between elements herein. These connections are described in general and, unless specified otherwise, may be direct or indirect; this specification is not intended to be limiting in this respect. Further, although elements herein are described in terms of either hardware or software, they may be implemented in either hardware and/or software. Additionally, elements of one embodiment may be combined with elements from other embodiments in appropriate combinations or sub-combinations. For example, sensor(s), power source(s), storage element(s), and interconnections of one embodiment may be combined with similar elements of another embodiment and used in any combination or sub combination. For example, network unit **112** may be combined with network unit **412a** so that the fiber optic transceiver part may provide communications between parts of power systems **100/400a** when good PLC communications in certain sections of power systems **100/400a** may be difficult to achieve. Another example may be the possible use of network units **112/412** as repeaters and/or to recondition signals sent between various sections of power systems **100/400a**. Further, the detachable/reconnectable nature of network units **112/412** may also allow for a retrofit of an existing power system so that power produced may be monitored and controlled via use of network units **112/400a**.

[0074] One skilled in the art will recognize that the various embodiments detailed above may be combined in suitable combinations and that portions of the embodiments may be unitized in various sub combinations. For example, network units **112** of Fig. 3C may be designed and disposed in a connection box **350** and may communicate with additional network units **112** designed as shown as Fig. 2A and installed as part a connection configuration **111** as shown in Fig. 1A.

[0075] According to a first illustrative embodiment, there is provided a power system. The power system includes a plurality of direct current (DC) power sources coupled to respective inputs of a plurality of power modules, wherein the outputs of the power modules are connected together with a plurality of first power lines in series to form a serial string. The power system also includes at least one power device with an input connected across the serial string. The power modules include at least one communication interface. The power modules also include at least one sensor interface operatively attached to the at least one communication interface,

wherein the at least one sensor interface includes at least one sensor configured to sense at least one parameter in the serial string. The power modules further include at least one network unit operatively attached to at least one of the first power lines and the at least one communication interface. The at least one network unit is operable to superimpose a first signal representative of the at least one parameter onto the first power lines, thereby to transmit the first signal to at least one of the other power modules or to the at least one power device. The at least one network unit is also operable to receive a second signal of the at least one parameter superimposed onto the first power lines from another network unit.

[0076] For the power system according to the first illustrative embodiment, the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

[0077] For the power system according to the first illustrative embodiment, the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

[0078] For the power system according to the first illustrative embodiment, the magnetic core comprises two members attachable and re-attachable to each other to form thereby the at least one aperture.

[0079] For the power system according to the first illustrative embodiment, the transceiver is operatively attached to the at least one communication interface.

[0080] For the power system according to the first illustrative embodiment, the at least one network unit is attachable or re-attachable to at least one location on at least one of the first power lines.

[0081] For the power system according to the first illustrative embodiment, the at least one parameter is selected from the group of parameters consisting of: voltage, current, power, temperature, coulombic charge, and solar irradiance.

[0082] For the power system according to the first illustrative embodiment, the first signal or the second signal is a control signal configured to control the power modules.

[0083] For the power system according to the first illustrative embodiment, the first signal or the second signal is a signal representative of the at least one parameter sensed by the at least one sensor.

[0084] For the power system according to the first illustrative embodiment, the first signal is superimposed onto the first power lines by a coupling between the network unit and the first power lines selected from the group of couplings consisting: an electromagnetic coupling, a capacitive coupling, and a direct coupling.

[0085] For the power system according to the first illustrative embodiment, the second signal is received from the first power lines by a coupling between the network unit and the first power lines selected from the group of couplings consisting of: an electromagnetic coupling, a capacitive coupling, and a direct coupling.

[0086] For the power system according to the first illustrative embodiment, the first signal and the second signal are respectively superimposed and received onto the first power lines by a variable capacitance configurable to correct the inductive reactance of the first power lines.

[0087] For the power system according to the first illustrative embodiment, the variable capacitance is a varicap diode.

[0088] For the power system according to the first illustrative embodiment, the variable capacitance is a switched capacitor circuit.

[0089] For the power system according to the first illustrative embodiment, the first signal and the second signal are respectively superimposed and received onto the first power lines by a coupling between the network unit and the first power lines, wherein the coupling is by a variable capacitance configurable to substantially correct the inductive reactance of the first power lines.

[0090] For the power system according to the first illustrative embodiment, the first signal and the second signal are respectively superimposed and received onto the first power lines by a coupling between the network unit and the first power lines, wherein the coupling is by a filter configurable to allow a bandwidth of the first signal and the second signal to be respectively superimposed and received onto the first power lines.

[0091] According to a second illustrative embodiment, there is provided a power system. The power system includes a plurality of direct current (DC) power sources coupled to respective inputs of a plurality of power modules, wherein the outputs of the power modules are connected together with a plurality of first power lines in series to form a serial string. The power system also includes at least one power device with an input connected across the serial string by a plurality of second power lines, wherein the second power lines include a fiber optic portion. The power modules include at least one communication interface. The power modules also include at least one sensor interface operatively attached to the at least one communication interface, wherein the at least one sensor interface includes at least one sensor configured to sense at least one parameter in the serial string. The power modules further include at least one network unit operatively attached to at least one of the second power lines and the at least one communication interface. The at least one network unit is operable to superimpose a first optical signal representative of the at least one parameter onto the fiber optic portion of the second power lines, thereby to transmit the first optical signal to at least one of the other power modules or to the at least one power device. The at least one network node is also op-

erable to receive a second optical signal of the at least one parameter superimposed onto the fiber optic portion of the second power lines from another network unit.

[0092] For the power system according to the second illustrative embodiment, the at least one network unit includes a magnetic core with at least one aperture there-through, wherein a power line is insert-able through the at least one aperture. The at least one network module also includes an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture. The at least one network module further includes a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the power line or to receive a signal present on the power line when the power line is inserted through the at least one aperture.

[0093] For the power system according to the second illustrative embodiment, the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

[0094] According to a third illustrative embodiment, there is provided a network unit. The network unit includes a magnetic core with at least one aperture there-through, wherein a first power line is insert-able through the at least one aperture. The network unit also includes an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture. The network unit further includes a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the first power line or to receive a signal present on the first power line when the first power line is inserted through the at least one aperture. The network unit is operable to superimpose, onto the first power line, a first signal representative of at least one parameter of a serial string of power modules connected with a plurality of power lines that includes the first power line, thereby to transmit the first signal to at least one of the power modules. The network unit is also operable to receive a second signal of the at least one parameter superimposed onto the first power line from another network unit.

[0095] Various characteristics of various embodiments of the invention as hereinafter highlighted in a set of numbered claims. These characteristics are not to be interpreted as being limiting on the invention or inventive concept, but are provided merely as a highlighting of some characteristics of the invention as described in the description without suggesting a particular order of importance or relevancy of such characteristics.

Clause 1: A power system comprising:

a plurality of direct current (DC) power sources coupled to respective inputs of a plurality of pow-

er modules, wherein the outputs of the power modules are connected together with a plurality of first power lines in series to form a serial string;

at least one power device with an input connected across the serial string;
wherein the power modules include:

at least one communication interface;

at least one sensor interface operatively attached to the at least one communication interface, wherein the at least one sensor interface includes at least one sensor configured to sense at least one parameter in the serial string;

at least one network unit operatively attached to at least one of the first power lines and the at least one communication interface, the at least one network unit is operable to:

superimpose a first signal representative of the at least one parameter onto the first power lines, thereby to transmit the first signal to at least one of the other power modules or to the at least one power device; and

receive a second signal of the at least one parameter superimposed onto the first power lines from another network unit.

Clause 2: The power system of clause 1, wherein the at least one network unit comprises:

a magnetic core with at least one aperture there-through, wherein a power line is insert-able through the at least one aperture;

an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture;

a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the power line or to receive a signal present on the power line when the power line is inserted through the at least one aperture.

Clause 3. The power system of clause 2, wherein the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

Clause 4. The power system of clause 2, wherein the magnetic core comprises two members attachable and re-attachable to each other to form thereby the at least one aperture.

5

Clause 5. The power system of clause 2, wherein the transceiver is operatively attached to the at least one communication interface.

Clause 6. The power system of clause 1, wherein the at least one network unit is attachable or re-attachable to at least one location on at least one of the first power lines.

10

Clause 7. The power system of clause 1, wherein the at least one parameter is selected from the group of parameters consisting of: voltage, current, power, temperature, coulombic charge, and solar irradiance.

15

Clause 8. The power system of clause 1, wherein the first signal or the second signal is a control signal configured to control the power modules.

20

Clause 9. The power system of clause 1, wherein the first signal or the second signal is a signal representative of the at least one parameter sensed by the at least one sensor.

25

Clause 10. The power system of clause 1, wherein the first signal is superimposed onto the first power lines by a coupling between the network unit and the first power lines selected from the group of couplings consisting: an electromagnetic coupling, a capacitive coupling, and a direct coupling.

30

35

Clause 11. The power system of clause 1, wherein the second signal is received from the first power lines by a coupling between the network unit and the first power lines selected from the group of couplings consisting of: an electromagnetic coupling, a capacitive coupling, and a direct coupling.

40

Clause 12. The power system of clause 1, wherein the first signal and the second signal are respectively superimposed and received onto the first power lines by a variable capacitance configurable to correct the inductive reactance of the first power lines.

45

Clause 13. The power system of clause **Fout! Verwijzingsbron niet gevonden.**, wherein the variable capacitance is a varicap diode.

50

Clause 14. The power system of clause **Fout! Verwijzingsbron niet gevonden.**, wherein the variable capacitance is a switched capacitor circuit.

55

Clause 15. The power system of clause 1, wherein

the first signal and the second signal are respectively superimposed and received onto the first power lines by a coupling between the network unit and the first power lines, wherein the coupling is by a variable capacitance configurable to substantially correct the inductive reactance of the first power lines.

Clause 16. The power system of clause 1, wherein the first signal and the second signal are respectively superimposed and received onto the first power lines by a coupling between the network unit and the first power lines, wherein the coupling is by a filter configurable to allow a bandwidth of the first signal and the second signal to be respectively superimposed and received onto the first power lines.

Clause 17. A power system comprising:

a plurality of direct current (DC) power sources coupled to respective inputs of a plurality of power modules, wherein the outputs of the power modules are connected together with a plurality of first power lines in series to form a serial string;

at least one power device with an input connected across the serial string by a plurality of second power lines, wherein the second power lines include a fiber optic portion;

wherein the power modules include:

at least one communication interface;

at least one sensor interface operatively attached to the at least one communication interface, wherein the at least one sensor interface includes at least one sensor configured to sense at least one parameter in the serial string;

at least one network unit operatively attached to at least one of the second power lines and the at least one communication interface, the at least one network unit is operable to:

superimpose a first optical signal representative of the at least one parameter onto the fiber optic portion of the second power lines, thereby to transmit the first optical signal to at least one of the other power modules or to the at least one power device; and

receive a second optical signal of the at least one parameter superimposed onto the fiber optic portion of the second power lines from another network unit.

Clause 18. The power system of clause 17, wherein the at least one network unit comprises:

a magnetic core with at least one aperture there-through, wherein a power line is insert-able through the at least one aperture;

an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture;

a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the power line or to receive a signal present on the power line when the power line is inserted through the at least one aperture.

Clause 19. The power system of clause 18, wherein the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

Clause 20. A network unit comprising:

a magnetic core with at least one aperture there-through, wherein a first power line is insert-able through the at least one aperture;

an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture;

a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the first power line or to receive a signal present on the first power line when the first power line is inserted through the at least one aperture,

wherein the network unit is operable to:

superimpose, onto the first power line, a first signal representative of at least one parameter of a serial string of power modules connected with a plurality of power lines that includes the first power line, thereby to transmit the first signal to at least one of the power modules; and

receive a second signal of the at least one parameter superimposed onto the first power line from another network unit.

Claims

1. A power system comprising:

a plurality of direct current (DC) power sources coupled to respective inputs of a plurality of power modules, wherein the outputs of the power modules are connected together with a plurality of first power lines in series to form a serial string; at least one power device with an input connected across the serial string; wherein the power modules include:

at least one communication interface;
at least one sensor interface operatively attached to the at least one communication interface, wherein the at least one sensor interface includes at least one sensor configured to sense at least one parameter in the serial string;

at least one network unit operatively attached to at least one of the first power lines and the at least one communication interface, the at least one network unit is operable to:

superimpose a first signal representative of the at least one parameter onto the first power lines, thereby to transmit the first signal to at least one of the other power modules or to the at least one power device; and receive a second signal of the at least one parameter superimposed onto the first power lines from another network unit.

2. The power system of claim 1, wherein the at least one network unit comprises:

a magnetic core with at least one aperture there-through, wherein a power line is insert-able through the at least one aperture;
an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture;
a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the power line or to receive a signal present on the power line when the power line is inserted through the at least one aperture.

3. The power system of claim 2, wherein the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

4. The power system of claim 2 or 3, wherein the magnetic core comprises two members attachable and re-attachable to each other to form thereby the at

least one aperture.

5. The power system of any of claims 2-4, wherein the transceiver is operatively attached to the at least one communication interface. 5
6. The power system of any of the preceding claims, wherein the at least one network unit is attachable or re-attachable to at least one location on at least one of the first power lines. 10
7. The power system of any of the preceding claims, wherein the at least one parameter is selected from the group of parameters consisting of: voltage, current, power, temperature, coulombic charge, and solar irradiance. 15
8. The power system of any of the preceding claims, wherein the first signal or the second signal is a control signal configured to control the power modules. 20
9. The power system of any of the preceding claims, wherein the first signal or the second signal is a signal representative of the at least one parameter sensed by the at least one sensor. 25
10. The power system of any of the preceding claims, wherein the first signal is superimposed onto the first power lines by a coupling between the network unit and the first power lines selected from the group of couplings consisting: an electromagnetic coupling, a capacitive coupling, and a direct coupling. 30
11. The power system of any of the preceding claims, wherein the second signal is received from the first power lines by a coupling between the network unit and the first power lines selected from the group of couplings consisting of: an electromagnetic coupling, a capacitive coupling, and a direct coupling. 35
12. A power system comprising:

a plurality of direct current (DC) power sources coupled to respective inputs of a plurality of power modules, wherein the outputs of the power modules are connected together with a plurality of first power lines in series to form a serial string; at least one power device with an input connected across the serial string by a plurality of second power lines, wherein the second power lines include a fiber optic portion; wherein the power modules include:

at least one communication interface;
at least one sensor interface operatively attached to the at least one communication interface, wherein the at least one sensor interface includes at least one sensor con-

figured to sense at least one parameter in the serial string;

at least one network unit operatively attached to at least one of the second power lines and the at least one communication interface, the at least one network unit is operable to:

superimpose a first optical signal representative of the at least one parameter onto the fiber optic portion of the second power lines, thereby to transmit the first optical signal to at least one of the other power modules or to the at least one power device; and receive a second optical signal of the at least one parameter superimposed onto the fiber optic portion of the second power lines from another network unit.

13. The power system of claim 12, wherein the at least one network unit comprises:

a magnetic core with at least one aperture there-through, wherein a power line is insert-able through the at least one aperture;
an inductor coil, wherein the wrapping of the inductor coil in turns on the magnetic core pass at least once through the at least one aperture;
a transceiver operatively attached to the inductor coil, wherein the transceiver is operable to superimpose a signal onto the power line or to receive a signal present on the power line when the power line is inserted through the at least one aperture.

14. The power system of claim 13, wherein the at least one aperture has a cross section selected from the group consisting of: a circular cross section, an elliptical cross section, a square cross section, a rectangular cross section, a triangular cross section, a pentagonal cross section, and a hexagonal cross section.

15. The power system of claim 13 or 14, wherein the magnetic core comprises two members attachable and re-attachable to each other to form thereby the at least one aperture.





Fig. 1A

Fig. 1B






Fig. 1C




Fig. 2A




Fig. 2B




Fig. 2C




Fig. 2D




Fig. 2E





Fig. 2G




Fig. 2H





Fig. 2I

SECTION 2I – 2I






Fig. 3B




Fig. 3C




Fig. 4A




Fig. 4B



EUROPEAN SEARCH REPORT

Application Number
EP 18 17 3581

5

10

15

20

25

30

35

40

45

50

55

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (IPC)
X	US 2011/121652 A1 (SELLA GUY [IL] ET AL) 26 May 2011 (2011-05-26) * paragraph [0034] - paragraph [0043] * -----	1, 6-12	INV. H04B3/54
A	US 2014/369098 A1 (LI SHENG-HUA [TW]) 18 December 2014 (2014-12-18) * paragraph [0032] - paragraph [0055] * -----	1-15	
			TECHNICAL FIELDS SEARCHED (IPC)
			H04B
The present search report has been drawn up for all claims			
Place of search The Hague		Date of completion of the search 9 August 2018	Examiner De Iulis, M
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

 1
EPO FORM 1503 03/82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 18 17 3581

5

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

09-08-2018

10

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 2011121652 A1	26-05-2011	US 2011121652 A1	26-05-2011
		US 2015288330 A1	08-10-2015

US 2014369098 A1	18-12-2014	CN 104242701 A	24-12-2014
		EP 2814131 A2	17-12-2014
		US 2014369098 A1	18-12-2014

15

20

25

30

35

40

45

50

55

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- US 62509411 A [0001]